



Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Revised: December 12, 2017

Requirements and procedures for initial configurations and software upgrades tend to change and therefore appear only in the switch or router software release notes. Before installing, configuring, or upgrading a switch, refer to the product release notes on Cisco.com for the latest information. This matrix does not replace or supersede the release notes.

This publication lists the Cisco platforms and minimum required software versions to support 10-Gigabit Ethernet transceiver modules.

Contents

10-Gigabit Ethernet Transceiver Module Models	4
• SFP+ Transceivers	4
• DWDM SFP+ Transceivers	4
• CWDM SFP+ Transceivers	6
• XENPAK Transceivers.....	6
• DWDM XENPAK Transceivers.....	6
• X2 Transceivers.....	7
• DWDM X2 Transceivers.....	7
• XFP Transceivers.....	8
• DWDM XFP Transceivers	9
Router Support and Minimum Software Release Requirements	10
• CRS Router.....	10
• Cisco Shared Port Adapter (SPA).....	11
• ASR 9000 Series Router	11
• ASR9000v Series Router	14
ASR 1000 Series Router	15
• Cisco ASR 901 Series.....	16
• Cisco ASR 903 Series.....	17
• Cisco 4400 Series Router	17

- Cisco SCE 8000..... 17
- Cisco 7600 Series Router 17
- Cisco RF Gateway Series..... 19
- Cisco NCS 5000 Series Router 19
- Cisco NCS 5500 Series 20
- Cisco NCS 6000 Series Router 21
- Industrial Ethernet and Smart Grid Support..... 21
- Cisco IE 5000 Series 21
- Data Center and Blade Switching Minimum Software Release Requirements 22
- Cisco Catalyst 2350 Series 22
- Cisco Catalyst 2360 Series 22
- Cisco Catalyst 3100 Blade Switches 22
- Cisco Nexus 2000 Series 23
- Cisco Nexus 3000 Series 26
- Cisco Nexus 3100 Series 30
- Cisco Nexus 3200 Series 39
- Cisco Nexus 3500 Series 41
- Cisco Nexus 3600 Series 42
- Cisco Nexus 4000 Series 42
- Cisco Nexus 5000 Series 42
- Cisco Unified Computing System 44
- Cisco Nexus 7000 Series 46
- Cisco Nexus 7700 Series 52
- Cisco Nexus 9000 Series (Modular 9500) NX-OS Mode 54
- Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode 56
- Cisco Nexus 9000 Series (Fixed 9200) NX-OS Mode 62
- Cisco Nexus 9000 Series (Fixed 9300) ACI Mode 65
- Cisco MDS 9000 Series 70
- Catalyst 2XXX and 3XXX Switch Support and Minimum Software Release Requirements 70
- Catalyst 2960-S Series 70
- Catalyst 2960-X Series 71

- Catalyst 2960-XR Series 73
- Catalyst 2960-L Series 73
- Catalyst 3560-E Series 74
- Catalyst 3560-X Series 75
- Catalyst 3560-CX Series 75
- Catalyst 3650 Series 76
- Catalyst 3750 Series 77
- Catalyst 3750-E Series 77
- Catalyst 3850 Series 79
- Catalyst 4XXX Switch Support and Minimum Software Release Requirements 82
- Catalyst 4500 Series 82
- Catalyst 4500-E Series 87
- Catalyst 4500-X Series 88
- Catalyst 4900 Series 90
- Cisco ME 4600 Series..... 92
- Cisco ME 4900 Series..... 92
- Catalyst 6XXX Switch Support and Minimum Software Release Requirements 93
- Catalyst 6500 Series 93
- Catalyst 6800 Series 96
- Catalyst 9300 Switch Support and Minimum Software Release Requirements..... 100
- Catalyst 9300 Series 100
- Catalyst 9400 Switch Support and Minimum Software Release Requirements..... 100
- Catalyst 9400 Series 100
- Catalyst 9500 Switch Support and Minimum Software Release Requirements..... 102
- Catalyst 9500 Series 102
- Metro Ethernet Support and Minimum Software Requirements 103
- Cisco ME 3600X 103
- Cisco ME 3800X 104
- Wireless LAN Controller Support and Minimum Software Release Requirements..... 104
- Cisco 5700 WLC Series..... 104
- Cisco Security Appliance Minimum Software Release Requirements..... 105
- Cisco Firepower 105

10-Gigabit Ethernet Transceiver Module Models

SFP+ Transceivers

Model Number	Transceiver Description
SFP-10G-SR=	10GBASE-SR SFP+ transceiver module for MMF, 850-nm wavelength, LC duplex connector
SFP-10G-SR-S=	10GBASE-SR SFP+ transceiver module for MMF, 850-nm wavelength, LC duplex connector
SFP-10G-SR-X=	10GBASE-SR SFP+ transceiver module for MMF, 850-nm wavelength, LC duplex connector, extended temperature range
SFP-10G-LRM=	10GBASE-LRM SFP+ transceiver module for MMF and SMF, 1310-nm wavelength, LC duplex connector
SFP-10G-LR=	10GBASE-LR SFP+ transceiver module for SMF, 1310-nm wavelength, LC duplex connector
SFP-10G-LR-S=	10GBASE-LR SFP+ transceiver module for SMF, 1310-nm wavelength, LC duplex connector
SFP-10G-LR-X=	10GBASE-LR SFP+ transceiver module for SMF, 1310-nm wavelength, LC duplex connector, extended temperature range
SFP-10G-ER=	10GBASE-ER SFP+ transceiver module for SMF, 1550-nm, LC duplex connector
SFP-10G-ER-S=	10GBASE-ER SFP+ transceiver module for SMF, 1550-nm, LC duplex connector
SFP-10G-ZR=	10GBASE-ZR SFP+ transceiver module for SMF, 1550-nm, LC duplex connector
SFP-10G-ZR-S=	10GBASE-ZR SFP+ transceiver module for SMF, 1550-nm, LC duplex connector
SFP-10G-BXD-I	10G SFP+ Bidirectional for 10km, downstream
SFP-10G-BXU-I	10G SFP+ Bidirectional for 10km, upstream
SFP-10G-BX40D-I	10G SFP+ Bidirectional for 40km, downstream
SFP-10G-BX40U-I	10G SFP+ Bidirectional for 40km, upstream
SFP-H10GB-CU1M=	1-m 10G SFP+ Twinax cable assembly, passive
SFP-H10GB-CU1-5M=	1.5-m 10G SFP+ Twinax cable assembly, passive
SFP-H10GB-CU2M=	2-m 10G SFP+ Twinax cable assembly, passive
SFP-H10GB-CU2-5M=	2.5-m 10G SFP+ Twinax cable assembly, passive
SFP-H10GB-CU3M=	3-m 10G SFP+ Twinax cable assembly, passive
SFP-H10GB-CU5M=	5-m 10G SFP+ Twinax cable assembly, passive
SFP-H10GB-ACU7M=	7-m 10G SFP+ Twinax cable assembly, active
SFP-H10GB-ACU10M=	10-m 10G SFP+ Twinax cable assembly, active
FET-10G	Cisco 10G Fabric Extender Transceiver, LC duplex connector

DWDM SFP+ Transceivers

Model Number	Transceiver Description
DWDM-SFP10G-61.41=	10GBASE-DWDM 1561.41 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-60.61=	10GBASE-DWDM 1560.61 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-59.79=	10GBASE-DWDM 1559.79 nm SFP+ (100-GHz ITU grid)

DWDM SFP+ Transceivers	
Model Number	Transceiver Description
DWDM-SFP10G-58.98=	10GBASE-DWDM 1558.98 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-58.17=	10GBASE-DWDM 1558.17 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-57.36=	10GBASE-DWDM 1557.36 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-56.55=	10GBASE-DWDM 1556.55 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-55.75=	10GBASE-DWDM 1555.75 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-54.94=	10GBASE-DWDM 1554.94 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-54.13=	10GBASE-DWDM 1554.13 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-53.33=	10GBASE-DWDM 1553.33 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-52.52=	10GBASE-DWDM 1552.52 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-51.72=	10GBASE-DWDM 1551.72 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-50.92=	10GBASE-DWDM 1550.92 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-50.12=	10GBASE-DWDM 1550.12 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-49.32=	10GBASE-DWDM 1549.32 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-48.51=	10GBASE-DWDM 1548.51 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-47.72=	10GBASE-DWDM 1547.72 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-46.92=	10GBASE-DWDM 1546.92 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-46.12=	10GBASE-DWDM 1546.12 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-45.32=	10GBASE-DWDM 1545.32 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-44.53=	10GBASE-DWDM 1544.53 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-43.73=	10GBASE-DWDM 1543.73 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-42.94=	10GBASE-DWDM 1542.94 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-42.14=	10GBASE-DWDM 1542.14 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-41.35=	10GBASE-DWDM 1541.35 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-40.56=	10GBASE-DWDM 1540.56 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-39.77=	10GBASE-DWDM 1539.77 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-38.98=	10GBASE-DWDM 1538.98 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-38.19=	10GBASE-DWDM 1538.19 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-37.40=	10GBASE-DWDM 1537.40 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-36.61=	10GBASE-DWDM 1536.61 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-35.82=	10GBASE-DWDM 1535.82 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-35.04=	10GBASE-DWDM 1535.04 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-34.25=	10GBASE-DWDM 1534.25 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-33.47=	10GBASE-DWDM 1533.47 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-32.68=	10GBASE-DWDM 1532.68 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-31.90=	10GBASE-DWDM 1531.90 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-31.12=	10GBASE-DWDM 1531.12 nm SFP+ (100-GHz ITU grid)
DWDM-SFP10G-30.33=	10GBASE-DWDM 1530.33 nm SFP+ (100-GHz ITU grid)

CWDM SFP+ Transceivers	
Model Number	Transceiver Description
CWDM-SFP10G-1470=	CWDM 1470 nm SFP+ 10 Gigabit Ethernet Transceiver Module
CWDM-SFP10G-1490=	CWDM 1490 nm SFP+ 10 Gigabit Ethernet Transceiver Module
CWDM-SFP10G-1510=	CWDM 1510 nm SFP+ 10 Gigabit Ethernet Transceiver Module
CWDM-SFP10G-1530=	CWDM 1530 nm SFP+ 10 Gigabit Ethernet Transceiver Module
CWDM-SFP10G-1550=	CWDM 1550 nm SFP+ 10 Gigabit Ethernet Transceiver Module
CWDM-SFP10G-1570=	CWDM 1570 nm SFP+ 10 Gigabit Ethernet Transceiver Module
CWDM-SFP10G-1590=	CWDM 1590 nm SFP+ 10 Gigabit Ethernet Transceiver Module
CWDM-SFP10G-1610=	CWDM 1610 nm SFP+ 10 Gigabit Ethernet Transceiver Module

XENPAK Transceivers	
Model Number	Transceiver Description
XENPAK-10GB-ER=	10GBASE-ER XENPAK transceiver module for SMF, 1550-nm wavelength, SC duplex connector
XENPAK-10GB-ER+=	10GBASE-ER XENPAK transceiver module for SMF, 1550-nm wavelength, SC duplex connector (supports DOM)
XENPAK-10GB-LR=	10GBASE-LR XENPAK transceiver module for SMF, 1310-nm wavelength, SC duplex connector
XENPAK-10GB-LR+=	10GBASE-LR XENPAK transceiver module for SMF, 1310-nm wavelength, SC duplex connector (supports DOM)
XENPAK-10GB-LRM=	10GBASE-LRM XENPAK transceiver module for MMF, 1310-nm wavelength, SC duplex connector
XENPAK-10GB-LW=	10GBASE-LW XENPAK transceiver module for SMF, 1310-nm wavelength, SC duplex connector
XENPAK-10GB-LX4=	10GBASE-LX4 XENPAK transceiver module for MMF, 1310-nm wavelength, SC duplex connector
XENPAK-10GB-SR=	10GBASE-SR XENPAK transceiver module for MMF, 850-nm wavelength, SC duplex connector
XENPAK-10GB-CX4=	10GBASE-CX4 XENPAK transceiver module for CX4 cable, copper, InfiniBand 4X connector
XENPAK-10GB-ZR=	10GBASE-ZR XENPAK transceiver module for SMF, 1550-nm wavelength, SC duplex connector

DWDM XENPAK Transceivers	
Model Number	Transceiver Description
DWDM-XENPAK-60.61=	10GBASE-DWDM 1560.61 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-59.79=	10GBASE-DWDM 1559.79 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-58.98=	10GBASE-DWDM 1558.98 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-58.17=	10GBASE-DWDM 1558.17 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-56.55=	10GBASE-DWDM 1556.55 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-55.75=	10GBASE-DWDM 1555.75 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-54.94=	10GBASE-DWDM 1554.94 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-54.13=	10GBASE-DWDM 1554.13 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-52.52=	10GBASE-DWDM 1552.52 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-51.72=	10GBASE-DWDM 1551.72 nm XENPAK (100-GHz ITU grid)

DWDM XENPAK Transceivers

Model Number	Transceiver Description
DWDM-XENPAK-50.92=	10GBASE-DWDM 1550.92 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-50.12=	10GBASE-DWDM 1550.12 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-48.51=	10GBASE-DWDM 1548.51 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-47.72=	10GBASE-DWDM 1547.72 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-46.92=	10GBASE-DWDM 1546.92 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-46.12=	10GBASE-DWDM 1546.12 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-44.53=	10GBASE-DWDM 1544.53 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-43.73=	10GBASE-DWDM 1543.73 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-42.94=	10GBASE-DWDM 1542.94 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-42.14=	10GBASE-DWDM 1542.14 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-40.56=	10GBASE-DWDM 1540.56 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-39.77=	10GBASE-DWDM 1539.77 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-38.98=	10GBASE-DWDM 1538.98 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-38.19=	10GBASE-DWDM 1538.19 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-36.61=	10GBASE-DWDM 1536.61 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-35.82=	10GBASE-DWDM 1535.82 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-35.04=	10GBASE-DWDM 1535.04 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-34.25=	10GBASE-DWDM 1534.25 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-32.68=	10GBASE-DWDM 1532.68 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-31.90=	10GBASE-DWDM 1531.90 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-31.12=	10GBASE-DWDM 1531.12 nm XENPAK (100-GHz ITU grid)
DWDM-XENPAK-30.33=	10GBASE-DWDM 1530.33 nm XENPAK (100-GHz ITU grid)

X2 Transceivers

Model Number	Transceiver Description
X2-10GB-LR=	10GBASE-LR X2 transceiver module for SMF, 1310-nm wavelength, SC duplex connector
X2-10GB-ER=	10GBASE-ER X2 transceiver module for SMF, 1550-nm wavelength, SC duplex connector
X2-10GB-ZR=	10GBASE-ZR X2 transceiver module for SMF, 1550-nm wavelength, SC duplex connector
X2-10GB-SR=	10GBASE-SR X2 transceiver module for MMF, 850-nm wavelength, SC duplex connector
X2-10GB-CX4=	10GBASE-CX4 X2 transceiver module for CX4 cable, copper, InfiniBand 4X connector
X2-10GB-LX4=	10GBASE-LX4 X2 transceiver module for MMF, 1310-nm wavelength, SC duplex connector
X2-10GB-LRM=	10GBASE-LRM X2 transceiver module for MMF, 1310-nm wavelength, SC duplex connector
X2-10GB-T	10GBASE-T X2 transceiver module for CAT6A/CAT7 cable, copper, RJ-45 connector

DWDM X2 Transceivers

Model Number	Transceiver Description
DWDM-X2-60.61=	10GBASE-DWDM 1560.61 nm X2 (100-GHz ITU grid)

DWDM X2 Transceivers	
Model Number	Transceiver Description
DWDM-X2-59.79=	10GBASE-DWDM 1559.79 nm X2 (100-GHz ITU grid)
DWDM-X2-58.98=	10GBASE-DWDM 1558.98 nm X2 (100-GHz ITU grid)
DWDM-X2-58.17=	10GBASE-DWDM 1558.17 nm X2 (100-GHz ITU grid)
DWDM-X2-56.55=	10GBASE-DWDM 1556.55 nm X2 (100-GHz ITU grid)
DWDM-X2-55.75=	10GBASE-DWDM 1555.75 nm X2 (100-GHz ITU grid)
DWDM-X2-54.94=	10GBASE-DWDM 1554.94 nm X2 (100-GHz ITU grid)
DWDM-X2-54.13=	10GBASE-DWDM 1554.13 nm X2 (100-GHz ITU grid)
DWDM-X2-52.52=	10GBASE-DWDM 1552.52 nm X2 (100-GHz ITU grid)
DWDM-X2-51.72=	10GBASE-DWDM 1551.72 nm X2 (100-GHz ITU grid)
DWDM-X2-50.92=	10GBASE-DWDM 1550.92 nm X2 (100-GHz ITU grid)
DWDM-X2-50.12=	10GBASE-DWDM 1550.12 nm X2 (100-GHz ITU grid)
DWDM-X2-48.51=	10GBASE-DWDM 1548.51 nm X2 (100-GHz ITU grid)
DWDM-X2-47.72=	10GBASE-DWDM 1547.72 nm X2 (100-GHz ITU grid)
DWDM-X2-46.92=	10GBASE-DWDM 1546.92 nm X2 (100-GHz ITU grid)
DWDM-X2-46.12=	10GBASE-DWDM 1546.12 nm X2 (100-GHz ITU grid)
DWDM-X2-44.53=	10GBASE-DWDM 1544.53 nm X2 (100-GHz ITU grid)
DWDM-X2-43.73=	10GBASE-DWDM 1543.73 nm X2 (100-GHz ITU grid)
DWDM-X2-42.94=	10GBASE-DWDM 1542.94 nm X2 (100-GHz ITU grid)
DWDM-X2-42.14=	10GBASE-DWDM 1542.14 nm X2 (100-GHz ITU grid)
DWDM-X2-40.56=	10GBASE-DWDM 1540.56 nm X2 (100-GHz ITU grid)
DWDM-X2-39.77=	10GBASE-DWDM 1539.77 nm X2 (100-GHz ITU grid)
DWDM-X2-38.98=	10GBASE-DWDM 1538.98 nm X2 (100-GHz ITU grid)
DWDM-X2-38.19=	10GBASE-DWDM 1538.19 nm X2 (100-GHz ITU grid)
DWDM-X2-36.61=	10GBASE-DWDM 1536.61 nm X2 (100-GHz ITU grid)
DWDM-X2-35.82=	10GBASE-DWDM 1535.82 nm X2 (100-GHz ITU grid)
DWDM-X2-35.04=	10GBASE-DWDM 1535.04 nm X2 (100-GHz ITU grid)
DWDM-X2-34.25=	10GBASE-DWDM 1534.25 nm X2 (100-GHz ITU grid)
DWDM-X2-32.68=	10GBASE-DWDM 1532.68 nm X2 (100-GHz ITU grid)
DWDM-X2-31.90=	10GBASE-DWDM 1531.90 nm X2 (100-GHz ITU grid)
DWDM-X2-31.12=	10GBASE-DWDM 1531.12 nm X2 (100-GHz ITU grid)
DWDM-X2-30.33=	10GBASE-DWDM 1530.33 nm X2 (100-GHz ITU grid)

XFP Transceivers	
Model Number	Transceiver Description
XFP-10GLR-OC192SR=	Cisco multirate XFP transceiver module for 10GBASE-LR Ethernet and OC-192/STM-64 short-reach (SR-1) Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector

XFP Transceivers	
Model Number	Transceiver Description
XFP10GLR-192SR-L=	Cisco multirate XFP transceiver module for 10GBASE-LR Ethernet and OC-192/STM-64 short-reach (SR-1) Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector, low power
XFP-10GER-OC192IR=	Cisco multirate XFP transceiver module for 10GBASE-ER Ethernet and OC-192/STM-64 intermediate-reach (IR-2) Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector
XFP-10GER-192IR+=	Cisco multirate XFP transceiver module for 10GBASE-ER Ethernet and OC-192/STM-64 intermediate-reach (IR-2) Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector
XFP10GER-192IR-L=	Cisco multirate XFP transceiver module for 10GBASE-ER Ethernet and OC-192/STM-64 intermediate-reach (IR-2) Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector
XFP-10GZR-OC192LR=	Cisco multirate XFP transceiver module for 10GBASE-ZR Ethernet and OC-192/STM-64 long-reach Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector
XFP-10G-MM-SR=	Cisco 10GBASE-SR Ethernet XFP transceiver module for MMF, dual LC connector
XFP10GLR192SR-RGD	Cisco multirate XFP transceiver module for 10GBASE-LR Ethernet and OC-192/STM-64 short-reach (SR-1) Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector, industrial temperature range
XFP10GER192IR-RGD	Cisco multirate XFP transceiver module for 10GBASE-ER Ethernet and OC-192/STM-64 intermediate-reach (IR-2) Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector, industrial temperature range
XFP10GZR192LR-RGD	Cisco multirate XFP transceiver module for 10GBASE-ZR Ethernet and OC-192/STM-64 long-reach Packet-over-SONET/SDH (POS) applications, SMF, dual LC connector, industrial temperature range

DWDM XFP Transceivers	
Model Number	Transceiver Description
DWDM-XFP-60.61=	10GBASE-DWDM 1560.61 nm XFP (100-GHz ITU grid)
DWDM-XFP-59.79=	10GBASE-DWDM 1559.79 nm XFP (100-GHz ITU grid)
DWDM-XFP-58.98=	10GBASE-DWDM 1558.98 nm XFP (100-GHz ITU grid)
DWDM-XFP-58.17=	10GBASE-DWDM 1558.17 nm XFP (100-GHz ITU grid)
DWDM-XFP-56.55=	10GBASE-DWDM 1556.55 nm XFP (100-GHz ITU grid)
DWDM-XFP-55.75=	10GBASE-DWDM 1555.75 nm XFP (100-GHz ITU grid)
DWDM-XFP-54.94=	10GBASE-DWDM 1554.94 nm XFP (100-GHz ITU grid)
DWDM-XFP-54.13=	10GBASE-DWDM 1554.13 nm XFP (100-GHz ITU grid)
DWDM-XFP-52.52=	10GBASE-DWDM 1552.52 nm XFP (100-GHz ITU grid)
DWDM-XFP-51.72=	10GBASE-DWDM 1551.72 nm XFP (100-GHz ITU grid)
DWDM-XFP-50.92=	10GBASE-DWDM 1550.92 nm XFP (100-GHz ITU grid)
DWDM-XFP-50.12=	10GBASE-DWDM 1550.12 nm XFP (100-GHz ITU grid)
DWDM-XFP-48.51=	10GBASE-DWDM 1548.51 nm XFP (100-GHz ITU grid)
DWDM-XFP-47.72=	10GBASE-DWDM 1547.72 nm XFP (100-GHz ITU grid)
DWDM-XFP-46.92=	10GBASE-DWDM 1546.92 nm XFP (100-GHz ITU grid)
DWDM-XFP-46.12=	10GBASE-DWDM 1546.12 nm XFP (100-GHz ITU grid)
DWDM-XFP-44.53=	10GBASE-DWDM 1544.53 nm XFP (100-GHz ITU grid)
DWDM-XFP-43.73=	10GBASE-DWDM 1543.73 nm XFP (100-GHz ITU grid)

DWDM XFP Transceivers

Model Number	Transceiver Description
DWDM-XFP-42.94=	10GBASE-DWDM 1542.94 nm XFP (100-GHz ITU grid)
DWDM-XFP-42.14=	10GBASE-DWDM 1542.14 nm XFP (100-GHz ITU grid)
DWDM-XFP-40.56=	10GBASE-DWDM 1540.56 nm XFP (100-GHz ITU grid)
DWDM-XFP-39.77=	10GBASE-DWDM 1539.77 nm XFP (100-GHz ITU grid)
DWDM-XFP-38.98=	10GBASE-DWDM 1538.98 nm XFP (100-GHz ITU grid)
DWDM-XFP-38.19=	10GBASE-DWDM 1538.19 nm XFP (100-GHz ITU grid)
DWDM-XFP-36.61=	10GBASE-DWDM 1536.61 nm XFP (100-GHz ITU grid)
DWDM-XFP-35.82=	10GBASE-DWDM 1535.82 nm XFP (100-GHz ITU grid)
DWDM-XFP-35.04=	10GBASE-DWDM 1535.04 nm XFP (100-GHz ITU grid)
DWDM-XFP-34.25=	10GBASE-DWDM 1534.25 nm XFP (100-GHz ITU grid)
DWDM-XFP-32.68=	10GBASE-DWDM 1532.68 nm XFP (100-GHz ITU grid)
DWDM-XFP-31.90=	10GBASE-DWDM 1531.90 nm XFP (100-GHz ITU grid)
DWDM-XFP-31.12=	10GBASE-DWDM 1531.12 nm XFP (100-GHz ITU grid)
DWDM-XFP-30.33=	10GBASE-DWDM 1530.33 nm XFP (100-GHz ITU grid)
DWDM-XFP-C=	10GBASE-DWDM Tuneable XFP (50-GHz ITU grid)

Router Support and Minimum Software Release Requirements

CRS Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
8-10GBE	CRS-XENPAK10GB-LR XENPAK-10GB-LR+	—	XR 3.0
	XENPAK-10GB-ER+	XR 3.3.3	XR 3.3.3
	XENPAK-10GB-ER	—	XR 3.2.2
	DWDM XENPAK	XR 3.0	XR 3.0
4-10GE	XENPAK-10GB-LR+ XENPAK-10GB-ER+ DWDM XENPAK	XR 3.8.1	XR 3.8.1
2-10GE-WL-FLEX	XFP-10G-MM-SR XFP-10GLR-OC192SR XFP-10GER-192IR+ XFP-10GZR-OC192LR DWDM XFP	XR 3.8.1	XR 3.8.1
4-10GBE-WL-XFP 8-10GBE-WL-XFP	XFP10GLR-192SR-L XFP10GER-192IR-L	XR 3.8.4, 3.9.1	XR 3.8.4, 3.9.1

[CRS Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	XFP-10G-MM-SR ¹ XFP-10GZR-OC192LR1 DWDM XFP1	XR 4.0.1	XR 4.0.1
	DWDM-XFP-C	XR 4.2.3	XR 4.2.3
14X10GBE-WL-XFP 20X10GBE-WL-XFP	XFP10GLR-192SR-L XFP10GER-192IR-L	XR 4.0	XR 4.0
	XFP-10G-MM-SR1 XFP-10GZR-OC192LR ² DWDM XFP1	XR 4.0.1	XR 4.0.1
	DWDM-XFP-C	XR 4.2.3	XR 4.2.3
40x10GE-WLO	SFP-10G-SR SFP-10G-SR-X SFP-10G-LRM SFP-10G-LR SFP-10G-LR-X SFP-10G-ER SFP-10G-ZR	XR 5.1.1	XR 5.1.1

Cisco [Shared Port Adapter \(SPA\)](#)

Network Device	Transceiver Model	Minimum Software Release Required
SPA-OC192POS-XFP SPA-1X10GE-WL-V2 SPA-1XTENGE-XFP SPA-1X10GE-L-V2	XFP-10G-MM-SR XFP-10GLR-OC192SR XFP10GLR-192SR-L XFP-10GER-OC192IR XFP-10GER-192IR+ XFP10GER-192IR-L XFP-10GZR-OC192LR DWDM XFP	SPA software support is determined by the platform on which the SPA is installed. Refer to the SPA release notes for the correct software release.

[ASR 9000 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
A9K-4T-B A9K-4T-E A9K-8T/4-E A9K-8T/4-B	XFP-10G-MM-SR XFP-10GLR-OC192SR XFP-10GER-192IR+ XFP-10GZR-OC192LR1 DWDM XFP	XR 3.7.3	XR 3.7.3

¹Only version -02 or later is supported.

²Only version -03 or later is supported.

ASR 9000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	DWDM-XFP-C	XR 4.0.1	XR 4.0.1
	XFP10GLR-192SR-L	XR 4.3.0	XR 4.3.0
A9K-2T20GE-B A9K-2T20GE-E A9K-2T20GE-L A9K-4T-L A9K-8T/4-L A9K-8T-L A9K-8T-E	XFP-10G-MM-SR XFP-10GLR-OC192SR XFP-10GER-192IR+ XFP-10GZR-OC192LR1 DWDM XFP	XR 3.9.0	XR 3.9.0
	DWDM-XFP-C	XR 4.0.1	XR 4.0.1
	XFP10GLR-192SR-L	XR 4.3.0	XR 4.3.0
A9K-8T-B	XFP-10G-MM-SR XFP-10GLR-OC192SR XFP-10GER-192IR+ XFP-10GZR-OC192LR1 DWDM XFP	XR 3.9.1	XR 3.9.1
A9K-SIP-700 with SPA-OC192POS-XFP	XFP-10GLR-OC192SR XFP-10GER-192IR+ XFP-10GZR-OC192LR1 DWDM XFP	XR 4.0.0	XR 4.0.0
	DWDM-XFP-C	XR 4.0.1	XR 4.0.1
	XFP10GLR-192SR-L	XR 4.3.0	XR 4.3.0
A9K-16T/8-B	SFP-10G-SR SFP-10G-LR SFP-10G-ER	XR 3.9.1	XR 3.9.1
A9K-4T16GE-TR A9K-4T16GE-SE	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-ZR SFP-H10GB-ACU7M SFP-H10GB-ACU10M DWDM SFP+	XR 5.3.0	XR 5.3.0
A9K-24X10GE-SE A9K-24X10GE-TR A9K-36X10GE-SE A9K-36X10GE-TR	SFP-10G-SR SFP-10G-SR-X SFP-10G-LR SFP-10G-LR-X SFP-10G-ER	XR 4.2.0	XR 4.2.0
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	XR 4.2.1
	SFP-10G-ZR DWDM SFP+	XR 4.2.3	XR 4.2.3

ASR 9000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I CWDM-SFP10G-xxxx	XR 5.2.0	XR 5.2.0
	DWDM-SFP10G-C	XR 5.2.2	XR 5.2.2
A9K-MPA-8X10GE	SFP-10G-SR SFP-10G-SR-X SFP-10G-LR SFP-10G-LR-X SFP-10G-ER	XR 4.2.0	XR 4.2.0
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	XR 4.2.1
	SFP-10G-ZR DWDM SFP+	XR 4.2.3	XR 4.2.3
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I CWDM-SFP10G-xxxx	XR 5.2.0	XR 5.2.0
	DWDM-SFP10G-C	XR 5.2.2	XR 5.2.2
A9K-MPA-2X10GE A9K-MPA-4X10GE	XFP-10G-MM-SR XFP-10GLR-OC192SR XFP-10GER-192IR+ XFP-10GZR-OC192LR1 DWDM XFP DWDM-XFP-C	XR 4.2.0	XR 4.2.0
	XFP10GLR-192SR-L XFP10GER-192IR-L	XR 4.3.0	XR 4.3.0
A9K-RSP440-TR A9K-RSP440-SE	SFP-H10GB-ACU7M1 SFP-H10GB-ACU10M1	—	XR 4.2.1
	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-ZR	XR 4.2.1	XR 4.2.1
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I	XR 5.2.0	XR 5.2.0
ASR-9922-RP-TR ASR-9922-RP-SE	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-ZR	XR 4.2.2	XR 4.2.2

[ASR 9000 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ASR-9900-RP-TR ASR-9900-RP-SE	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-ZR	XR 4.3.2	XR 4.3.2
A9K-RSP880-TR A9K-RSP880-SE ASR-9900-RP-TR ASR-9900-RP-SE	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-ZR	XR 5.3.0	XR 5.3.0
ASR-9001	SFP-10G-SR SFP-10G-LR SFP-10G-ER	XR 4.2.1	XR 4.2.1
	SFP-10G-ZR DWDM SFP+	XR 5.1.1	XR 5.1.1
	CWDM-SFP10G-xxxx DWDM-SFP10G-C	XR 5.2.2	XR 5.2.2
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I	XR 5.2.0	XR 5.2.0

[ASR9000v Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ASR-9000V-AC ASR-9000V-DC-A ASR-9000V-DC-E ASR-9000V-24-A	SFP-10G-SR SFP-10G-SR-X SFP-10G-LR SFP-10G-LR-X SFP-10G-ER SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-ZR	XR 5.1.0	XR 5.1.0
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I	XR 5.2.0	XR 5.2.0

ASR9000v Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
A9KV-V2-AC	SFP-10G-SR	XR 4.3.2	XR 4.3.2
A9KV-V2-DC-A	SFP-10G-SR-X		
A9KV-V2-DC-E	SFP-10G-LR		
	SFP-10G-LR-X		
	SFP-10G-ER		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-ZR		
	SFP-10G-BXD-I	XR 5.2.0	XR 5.2.0
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		

ASR 1000 Series Router

ASR 1000 platform with SPA cards: Software support on the ASR 1000 modular platforms is determined by the platform on which the SPA is installed. Refer to the [SPA release notes](#) for the correct software release.

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ASR 1001X	SFP-10G-SR		XE 3.12.0a
	SFP-10G-SR-X		
	SFP-10G-LR		
	SFP-10G-LRX		
	SFP-10G-ER		
	SFP-10G-AOC1M		XE 16.6.1
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-ZR		Not Supported
	DWDM-SFP10G-30.33		
	DWDM-SFP10G-61.41		
	SFP-H10GB-ACU7M		XE 16.3S
	SFP-H10GB-ACU10M		
	SFP-10G-BXD-I		XE 16.3S
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		
ASR 1002HX	SFP-10G-SR		XE 16.2S
	SFP-10G-SR-X		
	SFP-10G-LR		
	SFP-10G-LRX		
	SFP-10G-ER		

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

ASR 1000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-AOC1M		XE 16.6.1
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-ZR		IOS XE Denali 16.3.1
	DWDM-SFP10G-30.33		
	DWDM-SFP10G-61.41		
	SFP-H10GB-ACU7M		XE 16.2S
	SFP-H10GB-ACU10M		
	SFP-10G-BXD-I		IOS XE Denali 16.3.1
	SFP-10G-BXU-I		
SFP-10G-BX40D-I			
SFP-10G-BX40U-I			
ASR 1001HX	SFP-10G-SR		IOS XE Denali 16.3.1
	SFP-10G-SR-X		
	SFP-10G-LR		
	SFP-10G-LRX		
	SFP-10G-ER		
	SFP-10G-ZR		
	DWDM-SFP10G-30.33		
	DWDM-SFP10G-61.41		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-BXD-I		
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
SFP-10G-BX40U-I			
SFP-10G-AOC1M		XE 16.6.1	
SFP-10G-AOC2M			
SFP-10G-AOC3M			
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			

[Cisco ASR 901 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
A901-6CZ-F-D	SFP-10G-SR	15.2(2)SNH1	15.2(2)SNH1
A901-6-CZ-FT-D	SFP-10G-LRM		
A901-6CZ-F-A	SFP-10G-LR		
A901-6-CZ-FT-A	SFP-10G-ER		
(SFP+ ports)	SFP-10G-ZR		
	SFP-10G-SR-X		
	SFP-10G-LR-X		

[Cisco ASR 903 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
A900-IMA1X	XFP10GLR192SR-RGD XFP10GER192IR-RGD XFP10GZR192LR-RGD XFP-10G-MM-SR XFP10GLR-192SR-L XFP10GER-192IR-L XFP-10GZR-OC192LR DWDM-XFP-C	XE 3.5.0S	XE 3.5.0S

[Cisco 4400 Series Router](#)

4451-X, 4431, 4351, 4331, 4321: Refer to the [ISR 4000 Compatibility Matrix](#).

[Cisco SCE 8000](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
SCE8000-2X10GE-E SCE8000-4X10GE-E	XFP-10G-MM-SR XFP-10GLR-OC192SR XFP-10GER-OC192SR XFP-10GZR-OC192LR DWDM XFP	SCS 3.1.6	SCS 3.1.6

[Cisco 7600 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
7600-ES20-10G3C 7600-ES20-10G3CXL	XFP-10GLR-OC192SR XFP-10GER-OC192IR XFP-10GZR-OC192LR DWDM XFP XFP-10GER-192IR+ XFP-10G-MM-SR	12.2(33)SRB 12.2(33)SRB1 12.2(33)SRB3 12.2(33)SRD 12.2(33)SRE1	12.2(33)SRB 12.2(33)SRB1 12.2(33)SRB3 12.2(33)SRD 12.2(33)SRE1
7600-ES+2TG3C 7600-ES+2TG3CXL 7600-ES+4TG3C 7600-ES+4TG3CXL	XFP-10GLR-OC192SR XFP-10GER-192IR+ XFP-10GZR-OC192LR DWDM XFP XFP-10G-MM-SR DWDM-XFP-C	12.2(33)SRD 12.2(33)SRE1 15.0(1)S	12.2(33)SRD 12.2(33)SRE1 15.0(1)S

[Cisco 7600 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
76-ES+XT-2TG3C	XFP-10GLR-OC192SR	12.2(33)SRD1	12.2(33)SRD1
76-ES+XT-2TG3CXL	XFP-10GER-192IR+		
76-ES+XT-4TG3C	XFP-10GZR-OC192LR		
76-ES+XT-4TG3CXL	DWDM XFP		
	XFP-10G-MM-SR	12.2(33)SRE1	12.2(33)SRE1
	DWDM-XFP-C	15.0(1)S	15.0(1)S
76-ES+T-2TG	XFP-10GLR-OC192SR	12.2(33)SRD3	12.2(33)SRD3
76-ES+T-4TG	XFP-10GER-192IR+		
	XFP-10GZR-OC192LR		
	DWDM XFP		
	XFP-10G-MM-SR	12.2(33)SRE1	12.2(33)SRE1
	DWDM-XFP-C	15.0(1)S	15.0(1)S
76-ES+XC-20G3C	XFP-10GLR-OC192SR	12.2(33)SRE	12.2(33)SRE
76-ES+XC-20G3CXL	XFP-10GER-192IR+		
76-ES+XC-40G3C	XFP-10GZR-OC192LR		
76-ES+XC-40G3CXL	DWDM XFP		
	XFP-10G-MM-SR	12.2(33)SRE1	12.2(33)SRE1
	DWDM-XFP-C	15.0(1)S	15.0(1)S
WS-X6708-10G-3C	X2-10GB-CX4	—	12.2(33)SRC
WS-X6708-10G-3CXL	X2-10GB-LX4		
RSP720-10GE	X2-10GB-LR	12.2(33)SRD2	12.2(33)SRC
	X2-10GB-SR		
	X2-10GB-ER		
	X2-10GB-LRM	12.2(33)SRE	12.2(33)SRE
	X2-10GB-ZR		
	DWDM X2		
WS-SUP32-10GB-3B	XENPAK-10GB-CX4	—	12.2(33)SRA
	XENPAK-10GB-LX4		
	XENPAK-10GB-SR		
	XENPAK-10GB-LR		
	XENPAK-10GB-ER		
	XENPAK-10GB-LR+	12.2(33)SRA	12.2(33)SRA
	XENPAK-10GB-ER+		
	XENPAK-10GB-ZR		
	DWDM XENPAK		
WS-X6704-10GE	XENPAK-10GB-CX4	—	12.2(33)SRA
	XENPAK-10GB-LX4		
	XENPAK-10GB-SR		
	XENPAK-10GB-LR		
	XENPAK-10GB-ER		

[Cisco 7600 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	XENPAK-10GB-LW	12.2(33)SRA	12.2(33)SRA
	XENPAK-10GB-LR+		
	XENPAK-10GB-ER+		
	XENPAK-10GB-ZR		
	DWDM XENPAK		

[Cisco RF Gateway Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
RFGW-X4516-10GE	X2-10GB-SR	12.2(44)SQ	12.2(44)SQ
	X2-10GB-LR		

[Cisco NCS 5000 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NCS 5001	SFP-10G-SR		XR 6.0.0
NCS 5002	SFP-10G-LR		
	SFP-10G-SR-X		
	SFP-10G-LR-X		
	SFP-10G-ER		
	SFP-10G-ZR		
	DWDM-SFP+		
	CWDM-SFP10G-xxxx		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		

[Cisco NCS 5500 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NCS-5501	SFP-10G-ER		IOS XR 6.1.1
	SFP-10G-ER-S		
	SFP-10G-SR		
	SFP-10G-SR-S		
	SFP-10G-LR		
	SFP-10G-LR-S		
	SFP-10G-LR-X		
	SFP-10G-AOC1M		IOS XR 6.2.2
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-CU7M		
SFP-H10GB-CU10M			
CWDM-SFP10G-xxxx			
NCS-5501-SE	SFP-10G-ER		IOS XR 6.1.1
	SFP-10G-ER-S		
	SFP-10G-SR		
	SFP-10G-SR-S		
	SFP-10G-LR		
	SFP-10G-LR-S		
	SFP-10G-LR-X		
	SFP-10G-ZR		IOS XR 6.2.2
	SFP-10G-ZR-S		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU3M		
SFP-H10GB-CU5M			
SFP-H10GB-CU7M			
SFP-H10GB-CU10M			
DWDM-SFP+			
CWDM-SFP10G-xxxx			

[Cisco NCS 5500 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NC55-24X100G-SE NC55-24H12F-SE (modular line cards)	QSA (CVR-QSFP-SFP10G) w/ SFP-10G-ZR w/ SFP-10G-ZR-S w/ SFP-10G-ER w/ SFP-10G-ER-S w/ DWDM-SFP10G-C w/ DWDM-SFP+		IOS XR 6.2.2

[Cisco NCS 6000 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NCS-6008	SFP-10G-SR-X SFP-10G-LR-X SFP-10G-ER	XR 5.0.0	XR 5.0.0
NC6-60X10GE-L-S NC6-60X10GE-M-S	SFP-10G-SR SFP-10G-SR-X SFP-10G-LR SFP-10G-LR-X SFP-10G-ZR	XR 5.0.1	XR 5.0.1
	SFP-10G-ER	XR 5.2.1	XR 5.2.1

Industrial Ethernet and Smart Grid Support

[Cisco IE 5000 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
IE-5000-12S12P-10G	SFP-10G-SR-X SFP-10G-LR-X SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-ER SFP-10G-ZR	15.2(2)EB	15.2(2)EB
	SFP-H10GB-CUxM SFP-H10GB-ACUxM	—	15.2(2)EB
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I	15.2(4)EA1	15.2(4)EA1

SFP-10G-BX40U-I

Data Center and Blade Switching Minimum Software Release Requirements

[Cisco Catalyst 2350 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
2350-48TD-S	X2-10GB-CX4	—	12.2(46)EY
2350-48TD-SD	X2-10GB-SR X2-10GB-LRM		

[Cisco Catalyst 2360 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
2360-48TD-S	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	—	12.2(53)EY

[Cisco Catalyst 3100 Blade Switches](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-CBS3110X-S-I	X2-10GB-CX4 X2-10GB-SR X2-10GB-LX4	—	12.2(40)EX1
	X2-10GB-LRM X2-10GB-LR	—	12.2(46)SE
WS-CBS3120X-S WS-CBS3130X-S	X2-10GB-CX4 X2-10GB-SR X2-10GB-LRM	—	12.2(40)EX3

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

Cisco Catalyst 3100 Blade Switches

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	X2-10GB-LX4 X2-10GB-LR	—	12.2(46)SE
WS-CBS3110X-S-I WS-CBS3120X-S WS-CBS3130X-S (With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR SFP-10G-LR SFP-10G-LRM SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-10G-SR-S SFP-10G-LR-S	—	12.2(55)SE1

Cisco Nexus 2000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N2K-C2148T-1GE	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	NX-OS 4.0(1a)N2(1)	NX-OS 4.0(1a)N2(1)
	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	NX-OS 4.0(1a)N2(1)
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 4.2(1)N2(1)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)
N2K-C2248TP-1GE N2K-C2232PP-10GE	SFP-10G-SR SFP-10G-LR FET-10G SFP-10G-SR-S SFP-10G-LR-S	NX-OS 4.2(1)N1(1)	NX-OS 4.2(1)N1(1)
	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	NX-OS 4.2(1)N1(1)

Cisco Nexus 2000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 4.2(1)N2(1)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)
N2K-C2224TP-1GE	SFP-10G-SR SFP-10G-LR FET-10G SFP-10G-SR-S SFP-10G-LR-S	NX-OS 4.2(1)N2(1)	NX-OS 4.2(1)N2(1)
	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 4.2(1)N2(1)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)
	N2K-C2232TM-10GE	SFP-10G-SR SFP-10G-LR FET-10G SFP-10G-SR-S SFP-10G-LR-S	NX-OS 5.0(3)N2(1)
SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M		—	NX-OS 5.0(3)N2(1)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)
	N2K-C2232TM-E	SFP-10G-SR SFP-10G-LR FET-10G SFP-10G-SR-S SFP-10G-LR-S SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M	NX-OS 5.2(1)N1(1a)

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

Cisco Nexus 2000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-ER SFP-10G-ER-S		
N2K-2348UPQ	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GBACU7M SFP-H10GB-ACU10 SFP-10G-SR SFP-10G-SR-S SFP-10G-LR SFP-10G-LR-S SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	NX-OS 7.0(3)N1(1)
N2K-2348TQ (Uplink QSFP ports with QSA adapter)	SFP-10G-SR SFP-10G-SR-S SFP-10G-LR SFP-10G-LR-S SFP-10G-ER SFP-10G-ER-S FET-10G		NX-OS 7.1(0)N1(1)
N2K-2348TQ-E (Uplink QSFP ports with QSA adapter)	SFP-10G-SR SFP-10G-SR-S SFP-10G-LR SFP-10G-LR-S SFP-10G-ER SFP-10G-ER-S FET-10G		NX-OS 7.3(0)N1(1)
N2K-2332TQ (Uplink QSFP ports with QSA adapter)	QSA Adapter is not supported		
N2K-C2248TP-E-1GE	SFP-10G-SR SFP-10G-LR FET-10G SFP-10G-ER	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)

Cisco Nexus 2000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S		
	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.1(3)N1(1)
N2K-C2248PQ	SFP-10G-SR SFP-10G-LR FET-10G SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M		NX-OS 6.0(2)N1(1)

Cisco Nexus 3000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C3064PQ	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S		NX-OS 5.0(3)U1(1a)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	NX-OS 5.0(3)U1(1d)

Cisco Nexus 3000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-ER	NX-OS 5.0(3)U2(2c)	NX-OS 5.0(3)U2(2c)
	SFP-10G-ER-S		
	SFP-10G-AOC1M	—	NX-OS 5.0(3)U5(1)
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
N3K-C3064PQ-10GE (Native SFP+ ports)	SFP-10G-SR	NX-OS 5.0(3)U1(2)	NX-OS 5.0(3)U1(2)
	SFP-10G-LR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-H10GB-CU1M	—	NX-OS 5.0(3)U1(2)
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-10G-ER	NX-OS 5.0(3)U2(2c)	NX-OS 5.0(3)U2(2c)
	SFP-10G-ER-S		
	SFP-H10GB-ACU7M	—	NX-OS 5.0(3)U3(2b)
	SFP-H10GB-ACU10M		
	SFP-10G-ZR	NX-OS 5.0(3)U3(2b)	NX-OS 5.0(3)U3(2b)
	SFP-10G-ZR-S		
	DWDM SFP+		
SFP-10G-AOC1M	—	NX-OS 5.0(3)U5(1)	
SFP-10G-AOC2M			
SFP-10G-AOC3M			
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			
N3K-C3016Q-40GE	SFP-10G-SR	—	NX-OS 6.0(2)U2(1)
N3K-C3064PQ-10GE	SFP-10G-LR		
N3K-C3064TQ-10GT	SFP-10G-ER		
(QSFP ports with QSA adapter)	SFP-10G-ZR		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		

Cisco Nexus 3000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-AOC1M	—	NX-OS 6.0(2)U3(1)
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
N3K-C3064PQ-10GX (Native SFP+ ports)	SFP-10G-SR	NX-OS 5.0(3)U3(1)	NX-OS 5.0(3)U3(1)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-H10GB-CU1M	—	NX-OS 5.0(3)U3(1)
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M	—	NX-OS 5.0(3)U3(2b)
	SFP-H10GB-ACU10M		
	SFP-10G-ZR	NX-OS 5.0(3)U4(1)	NX-OS 5.0(3)U4(1)
	DWDM SFP+		
	SFP-10G-AOC1M	—	NX-OS 5.0(3)U5(1)
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
SFP-10G-AOC10M			
N3K-C3064PQ-10GX (QSFP ports with QSA adapter)	SFP-10G-SR-S	NX-OS 7.0(3)I2(1a)	NX-OS 7.0(3)I2(1a)
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	SFP-10G-SR	—	NX-OS 6.0(2)U1(a)
	SFP-H10GB-CU1M		
	SFP-H10GB-CU3M		
	SFP-10G-LR	—	NX-OS 6.0(2)U2(1)
	SFP-10G-ER		
	SFP-10G-ZR		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU5M		
SFP-H10GB-ACU7M			
SFP-H10GB-ACU10M			
	SFP-10G-AOC1M	—	NX-OS 6.0(2)U3(1)
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

[Cisco Nexus 3000 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S	—	NX-OS 7.0(3)I4(1)
N3K-C3048TP-1GE	SFP-10G-SR SFP-10G-LR	NX-OS 5.0(3)U2(2b)	NX-OS 5.0(3)U2(2b)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	NX-OS 5.0(3)U2(2b)
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.0(3)U3(2b)
	SFP-10G-ZR DWDM SFP+	NX-OS 5.0(3)U4(1)	NX-OS 5.0(3)U4(1)
	SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	NX-OS 5.0(3)U5(1)
	SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S	NX-OS 7.0(3)I2(1a)	NX-OS 7.0(3)I2(1a)

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C3132Q-40GE (Native SFP+ ports)	SFP-10G-SR	When supported by transceiver module	NX-OS 6.0(2)U2(1)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-SR-S		NX-OS 7.0(3)I2(1a)
SFP-10G-LR-S			
SFP-10G-ER-S			
SFP-10G-ZR-S			
SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)	
N3K-C3132Q-40GE (QSFP ports with QSA adapter)	SFP-10G-SR	When supported by transceiver module	NX-OS 6.0(2)U2(1)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		NX-OS 6.0(2)U3(1)
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
SFP-10G-AOC7M			
SFP-10G-AOC10M			

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S		NX-OS 7.0(3)I4(1)
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)
N3K-C3132Q-40GX (Native SFP+ ports)	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	When supported by transceiver module	NX-OS 6.0(2)U4(1)
	SFP-10G-ZR SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S DWDM SFP+ (40 channels)		NX-OS 7.0(3)I2(1a)
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)

[Cisco Nexus 3100 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C3132Q-40GX (QSFP ports with QSA adapter)	SFP-10G-SR	When supported by transceiver module	NX-OS 6.0(2)U4(1)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
SFP-10G-AOC7M			
SFP-10G-AOC10M			
SFP-10G-ZR		NX-OS 7.0(3)I3(1)	
DWDM SFP+ (40 channels)			
SFP-10G-SR-S		NX-OS 7.0(3)I4(1)	
SFP-10G-LR-S			
SFP-10G-ER-S			
SFP-10G-ZR-S			
SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)	

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C3132Q-XL (Native SFP+ ports and QSFP ports with QSA adapter)	SFP-10G-SR	When supported by transceiver module	NXOS 7.0(3)I2(2)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			
SFP-10G-LRM (over SMF only)			NX-OS 7.0(3)I5(1)
N3K-C3132Q-V (Native SFP+ ports and	SFP-10G-SR	When supported by transceiver module	NX-OS 7.0(3)I4(1)
	SFP-10G-LR		
	SFP-10G-ER		

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
QSFP ports with QSA adapter)	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)
N3K-C3172PQ-10GE (Native SFP+ ports)	SFP-10G-ER	When supported by transceiver module	NX-OS 6.0(2)U3(1)
	SFP-10G-ZR		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-SR		NX-OS 6.0(2)U4(1)
	SFP-10G-LR		
	SFP-10G-SR-S		NX-OS 7.0(3)I4(1)
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)
N3K-C3172PQ-10GE (QSFP ports with QSA adapter)	SFP-10G-SR	When supported by transceiver module	NX-OS 6.0(2)U3(1)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
SFP-10G-AOC7M			
SFP-10G-AOC10M			
	SFP-10G-SR-S		NX-OS 7.0(3)I4(1)
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)
N3K-C3172TQ-10GT (QSFP ports with QSA adapter)	SFP-10G-SR	When supported by transceiver module	NX-OS 6.0(2)U3(1)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		

[Cisco Nexus 3100 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	DWDM SFP+ (40 channels) SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M		NX-OS 6.0(2)U4(1)
	SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S		NX-OS 7.0(3)I4(1)
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C3172PQ-XL (Native SFP+ ports)	SFP-10G-SR	When supported by transceiver module	NXOS 7.0(3)I2(2)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)
N3K-C3172PQ-XL N3K-C3172TQ-XL (QSFP ports with QSA adapter)	SFP-10G-SR	When supported by transceiver module	NXOS 7.0(3)I2(2)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)
N3K-C31108PC-V (Native SFP+ ports)	SFP-10G-SR	When supported by transceiver module	NXOS 7.0(3)I4(1)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
SFP-10G-AOC7M			
SFP-10G-AOC10M			
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)
N3K-C31108PC-V N3K-C31108TC-V (QSFP ports with QSA adapter)	SFP-10G-SR	When supported by transceiver module	NXOS 7.0(3)I4(1)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+ (40 channels)		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
SFP-10G-AOC7M			
SFP-10G-AOC10M			

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)
N3K-C31128PQ-10GE (Native SFP+ ports)	SFP-10G-SR	When supported by transceiver module	NX-OS 7.0(3)I2(1a)
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
SFP-10G-AOC10M			
	SFP-10G-SR-S		NX-OS 7.0(3)I4(1)
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+ (40 channels)		
	SFP-10G-LRM (over SMF only)		NX-OS 7.0(3)I5(1)

Cisco Nexus 3200 Series

Network Device	Transceiver Model	Minimum Software Release Required		
		DOM Support	Software Release	
N3K-C3264Q N3K-C3232C (Native SFP+ Ports)	SFP-10G-SR	When supported by transceiver module	NX-OS 7.0(3)IX1(2)	
	SFP-H10GB-CU1M			
	SFP-10G-AOC1M			
	SFP-10G-AOC3M			
	SFP-H10GB-CU1-5M			NX-OS 7.0(3)I4(1)
	SFP-H10GB-CU2M			
	SFP-H10GB-CU2-5M			
	SFP-H10GB-CU3M			
	SFP-H10GB-CU5M			
	SFP-H10GB-ACU7M			
SFP-H10GB-ACU10M				
SFP-10G-AOC2M				
SFP-10G-AOC5M				

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

	SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-SR-S SFP-10G-LR SFP-10G-LR-S SFP-10G-ER SFP-10G-ER-S SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+ (40 channels)	
	SFP-10G-LRM (over SMF only)	NX-OS 7.0(3)I5(1)
N3K-C3232C (QSFP Ports with QSA adapter)	SFP-10G-SR SFP-10G-SR-S SFP-10G-LR SFP-10G-LR-S SFP-10G-ER SFP-10G-ER-S SFP-10G-ZR SFP-10G-ZR-S SFP-10G-LRM (over SMF only) DWDM SFP+ (40 channels) SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	NX-OS 7.0(3)I5(1)
N3K-C3232C (QSFP ports with SLIC adapter)	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M* SFP-H10GB-ACU10M* SFP-10G-AOC1M* SFP-10G-AOC2M* SFP-10G-AOC3M* SFP-10G-AOC5M* SFP-10G-AOC7M* SFP-10G-AOC10M* SFP-10G-SR* SFP-10G-SR-S*	NX-OS 7.0(3)I4(1)

* Up to 4 per SLIC adapter, up to 32 per switch through SLIC adapter

Cisco Nexus 3500 Series

Network Device	Transceiver Model	Minimum Software Release Required				
		DOM Support	Software Release			
N3K-C3548P-10G N3K-C3524P-10G	SFP-10G-SR	When supported by transceiver module	NX-OS 5.0(3)A1(1)			
	SFP-10G-LR					
	SFP-10G-ER					
	SFP-H10GB-CU1M					
	SFP-H10GB-CU3M					
	SFP-H10GB-CU5M					
	SFP-H10GB-ACU7M					
	SFP-H10GB-ACU10M					
	DWDM SFP+ (40 channels)		NX-OS 6.0(2)A1(1)			
	SFP-10G-SR-S		NX-OS 6.0(2)A6(8)			
	SFP-10G-LR-S					
	SFP-10G-ER-S					
	SFP-10G-ZR-S					
	SFP-H10GB-CU1-5M		NX-OS 6.0(2)A3(1)			
	SFP-H10GB-CU2M					
	SFP-H10GB-CU2-5M					
	SFP-10G-AOC1M					
	SFP-10G-AOC2M					
	SFP-10G-AOC3M					
	SFP-10G-AOC5M					
	SFP-10G-AOC7M					
	SFP-10G-ZR					
N3K-C3548P-10GX N3K-C3524P-10GX	SFP-10G-SR	When supported by transceiver module	NX-OS 6.0(2)A6(1)			
	SFP-10G-LR					
	SFP-10G-ER					
	SFP-10G-ZR					
	DWDM SFP+ (40 channels)					
	SFP-H10GB-CU1M					
	SFP-H10GB-CU1-5M					
	SFP-H10GB-CU2M					
	SFP-H10GB-CU2-5M					
	SFP-H10GB-CU3M					
	SFP-H10GB-CU5M					
	SFP-H10GB-ACU7M					
	SFP-H10GB-ACU10M					
	SFP-10G-AOC1M					
	SFP-10G-AOC2M					
	SFP-10G-AOC3M					
	SFP-10G-AOC5M					
	SFP-10G-AOC7M					
				SFP-10G-SR-S		NX-OS 6.0(2)A6(8)
	SFP-10G-LR-S					
	SFP-10G-ER-S					
	SFP-10G-ZR-S					

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

[Cisco Nexus 3600 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C36180YC-R	SFP-10G-SR SFP-10G-LR	NX-7.0(3)F3(1)	NX-7.0(3)F3(1)
	SFP-10G-AOC3M	-	

[Cisco Nexus 4000 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N4K-4001I-XPX	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	NX-OS 4.1(2)E1(1)	NX-OS 4.1(2)E1(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	NX-OS 4.1(2)E1(1)

[Cisco Nexus 5000 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N5K-C5020P-BF N5K-M1600 N5K-M1404	SFP-10G-SR SFP-10G-SR-S	NX-OS 4.0(0)N1(1)	NX-OS 4.0(0)N1(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	NX-OS 4.0(0)N1(1)
	SFP-10G-LR SFP-10G-LR-S	NX-OS 4.0(1a)N1(1)	NX-OS 4.0(1a)N1(1)
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 4.2(1)N2(1)
	FET-10G		NX-OS 4.2(1)N1(1)
N5K-C5010P-BF	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	NX-OS 4.0(1a)N1(1)	NX-OS 4.0(1a)N1(1)

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

Cisco Nexus 5000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	NX-OS 4.0(1a)N1(1)
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 4.2(1)N2(1)
	FET-10G	NX-OS 4.2(1)N1(1)	NX-OS 4.2(1)N1(1)
N5K-C5548P-FA N55-M16P N55-M8P8FP	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	NX-OS 5.0(2)N1(1)	NX-OS 5.0(2)N1(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.0(2)N1(1)
	FET-10G	NX-OS 5.0(2)N1(1)	NX-OS 5.0(2)N1(1)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)
N5K-C5548P-FA N55-M16UP	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S FET-10G	NX-OS 5.0(3)N1(1B)	NX-OS 5.0(3)N1(1B)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.0(3)N1(1B)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)
N5K-C5548UP-FA N5K-C5596UP-FA N55-M16UP N55-M16P N55-M8P8FP	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S FET-10G	NX-OS 5.0(3)N1(1B)	NX-OS 5.0(3)N1(1B)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.0(3)N1(1B)

Cisco Nexus 5000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-ER SFP-10G-ER-S	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)
N5K- 5672UP	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S FET-10G	NX-OS 7.0(1)N1(1)	NX-OS 7.0(1)N1(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 7.0(1)N1(1)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 7.0(1)N1(1)	NX-OS 7.0(1)N1(1)
N5K- 56128UP	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S FET-10G	NX-OS 7.0(2)N1(1)	NX-OS 7.0(2)N1(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 7.0(2)N1(1)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 7.0(2)N1(1)	NX-OS 7.0(2)N1(1)

Cisco Unified Computing System

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.0(3)N1(1B)
	SFP-10G-ER	NX-OS 5.1(3)N1(1)	NX-OS 5.1(3)N1(1)
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	UCS Manager v1.4(2)

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

Cisco Unified Computing System

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N10-S6200 N10-E0440 N10-E0600 N20-I6584	SFP-10G-SR SFP-10G-LR	UCS Manager v1.1(1)	UCS Manager v1.1(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	UCS Manager v1.1(1)
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	UCS Manager v1.4(2)
UCSB-5108-AC2 UCS-IOM-2204XP UCS-IOM-2208XP	SFP-10G-SR SFP-10G-LR FET-10G SFP-10G-SR-S SFP-10G-LR-S	—	UCS Manager v2.0(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M		
UCS-FI-6324UP	SFP-10G-SR SFP-10G-LR SFP-10G-SR-X	UCS Manager v3.0	UCS Manager v3.0
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M		
UCS-FI-6332-16UP-U	SFP-10G-SR SFP-10G-SR-S SFP-10G-LR SFP-10G-LR-S	UCS Manager v3.0	UCS Manager v3.0
	SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M		

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

Cisco Unified Computing System

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M FET-10G		
UCS-FI-6248UP UCS-FI-6296UP UCS-FI-E16UP	SFP-10G-SR SFP-10G-LR FET-10G SFP-10G-SR-S SFP-10G-LR-S	UCS Manager v2.0(1)	UCS Manager v2.0(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	UCS Manager v2.0(1)
UCSC-PCIE-CSC-02 (VIC 1225)	SFP-10G-SR SFP-10G-LR SFP-H10GB-CU1M= SFP-H10GB-CU3M= SFP-H10GB-CU5M= SFP-H10GB-ACU7M=	-	UCS Manager v2.0(2)
UCSC-MLOM-CSC-02 (VIC 1227)	SFP-10G-SR SFP-10G-LR SFP-H10GB-CU1M= SFP-H10GB-CU3M= SFP-H10GB-CU5M= SFP-H10GB-ACU7M=	-	UCS Manager v2.2(3)

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N7K-M132XP-12	SFP-10G-SR SFP-10G-SR-S	NX-OS 4.0 (1)	NX-OS 4.0 (1)
	SFP-10G-LR SFP-10G-LR-S	NX-OS 4.0 (3)	NX-OS 4.0 (3)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 4.2.6	NX-OS 4.2.6
	FET-10G	NX-OS 5.1	NX-OS 5.1

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M	—	—
	SFP-H10GB-CU3M	—	—
	SFP-H10GB-CU5M	—	—
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.1(2)
N7K-M108X2-12L	X2-10GB-SR X2-10GB-LR X2-10GB-LRM X2-10GB-ER DWDM X2	NX-OS 5.0	NX-OS 5.0
	X2-10GB-ZR	NX-OS 5.1	NX-OS 5.1
	X2-10GB-CX4 X2-10GB-LX4	—	NX-OS 5.1
N7K-M108X2-12L (With CVR-X2-SFP10G converter for X2 ports)	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	NX-OS 5.2
	SFP-10G-SR SFP-10G-SR-S	NX-OS 5.2	NX-OS 5.2
N7K-M108X2-12L (With OneX converter)	SFP-10G-LR SFP-10G-LR-S SFP-10G-LRM	NX-OS 5.2(3a)	NX-OS 5.2(3a)
N7K-M132XP-12L	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-LRM	NX-OS 5.1	NX-OS 5.1
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.1
	FET-10G	NX-OS 5.1	NX-OS 5.1
	SFP-10G-ZR SFP-10G-ZR-S DWDM SFP10G	NX-OS 6.1(1)	NX-OS 6.1(1)

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	NX-OS 6.2(2)	NX-OS 6.2(2)
	SFP-10G-BXD-I SFP-10G-BXU-I		NX-OS 7.2(0)D1(1)
N7K-F132XP-15	SFP-10G-SR SFP-10G-SR-S SFP-10G-LRM SFP-10G-LR SFP-10G-LR-S	NX-OS 5.1	NX-OS 5.1
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 5.1
	SFP-10G-ER SFP-10G-ER-S	NX-OS 5.2	NX-OS 5.2
	SFP-10G-ZR SFP-10G-ZR-S DWDM SFP10G	NX-OS 6.1(1)	NX-OS 6.1(1)
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	NX-OS 6.2(2)	NX-OS 6.2(2)
	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-ER FET-10G SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S	NX-OS 6.0	NX-OS 6.0

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required				
		DOM Support	Software Release			
	SFP-H10GB-CU1M	—	NX-OS 6.0			
	SFP-H10GB-CU3M					
	SFP-H10GB-CU5M					
	SFP-H10GB-ACU7M					
	SFP-H10GB-ACU10M					
	SFP-10G-ZR	NX-OS 6.1(1)	NX-OS 6.1(1)			
	SFP-10G-ZR-S					
	DWDM SFP10G					
	SFP-H10GB-CU1-5M	NX-OS 6.2(2)	NX-OS 6.2(2)			
	SFP-H10GB-CU2M					
	SFP-H10GB-CU2-5M					
	SFP-10G-AOC1M					
	SFP-10G-AOC2M					
	SFP-10G-AOC3M					
	SFP-10G-AOC5M					
	SFP-10G-AOC7M					
	SFP-10G-AOC10M					
				SFP-10G-BXD-I		NX-OS 7.2(0)D1(1)
SFP-10G-BXU-I						
N7K-F248XP-25E	SFP-10G-SR	NX-OS 6.1(2)	NX-OS 6.1(2)			
	SFP-10G-LRM					
	SFP-10G-LR Error! Bookmark not defined.					
	SFP-10G-ER					
	SFP-10G-SR-S					
	SFP-10G-LR-S					
	SFP-10G-ER-S					
	FET-10G					
				SFP-H10GB-CU1M	—	NX-OS 6.1(2)
				SFP-H10GB-CU3M		
SFP-H10GB-CU5M						
SFP-H10GB-ACU7M						
SFP-H10GB-ACU10M						
	SFP-10G-ZR	NX-OS 6.1(2)	NX-OS 6.1(2)			
	SFP-10G-ZR-S					
	DWDM SFP10G					
	SFP-H10GB-CU1-5M	NX-OS 6.2(2)	NX-OS 6.2(2)			
	SFP-H10GB-CU2M					
	SFP-H10GB-CU2-5M					
	SFP-10G-AOC1M					
	SFP-10G-AOC2M					
	SFP-10G-AOC3M					
	SFP-10G-AOC5M					
	SFP-10G-AOC7M					
	SFP-10G-AOC10M					

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-BXD-I SFP-10G-BXU-I		NX-OS 7.2(0)D1(1)
N7K-M224XP-23L	SFP-10G-SR SFP-10G-LRM SFP-10G-LR Error! Bookmark not defined. SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S FET-10G	NX-OS 6.1(1)	NX-OS 6.1(1)
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 6.1(1)
	SFP-10G-ZR SFP-10G-ZR-S	NX-OS 6.1(1)	NX-OS 6.1(1)
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	NX-OS 6.2(2)	NX-OS 6.2(2)
	SFP-10G-BXD-I SFP-10G-BXU-I		NX-OS 7.2(0)D1(1)
N7K-F348XP-25	FET-10G SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-ZR SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	NX-OS 6.2(12)	NX-OS 6.2(12)

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-LRM ³ SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M DWDM-SFP+		
	SFP-10G-BXD-I SFP-10G-BXU-I		NX-OS 7.2(0)D1(1)
	CWDM-SFP10G-xxxx	-	NX-OS 8.0(1)
N7K-M348XP-25L	SFP-10G-SR SFP-10G-LR SFP-10G-LRM SFP-10G-ER SFP-10G-ZR SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S DWDM SFP10G CWDM-SFP10G-xxxx SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-BXD-I SFP-10G-BXU-I		NX-OS 8.0(1)
	FET-10G		NX-OS 8.1(1)

³MMF support on ports 41 to 48 only, SMF support on all ports.

Cisco Nexus 7700 Series

Network Device	Transceiver Model	Minimum Software Release Required			
		DOM Support	Software Release		
N77-F248XP-23E	SFP-10G-SR	NX-OS 6.2(2)	NX-OS 6.2(2)		
	SFP-10G-LRM				
	SFP-10G-LR				
	SFP-10G-ER				
	SFP-10G-ZR				
	SFP-10G-SR-S				
	SFP-10G-LR-S				
	SFP-10G-ER-S				
	SFP-10G-ZR-S				
	FET-10G				
	SFP-H10GB-CU1M				
	SFP-H10GB-CU1-5M				
	SFP-H10GB-CU2M				
	SFP-H10GB-CU2-5M				
	SFP-H10GB-CU3M				
	SFP-H10GB-CU5M				
	SFP-H10GB-ACU7M				
	SFP-H10GB-ACU10M				
	SFP-10G-AOC1M				
	SFP-10G-AOC2M				
	SFP-10G-AOC3M				
	SFP-10G-AOC5M				
	SFP-10G-AOC7M				
SFP-10G-AOC10M					
SFP-10G-BXD-I		NX-OS 7.2(0)D1(1)			
SFP-10G-BXU-I					
N77-F348XP-23	FET-10G	NX-OS 6.2(6)	NX-OS 6.2(6)		
	SFP-10G-SR				
	SFP-10G-LR				
	SFP-10G-ER				
	SFP-10G-ZR				
	DWDM-SFP+				
	SFP-10G-LRM ⁴			NX-OS 6.2(8)	NX-OS 6.2(8)
	SFP-H10GB-CU1M			—	NX-OS 6.2(8)
	SFP-H10GB-CU1-5M				
	SFP-H10GB-CU2M				
	SFP-H10GB-CU2-5M				
	SFP-H10GB-CU3M				
	SFP-H10GB-CU5M				
SFP-H10GB-ACU7M					
SFP-H10GB-ACU10M					

⁴MMF support on ports 41 to 48 only, SMF support on all ports.

Cisco Nexus 7700 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	NX-OS 6.2(10)
	SFP-10G-BXD-I SFP-10G-BXU-I	—	NX-OS 7.2(0)D1(1)
	SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S		NX-OS 7.3(2)D1(1)
	CWDM-SFP10G-xxxx	-	NX-OS 8.0(1)
N77-M348XP-23L	SFP-10G-LRM	-	NX-OS 7.3(0)DX(1)
	SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S		NX-OS 7.3(2)D1(1)
	CWDM-SFP10G-xxxx	-	NX-OS 8.0(1)
	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-ZR DWDM SFP10G CWDM-SFP10G-xxxx SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-BXD-I SFP-10G-BXU-I		NX-OS 7.3(0)DX(1)
	FET-10G		NX-OS 8.1(1)

[Cisco Nexus 9000 Series](#) (Modular 9500) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required			
		DOM Support	Software Release		
N9K-X9564PX (downlinks) (NX-OS Mode)	SFP-10G-SR	NX-OS 6.1(2)I1(1)	NX-OS 6.1(2)I1(1)		
	SFP-10G-LR				
	SFP-10G-SR-S				
	SFP-10G-LR-S				
	SFP-H10GB-CU1M			—	NX-OS 6.1(2)I2(1)
	SFP-H10GB-CU2M				
	SFP-H10GB-CU3M				
	SFP-H10GB-CU5M				
	SFP-H10GB-ACU7M				
	SFP-H10GB-ACU10M				
SFP-10G-LRM* (supported in SMF upto 300m)		NX-OS 6.1(2)I3(2)			
SFP-10G-AOC1M	—	NX-OS 6.1(2)I2(2a)			
SFP-10G-AOC2M					
SFP-10G-AOC3M					
SFP-10G-AOC5M					
SFP-10G-AOC7M					
SFP-10G-AOC10M					
SFP-10G-ER	NX-OS 6.1(2)I2(2)	NX-OS 6.1(2)I2(2)			
SFP-10G-ER-S					
SFP-10G-BXD-I	—	NX-OS 7.0(3)I3.1			
SFP-10G-BXU-I					
CWDM SFP+					
SFP10G-USR	—	NX-OS 7.0(3)I1(2)			
SFP-10G-ZR					
SFP-10G-ZR-S					
DWDM SFP+					
FET-10G					
SFP-10G-BX40D-I		NX-OS 7.0(3)I5(2)			
SFP-10G-BX40U-I					

[Cisco Nexus 9000 Series](#) (Modular 9500) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required			
		DOM Support	Software Release		
N9K-X9464PX (NX-OS Mode)	SFP-H10GB-CU1M	—	NX-OS 6.1(2)I2(2a)		
	SFP-H10GB-CU2M				
	SFP-H10GB-CU3M				
	SFP-H10GB-CU5M				
	SFP-H10GB-ACU7M				
	SFP-H10GB-ACU10M				
	SFP-10G-AOC1M				
	SFP-10G-AOC2M				
	SFP-10G-AOC3M				
	SFP-10G-AOC5M				
	SFP-10G-AOC7M				
	SFP-10G-AOC10M				
	SFP-10G-LRM* (supported in SMF upto 300m)				NX-OS 6.1(2)I3(2)
	SFP-10G-SR			NX-OS 6.1(2)I2(2a)	NX-OS 6.1(2)I2(2a)
SFP-10G-LR					
SFP-10G-ER					
SFP-10G-SR-S					
SFP-10G-LR-S					
SFP-10G-ER-S					
SFP10G-USR	—	NX-OS 6.1(2)I3(1)			
SFP-10G-BXD-I	—	NX-OS 7.0(3)I3.1			
SFP-10G-BXU-I					
CWDM SFP+					
SFP-10G-ZR	—	NX-OS 7.0(3)I1(2)			
SFP-10G-ZR-S					
DWDM SFP+					
FET-10G					
SFP-10G-BX40D-I		NX-OS 7.0(3)I5(2)			
SFP-10G-BX40U-I					
N9K-X97160YC-EX (downlinks) (NX-OS Mode)	SFP-H10GB-CU1M		NX-OS 703I5.2		
	SFP-H10GB-CU2M				
	SFP-H10GB-CU3M				
	SFP-H10GB-CU5M				
	SFP-H10GB-ACU7M				
	SFP-H10GB-ACU10M				
	SFP-10G-AOC1M				
	SFP-10G-AOC2M				
	SFP-10G-AOC3M				
	SFP-10G-AOC5M				
	SFP-10G-AOC7M				
	SFP-10G-AOC10M				
	QSFP-4X10G-AOC1M				
	QSFP-4X10G-AOC3M				

[Cisco Nexus 9000 Series](#) (Modular 9500) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	QSFP-4X10G-AOC5M QSFP-4X10G-AOC7M QSFP-4X10G-AOC10M SFP-H10GB-CU1-5M SFP-H10GB-CU2-5M SFP10G-USR DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M QSFP-4X10G-AC7M QSFP-4X10G-AC10M FET-10G SFP-10G-LRM (supported in SMF up to 300m) SFP-10G-BX40D-I SFP-10G-BX40U-I SFP-10G-BXD-I SFP-10G-BXU-I		
	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR SFP-10G-ZR-S	NX-OS 703I5.2	NX-OS 703I5.2

[Cisco Nexus 9000 Series](#) (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C9396PX (NX-OS Mode)	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	NX-OS 6.1(2)I2(1)	NX-OS 6.1(2)I2(1)
	SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M	—	NX-OS 6.1(2)I2(1)
	FET-10G	—	NX-OS 6.1(2)I2(3)

[Cisco Nexus 9000 Series](#) (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M QSFP-4X10G-AOC1M QSFP-4X10G-AOC3M QSFP-4X10G-AOC5M QSFP-4X10G-AOC7M QSFP-4X10G-AOC10M	—	NX-OS 6.1(2)I2(2a)
	SFP-10G-ER SFP-10G-ER-S	NX-OS 6.1(2)I2(2)	NX-OS 6.1(2)I2(2)
	SFP-10G-LRM (supported in SMF upto 300m) SFP-H10GB-CU1-5M SFP-H10GB-CU2-5M	—	NX-OS 6.1(2)I3(2)
	SFP-10G-BXD-I SFP-10G-BXU-I CWDM SFP+	—	NX-OS 7.0(3)I3.1
	SFP10G-USR SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M QSFP-4X10G-AC7M QSFP-4X10G-AC10M	—	NX-OS 7.0(3)I1(2)
	SFP-10G-BX40D-I SFP-10G-BX40U-I		NX-OS 7.0(3)I5(2)
N9K-C9372PX (downlinks) (NX-OS Mode)	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S	NX-OS 6.1(2)I3(1)	NX-OS 6.1(2)I3(2)

Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M FET-10G SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M QSFP-4X10G-AOC1M QSFP-4X10G-AOC3M QSFP-4X10G-AOC5M QSFP-4X10G-AOC7M QSFP-4X10G-AOC10M	—	NX-OS 6.1(2)I3(1)
	SFP-H10GB-CU1-5M SFP-H10GB-CU2-5M SFP-10G-LRM (supported in SMF up to 300m)	—	NX-OS 6.1(2)I3(2)
	SFP-10G-BXD-I SFP-10G-BXU-I CWDM SFP+	—	NX-OS 7.0(3)I3.1
	SFP10G-USR SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M QSFP-4X10G-AC7M QSFP-4X10G-AC10M	—	NX-OS 7.0(3)I1(2)
	SFP-10G-BX40D-I SFP-10G-BX40U-I		NX-OS 7.0(3)I5(2)
N9K-C9372PX-E (downlinks) (NX-OS Mode)	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR SFP-10G-ZR-S	NX-OS 7.0(3)I2(1)	NX-OS 7.0(3)I2(1)

Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M FET-10G SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M QSFP-4X10G-AOC1M QSFP-4X10G-AOC3M QSFP-4X10G-AOC5M QSFP-4X10G-AOC7M QSFP-4X10G-AOC10M SFP-H10GB-CU1-5M SFP-H10GB-CU2-5M SFP-10G-LRM* *(supported in SMF up to 300m) SFP10G-USR DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M QSFP-4X10G-AC7M QSFP-4X10G-AC10M	—	NX-OS 7.0(3)I2(1)
	SFP-10G-BXD-I SFP-10G-BXU-I CWDM SFP+	—	NX-OS 7.0(3)I3.1
	SFP-10G-BX40D-I SFP-10G-BX40U-I		NX-OS 7.0(3)I5(2)
N9K-C93180YC-EX (downlinks) (NX-OS Mode)	FET-10G SFP-10G-LRM* *(supported in SMF up to 300m)		NX-OS 703I5.1
	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR SFP-10G-ZR-S	NX-OS 703I4.2	NX-OS 703I4.2

Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M QSFP-4X10G-AOC1M QSFP-4X10G-AOC3M QSFP-4X10G-AOC5M QSFP-4X10G-AOC7M QSFP-4X10G-AOC10M SFP-H10GB-CU1-5M SFP-H10GB-CU2-5M SFP10G-USR DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M QSFP-4X10G-AC7M QSFP-4X10G-AC10M	-	NX-OS 70314.2
	SFP-10G-BX40D-I SFP-10G-BX40U-I SFP-10G-BXD-I SFP-10G-BXU-I	—	NX-OS 70315.2
N9K-C9348GC-FXP (NX-OS Mode)	(Supported on ports 49 through 52 only) - SFP-H10G-CU1M SFP-H10G-CU2M SFP-H10G-CU3M SFP-H10G-CU5M SFP-H10G-ACU7M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-SR SFP-10G-SR-S SFP-10G-LR SFP-10G-LR-S SFP-10G-ER SFP-10G-ER-S SFP-10G-ZR	-	NXOS-70317.1

Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-ZR-S		
N9K-C93180YC-FX (downlinks) (NX-OS Mode)	FET-10G SFP-10G-LRM* *(supported in SMF up to 300m) SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR SFP-10G-ZR-S SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M QSFP-4X10G-AOC1M QSFP-4X10G-AOC3M QSFP-4X10G-AOC5M QSFP-4X10G-AOC7M QSFP-4X10G-AOC10M SFP-H10GB-CU1-5M SFP-H10GB-CU2-5M SFP10G-USR DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M QSFP-4X10G-AC7M QSFP-4X10G-AC10M SFP-10G-BX40D-I SFP-10G-BX40U-I SFP-10G-BXD-I SFP-10G-BXU-I	-	NXOS-703I7.1
N9K-C9364C (NX-OS Mode)	(Supported on ports 65 and 66 only) SFP-10G-SR SFP-10G-ER SFP-10G-SR-S SFP-10G-ER-S	-	NXOS-703I7.2

[Cisco Nexus 9000 Series](#) (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-ZR		
	SFP-10G-ZR-S		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1.5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2.5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	(10G breakout end only)		
	QSFP-4X10G-AOC1M		
	QSFP-4X10G-AOC2M		
	QSFP-4X10G-AOC3M		
	QSFP-4X10G-AOC5M		
	QSFP-4X10G-AOC10M		

[Cisco Nexus 9000 Series](#) (Fixed 9200) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C92160YC-X (NX-OS Mode)	SFP-10G-SR	NX-OS 7.0(3)I3.1	NX-OS 7.0(3)I3.1
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR		
	SFP-10G-ZR-S		

[Cisco Nexus 9000 Series](#) (Fixed 9200) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M QSFP-4X10G-AOC1M (Supported on port 50, 52) QSFP-4X10G-AOC3M (Supported on port 50, 52) QSFP-4X10G-AOC5M (Supported on port 50, 52) QSFP-4X10G-AOC7M (Supported on port 50, 52) QSFP-4X10G-AOC10M (Supported on port 50, 52) QSFP-4SFP10G-CU1M (Supported on port 50, 52) QSFP-4SFP10G-CU3M (Supported on port 50, 52) QSFP-4SFP10G-CU5M (Supported on port 50, 52) SFP-H10GB-CU1-5M SFP-H10GB-CU2-5M SFP-10G-LRM (Supported in SMF up to 300m) SFP10G-USR DWDM SFP+	-	NX-OS 7.0(3)I3.1
N9K-C9236C (NX-OS Mode)	(QSFP ports with SLIC adapter) SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M* SFP-H10GB-ACU10M* SFP-10G-AOC1M* SFP-10G-AOC2M* SFP-10G-AOC3M* SFP-10G-AOC5M* SFP-10G-AOC7M* SFP-10G-AOC10M* SFP-10G-SR* SFP-10G-SR-S*	-	NX-OS 7.0(3)I4(1)

[Cisco Nexus 9000 Series](#) (Fixed 9200) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	(QSFP ports with QSA: CVR-QSFP-SFP10G) w/ SFP-10G-SR w/ SFP-10G-LR w/ SFP-10G-ER w/ SFP-10G-SR-S w/ SFP-10G-LR-S w/ SFP-10G-ER-S w/ SFP-H10GB-CU1M w/ SFP-H10GB-CU3M w/ SFP-H10GB-CU5M w/ SFP-H10GB-ACU7M w/ SFP-H10GB-ACU10M w/ SFP-10G-AOC1M w/ SFP-10G-AOC2M w/ SFP-10G-AOC3M w/ SFP-10G-AOC5M w/ SFP-10G-AOC7M w/ SFP-10G-AOC10M	-	NX-OS-703I5.1
N9K-C92300YC (NX-OS Mode)	SFP-10G-SR SFP-10G-LR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR SFP-10G-ZR-S	NXOS-703I6.1	NXOS-703I6.1
	SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-LRM (Supported in SMF up to 300m) SFP10G-USR DWDM SFP+	-	NXOS-703I6.1

* Up to 4 per SLIC adapter, up to 32 per switch through SLIC adapter

[Cisco Nexus 9000 Series](#) (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C9396PX (ACI Mode)	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S FET-10G SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	ACI-N9KDK9-11.0
	SFP-10G-ER SFP-10G-ER-S SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M		ACI-N9KDK9-11.0(2j)
	SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M		ACI-N9KDK9-11.0(3f)
N9K-C9372PX (downlinks) (ACI Mode)	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S FET-10G SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-ER SFP-10G-ER-S SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+		ACI-N9KDK9-11.0(3f)

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Data Center and Blade Switching Minimum Software Release Requirements

[Cisco Nexus 9000 Series](#) (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M		
N9K-C9372PX-E (downlinks) (ACI Mode)	SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S FET-10G SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-ER SFP-10G-ER-S SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M		ACI-N9KDK9-11.1(2h)

[Cisco Nexus 9000 Series](#) (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C93180YC-EX (downlinks) (ACI Mode)	SFP-10G-SR	-	ACI-N9KDK9-11.3
	SFP-10G-LR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	FET-10G		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-ER		
	SFP-10G-ER-S		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-ZR		
SFP-10G-ZR-S			
DWDM SFP+			
QSFP-4SFP10G-CU1M			
QSFP-4SFP10G-CU3M			
QSFP-4SFP10G-CU5M			
CWDM SFP+	-	ACI-N9KDK9-12.2A	

[Cisco Nexus 9000 Series](#) (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C93180YC-FX (downlinks) (ACI Mode)	SFP-10G-SR	-	ACI-N9KDK9-12.2A
	SFP-10G-LR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	FET-10G		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-ER		
	SFP-10G-ER-S		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-ZR		
	SFP-10G-ZR-S		
	DWDM SFP+		
	QSFP-4SFP10G-CU1M		
QSFP-4SFP10G-CU3M			
QSFP-4SFP10G-CU5M			
CWDM SFP+			

[Cisco Nexus 9000 Series](#) (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required			
		DOM Support	Software Release		
N9K-C9364C (ACI Mode)	(Ports 65/66 SFP+ are supported natively)	-	ACI-N9KDK9-13.0		
	SFP-10G-SR				
	SFP-10G-LR				
	SFP-10G-SR-S				
	SFP-10G-LR-S				
	SFP-10G-AOC1M				
	SFP-10G-AOC2M				
	SFP-10G-AOC3M				
	SFP-10G-AOC5M				
	SFP-10G-AOC7M				
	SFP-10G-AOC10M				
	SFP-10G-ER				
	SFP-10G-ER-S				
	SFP-H10GB-CU1M				
	SFP-H10GB-CU2M				
	SFP-H10GB-CU3M				
	SFP-H10GB-CU5M				
	SFP-H10GB-ACU7M				
	SFP-H10GB-ACU10M				
	SFP-10G-ZR				
	SFP-10G-ZR-S				
	DWDM SFP+				
	QSFP-4SFP10G-CU1M				
	QSFP-4SFP10G-CU3M				
	QSFP-4SFP10G-CU5M				
	CWDM SFP+				
	(Ports 1 - 48 are supported only w/ QSA (CVR-QSFP-SFP10G))				
	QSA (CVR-QSFP-SFP10G)				
w/ SFP-10G-SR					
w/ SFP-10G-LR					
w/ SFP-10G-ZR					
w/ SFP-10G-SR-S					
w/ SFP-10G-LR-S					

[Cisco Nexus 9000 Series](#) (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C9348GC-FXP (ACI Mode)	(Supported on ports 49-52 only) SFP-10G-SR SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-ER SFP-10G-ER-S SFP-H10GB-CU1M SFP-H10GB-CU2M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+ QSFP-4SFP10G-CU1M QSFP-4SFP10G-CU3M QSFP-4SFP10G-CU5M CWDM SFP+	-	ACI-N9KDK9-13.0

Cisco MDS 9000 Series

Refer to the [Cisco MDS 9000 Family Pluggable Transceivers Data Sheet](#).

Catalyst 2XXX and 3XXX Switch Support and Minimum Software Release Requirements

[Catalyst 2960-S Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960S-48FPD-L	SFP-H10GB-CU1M	—	12.2(53)SE1
WS-C2960S-48LPD-L	SFP-H10GB-CU3M		
WS-C2960S-24PD-L	SFP-H10GB-CU5M		

[Catalyst 2960-S Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960S-48TD-L WS-C2960S-24TD-L	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	12.2(53)SE1	12.2(53)SE1
	SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+	15.2(1)E	15.2(1)E
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	15.2(2)E

[Catalyst 2960-X Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960X-24TD-L WS-C2960X-24PD-L WS-C2960X-48TD-L WS-C2960X-48LPD-L WS-C2960X-48FPD-L	SFP-10G-LR SFP-10G-SR SFP-10G-LRM SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S	15.0(2)EX	15.0(2)EX
	SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+	15.2(2)E3	15.2(2)E3

Catalyst 2960-X Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	15.2(2)E
C2960X-HYBRID-STK C2960X-FIBER-STK	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M SFP-10G-SR SFP-10G-LR SFP-10G-LRM SFP-10G-ER SFP-10G-ZR SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S DWDM-SFP+	-	15.2(6)E/3.10.0E

[Catalyst 2960-XR Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960XR-24TD-I WS-C2960XR-48TD-I WS-C2960XR-24PD-I WS-C2960XR-48LPD-I WS-C2960XR-48FPD-I	SFP-10G-LR SFP-10G-SR SFP-10G-LRM SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S	15.0(2)EX1	15.0(2)EX1
	SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+	15.2(2)E3	15.2(2)E3
	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	15.2(2)E

[Catalyst 2960-L Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960L-24TQ-LL WS-C2960L-24PQ-LL WS-C2960L-48TQ-LL WS-C2960L-48PQ-LL	SFP-10G-LR SFP-10G-SR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S	15.2(6)E	15.2(6)E
	SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M	—	15.2(6)E

Catalyst 2960-L Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M		

Catalyst 3560-E Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560E-24TD WS-C3560E-24PD WS-C3560E-48TD WS-C3560E-48PD WS-C3560E-48PDF	X2-10GB-LR X2-10GB-ER X2-10GB-LX4 X2-10GB-SR X2-10GB-CX4	12.2(46)SE	12.2(35)SE2
	X2-10GB-LRM	12.2(46)SE	12.2(40)SE
	X2-10GB-ZR	12.2(50)SE	12.2(50)SE
	DWDM X2	12.2(52)SE	12.2(52)SE
WS-C3560E-12D WS-C3560E-12SD	X2-10GB-LR X2-10GB-ER X2-10GB-LX4 X2-10GB-SR X2-10GB-CX4 X2-10GB-LRM	12.2(46)SE	12.2(40)EX
	X2-10GB-ZR	12.2(50)SE	12.2(50)SE
	DWDM X2	12.2(52)SE	12.2(52)SE
WS-C3560E-24TD WS-C3560E-24PD WS-C3560E-48TD WS-C3560E-48PD WS-C3560E-48PDF WS-C3560E-12D WS-C3560E-12SD (With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR SFP-10G-LR SFP-10G-LRM SFP-10G-SR-S SFP-10G-LR-S SFP-H10GB-CU1M SFP-H10GB-CU3M7 SFP-H10GB-CU5M7	12.2(55)SE1 —	12.2(55)SE1 12.2(55)SE1

Catalyst 3560-X Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560X-24T	SFP-H10GB-CU1M	—	12.2(53)SE
WS-C3560X-48T	SFP-H10GB-CU3M7		
WS-C3560X-24P	SFP-H10GB-CU5M7		
WS-C3560X-48P			
WS-C3560X-48PF (With C3KX-NM-10G and C3KX-SM-10G uplink modules)	SFP-10G-SR	12.2(53)SE	12.2(53)SE
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER	15.0(2)SE	15.0(2)SE
	SFP-10G-ER-S		
	SFP-10G-ZR	15.2(1)E	15.2(1)E
	SFP-10G-ZR-S		
	DWDM SFP+		
	SFP-H10GB-CU1-5M	—	15.2(2)E
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

Catalyst 3560-CX Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560CX-12PD-S	SFP-10G-LR	15.2(3)E	15.2(3)E
WS-C3560CX-8XPD-S	SFP-10G-SR		
	SFP-10G-LRM		
	SFP-10G-ER		
	SFP-10G-ZR		
	DWDM SFP+		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		

Catalyst 3560-CX Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

Catalyst 3650 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3650-24TD	SFP-H10GB-CU1M	—	XE 3.3.0SE
WS-C3650-48TD	SFP-H10GB-CU3M		
WS-C3650-24PD	SFP-H10GB-CU5M		
WS-C3650-48PD			
WS-C3650-48FD	SFP-10G-SR	XE 3.3.0SE	XE 3.3.0SE
WS-C3650-48FQ	SFP-10G-LRM		
WS-C3650-48PQ	SFP-10G-LR		
WS-C3650-48TQ	SFP-10G-ER		
WS-C3650-24PDM ³	SFP-10G-SR-S		
WS-C3650-48FQM ³	SFP-10G-LR-S		
WS-C3650-8X24UQ ³	SFP-10G-ER-S		
WS-C3650-12X48UQ ³	SFP-10G-ZR	XE 3.3.3SE	XE 3.3.3SE
WS-C3650-12X48UR ³	SFP-10G-ZR-S		
WS-C3650-12X48UZ ³	DWDM SFP+		
	CWDM SFP+	XE 3.7.0E	XE 3.7.0E
	SFP-H10GB-CU1-5M	—	XE 3.6.0E
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-BXD-I	XE 3.7.1E	XE 3.7.1E
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		

³-These models are supported on Cisco IOS Release XE 16.2.1 and above only.

[Catalyst 3750 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3750G-16TD	XENPAK-10GB-ER C3-XENPAK10GB-LR	—	12.2(18)SE

[Catalyst 3750-E Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3750E-24TD	X2-10GB-LR	12.2(46)SE	12.2(35)SE2
WS-C3750E-24PD	X2-10GB-ER		
WS-C3750E-48TD	X2-10GB-LX4		
WS-C3750E-48PD	X2-10GB-SR		
WS-C3750E-48PDF	X2-10GB-CX4		
	X2-10GB-LRM	12.2(46)SE	12.2(40)SE
	X2-10GB-ZR	12.2(50)SE	12.2(50)SE
	DWDM X2	12.2(52)SE	12.2(52)SE
WS-C3750E-24TD	SFP-10G-SR	12.2(55)SE1	12.2(55)SE1
WS-C3750E-24PD	SFP-10G-LR		
WS-C3750E-48TD	SFP-10G-LRM		
WS-C3750E-48PD	SFP-10G-SR-S		
WS-C3750E-48PDF	SFP-10G-LR-S		
(With CVR-X2-SFP10G converter for X2 ports)	SFP-H10GB-CU1M	—	12.2(55)SE1
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
WS-C3750X-24T	SFP-H10GB-CU1M	—	12.2(53)SE
WS-C3750X-48T	SFP-H10GB-CU3M		
WS-C3750X-24P	SFP-H10GB-CU5M		
WS-C3750X-48P			
WS-C3750X-48PF	SFP-10G-SR	12.2(53)SE	12.2(53)SE
(With C3KX-NM-10G and C3KX-SM-10G uplink modules)	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER	15.0(2)SE	15.0(2)SE
	SFP-10G-ER-S		
	SFP-10G-ZR	15.2(1)E	15.2(1)E
	SFP-10G-ZR-S		
	DWDM SFP+		

Catalyst 3750-E Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	15.2(2)E
WS-C3750X-12S WS-C3750X-24S (With C3KX-NM-10G and C3KX-SM-10G uplink modules)	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	12.2(55)SE5
	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	12.2(55)SE5	12.2(55)SE5
	SFP-10G-ER SFP-10G-ER-S	15.0(2)SE	15.0(2)SE
	SFP-10G-ZR SFP-10G-ZR-S DWDM SFP+	15.2(1)E	15.2(1)E
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	15.2(2)E

Catalyst 3850 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3850-24T	SFP-H10GB-CU1M	—	XE 3.2.0SE
WS-C3850-24P	SFP-H10GB-CU3M		
WS-C3850-48T	SFP-H10GB-CU5M		
WS-C3850-48P			
WS-C3850-48F (With C3850-NM-2-10G or C3850-NM-4-10G uplink modules)	SFP-10G-SR	XE 3.2.0SE	XE 3.2.0SE
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR	XE 3.3.3SE	XE 3.3.3SE
	SFP-10G-ZR-S		
	DWDM SFP+		
	CWDM SFP+	XE 3.7.0	XE 3.7.0
	SFP-H10GB-CU1-5M	—	XE 3.6.0E
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-BXD-I	XE 3.7.1E	XE 3.7.1E
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		

Catalyst 3850 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3850-12XS	SFP-10G-SR	XE 3.7.1E	XE 3.7.1E
WS-C3850-16XS	SFP-10G-LRM		
WS-C3850-24XS	SFP-10G-LR		
WS-C3850-32XS	SFP-10G-ER		
(C3850-NM-8-10G uplink modules)	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+		
	CWDM SFP+		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
SFP-10G-AOC10M			
SFP-10G-BXD-I			
SFP-10G-BXU-I			
SFP-10G-BX40D-I			
SFP-10G-BX40U-I			

Catalyst 3850 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3850-48XS-S	SFP-10G-SR	XE 3.7.2	XE 3.7.2
WS-C3850-48XS-E	SFP-10G-LRM		
WS-C3850-48XS-F-S	SFP-10G-LR		
WS-C3850-48XS-F-E	SFP-10G-ER		
WS-C3850-48XS	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+		
	CWDM SFP+		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	SFP-10G-BXD-I		
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		
WS-C3850-12S	SFP-H10GB-CU1M	—	XE 3.3.3SE
WS-C3850-24S	SFP-H10GB-CU3M		
(With C3850-NM-2-10G or C3850-NM-4-10G or C3850-NM-8-10G uplink modules)	SFP-H10GB-CU5M		
	SFP-10G-SR	XE 3.3.3SE	XE 3.3.3SE
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+		
	CWDM SFP+	XE 3.7.0	XE 3.7.0

Catalyst 3850 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	XE 3.6.0E
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I	XE 3.7.1E	XE 3.7.1E

Catalyst 4XXX Switch Support and Minimum Software Release Requirements

Catalyst 4500 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-X4516-10GE	X2-10GB-CX4 X2-10GB-LX4	—	12.2(25)EW
	X2-10GB-LR X2-10GB-SR X2-10GB-ER	12.2(54)SG	12.2(25)EW
	X2-10GB-LRM	12.2(54)SG	12.2(31)SGA
	X2-10GB-ZR	12.2(54)SG	12.2(50)SG
	DWDM X2	12.2(50)SG	12.2(50)SG
WS-X4516-10GE (With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	12.2(54)SG	12.2(54)SG

[Catalyst 4500 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	12.2(54)SG
WS-X4013+10GE	X2-10GB-CX4 X2-10GB-LX4	—	12.2(25)SG
	X2-10GB-LR X2-10GB-SR X2-10GB-ER	12.(54)SG	12.2(25)SG
	X2-10GB-LRM	12.2(54)SG	12.2(31)SGA
	X2-10GB-ZR	12.2(54)SG	12.2(50)SG
	DWDM X2	12.2(50)SG	12.2(50)SG
WS-X4013+10GE (With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	12.2(54)SG	12.2(54)SG
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	12.2(54)SG
WS-X45-SUP6L-E	X2-10GB-CX4 X2-10GB-LX4	—	12.2(52)XO
	X2-10GB-LR X2-10GB-SR X2-10GB-ER X2-10GB-LRM X2-10GB-ZR	12.2(54)SG	12.2(52)XO
	X2-10GB-T	15.1(2)SG	15.1(2)SG
	DWDM X2	12.2(52)XO	12.2(52)XO
WS-X45-SUP6-E WS-X4606-X2-E	X2-10GB-CX4 X2-10GB-LX4	—	12.2(40)SG
	X2-10GB-LR X2-10GB-SR X2-10GB-ER X2-10GB-LRM	12.2(54)SG	12.2(40)SG
	X2-10GB-ZR	12.2(54)SG	12.2(50)SG
	X2-10GB-T	15.1(2)SG	15.1(2)SG

Catalyst 4500 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	DWDM X2	12.2(50)SG	12.2(50)SG
WS-X45-SUP6-E WS-X4606-X2-E (With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR	12.2(54)SG	12.2(50)SG
	SFP-10G-SR-S		
	SFP-10G-LRM	12.2(54)SG	12.2(54)SG
	SFP-10G-LR SFP-10G-LR-S		
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	12.2(53)SG1
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M	—	15.2(2)E
WS-X45-SUP6L-E (With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR	12.2(54)SG	12.2(52)XO
	SFP-10G-SR-S		
	SFP-10G-LRM	12.2(54)SG	12.2(54)SG
	SFP-10G-LR SFP-10G-LR-S		
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	12.2(53)SG1
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M	—	15.2(2)E
WS-X4712-SFP+E WS-X45-SUP7-E	SFP-10G-SR	3.1.0SG	3.1.0SG
	SFP-10G-LRM		
	SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S		
	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	3.1.0SG
	SFP-10G-ER SFP-10G-ZR SFP-10G-ER-S SFP-10G-ZR-S	3.2.0SG	3.2.0SG
	DWDM SFP+	3.5.0E	3.5.0E

Catalyst 4500 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-BXD-I	3.8.0E	3.8.0E
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		
	SFP-H10GB-CU1-5M	—	3.6.0E
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
SFP-10G-AOC2M			
SFP-10G-AOC3M			
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			
WS-X45-SUP7L-E	SFP-10G-SR	3.2.0XO	3.2.0XO
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	SFP-H10GB-CU1M	—	3.2.0XO
SFP-H10GB-CU3M			
SFP-H10GB-CU5M			
DWDM SFP+	3.5.0E	3.5.0E	
SFP-10G-BXD-I	3.8.0E	3.8.0E	
SFP-10G-BXU-I			
SFP-10G-BX40D-I			
SFP-10G-BX40U-I			
SFP-H10GB-CU1-5M	—	3.6.0E	
SFP-H10GB-CU2M			
SFP-H10GB-CU2-5M			
SFP-H10GB-ACU7M			
SFP-H10GB-ACU10M			
SFP-10G-AOC1M			
SFP-10G-AOC2M			
SFP-10G-AOC3M			
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			

Catalyst 4500 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-X45-SUP8-E	SFP-10G-SR	3.3.0XO	3.3.0XO
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	SFP-H10GB-CU1M	—	3.3.0XO
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	DWDM SFP+	3.6.0E	3.6.0E
	SFP-10G-BXD-I	3.8.0E	3.8.0E
	SFP-10G-BXU-I		
SFP-10G-BX40D-I			
SFP-10G-BX40U-I			
SFP-H10GB-CU1-5M	—	3.6.0E	
SFP-H10GB-CU2M			
SFP-H10GB-CU2-5M			
SFP-H10GB-ACU7M			
SFP-H10GB-ACU10M			
SFP-10G-AOC1M			
SFP-10G-AOC2M			
SFP-10G-AOC3M			
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			

[Catalyst 4500 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-X45-SUP8L-E	SFP-10G-SR	3.8.1E	3.8.1E
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
	GLC-BX40-D-I		
GLC-BX40-U-I			
GLC-BX80-D-I			
GLC-BX80-U-I			

[Catalyst 4500-E Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-X45-SUP9-E	SFP-10G-SR	3.10 XE	3.10 XE
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+		
	SFP-10G-BXD-I		
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		

[Catalyst 4500-E Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M	-	
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

[Catalyst 4500-X Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C4500X-32SFP+	SFP-10G-SR	3.3.0SG	3.3.0SG
WS-C4500X-F-32SFP+	SFP-10G-LRM		
WS-C4500X-40X-ES	SFP-10G-LR		
C4KX-NM-8SFP+	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+	3.5.0E	3.5.0E
	SFP-H10GB-CU1M ¹	—	3.3.0SG
	SFP-H10GB-CU3M ¹		
	SFP-H10GB-CU5M ¹		
	SFP-10G-BXD-I	3.8.0E	3.8.0E
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		

Catalyst 4500-X Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	3.6.0E
	CWDM-SFP10G-1590 CWDM-SFP10G-1570 CWDM-SFP10G-1530 CWDM-SFP10G-1510 CWDM-SFP10G-1550 CWDM-SFP10G-1470 CWDM-SFP10G-1610 CWDM-SFP10G-1490	—	3.9.1E
WS-C4500X-16SFP+ WS-C4500X-F-16SFP+ WS-C4500X-24X-ES	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-ER SFP-10G-SR-S SFP-10G-LR-S SFP-10G-ER-S SFP-10G-ZR-S SFP-10G-ZR Error! Bookmark not defined.	3.3.1SG	3.3.1SG
	DWDM SFP+	3.5.0E	3.5.0E
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I	3.8.0E	3.8.0E
	SFP-H10GB-CU1M ¹ SFP-H10GB-CU3M ¹ SFP-H10GB-CU5M ¹	—	3.3.1SG

Catalyst 4500-X Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M	—	3.6.0E
	CWDM-SFP10G-1590 CWDM-SFP10G-1570 CWDM-SFP10G-1530 CWDM-SFP10G-1510 CWDM-SFP10G-1550 CWDM-SFP10G-1470 CWDM-SFP10G-1610 CWDM-SFP10G-1490	—	3.9.1E

Catalyst 4900 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C4948-10GE WS-C4928-10GE	X2-10GB-CX4 X2-10GB-LX4	—	12.2(25)EW
	X2-10GB-LR X2-10GB-SR X2-10GB-ER	12.2(54)SG	12.2(25)EW
	X2-10GB-LRM	12.2(54)SG	12.2(31)SGA
	X2-10GB-ZR	12.2(54)SG	12.2(50)SG
	DWDM X2	12.2(50)SG	12.2(50)SG
WS-C4948-10GE WS-C4928-10GE (With CVR-X2-SFP10G converter for X2 ports)	SFP-H10GB-CU1M ¹ SFP-H10GB-CU3M ¹ SFP-H10GB-CU5M ¹	—	12.2(54)SG
	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-SR-S	12.2(54)SG	12.2(54)SG

[Catalyst 4900 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-LR-S		
WS-C4948E	SFP-H10GB-CU1M ¹ SFP-H10GB-CU3M ¹ SFP-H10GB-CU5M ¹	—	12.2(54)SG
	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	12.2(54)SG	12.2(54)SG
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I	3.8.0E	3.8.0E
	SFP-10G-ER SFP-10G-ZR SFP-10G-ER-S SFP-10G-ZR-S	15.0(2)SG	15.0(2)SG
	DWDM SFP+	—	15.2(1)E
WS-C4900M WS-X4904-10GE WS-X4908-10GE	X2-10GB-CX4 X2-10GB-LX4	—	12.2(40)XO or 12.2(44)SG
	X2-10GB-LR X2-10GB-SR X2-10GB-ER X2-10GB-LRM	12.2(54)SG	12.2(40)XO or 12.2(44)SG
	X2-10GB-ZR	12.2(54)SG	12.2(50)SG
	X2-10GB-T	15.1(2)SG	15.1(2)SG
	SFP-10G-BXD-I SFP-10G-BXU-I SFP-10G-BX40D-I SFP-10G-BX40U-I	3.8.0E	3.8.0E
	DWDM X2	12.2(50)SG	12.2(50)SG
WS-C4900M WS-X4904-10GE WS-X4908-10GE (With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR SFP-10G-SR-S	12.2(54)SG	12.2(50)SG
	SFP-10G-LRM SFP-10G-LR SFP-10G-LR-S	12.2(54)SG	12.2(54)SG

[Catalyst 4900 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-H10GB-CU1M ¹ SFP-H10GB-CU3M ¹ SFP-H10GB-CU5M ¹	—	12.2(53)SG1

[Cisco ME 4600 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME4600-UMX-4x10GE	XFP-10G-MM-SR XFP10GLR-192SR-L XFP10GLR192SR-GD XFP10GER-192IR-L XFP10GER192IR-RGD XFP-10GZR-OC192LR XFP10GZR192LR-RGD	3.3.1	3.3.1

[Cisco ME 4900 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME-4924-10GE	X2-10GB-CX4 X2-10GB-LX4	—	12.2(31)SGA
	X2-10GB-LR X2-10GB-SR X2-10GB-ER X2-10GB-LRM	12.2(54)SG	12.2(31)SGA
	X2-10GB-ZR	12.2(54)SG	12.2(50)SG
	DWDM X2	12.2(50)SG	12.2(50)SG
	SFP-H10GB-CU1M ¹ SFP-H10GB-CU3M ¹ SFP-H10GB-CU5M ¹	—	12.2(54)SG
ME-4924-10GE (With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-SR-S SFP-10G-LR-S	12.2(54)SG	12.2(54)SG

Catalyst 6XXX Switch Support and Minimum Software Release Requirements

Catalyst 6500 Series

Network Device	Transceiver Model	Minimum Software Release Required		
		Cisco IOS	DOM Support	
WS-X6704-10GE WS-SUP32-10GE-3B	XENPAK-10GB-LR	12.2(17a)SX	—	
	XENPAK-10GB-LR+	12.2(17a)SX	12.2(18)SXE	
	XENPAK-10GB-LW	12.2(18)SXE	12.2(18)SXE	
	XENPAK-10GB-ER	12.2(17a)SX	—	
	XENPAK-10GB-ER+	12.2(17a)SX	12.2(18)SXE	
	XENPAK-10GB-LX4	12.2(17a)SX1	—	
	XENPAK-10GB-SR	12.2(17a)SX1	—	
	XENPAK-10GB-CX4	12.2(17a)SXB1	—	
	XENPAK-10GB-ZR	12.2(18)SXF	12.2(18)SXF	
	XENPAK-10GB-LRM	12.2(18)SXF11	12.2(18)SXF11	
	DWDM XENPAK	12.2(18)SXF	12.2(18)SXF	
WS-SUP32-10GE-PISA	XENPAK-10GB-LR	—	12.2(18)ZY	12.2(18)ZY
	XENPAK-10GB-LR+			
	XENPAK-10GB-LW			
	XENPAK-10GB-ER			
	XENPAK-10GB-ER+			
	XENPAK-10GB-LX4			
	XENPAK-10GB-SR			
	XENPAK-10GB-CX4			
	XENPAK-10GB-ZR			
	XENPAK-10GB-LRM			
	DWDM XENPAK			
VS-S720-10G-3C VS-S720-10G-3CXL WS-X6716-10G-3C WS-X6716-10G-3CXL	X2-10GB-LR	—	12.2(33)SXH2	12.2(33)SXH2
	X2-10GB-SR			
	X2-10GB-CX4			
	X2-10GB-ER			
	X2-10GB-LX4			
	X2-10GB-LRM			
	X2-10GB-ZR	—	12.2(33)SXI	12.2(33)SXI
	DWDM X2			
	X2-10GB-T	—	12.2(33)SJ11	—

Catalyst 6500 Series

Network Device	Transceiver Model	Minimum Software Release Required		
		Cisco IOS	DOM Support	
WS-X6708-10G-3C WS-X6708-10G-3CXL	X2-10GB-LR	—	12.2(18)SXF5	12.2(18)SXF5
	X2-10GB-SR			
	X2-10GB-CX4			
	X2-10GB-ER			
	X2-10GB-LX4			
	X2-10GB-LRM	—	12.2(18)SXF8	12.2(18)SXF8
	X2-10GB-ZR	—	12.2(33)SXI	12.2(33)SXI
	DWDM X2			
	X2-10GB-T	—	12.2(33)SJI1	—
VS-S720-10G-3C	SFP-H10GB-CU1M	—	—	12.2(33)SXI2
VS-S720-10G-3CXL	SFP-H10GB-CU3M			
WS-X6708-10G-3C	SFP-H10GB-CU5M			
WS-X6708-10G-3CXL				
WS-X6716-10G-3C	SFP-10G-SR	—	12.2(33)SXI2	12.2(33)SXI2
WS-X6716-10G-3CXL	SFP-10G-SR-S			
(With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-LRM	—	12.2(33)SXI4	12.2(33)SXI4
	SFP-10G-LR	—	12.2(33)SXJ1	12.2(33)SXJ1
	SFP-10G-LR-S			
	X2-10GB-CX4	—	—	12.2(50)SY
	X2-10GB-SR	—	12.2(50)SY	12.2(50)SY
	X2-10GB-LRM			
	X2-10GB-LX4			
	X2-10GB-LR			
	X2-10GB-ER			
	X2-10GB-ZR			
	DWDM X2			
C6800-32P10G(-XL)	SFP-10G-LR	—	15.2(1)SY	15.2(1)SY
C6800-16P10G(-XL)	SFP-10G-SR			
C6800-8P10G(-XL)	SFP-10G-LRM			
	SFP-10G-ER			
	SFP-10G-ZR			
	SFP-10G-LR-S			
	SFP-10G-SR-S			
	SFP-10G-ER-S			
	SFP-10G-ZR-S			
	DWDM SFP+			
	SFP-H10GB-CU1M			
	SFP-H10GB-CU1-5M			
	SFP-H10GB-CU2M			
	SFP-H10GB-CU2-5M			
	SFP-H10GB-CU3M			
	SFP-H10GB-CU5M			

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 6XXX Switch Support and Minimum Software Release Requirements

Catalyst 6500 Series

Network Device	Transceiver Model	Minimum Software Release Required		
		Cisco IOS	DOM Support	
	SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M CVR-4SFP10G-QSFP			
C6800-SUP6T C6800-SUP6T-XL	SFP-10G-LR SFP-10G-SR SFP-10G-LRM SFP-10G-ER SFP-10G-ZR SFP-10G-LR-S SFP-10G-SR-S SFP-10G-ER-S SFP-10G-ZR-S SFP-10G-BX40D-I SFP-10G-BX40U-I CWDM-SFP10G-1590 DWDM-SFP+ SFP-H10GB-CU1M SFP-H10GB-CU1-5M SFP-H10GB-CU2M SFP-H10GB-CU2-5M SFP-H10GB-CU3M SFP-H10GB-CU5M SFP-H10GB-ACU7M SFP-H10GB-ACU10M SFP-10G-AOC1M SFP-10G-AOC2M SFP-10G-AOC3M SFP-10G-AOC5M SFP-10G-AOC7M SFP-10G-AOC10M CVR-4SFP10G-QSFP	—	15.3(1)SY	15.3(1)SY
VS-S2T-10G VS-S2T-10G-XL WS-X6816-10G-2T	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	—	15.3(1)SY

Catalyst 6500 Series

Network Device	Transceiver Model	Minimum Software Release Required		
		Cisco IOS	DOM Support	
WS-X6816-10G-2TXL	SFP-10G-SR	—	12.2(50)SY	12.2(50)SY
WS-X6908-10G-2T	SFP-10G-LRM			
WS-X6908-10G-2TXL	SFP-10G-LR			
(With CVR-X2-SFP10G converter for X2 ports)	SFP-10G-SR-S			
	SFP-10G-LR-S			
WS-X6904-40G-2T	SFP-H10GB-CU1M	—	—	15.0(1)SY1
WS-X6904-40G-2TXL	SFP-H10GB-CU3M			
With CVR-CFP-4SFP10G FourX converter for CFP ports	SFP-H10GB-CU5M			
	SFP-10G-SR	—	15.0(1)SY1	15.0(1)SY1
	SFP-10G-LRM			
	SFP-10G-LR			
	SFP-10G-ER			
	SFP-10G-SR-S			
	SFP-10G-LR-S			
	SFP-10G-ER-S			
	SFP-10G-ZR	—	15.0(2)SY3	15.0(2)SY3
	SFP-10G-ZR-S			
	DWDM SFP+	—	15.1(2)SY	15.1(2)SY

Catalyst 6800 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-ZR	15.2(1)SY	15.2(1)SY
	SFP-10G-ZR-S		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

Catalyst 6800 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
C6800IA-48FPDR	SFP-10G-ER	15.1(2)SY3	15.1(2)SY3
	SFP-10G-LR		
	SFP-10G-SR		
	SFP-10G-LRM		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-H10GB-CU1M1		
	SFP-H10GB-CU3M1		
	SFP-H10GB-CU5M1		
	SFP-H10GB-CU7M1		
	SFP-10G-ZR	15.2(1)SY	15.2(1)SY
	SFP-10G-ZR-S		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC3M		
SFP-10G-AOC5M			
SFP-10G-AOC7M			
SFP-10G-AOC10M			
C6880-X	SFP-10G-LR	15.1(2)SY1	15.1(2)SY1
	SFP-10G-SR		
	SFP-10G-LRM		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-SR-S		
	SFP-10G-LR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

Catalyst 6800 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
C6800-32P10G(-XL)	SFP-10G-LR	15.2(1)SY	15.2(1)SY
C6800-16P10G(-XL)	SFP-10G-SR		
C6800-8P10G(-XL)	SFP-10G-LRM		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-LR-S		
	SFP-10G-SR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	DWDM SFP+		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

Catalyst 6800 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
C6800-SUP6T	SFP-10G-LR	15.3(1)SY	15.3(1)SY
C6800-SUP6T-XL	SFP-10G-SR		
	SFP-10G-LRM		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-LR-S		
	SFP-10G-SR-S		
	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		
	CWDM-SFP10G-1590		
	DWDM-SFP+		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
C6816-X-LE	SFP-10G-LR	15.2(2)SY	15.2(2)SY
C6824-X-LE-40G	SFP-10G-SR		
C6832-X-LE	SFP-10G-LRM		
C6840-X-LE-40G	SFP-10G-ER		
	SFP-10G-ZR		
	DWDM-SFP+		
	SFP-10G-ZR		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		

Catalyst 9300 Switch Support and Minimum Software Release Requirements

[Catalyst 9300 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
C9300-24T	SFP-10G-LR	—	XE 16.5.1a
C9300-24P	SFP-10G-SR		
C9300-24U	SFP-10G-LRM		
C9300-24XU	SFP-10G-ER		
C9300-48T	SFP-10G-ZR		
C9300-48P	SFP-10G-SR-S		
C9300-48U	SFP-10G-LR-S		
(With C9300-NM-8X for 10G uplink modules)	SFP-10G-ER-S		
	SFP-10G-ZR-S		
	SFP-10G-BXD-I		
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		
	DWDM SFP10G		
	CWDM SFP10G		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

Catalyst 9400 Switch Support and Minimum Software Release Requirements

[Catalyst 9400 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
C9400-SUP-1	SFP-10G-SR	XE 16.6.1	XE 16.6.1
	SFP-10G-SR-S		
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR		
	SFP-10G-BXD-I		

Cisco 10-Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 9400 Switch Support and Minimum Software Release Requirements

Catalyst 9400 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		
	DWDM-SFP+		
	CWDM-SFP10G-xxxx		
	SFP-10G-LR-S		
	SFP-10GE-ER-S		
	SFP-10GE-ZR-S		
	SFP-H10GB-CU1M	-	
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		
C9400-Sup-1XL	SFP-10G-SR	XE 16.6.2	XE 16.6.2
C9400-LC-24XS	SFP-10G-SR-S		
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-LR-S		
	SFP-10G-ER		
	SFP-10G-ER-S		
	SFP-10G-ZR		
	SFP-10G-ZR-S		
	SFP-10G-BXD-I		
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		
	DWDM-SFP+		
	CWDM-SFP10G-xxxx		
	SFP-H10GB-CU1M	-	
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

Catalyst 9500 Switch Support and Minimum Software Release Requirements

[Catalyst 9500 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
C9500-12Q	SFP-10G-SR (used with CVR-QSFP-SFP10G)		XE 16.6.1
C9500-24Q	SFP-10G-LR (used with CVR-QSFP-SFP10G)		
	SFP-10G-ER (used with CVR-QSFP-SFP10G)		
	SFP-10G-ZR (used with CVR-QSFP-SFP10G)		
	SFP-10G-SR-S (used with CVR-QSFP-SFP10G)		
	SFP-10G-LR-S (used with CVR-QSFP-SFP10G)		
	SFP-10G-ER-S (used with CVR-QSFP-SFP10G)		
	SFP-10G-ZR-S (used with CVR-QSFP-SFP10G)		
	DWDM-SFP+ (used with CVR-QSFP-SFP10G)		
	SFP-H10GB-CU1M (used with CVR-QSFP-SFP10G)		
	SFP-H10GB-CU3M (used with CVR-QSFP-SFP10G)		
	SFP-H10GB-CU5M (used with CVR-QSFP-SFP10G)		
	CWDM-SFP10G-xxxx (used with CVR-QSFP-SFP10G)		
C9500-40X	SFP-10G-SR		
	SFP-10G-SR-S		
	SFP-10G-LR		
	SFP-10G-LR-S		
	SFP-10G-LRM		
	SFP-10G-ER		
	SFP-10G-ER-S		
	SFP-10G-ZR		
	SFP-10G-ZR-S		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	DWDM-SFP+		
	CWDM-SFP10G-xxxx		
	SFP-10G-BXD-I		
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		

Metro Ethernet Support and Minimum Software Requirements

[Cisco ME 3600X](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME-3600X-24TS-M ME-3600X-24FS-M (SFP+ ports)	SFP-H10GB-CU1M	—	12.2(52)EY
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-10G-SR	12.2(52)EY	12.2(52)EY
	SFP-10G-LRM		
	SFP-10G-LR		
	SFP-10G-ER		
	SFP-10G-ZR	15.1(2)EY1	15.1(2)EY1
	SFP-10G-BXD-I	15.4(03)S	15.4(03)S
	SFP-10G-BXU-I		
	SFP-10G-BX40D-I		
	SFP-10G-BX40U-I		
	DWDM SFP+	15.2(4)S	15.2(4)S
ME-3600X-24CX-M	XFP-10G-MM-SR	15.2(2)S	15.2(2)S
	XFP10GLR192SR-RGD		
	XFP10GLR-192SR-L		
	XFP10GER192IR-RGD		
	XFP10GER-192IR-L		
	XFP10GZR192LR-RGD		
	XFP-10GZR-OC192LR		
	DWDM-XFP-C		
	XFP-10GER-OC192IR	15.3(3)S	15.3(3)S
	XFP-10GER-192IR+		

[Cisco ME 3800X](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME-3800X-24FS-M (SFP+ ports)	SFP-H10GB-CU1M SFP-H10GB-CU3M SFP-H10GB-CU5M	—	12.2(52)EY
	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-ER	12.2(52)EY	12.2(52)EY
	SFP-10G-ZR	15.1(2)EY1	15.1(2)EY1
	DWDM SFP+	15.2(4)S	15.2(4)S

Wireless LAN Controller Support and Minimum Software Release Requirements

[Cisco 5700 WLC Series](#)

Network Device	Transceiver Model	Minimum Software Release Required			
		DOM Support	Software Release		
AIR-CT5760-25-K9 AIR-CT5760-50-K9 AIR-CT5760-100-K9 AIR-CT5760-250-K9 AIR-CT5760-500-K9	SFP-10G-SR SFP-10G-LRM SFP-10G-LR SFP-10G-ER	XE 3.2.0SE	XE 3.2.0SE		
AIR-CT5760-1K-K9 AIR-CT5760-HA-K9	SFP-10G-ZR DWDM SFP+			XE 3.3.3SE	XE 3.3.3SE

Cisco Security Appliance Minimum Software Release Requirements

[Cisco Firepower](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
FPR2K-NM-8X10G	SFP-10G-SR		1.1.4
FPR4K-NM-8X10G	SFP-10G-SR-S		
FPR9K-NM-8X10G	SFP-10G-LR		
	SFP-10G-LR-S		
	SFP-10G-LRM		
	SFP-10G-ER		
	SFP-H10GB-CU1M		
	SFP-H10GB-CU1-5M		
	SFP-H10GB-CU2M		
	SFP-H10GB-CU2-5M		
	SFP-H10GB-CU3M		
	SFP-H10GB-CU5M		
	SFP-H10GB-ACU7M		
	SFP-H10GB-ACU10M		
	SFP-10G-AOC1M		
	SFP-10G-AOC2M		
	SFP-10G-AOC3M		
	SFP-10G-AOC5M		
	SFP-10G-AOC7M		
	SFP-10G-AOC10M		

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, using the Cisco Bug Search Tool (BST), submitting a service request, and gathering additional information, see [What's New in Cisco Product Documentation](#).

To receive new and revised Cisco technical content directly to your desktop, you can subscribe to the [What's New in Cisco Product Documentation RSS feed](#). The RSS feeds are a free service.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2017 Cisco Systems, Inc. All rights reserved.