



Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Revised: December 12, 2017

Requirements and procedures for initial configurations and software upgrades tend to change and therefore appear only in the switch or router software release notes. Before installing, configuring, or upgrading a switch, refer to the product release notes on Cisco.com for the latest information. This matrix does not replace or supersede the release notes.

This publication contains information on the Cisco platforms and minimum software releases that support the Gigabit Interface Converter (GBIC) and Gigabit Ethernet Small Form-Factor Pluggable (SFP) transceiver modules.

Contents

Gigabit Ethernet Transceiver Models.....	5
• GBIC Transceivers.....	5
• CWDM GBIC Transceivers (Dual SC/PC connectors).....	5
• DWDM GBIC Transceivers (Dual SC/PC connectors).....	6
• SFP Transceivers	7
• CWDM SFP Transceivers (dual LC/PC connector).....	9
• DWDM SFP Transceivers (dual LC/PC connector).....	9
• DWDM SFP Transceivers (8 additional wavelengths) (dual LC/PC connector)	11
Catalyst Express 500 Support.....	11
• Catalyst Express 500.....	11
• Catalyst Express 520.....	12
Metro Ethernet Support.....	12
• Cisco ME 2400.....	12
• Cisco ME2600X	12
• Cisco ME 3400.....	13
• Cisco ME 3400E.....	16
• Catalyst 3750 Metro.....	16
• Cisco ME 3600X	17
• Cisco ME 3800X	19
• Cisco ME 4600 Series.....	19
• Cisco ME 4900 Series.....	20
• Cisco ME 6500 Series.....	21

Catalyst 2900 Switches Support	21
● Catalyst 2900 series	21
● Catalyst 2940 series	22
● Catalyst 2950 series	23
● Catalyst 2960 series	24
● Catalyst 2960 Plus Series.....	26
● Catalyst 2960 S Series.....	26
● Catalyst 2960 SF Series	27
● Catalyst 2960 C Series.....	28
● Catalyst 2960 X Series.....	29
● Catalyst 2960 XR Series.....	30
● Catalyst 2960 L Series	31
● Catalyst 2960 CX Series	31
● Catalyst 2970 series	32
● Catalyst 2975 series	32
Catalyst 3500 Switches Support	32
● Catalyst 3500XL series	32
● Catalyst 3550 series	33
● Catalyst 3560 series	34
● Catalyst 3560 E Series	36
● Catalyst 3560 X Series	38
● Catalyst 3560 CX Series	40
● Catalyst 3560 C Series.....	40
Catalyst 3600 Series Switches Support	41
Catalyst 3700 Series Switches Support	42
● Catalyst 3750 series	42
● Catalyst 3750-E series.....	46
● Catalyst 3750-X series.....	46
Catalyst 3800 Series Switches Support	49
● Catalyst 3850 series	49
Catalyst 9300 Series Switches Support	52
● Catalyst 9300 series	52
Catalyst 9400 Series Switches Support	53
● Catalyst 9400 series	53
Catalyst 9500 Series Switches Support	53
● Catalyst 9500 series	53
Industrial Ethernet and Smart Grid Support	54
● Cisco IE1000 series	54

● Cisco IE2000 series	55
● Cisco IE2000U series	55
● Cisco IE3000 series	57
● Cisco IE3010 series	58
● Cisco IE4000 series	59
● Cisco IE4010 series	60
● Cisco IE5000 series	61
● Cisco 2500 Connected Grid Switch Series	62
● Cisco 2000 Connected Grid Router Series	63
Catalyst 4500 Switches Support	65
● Catalyst 4500 series	65
Catalyst 4500-E Series Support	73
Catalyst 4500X Series Support	74
Catalyst 4900 Switches Support	75
Catalyst 6500 Series Switches Support	77
Catalyst 6800 Series Switches Support	82
Data Center and Blade Switching Support	84
● Cisco Catalyst 2350 Series	84
● Cisco Catalyst 2360 Series	84
● Cisco Catalyst 3000 and 3100 Blade Switches	84
● Cisco Nexus 2000 Series	85
● Cisco Nexus 3000 Series	86
● Cisco Nexus 3100 Series	87
● Cisco Nexus 3200 Series	91
● Cisco Nexus 3500 Series	92
● Cisco Nexus 3600 Series	92
● Cisco Nexus 4000 Series	93
● Cisco Nexus 5000 Series	93
● Cisco Unified Computing System	94
● Cisco Nexus 7000 Series	95
● Cisco Nexus 7700 Series	98
● Cisco Nexus 9000 Series (Modular 9500) NX-OS Mode	98
● Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode	100
● Cisco Nexus 9000 Series (Fixed 9200) NX-OS Mode	103
● Cisco Nexus 9000 Series (Fixed 9300) ACI Mode	104
● Cisco CSS 11500 Series	106

Cisco MDS 9000 series: Please refer to the data sheet.....	106
Router Support	107
• Cisco 892F series	107
• Cisco 1921 Series Router.....	107
• Cisco1941 Series Router.....	108
• Cisco 2600 Series Router.....	108
• Cisco 2800 Series Router.....	109
• Cisco 2900 Series Router.....	109
• Cisco 3200 Series Rugged Routers Cisco 3600 Series Router	110
• Cisco 3700 Series Router.....	111
• Cisco 3800 Series Router.....	111
• Cisco 3900 Series Router.....	112
Cisco 4400 Series Router	113
• Cisco 6400 Universal Access Router.....	113
• Cisco 7200 Series Router.....	114
• Cisco uBR7200 series	115
• Cisco 7300 Series Router.....	115
• Cisco 7500 Series Router.....	116
• Cisco 7600 Series Router.....	117
• Cisco 10000 Series Router.....	120
• Cisco uBR10000 Series Router	121
• Cisco RF Gateway Series	121
• Cisco 12000 Series Router.....	121
• Cisco NCS 5000 Series.....	122
• Cisco NCS 5500 Series.....	122
• Shared Port Adapters (SPAs)	123
• CRS Router Series	123
• ASR 901 Series Router.....	124
• Cisco ASR 903 Series	125
• ASR 1000 Series Router.....	125
• ASR 9000 Series Router.....	126
• ASR 9000 Series Router (EOBC-supported optics)	128
• ASR9000v Series Router	129
• Cisco MWR 2941 Mobile Wireless Routers.....	130
Appliance Support	130
• ASA5500 Series appliances	130
• NAM 2200 Series appliances	131
Wireless LAN Controllers Support.....	131
• Cisco 5700 WLC Series	131

Gigabit Ethernet Transceiver Models

Cisco Security Appliance Minimum Software Release Requirements	132
• Cisco Firepower	132
Obtaining Documentation and Submitting a Service Request	132

Gigabit Ethernet Transceiver Models

GBIC Transceivers	
Model Number	Description
WS-G5482=	1000BASE-T GBIC transceiver module for Category 5 copper wire, RJ-45 connector
WS-G5483=	1000BASE-T GBIC transceiver module for Category 5 copper wire, RJ-45 connector
WS-G5484=	1000BASE-SX GBIC transceiver module for Multi mode Fiber (MMF), 850-nanometer (nm) wavelength, dual SC/PC connector
WS-G5486=	1000BASE-LX/LH GBIC transceiver module for MMF and SMF, 1300-nm wavelength, dual SC/PC connector
WS-G5487=	1000BASE-ZX GBIC transceiver module for Single Mode Fiber (SMF), 1550-nm wavelength, dual SC/PC connector

CWDM GBIC Transceivers (Dual SC/PC connectors)	
Model Number	Description
CWDM-GBIC-1470=	Cisco 1000BASE-CWDM GBIC 1470 nm
CWDM-GBIC-1490=	Cisco 1000BASE-CWDM GBIC 1490 nm
CWDM-GBIC-1510=	Cisco 1000BASE-CWDM GBIC 1510 nm
CWDM-GBIC-1530=	Cisco 1000BASE-CWDM GBIC 1530 nm
CWDM-GBIC-1550=	Cisco 1000BASE-CWDM GBIC 1550 nm
CWDM-GBIC-1570=	Cisco 1000BASE-CWDM GBIC 1570 nm
CWDM-GBIC-1590=	Cisco 1000BASE-CWDM GBIC 1590 nm
CWDM-GBIC-1610=	Cisco 1000BASE-CWDM GBIC 1610 nm

DWDM GBIC Transceivers (Dual SC/PC connectors)	
Model Number	Transceiver Description
DWDM-GBIC-60.61=	1000BASE-DWDM GBIC 1560.61 nm
DWDM-GBIC-59.79=	1000BASE-DWDM GBIC 1559.79 nm
DWDM-GBIC-58.98=	1000BASE-DWDM GBIC 1558.98 nm
DWDM-GBIC-58.17=	1000BASE-DWDM GBIC 1558.17 nm
DWDM-GBIC-56.55=	1000BASE-DWDM GBIC 1556.55 nm
DWDM-GBIC-55.75=	1000BASE-DWDM GBIC 1555.75 nm
DWDM-GBIC-54.94=	1000BASE-DWDM GBIC 1554.94 nm
DWDM-GBIC-54.13=	1000BASE-DWDM GBIC 1554.13 nm
DWDM-GBIC-52.52=	1000BASE-DWDM GBIC 1552.52 nm
DWDM-GBIC-51.72=	1000BASE-DWDM GBIC 1551.72 nm
DWDM-GBIC-50.92=	1000BASE-DWDM GBIC 1550.92 nm
DWDM-GBIC-50.12=	1000BASE-DWDM GBIC 1550.12 nm
DWDM-GBIC-48.51=	1000BASE-DWDM GBIC 1548.51 nm
DWDM-GBIC-47.72=	1000BASE-DWDM GBIC 1547.72 nm
DWDM-GBIC-46.92=	1000BASE-DWDM GBIC 1546.92 nm
DWDM-GBIC-46.12=	1000BASE-DWDM GBIC 1546.12 nm
DWDM-GBIC-44.53=	1000BASE-DWDM GBIC 1544.53 nm
DWDM-GBIC-43.73=	1000BASE-DWDM GBIC 1543.73 nm
DWDM-GBIC-42.94=	1000BASE-DWDM GBIC 1542.94 nm
DWDM-GBIC-42.14=	1000BASE-DWDM GBIC 1542.14 nm
DWDM-GBIC-40.56=	1000BASE-DWDM GBIC 1540.56 nm
DWDM-GBIC-39.77=	1000BASE-DWDM GBIC 1539.77 nm
DWDM-GBIC-39.98=	1000BASE-DWDM GBIC 1539.98 nm
DWDM-GBIC-38.19=	1000BASE-DWDM GBIC 1538.19 nm

DWDM GBIC Transceivers (Dual SC/PC connectors)	
Model Number	Transceiver Description
DWDM-GBIC-35.82=	1000BASE-DWDM GBIC 1535.82 nm
DWDM-GBIC-35.04=	1000BASE-DWDM GBIC 1535.04 nm
DWDM-GBIC-34.25=	1000BASE-DWDM GBIC 1534.25 nm
DWDM-GBIC-32.68=	1000BASE-DWDM GBIC 1532.68 nm
DWDM-GBIC-31.90=	1000BASE-DWDM GBIC 1531.90 nm
DWDM-GBIC-31.12=	1000BASE-DWDM GBIC 1531.12 nm
DWDM-GBIC-30.33=	1000BASE-DWDM GBIC 1530.33 nm

SFP Transceivers	
Model Number	Transceiver Description
GLC-T=	1000BASE-T SFP transceiver module for Category 5 copper wire, RJ-45 connector
GLC-TE=	1000BASE-T SFP transceiver module for Category 5 copper wire, RJ-45 connector, Extended Temperature
GLC-SX-MM=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, dual LC/PC connector
GLC-LH-SM=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, dual LC/PC connector
GLC-ZX-SM=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, dual LC/PC connector
GLC-BX-D=	1000BASE-BX10 SFP module for single-strand SMF, 1490-nm TX/1310-nm RX wavelength, single LC/PC connector
GLC-BX-U=	1000BASE-BX10 SFP module for single-strand SMF, 1310-nm TX/1490-nm RX wavelength, single LC/PC connector
GLC-BX40-D-I	1000BASE-BX10 SFP module for single-strand SMF, 1550-nm TX/1310-nm RX wavelength, single LC/PC connector
GLC-BX40-U-I	1000BASE-BX10 SFP module for single-strand SMF, 1310-nm TX/1550-nm RX wavelength, single LC/PC connector
GLC-BX80-D-I	1000BASE-BX10 SFP module for single-strand SMF, 1570-nm TX/1490-nm RX wavelength, single LC/PC connector

SFP Transceivers	
Model Number	Transceiver Description
GLC-BX80-U-I	1000BASE-BX10 SFP module for single-strand SMF, 1490-nm TX/1570-nm RX wavelength, single LC/PC connector
GLC-BX40-DA-I	1000BASE-BX10 SFP module for single-strand SMF, 1490-nm TX/1310-nm RX wavelength, single LC/PC connector
GLC-2BX-D=	Dual-channel 1000BASE-BX10 SFP module for single-strand SMF, 1490-nm TX/1310-nm RX wavelength, two single LC/PC connectors
SFP-GE-S=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-L=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-EX-SMD=	1000BASE-EX SFP transceiver module for SMF, 1310-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-Z=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-T=	1000BASE-T SFP transceiver module for Category 5 copper wire, extended operating temperature range, RJ-45 connector
GLC-SX-MM-RGD	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, industrial Ethernet, dual LC/PC connector
GLC-LX-SM-RGD	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, industrial Ethernet, dual LC/PC connector
GLC-ZX-SM-RGD	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, industrial Ethernet, dual LC/PC connector
GLC-SX-MMD=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-LH-SMD=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-ZX-SMD=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, dual LC/PC connector
SFP-GPON-B	Gigabit passive optical network (GPON) Class B+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength
SFP-GPON-B-I	Gigabit passive optical network (GPON) Class B+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength, industrial temperature range

SFP Transceivers	
Model Number	Transceiver Description
SFP-GPON-C	Gigabit passive optical network (GPON) Class C+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength
SFP-GPON-C-I	Gigabit passive optical network (GPON) Class C+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength, industrial temperature range

CWDM SFP Transceivers (dual LC/PC connector)	
Model Number	Transceiver Description
CWDM-SFP-1470=	Cisco CWDM SFP 1470 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1490=	Cisco CWDM SFP 1490 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1510=	Cisco CWDM SFP 1510 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1530=	Cisco CWDM SFP 1530 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1550=	Cisco CWDM SFP 1550 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1570=	Cisco CWDM SFP 1570 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1590=	Cisco CWDM SFP 1590 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1610=	Cisco CWDM SFP 1610 nm; Gigabit Ethernet and 1G/2G FC

DWDM SFP Transceivers (dual LC/PC connector)	
Model Number	Transceiver Description
DWDM-SFP-6061=	Cisco 1000BASE-DWDM SFP 1560.61 nm
DWDM-SFP-5979=	Cisco 1000BASE-DWDM SFP 1559.79 nm
DWDM-SFP-5898=	Cisco 1000BASE-DWDM SFP 1558.98 nm
DWDM-SFP-5817=	Cisco 1000BASE-DWDM SFP 1558.17 nm
DWDM-SFP-5655=	Cisco 1000BASE-DWDM SFP 1556.55 nm
DWDM-SFP-5575=	Cisco 1000BASE-DWDM SFP 1555.75 nm

DWDM SFP Transceivers (dual LC/PC connector)	
Model Number	Transceiver Description
DWDM-SFP-5413=	Cisco 1000BASE-DWDM SFP 1554.13 nm
DWDM-SFP-5494=	Cisco 1000BASE-DWDM SFP 1554.94 nm
DWDM-SFP-5252=	Cisco 1000BASE-DWDM SFP 1552.52 nm
DWDM-SFP-5172=	Cisco 1000BASE-DWDM SFP 1551.72 nm
DWDM-SFP-5092=	Cisco 1000BASE-DWDM SFP 1550.92 nm
DWDM-SFP-5012=	Cisco 1000BASE-DWDM SFP 1550.12 nm
DWDM-SFP-4851=	Cisco 1000BASE-DWDM SFP 1548.51 nm
DWDM-SFP-4772=	Cisco 1000BASE-DWDM SFP 1547.72 nm
DWDM-SFP-4692=	Cisco 1000BASE-DWDM SFP 1546.92 nm
DWDM-SFP-4612=	Cisco 1000BASE-DWDM SFP 1546.12 nm
DWDM-SFP-4453=	Cisco 1000BASE-DWDM SFP 1544.53 nm
DWDM-SFP-4373=	Cisco 1000BASE-DWDM SFP 1543.73 nm
DWDM-SFP-4294=	Cisco 1000BASE-DWDM SFP 1542.94 nm
DWDM-SFP-4214=	Cisco 1000BASE-DWDM SFP 1542.14 nm
DWDM-SFP-4056=	Cisco 1000BASE-DWDM SFP 1540.56 nm
DWDM-SFP-3977=	Cisco 1000BASE-DWDM SFP 1539.77 nm
DWDM-SFP-3898=	Cisco 1000BASE-DWDM SFP 1539.98 nm
DWDM-SFP-3819=	Cisco 1000BASE-DWDM SFP 1538.19 nm
DWDM-SFP-3661=	Cisco 1000BASE-DWDM SFP 1536.61 nm
DWDM-SFP-3582=	Cisco 1000BASE-DWDM SFP 1535.82 nm
DWDM-SFP-3504=	Cisco 1000BASE-DWDM SFP 1535.04 nm
DWDM-SFP-3425=	Cisco 1000BASE-DWDM SFP 1534.25 nm
DWDM-SFP-3268=	Cisco 1000BASE-DWDM SFP 1532.68 nm
DWDM-SFP-3190=	Cisco 1000BASE-DWDM SFP 1531.90 nm

DWDM SFP Transceivers (dual LC/PC connector)	
Model Number	Transceiver Description
DWDM-SFP-3112=	Cisco 1000BASE-DWDM SFP 1531.12 nm
DWDM-SFP-3033=	Cisco 1000BASE-DWDM SFP 1530.33 nm

DWDM SFP Transceivers (8 additional wavelengths) (dual LC/PC connector)	
Model Number	Transceiver Description
DWDM-SFP-6141=	Cisco 1000BASE-DWDM SFP 1561.42 nm
DWDM-SFP-5736=	Cisco 1000BASE-DWDM SFP 1557.36 nm
DWDM-SFP-5332=	Cisco 1000BASE-DWDM SFP 1553.33 nm
DWDM-SFP-4931=	Cisco 1000BASE-DWDM SFP 1549.32 nm
DWDM-SFP-4532=	Cisco 1000BASE-DWDM SFP 1545.32 nm
DWDM-SFP-4134=	Cisco 1000BASE-DWDM SFP 1541.35 nm
DWDM-SFP-3739=	Cisco 1000BASE-DWDM SFP 1537.40 nm
DWDM-SFP-3346=	Cisco 1000BASE-DWDM SFP 1533.47 nm

Catalyst Express 500 Support

Catalyst Express 500

Minimum Software Release Required			
Network Device	Transceiver Module	DOM Support	Cisco IOS Release
WS-CE500-24LC	GLC-SX-MM	--	12.2(25)FY
WS-CE500-24PC	GLC-LH-SM		
WS-CE500G-12TC	GLC-SX-MMD GLC-LH-SMD		

Catalyst Express 520

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-CE520-8PC-K9	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(35)EX
WS-CE520-24LC-K9	GLC-SX-MM	--	12.2(37)EX
WS-CE520-24PC-K9	GLC-LH-SM		
WS-CE520G-24TC-K9	GLC-SX-MMD GLC-LH-SMD		

Metro Ethernet Support

Cisco ME 2400

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
ME-2400-24TS-A	GLC-T(10/100/1000)	--	12.2(25)EX
ME-2400-24TS-D	GLC-TE GLC-SX-MM GLC-LH-SM GLC-ZX-SM		
	GLC-BX-D GLC-BX-U CDWM SFP	12.2(44)SE	12.2(25)EX

Cisco ME2600X

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME2600X-44FA-D-K9=	GLC-BX-D	--	15.2(02)SA
ME2600X-44FE-D-K9=	GLC-BX-U		
ME2600X-44FA-A-K9=			

Cisco ME 3400

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME-3400-24TS-A	GLC-T (10/100/1000)	--	12.2(25)EX
ME-3400-24TS-D	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD	12.2(46)SE	12.2(25)EX
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-ZX-SM	12.2(46)SE	12.2(25)EX
	GLC-BX-D	12.2(44)SE	12.2(25)EX
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP	12.2(44)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
	SFP-GE-S	12.2(46)SE	12.2(46)SE
	SFP-GE-L		
	SFP-GE-T (10/100/1000)	--	12.2(46)SE
	GLC-EX-SMD	12.2(52)SE	12.2(52)SE
ME-3400G-12CS-A	GLC-T (10/100/1000)	--	12.2(25)SEG1
ME-3400G-12CS-D	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD	12.2(46)SE	12.2(25)SEG1
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-ZX-SM	12.2(46)SE	12.2(25)SEG1
	GLC-BX-D	12.2(44)SE	12.2(25)SEG1
	GLC-BX-U	12.2(44)SE	12.2(25)SEG1
	CWDM SFP	12.2(44)SE	12.2(25)SEG1

Cisco ME 3400

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	DWDM SFP	12.2(44)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
	SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
	SFP-GE-T (10/100/1000)	--	12.2(46)SE
	GLC-EX-SMD	12.2(52)SE	12.2(52)SE
ME-3400G-2CS-A	GLC-T (10/100/1000) GLC-TE GLC-SX-MM GLC-LH-SM	--	12.2(35)SE1
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM	12.2(46)SE	12.2(35)SE1
	GLC-BX-D GLC-BX-U	12.2(44)SE	12.2(35)SE1
	CWDM SFP	12.2(44)SE	12.2(35)SE1
	DWDM SFP	12.2(44)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
	SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
	SFP-GE-T (10/100/1000)	--	12.2(46)SE
	GLC-EX-SMD	12.2(52)SE	12.2(52)SE
ME-3400-24FS-A	GLC-T (10/100/1000) GLC-TE GLC-SX-MM GLC-LH-SM	--	12.2(40)SE

Cisco ME 3400

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-ZX-SM	12.2(46)SE	12.2(40)SE
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-BX-D	12.2(44)SE	12.2(40)SE
	GLC-BX-U		
	CWDM SFP	12.2(44)SE	12.2(40)SE
	DWDM SFP	12.2(50)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
	SFP-GE-S	12.2(46)SE	12.2(46)SE
	SFP-GE-L		
	SFP-GE-T (10/100/1000)	--	12.2(46)SE
	GLC-EX-SMD	12.2(52)SE	12.2(52)SE

Cisco ME 3400E

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
ME-3400E-24TS-M	GLC-SX-MM	--	12.2(44)EY
ME-3400EG-2CS-A	GLC-LH-SM		
ME-3400EG-12CS-M	GLC-SX-MMD	12.2(44)EY	12.2(44)EY
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-ZX-SM		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
	GLC-EX-SMD	12.2(52)SE	12.2(52)SE

Catalyst 3750 Metro

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
ME-C3750-24TE-M	GLC-T (1000BASE-T)	--	12.1(14)AX
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM	12.2(46)SE	12.1(14)AX1
	CWDM SFP	12.2(44)SE	12.1(14)AX1
	GLC-BX-D	12.2(44)SE	12.2(25)EY2
	GLC-BX-U		
	DWDM SFP	12.2(44)SE	12.2(40)SE

Catalyst 3750 Metro

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
	SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
	SFP-GE-T (10/100/1000)	--	12.2(46)SE
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-EX-SMD	12.2(52)SE	12.2(52)SE

Cisco ME 3600X

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME-3600X-24FS-M (SFP ports)	GLC-T (10/100/1000) GLC-TE GLC-SX-MM GLC-LH-SM SFP-GE-T (10/100/1000)	--	12.2(52)EY
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L GLC-BX-U (CPN 10-2094-02) GLC-BX-D (CPN 10-2093-02)	12.2(52)EY	12.2(52)EY
	CWDM SFP DWDM SFP DWDM SFP (add.) GLC-EX-SMD GLC-ZX-SM	15.1(2)EY	15.1(2)EY
ME-3600X-24FS-M	GLC-SX-MM	--	12.2(52)EY

Cisco ME 3600X

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME-3600X-24TS-M (SFP+ ports)	GLC-LH-SM		
	GLC-BX40-U-I	15.4(03)S	15.4(03)S
	GLC-BX40-D-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		
	GLC-BX40-DA-I		
	GLC-SX-MMD	12.2(52)EY	12.2(52)EY
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-ZX-SM		
	SFP-GE-S		
	SFP-GE-L		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)		
ME-3600X-24CX-M	SFP-GE-Z	15.3(1)S	15.3(1)S
	GLC-SX-MM-RGD	15.2(2)S1	15.2(2)S1
	GLC-LX-SM-RGD		
	GLC-ZX-SM-RGD		
	GLC-SX-MMD		
	GLC-EX-SMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
	SFP-GE-L		
	SFP-GE-S		
	GLC-LH-SM		
	GLC-SX-MM		
	GLC-T		
	GLC-TE		
	SFP-GE-T		
	GLC-BX-U		
	GLC-BX-D		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)		

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Metro Ethernet Support

Cisco ME 3800X

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME-3800X-24FS-M (client ports)	GLC-T (10/100/1000) GLC-TE GLC-SX-MM GLC-LH-SM SFP-GE-T (10/100/1000)	--	12.2(52)EY
	GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(52)EY	12.2(52)EY
ME-3800X-24FS-M (SFP+ ports)	GLC-SX-MM GLC-LH-SM	--	12.2(52)EY
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(52)EY	12.2(52)EY

Cisco ME 4600 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME4600-AMX-16GPON	SFP-GPON-B SFP-GPON-B-I SFP-GPON-C SFP-GPON-C-I	3.1.1	3.1.1

Cisco ME 4600 Series

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
ME4600-AMX-48GE	GLC-BX-D GLC-BX-U GLC-2BX-D	3.1.1	3.1.1

Cisco ME 4900 Series

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
ME-4924-10GE	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(31)SGA
	GLC-ZX-SMD GLC-BX-D GLC-BX-U CDWM SFP	12.2(31)SGA	12.2(31)SGA
	DWDM SFP	12.2(37)SG	12.2(37)SG

Cisco ME 6500 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ME-C6524GS-8S	GLC-T (1000BASE-T)	--	12.2(18)ZU
ME-C6524GT-8S	GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CDWM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD		
	GLC-T (10/100/1000)	--	12.2(33)SXH
	GLC-TE		
	DWDM SFP	--	12.2(18)ZU2

Catalyst 2900 Switches SupportCatalyst 2900 series

Network Device	Transceiver Module	Minimum Software Release Required	
		Catalyst OS	Cisco IOS Release
WS-C2980G-A	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2.1	--
WS-C2948G	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2	--
WS-C2948G-L3	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2	--

Catalyst 2900 series

Network Device	Transceiver Module	Minimum Software Release Required	
		Catalyst OS	Cisco IOS Release
WS-C2948G-GE-TX	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD CWDM SFP	8.2(1)GLX --	--
WS-C2912MF-XL with WS-X2931-XL	WS-G5482 WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	-- -- -- --	12.0(5)XW 12.0(5)WC3b 12.0(5)WC5
WS-C2924M-XL-EN with WS-X2931-XL	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	-- -- --	12.0(5)WC3b 12.0(5)WC5
WS-C2924M-XL-EN-DC with WS-X2931-XL	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	-- -- --	12.0(5)WC3b 12.0(5)WC5

Catalyst 2940 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2940-8TF-S	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	12.1(13)AY

Catalyst 2940 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-ZX-SMD		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		

Catalyst 2950 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2950G-12-EI	WS-G5483	--	12.1(6)EA2b
WS-C2950G-24-EI	WS-G5484	--	
WS-C2950G-24-EI-DC	WS-G5486	--	
WS-C2950G-48-EI	WS-G5487	--	
	CWDM GBIC	--	12.1(12c)EA1
	DWDM GBIC	--	12.1(20)EA2
WS-C2950ST-8 LRE	GLC-T (1000BASE-T)	--	12.1(19)EA1c
WS-C2950ST-24 LRE	GLC-TE (1000BASE-T)	--	
WS-C2950ST-24 LRE997	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	

Catalyst 2960 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960-24TC-L	GLC-T (1000BASE-T)	--	12.2(25)FX
WS-C2960G-24TC-L	GLC-TE (1000BASE-T)		
WS-C2960-48TC-L	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD		
WS-C2960-24PC-L	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.2(44)SE
WS-C2960-24TC-S	GLC-T (1000BASE-T)	--	12.2(37)EY
WS-C2960-48TC-S	GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD		
WS-C2960-8TC-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(46)SE

Catalyst 2960 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960-48PST-L	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.2(46)SE
WS-C2960-8TC-L	GLC-SX-MM	--	12.2(35)SE
WS-C2960G-8TC-L	GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD		
WS-C2960G-48TC-L	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.2(25)SEE
WS-C2960-48PST-S	GLC-T (1000BASE-T)	--	12.2(50)SE
WS-C2960-24PC-S	GLC-TE (1000BASE-T)		
WS-C2960-24LC-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD		

Catalyst 2960 Plus Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960+48PST-L	GLC-T (1000BASE-T)	--	15.0(2)EZ
WS-C2960+24PC-L	GLC-TE (1000BASE-T)		
WS-C2960+24LC-L	GLC-SX-MM		
WS-C2960+48TC-L	GLC-LH-SM		
WS-C2960+24TC-L	GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD		
WS-C2960+48PST-S	GLC-T (1000BASE-T)	--	15.0(2)EZ
WS-C2960+24PC-S	GLC-TE (1000BASE-T)		
WS-C2960+24LC-S	GLC-SX-MM		
WS-C2960+48TC-S	GLC-LH-SM		
WS-C2960+24TC-S	GLC-SX-MMD GLC-LH-SMD		

Catalyst 2960 S Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960S-24TS-S	GLC-T (1000BASE-T)	--	12.2(53)SE1
WS-C2960S-48TS-S	GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SM		
	GLC-EX-SMD ¹	--	IOS 12.2(58)SE

¹ CPN 10-2624-01 or later only.

Catalyst 2960 S Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960S-48FPS-L	GLC-T (1000BASE-T)	--	12.2(53)SE1
WS-C2960S-48LPS-L	GLC-TE (1000BASE-T)	--	
WS-C2960S-24PS-L	GLC-SX-MM	--	
WS-C2960S-48TS-L	GLC-LH-SM	--	
WS-C2960S-24TS-L	GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	IOS 12.2(58)SE
	GLC-EX-SMD ¹	--	IOS 12.2(58)SE
WS-C2960S-48FPD-L	GLC-SX-MM	--	12.2(53)SE1
WS-C2960S-48LPD-L	GLC-LH-SM	--	
WS-C2960S-24PD-L	GLC-ZX-SM	--	
WS-C2960S-48TD-L	GLC-ZX-SMD	--	
WS-C2960S-24TD-L	GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	IOS 12.2(58)SE
	GLC-EX-SMD ¹	--	IOS 12.2(58)SE

Catalyst 2960 SF Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
2960S-F48TS-S	GLC-T (1000BASE-T)	--	15.0(2)SE
2960S-F24TS-S	GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD ¹	--	

Catalyst 2960 SF Series

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
2960S-F48FPS-L	GLC-T (1000BASE-T)	--	15.0(2)SE
2960S-F48LPS-L	GLC-TE (1000BASE-T)		
2960S-F24PS-L	GLC-SX-MM		
2960S-F48TS-L	GLC-LH-SM		
2960S-F24TS-L	GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD ¹		

Catalyst 2960 C Series

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
WS-C2960CG-8TC-L	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP	--	12.2(55)EX1
	GLC-EX-SMD ¹	--	15.0(2)SE
WS-C2960C-8TC-S	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD	--	12.2(55)EX3

Catalyst 2960 C Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960C-8TC-L	GLC-SX-MM	--	12.2(55)EX3
WS-C2960C-8PC-L	GLC-SX-MMD		
WS-C2960C-12PC-L	GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP		
	GLC-EX-SMD ¹	--	15.0(2)SE

Catalyst 2960 X Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960X-24TS-LL	GLC-LH-SMD	15.0(2)EX	15.0(2)EX
WS-C2960X-48TS-LL	GLC-SX-MMD GLC-EX-SMD ¹ GLC-T GLC-TE GLC-LH-SM GLC-SX-MM GLC-GE-100FX		
WS-C2960X-24PSQ-L	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD ¹ GLC-ZX-SMD GLC-T GLC-TE GLC-ZX-SM GLC-LH-SM GLC-SX-MM	15.0(2)EX	15.0(2)EX

Catalyst 2960 X Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960X-24PS-L	GLC-BX-D	15.0(2)EX	15.0(2)EX
WS-C2960X-24TS-L	GLC-BX-U		
WS-C2960X-48TS-L	GLC-LH-SMD		
WS-C2960X-48LPS-L	GLC-SX-MMD		
WS-C2960X-48FPS-L	GLC-EX-SMD ¹		
WS-C2960X-24TD-L	GLC-ZX-SMD		
WS-C2960X-24PD-L	GLC-T		
WS-C2960X-48TD-L	GLC-TE		
WS-C2960X-48LPD-L	GLC-ZX-SM		
WS-C2960X-48FPD-L	GLC-LH-SM GLC-SX-MM CWDM-SFP GLC-GE-100FX		

Catalyst 2960 XR Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960XR-24TS-I	GLC-BX-D	15.0(2)EX1	15.0(2)EX1
WS-C2960XR-48TS-I	GLC-BX-U		
WS-C2960XR-24PS-I	GLC-LH-SMD		
WS-C2960XR-48LPS-I	GLC-SX-MMD		
WS-C2960XR-48FPS-I	GLC-EX-SMD ¹		
WS-C2960XR-24TD-I	GLC-ZX-SMD		
WS-C2960XR-48TD-I	GLC-T		
WS-C2960XR-24PD-I	GLC-TE		
WS-C2960XR-48LPD-I	GLC-ZX-SM		
WS-C2960XR-48FPD-I	GLC-LH-SM GLC-SX-MM CWDM-SFP GLC-GE-100FX		

Catalyst 2960 L Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960L-8TS-LL	GLC-BX-D	15.2(5)E	15.2(5)E
WS-C2960L-8PS-LL	GLC-BX-U		
WS-C2960L-16TS-LL	GLC-LH-SMD		
WS-C2960L-16PS-LL	GLC-SX-MMD		
WS-C2960L-24TS-LL	GLC-EX-SMD		
WS-C2960L-24PS-LL	GLC-ZX-SMD		
WS-C2960L-48TS-LL	GLC-T		
WS-C2960L-48PS-LL	GLC-ZX-SM		
WS-C2960L-24TQ-LL	GLC-LH-SM		
WS-C2960L-24PQ-LL	GLC-SX-MM		
WS-C2960L-48TQ-LL	CWDM SFP		
WS-C2960L-48PQ-LL			
	GLC-TE		15.2(5)E2

Catalyst 2960 CX Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2960CX-8TC-L	GLC-BX-D	15.2(3)E	15.2(3)E
WS-C2960CX-8PC-L	GLC-BX-U		
	GLC-GE-100FX		
	GLC-LH-SMD		
	GLC-SX-MMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
	GLC-ZX-SM		
	GLC-LH-SM		
	GLC-SX-MM		
	CWDM SFP		
WS-C2960CX-8TC-L	GLC-T (10/100/1000)	15.2(5)E	15.2(5)E
WS-C2960CX-8PC-L	GLC-TE		

Catalyst 2970 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2970G-24TS-E	GLC-T (10/100/1000)	--	12.1(14)EA1
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	GLC-SX-MMD		
	GLC-LH-SMD		

Catalyst 2975 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C2975GS-48PS-L	GLC-T (1000BASE-T)	--	12.2(46)EX
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		

Catalyst 3500 Switches SupportCatalyst 3500XL series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
WS-C3508G-XL-EN	WS-G5482	--	12.0(5)XW
WS-C3512-XL-EN			
WS-C3524-XL-EN	WS-G5483	--	12.0(5)WC3b
WS-C3524-PWR-XL-EN	WS-G5484		
WS-C3548-XL-EN	WS-G5486		
	WS-G5487		
	CWDM GBIC		

Catalyst 3550 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3550-24-SMI	WS-G5482	--	12.1(6)EA1a
WS-C3550-24-EMI			
WS-C3550-24-DC-SMI	WS-G5483	--	12.1(8)EA1b
	WS-G5484		
	WS-G5486		
	WS-G5487		
	CWDM GBIC	--	12.1(12c)EA1
	DWDM GBIC	--	12.1(20)EA2
WS-C3550-24-FX-SMI	WS-G5482	--	12.1(12c)EA1
WS-C3550-24PWR-SMI	WS-G5483		
WS-C3550-24PWR-EMI	WS-G5484		
	WS-G5486		
	WS-G5487		
	CWDM GBIC	--	12.1(20)EA2
WS-C3550-48-SMI	WS-G5482	--	12.1(8)EA1b
WS-C3550-48-EMI	WS-G5483		
	WS-G5484		
	WS-G5486		
	WS-G5487		
	CWDM GBIC	--	12.1(12c)EA1
	DWDM GBIC	--	12.1(20)EA2
WS-C3550-12G	WS-G5482	--	12.1(6)EA1
WS-C3550-12T	WS-G5483	--	12.1(8)EA1b
	WS-G5484		
	WS-G5486		
	WS-G5487		
	CWDM GBIC	--	12.1(12c)EA1
	DWDM GBIC	--	12.1(20)EA2

Catalyst 3560 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560-24PS	GLC-T (10/100/1000)	--	12.1(19)EA1c
WS-C3560-48PS	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD	12.2(46)SE	12.1(19)EA1c
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D	12.2(46)SE	12.2(25)SEB
	GLC-BX-U		
	DWDM SFP	12.2(46)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
WS-C3560G-24TS	GLC-T (10/100/1000)	--	12.2(20)SE3
WS-C3560G-48TS	GLC-TE		
WS-C3560G-48PS	GLC-SX-MM		
WS-C3560G-24PS	GLC-LH-SM		
	GLC-SX-MMD	12.2(46)SE	12.2(20)SE3
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D	12.2(46)SE	12.2(25)SEB
	GLC-BX-U		
	DWDM SFP	12.2(46)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE

Catalyst 3560 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560-48TS	GLC-T (10/100/1000)	--	12.2(20)SE3
WS-C3560-24TS	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD	12.2(46)SE	12.2(20)SE3
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D	12.2(46)SE	12.2(25)SEB
	GLC-BX-U		
	DWDM SFP	12.2(46)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
WS-C3560-8PC	GLC-T (10/100/1000)	--	12.2(35)SE
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SM	12.2(46)SE	12.2(35)SE
	GLC-ZX-SMD		
	CWDM SFP		
	GLC-BX-D		
	GLC-BX-U		
WS-C3560-12PC-S	GLC-SX-MM	--	12.2(46)SE
	GLC-LH-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SM	12.2(46)SE	12.2(46)SE
	GLC-ZX-SMD		
	CWDM SFP		
	GLC-BX-D		
	GLC-BX-U		

Catalyst 3560 series

		Minimum Software Release Required	
Network Device	Transceiver Model	DOM Support	Software Release
WS-C3560V2-24PS	GLC-T (10/100/1000)	--	12.2(50)SE
WS-C3560V2-24TS	GLC-TE		
WS-C3560V2-48PS	GLC-SX-MM		
WS-C3560V2-48TS	GLC-LH-SM		
	GLC-SX-MMD	12.2(50)SE	12.2(50)SE
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	SFP-GE-S		
	SFP-GE-L		
	CWDM SFP		
	GLC-BX-D		
	GLC-BX-U		
	DWDM SFP		
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE

Catalyst 3560 E Series

		Minimum Software Release Required	
Network Device	Transceiver Model	DOM Support	Software Release
WS-C3560E-24TD	GLC-T (10/100/1000)	--	12.2(35)SE2
WS-C3560E-24PD	GLC-TE		
WS-C3560E-48TD	GLC-SX-MM		
WS-C3560E-48PD	GLC-LH-SM		
WS-C3560E-48PDF			
With CVR-X2-SFP (for X2 ports)	GLC-SX-MMD	12.2(46)SE	12.2(35)SE2
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	DWDM SFP	12.2(46)SE	12.2(40)SE

Catalyst 3560 E Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE
WS-C3560E-12D With CVR-X2-SFP (for X2 ports)	GLC-T (10/100/1000)	--	12.2(40)EX
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD	12.2(46)SE	12.2(40)EX
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE
WS-C3560E-12SD	GLC-T (10/100/1000)	--	12.2(44)SE
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD	12.2(46)SE	12.2(44)SE
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE

Catalyst 3560 E Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE
WS-C3560E-12SD With CVR-X2-SFP (for X2 ports)	GLC-T (10/100/1000) GLC-TE GLC-SX-MM GLC-LH-SM	--	12.2(44)SE
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(44)SE
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE

Catalyst 3560 X Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560X-24T	GLC-T (10/100/1000)	--	12.2(53)SE
WS-C3560X-48T	GLC-TE		
WS-C3560X-24P	GLC-SX-MM		
WS-C3560X-48P	GLC-LH-SM		

Catalyst 3560 X Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560X-48PF With C3KX-NM-1G and C3KX-NM-10G (slots 1 and 3) network modules	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(53)SE	12.2(53)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE
WS-C3560X-24T WS-C3560X-48T WS-C3560X-24P WS-C3560X-48P WS-C3560X-48PF With C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP DWDM SFP (add.)	--	12.2(53)SE 12.2(53)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE

Catalyst 3560 CX Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560CX-8PC-S	GLC-BX-D	15.2(3)E	15.2(3)E
WS-C3560CX-8TC-S	GLC-BX-U		
WS-C3560CX-12TC-S	GLC-GE-100FX		
WS-C3560CX-12PC-S	GLC-LH-SMD		
WS-C3560CX-12PD-S	GLC-SX-MMD		
WS-C3560CX-8XPD-S	GLC-EX-SMD GLC-ZX-SMD GLC-ZX-SM GLC-LH-SM GLC-SX-MM DWDM SFP CWDM SFP		
WS-C3560CX-8PC-S	GLC-T(10/100/1000	15.2(5)E	15.2(5)E
WS-C3560CX-8TC-S	GLC-TE		
WS-C3560CX-12TC-S			
WS-C3560CX-12PC-S			
WS-C3560CX-12PD-S			
WS-C3560CX-8XPD-S			

Catalyst 3560 C Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560CG-8TC-S	GLC-SX-MM	--	12.2(55)EX
WS-C3560CG-8PC-S	GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP		
	GLC-EX-SMD ¹	--	15.0(2)SE

Catalyst 3560 C Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3560C-8PC-S	GLC-SX-MM	--	12.2(55)EX3
WS-C3560C-12PC-S	GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP		
	GLC-EX-SMD ¹	--	15.0(2)SE

Catalyst 3600 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
WS-C3650-24TS	GLC-T (10/100/1000)	XE 3.3.0SE,	XE 3.3.0SE, 16.1.1
WS-C3650-48TS	GLC-LH-SM	16.1.1	
WS-C3650-24PS	GLC-LH-SMD		
WS-C3650-48PS	GLC-SX-MM		
WS-C3650-48FS	GLC-SX-MMD		
WS-C3650-24TD	GLC-EX-SMD ¹		
WS-C3650-48TD	GLC-ZX-SM		
WS-C3650-24PD	GLC-ZX-SMD		
WS-C3650-48PD	GLC-BX-D		
WS-C3650-48FD	GLC-BX-U		
WS-C3650-48FQ	CWDM SFP		
WS-C3650-48PQ	SFP-GE-S		
WS-C3650-48TQ	SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP		
	GLC-BX40-D-I	XE 3.7.1E, 16.1.1	XE 3.7.1E, 16.1.1
	GLC-BX40-DA-I		
	GLC-BX40-U-I		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	GLC-TE	XE 3.6.7E, XE 3.7.5E, 16.5.1a, 16.3.5	

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 3700 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
WS-C3650-24PDM	GLC-T (10/100/1000)	16.2.1	16.2.1
WS-C3650-48FQMR	GLC-LH-SM		
WS-C3650-8X24UQ	GLC-LH-SMD		
WS-C3650-12X48UQ	GLC-SX-MM		
WS-C3650-12X48UR	GLC-SX-MMD		
WS-C3650-12X48UZ	GLC-EX-SMD ¹		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-T		
	SFP-GE-Z		
	DWDM SFP		
	GLC-BX40-D-I	16.2.1	16.2.1
	GLC-BX40-DA-I		
	GLC-BX40-U-I		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	GLC-TE		16.5.1a, 16.3.5

Catalyst 3700 Series Switches Support

Catalyst 3750 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
WS-C3750G-12S	GLC-T (10/100/1000)	--	12.1.(14)EA1
WS-C3750G-24TS	GLC-TE		
WS-C3750G-48TS	GLC-SX-MM		
WS-C3750G-24PS	GLC-LH-SM		
WS-C3750G-48PS	GLC-SX-MMD	12.2(46)SE	12.1(14)EA1
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		

Catalyst 3750 series

Catalyst 3750 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
	GLC-SX-MMD	12.2(46)SE	12.1(19)EA1c
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D	12.2(46)SE	12.2(25)SEB
	GLC-BX-U		
	DWDM SFP	12.2(46)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
WS-C3750-24FS-S	GLC-T (10/100/1000)	--	12.2(25)SEB
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD	12.2(46)SE	12.2(25)SEB
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	CWDM SFP		
	GLC-BX-D		
	GLC-BX-U		
	DWDM SFP	12.2(46)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
WS-C3750-24WFS	GLC-T (1000BASE-T)	--	12.2(25)FZ
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		

Catalyst 3750 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
	GLC-SX-MMD	12.2(46)SE	12.2(25)FZ
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	CWDM SFP		
	GLC-BX-D		
	GLC-BX-U		
	DWDM SFP	12.2(46)SE	12.2(40)SE
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
WS-C3750V2-24PS	GLC-T (10/100/1000)	--	12.2(50)SE
WS-C3750V2-24TS	GLC-TE		
WS-C3750V2-48PS	GLC-SX-MM		
WS-C3750V2-48TS	GLC-LH-SM		
WS-C3750V2-24FS (uplink ports)	GLC-SX-MMD	12.2(50)SE	12.2(50)SE
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	CWDM SFP		
	GLC-BX-D		
	GLC-BX-U		
	DWDM SFP		
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE

Catalyst 3750-E series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3750E-24TD	GLC-T (10/100/1000)	--	12.2(35)SE2
WS-C3750E-24PD	GLC-TE		
WS-C3750E-48TD	GLC-SX-MM		
WS-C3750E-48PD	GLC-LH-SM		
WS-C3750E-48PDF			
With CVR-X2-SFP (for X2 ports)	GLC-SX-MMD	12.2(46)SE	12.2(35)SE2
	GLC-LH-SMD		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
DWDM SFP		12.2(44)SE	12.2(40)SE
DWDM SFP (add.)		12.2(52)SE	12.2(52)SE
GLC-EX-SMD ¹		12.2(58)SE	12.2(58)SE

Catalyst 3750-X series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3750X-24T	GLC-T (10/100/1000)	--	12.2(53)SE
WS-C3750X-48T	GLC-TE		
WS-C3750X-24P	GLC-SX-MM		
WS-C3750X-48P	GLC-LH-SM		

Catalyst 3750-X series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-C3750X-48PF With C3KX-NM-1G and C3KX-NM-10G (slots 1 and 3) network modules	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)	12.2(53)SE	12.2(53)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE
WS-C3750X-24T WS-C3750X-48T WS-C3750X-24P WS-C3750X-48P WS-C3750X-48PF With C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)	--	12.2(53)SE
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE
WS-C3750X-12S WS-C3750X-24S Client ports and uplink ports with C3KX-NM-1G and	GLC-T (10/100/1000) GLC-TE GLC-SX-MM GLC-LH-SM	--	12.2(55)SE5

Catalyst 3750-X series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
C3KX-NM-10G (slots 1 and 3) network modules	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)	12.2(55)SE5	12.2(55)SE5
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE
WS-C3750X-12S WS-C3750X-24S	GLC-SX-MM GLC-LH-SM	--	12.2(55)SE5
Uplink ports with C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)	12.2(55)SE5	12.2(55)SE5
	GLC-EX-SMD ¹	12.2(58)SE	12.2(58)SE

Catalyst 3800 Series Switches Support

Catalyst 3850 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
C3850-NM-4-1G Uplink Module	GLC-T (10/100/1000) GLC-LH-SM GLC-LH-SMD	XE 3.2.0SE, 16.1.1	XE 3.2.0SE, 16.1.1
WS-C3850-12S WS-C3850-24S	GLC-SX-MM GLC-SX-MMD GLC-EX-SMD ¹ GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP DWDM SFP (add.)	XE 3.3.3SE, 16.1.1	XE 3.3.3SE, 16.1.1
	GLC-BX40-D-I GLC-BX40-DA-I GLC-BX40-U-I GLC-BX80-D-I GLC-BX80-U-I	XE 3.7.1E, 16.1.1	XE 3.7.1E, 16.1.1
	GLC-TE	XE 3.6.7E, XE 3.7.5E, 16.5.1a, 16.3.5	

Catalyst 3850 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
WS-C3850-12XS	GLC-T (10/100/1000)	XE 3.7.1E, 16.1.1	XE 3.7.1E, 16.1.1
WS-C3850-16XS	GLC-LH-SM		
WS-C3850-24XS	GLC-LH-SMD		
WS-C3850-32XS	GLC-SX-MM		
(with C3850-NM-8-10G NM)	GLC-SX-MMD GLC-EX-SMD ¹ GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP DWDM SFP (add.) GLC-BX40-D-I GLC-BX40-DA-I GLC-BX40-U-I GLC-BX80-D-I GLC-BX80-U-I		
GLC-TE	-		XE 3.7.5E, 16.5.1a, 16.3.5

Catalyst 3850 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
WS-C3850-48XS-S	GLC-T (10/100/1000)	XE 3.7.2E, 16.2.1	XE 3.7.2E, 16.2.1
WS-C3850-48XS-E	GLC-LH-SM		
WS-C3850-48XS-F-S	GLC-LH-SMD		
WS-C3850-48XS-F-E	GLC-SX-MM		
WS-C3850-48XS	GLC-SX-MMD		
	GLC-EX-SMD ¹		
	GLC-ZX-SM		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-T		
	SFP-GE-Z		
	DWDM SFP		
	DWDM SFP (add.)		
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX40-U-I		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
GLC-TE	-		XE 3.7.5E, 16.5.1a, 16.3.5

Catalyst 9300 Series Switches Support

Catalyst 9300 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
C9300-24T	GLC-LH-SM		XE 16.5.1a
C9300-24P	GLC-LH-SMD		
C9300-24U	GLC-SX-MM		
C9300-24XU	GLC-SX-MMD		
C9300-48T	GLC-EX-SMD ¹		
C9300-48P	GLC-ZX-SM		
C9300-48U (With C9300-NM-8X, or C9300-NM-4G, or C3850-NM-4-1G, or C3850-NM-8-10G for 1G uplink modules)	GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP DWDM SFP (add.) GLC-BX40-D-I GLC-BX40-DA-I GLC-BX40-U-I GLC-BX80-D-I GLC-BX80-U-I		
	GLC-T	-	XE 16.5.1a
	GLC-TE		

Catalyst 9400 Series Switches Support

Catalyst 9400 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
C9400-SUP-1	GLC-T (1000BASE-T) GLC-TE (1000BASE-T)	-	XE 16.6.1
	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD CWDM-SFP-xxxx DWDM-SFP-xxxx		XE 16.6.1
C9400-Sup-1XL	GLC-SX-MM	XE 16.6.2	XE 16.6.2
C9400-LC-24XS	GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD CWDM-SFP-xxxx DWDM-SFP-xxxx		
	GLC-T (1000BASE-T) GLC-TE (1000BASE-T)	-	

Catalyst 9500 Series Switches Support

Catalyst 9500 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release

Catalyst 9500 series

Minimum Software Release Required			
Network Device	Transceiver Module	DOM Support	Cisco IOS Release
C9500-40X	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-T GLC-TE GLC-BX-U GLC-BX-D GLC-GE-100FX CWDM-SFP DWDM-SFP		XE 16.6.1

Industrial Ethernet and Smart Grid Support

Cisco IE1000 series

Minimum Software Release Required			
Network Device	Transceiver Module	DOM Support	Cisco OS Release
IE-1000-4P2S-LM	GLC-SX-MM-RGD	NA	1.3
IE-1000-8P2S-LM	GLC-LX-SM-RGD GLC-ZX-SM-RGD GLC-SX-MM* GLC-SX-MMD* GLC-LH-SM* GLC-LH-SMD* GLC-EX-SMD* GLC-BX-D* GLC-BX-U* GLC-BX40-U-I GLC-BX40-DA-I GLC-BX80-U-I GLC-BX80-D-I GLC-T* GLC-TE*		

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Industrial Ethernet and Smart Grid Support

Cisco IE2000 series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
IE-2000-4TS-G-L	GLC-SX-MM-RGD	15.0(1)EY	15.0(1)EY
IE-2000-4TS-G-B	GLC-LX-SM-RGD		
IE-2000-4S-TS-G-L	GLC-ZX-SM-RGD		
IE-2000-4S-TS-G-B	SFP-GE-S*		
IE-2000-8TC-G-L	SFP-GE-L*		
IE-2000-8TC-G-B	SFP-GE-Z*		
IE-2000-8TC-G-E	GLC-ZX-SM*		
IE-2000-8TC-G-N	GLC-SX-MMD*		
IE-2000-16TC-G-L	GLC-LH-SMD*		
IE-2000-16TC-G-E	GLC-EX-SMD*		
IE-2000-16TC-G-X	GLC-ZX-SMD*		
IE-2000-16TC-G-N	GLC-BX-D*		
IE-2000-16PTC-G-L	GLC-BX-U*		
IE-2000-16PTC-G-E	CWDM-SFP-xxxx*		
IE-2000-16PTC-G-NX	DWDM-SFP-xxxx*		
	GLC-SX-MM*	--	15.0(1)EY
	GLC-LH-SM*		
	GLC-T*	--	15.2(1)EY
	GLC-TE*		
	GLC-BX40-U-I	15.2(3)EA	15.2(3)EA
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Cisco IE2000U series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
IE 2000U-4TS-G	GLC-SX-MM-RGD	15.0(2)EK1	15.0(2)EH
IE 2000U-8TC-G	GLC-LX-SM-RGD		
IE 2000U-16TC-G	GLC-ZX-SM-RGD		
IE 2000U-16TC-G-X	SFP-GE-S*		
	SFP-GE-L*		

Cisco IE2000U series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
IE 2000U-16TC-GP	SFP-GE-Z*		
	GLC-ZX-SM*		
	GLC-SX-MMD*		
	GLC-LH-SMD*		
	GLC-EX-SMD*		
	GLC-ZX-SMD*		
	GLC-BX-D*		
	GLC-BX-U*		
	CWDM-SFP-xxxx*		
	DWDM-SFP-xxxx*		
IE-2000U-4S-G	GLC-SX-MM*	--	15.0(2)EH
	GLC-LH-SM*		
	GLC-T*	--	15.2(4)EA
	GLC-TE*		
	GLC-BX40-U-I	15.2(3)EA	15.2(3)EA
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		
	GLC-SX-MM-RGD	15.0(2)EK1	15.0(2)EK1
IE-2000U-4S-G	GLC-LX-SM-RGD		
	GLC-ZX-SM-RGD		
	SFP-GE-S*		
	SFP-GE-L*		
	SFP-GE-Z*		
	GLC-ZX-SM*		
	GLC-SX-MMD*		
	GLC-LH-SMD*		
	GLC-EX-SMD*		
	GLC-ZX-SMD*		
IE-2000U-4S-G	GLC-BX-D*		
	GLC-BX-U*		
	CWDM-SFP-xxxx*		
	DWDM-SFP-xxxx*		
	GLC-SX-MM*	--	15.0(2)EK1
	GLC-LH-SM*		
	GLC-T*	--	15.2(4)EA
	GLC-TE*		

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Industrial Ethernet and Smart Grid Support

Cisco IE2000U series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-BX40-U-I	15.2(3)EA	15.2(3)EA
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Cisco IE3000 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
IE-3000-4TC	GLC-SX-MM-RGD	12.2(44)EX	12.2(44)EX
IE-3000-8TC	GLC-LX-SM-RGD		
	GLC-ZX-SM-RGD		
	SFP-GE-S*		
	SFP-GE-L*		
	SFP-GE-Z*		
	GLC-ZX-SM*		
	GLC-SX-MMD*		
	GLC-LH-SMD*		
	GLC-ZX-SMD*		
	GLC-BX-D*		
	GLC-BX-U*		
	CWDM-SFP-xxxx*		
	DWDM-SFP-xxxx*		
	GLC-SX-MM*	--	12.2(44)EX
	GLC-LH-SM*		
	GLC-T*		
	GLC-TE*		
	GLC-EX-SMD*	12.2(58)SE1	12.2(58)SE1
	GLC-BX40-U-I	15.2(3)EA	15.2(3)EA
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Cisco IE3010 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
IE-3010-24TC	GLC-SX-MM-RGD	12.2(53)EZ	12.2(53)EZ
IE-3010-16S-8PC	GLC-LX-SM-RGD GLC-ZX-SM-RGD SFP-GE-S* SFP-GE-L* SFP-GE-Z* GLC-ZX-SM* GLC-SX-MMD* GLC-LH-SMD* GLC-ZX-SMD* GLC-BX-D* GLC-BX-U* CWDM-SFP-xxxx* DWDM-SFP-xxxx*		
	GLC-SX-MM*	--	12.2(53)EZ
	GLC-LH-SM*		
	GLC-BX40-U-I GLC-BX40-D-I GLC-BX40-DA-I GLC-BX80-U-I GLC-BX80-D-I	15.2(3)EA	15.2(3)EA
	GLC-EX-SMD*	15.0(2)SE	15.0(2)SE
	GLC-T* GLC-TE*	--	Not Supported (Has Combo Ports)

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Cisco IE4000 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
IE-4000-4TC4G-E	GLC-SX-MM-RGD	15.2(2)EA	15.2(2)EA
IE-4000-8T4G-E	GLC-LX-SM-RGD		
IE-4000-8S4G-E	GLC-ZX-SM-RGD		
IE-4000-4T4P4G-E	SFP-GE-S*		
IE-4000-16T4G-E	SFP-GE-L*		
IE-4000-4S8P4G-E	SFP-GE-Z*		
IE-4000-8GT4G-E	GLC-ZX-SM*		
IE-4000-8GS4G-E	GLC-SX-MMD*		
IE-4000-4GC4GP4G-E	GLC-LH-SMD*		
IE-4000-16GT4G-E	GLC-EX-SMD*		
IE-4000-8GT8GP4G-E	GLC-ZX-SMD*		
IE-4000-4GS8GP4G-E	GLC-BX-D*		
	GLC-BX-U*		
	CWDM-SFP-xxxx*		
	DWDM-SFP-xxxx*		
	GLC-SX-MM*	--	15.2(2)EA
	GLC-LH-SM*		
	GLC-T*		
	GLC-TE*		
	GLC-BX40-U-I	15.2(4)EA	15.2(4)EA
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Cisco IE4010 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
IE-4010-4S24P	GLC-SX-MM-RGD	15.2(4)EC	15.2(4)EC
IE-4010-16S12P	GLC-LX-SM-RGD GLC-ZX-SM-RGD SFP-GE-S* SFP-GE-L* SFP-GE-Z* GLC-ZX-SM* GLC-SX-MMD* GLC-LH-SMD* GLC-EX-SMD* GLC-ZX-SMD* GLC-BX-D* GLC-BX-U* GLC-BX40-U-I GLC-BX40-D-I GLC-BX40-DA-I GLC-BX80-U-I GLC-BX80-D-I CWDM-SFP-xxxx* DWDM-SFP-xxxx*		
	GLC-SX-MM* GLC-LH-SM* GLC-T* GLC-TE*	-	15.2(4)EC

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Cisco IE5000 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
IE-5000-12S12P-10G	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD SFP-GE-S* SFP-GE-L* SFP-GE-Z* GLC-ZX-SM* GLC-SX-MMD* GLC-LH-SMD* GLC-EX-SMD* GLC-ZX-SMD* GLC-BX-D* GLC-BX-U* CWDM-SFP-xxxx* DWDM-SFP-xxxx*	15.2(2)EB	15.2(2)EB
	GLC-SX-MM* GLC-LH-SM* GLC-T* GLC-TE*	--	15.2(2)EB
	GLC-BX40-U-I GLC-BX40-D-I GLC-BX40-DA-I GLC-BX80-U-I GLC-BX80-D-I	15.2(4)EA1	15.2(4)EA1
IE-5000-16S12P	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD SFP-GE-S* SFP-GE-L* SFP-GE-Z* GLC-ZX-SM* GLC-SX-MMD* GLC-LH-SMD* GLC-EX-SMD* GLC-ZX-SMD* GLC-BX-D* GLC-BX-U* CWDM-SFP-xxxx* DWDM-SFP-xxxx*	15.2(2)EB1	15.2(2)EB1

Cisco IE5000 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-SX-MM*	--	15.2(2)EB1
	GLC-LH-SM*		
	GLC-T*		
	GLC-TE*		
	GLC-BX40-U-I	15.2(4)EA1	15.2(4)EA1
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Cisco 2500 Connected Grid Switch Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
CGS-2520-24TC	GLC-SX-MM-RGD	12.2(53)EX	12.2(53)EX
CGS-2520-16S-8PC	GLC-LX-SM-RGD		
	GLC-ZX-SM-RGD		
	SFP-GE-S*		
	SFP-GE-L*		
	SFP-GE-Z*		
	GLC-ZX-SM*		
	GLC-SX-MMD*		
	GLC-LH-SMD*		
	GLC-ZX-SMD*		
	GLC-BX-D*		
	GLC-BX-U*		
	CWDM-SFP-xxxx*		
	DWDM-SFP-xxxx*		
	GLC-SX-MM*	--	12.2(53)EX
	GLC-LH-SM*		
	GLC-EX-SMD*	12.2(58)EY	12.2(58)EY
	GLC-BX40-U-I	15.2(3)EA	15.2(3)EA
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		

Cisco 2500 Connected Grid Switch Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-T*	--	Not Supported(Has Combo Ports)
	GLC-TE*		

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated. Please refer to [table 2](#).

Cisco 2000 Connected Grid Router Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
CGR 2010 (Router Onboard Ethernet)	GLC-SX-MM-RGD	15.3(3)M	15.1(1)T
	GLC-LX-SM-RGD		
	GLC-ZX-SM-RGD		
	SFP-GE-S*	15.3(3)M	15.3(3)M
	SFP-GE-L*		
	SFP-GE-Z*		
	GLC-SX-MM*		
	GLC-LH-SM*		
	GLC-ZX-SM*		
	GLC-SX-MMD*		
	GLC-LH-SMD*		
	GLC-ZX-SMD*		
	GLC-BX-D*		
	GLC-BX-U*		
	CWDM-SFP-xxxx*		
	DWDM-SFP-xxxx*		
	GLC-EX-SMD*	15.4(3)M	15.4(3)M
	GLC-T*	--	Not Supported
	GLC-TE*		(Has Combo Ports)
	GLC-BX40-U-I	--	Not Supported Yet
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		

Cisco 2000 Connected Grid Router Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
GRWIC-D-ES-2S-8PC	GLC-SX-MM-RGD	12.2(58)EY	12.2(58)EY
GRWIC-D-ES-6S	GLC-LX-SM-RGD		
	GLC-ZX-SM-RGD		
	SFP-GE-S*		
	SFP-GE-L*		
	SFP-GE-Z*		
	GLC-ZX-SM*		
	GLC-SX-MMD*		
	GLC-LH-SMD*		
	GLC-EX-SMD*		
	GLC-ZX-SMD*		
	GLC-BX-D*		
	GLC-BX-U*		
	CWDM-SFP-xxxx*		
	DWDM-SFP-xxxx*		
	GLC-SX-MM*	--	12.2(58)EY
	GLC-LH-SM*		
	GLC-T*	--	15.2(3)EA
	GLC-TE*		(Only in G0/2 since G0/1 is Combo Port)
	GLC-BX40-U-I	15.2(3)EA	15.2(3)EA
	GLC-BX40-D-I		
	GLC-BX40-DA-I		
	GLC-BX80-U-I		
	GLC-BX80-D-I		

*When using non-rugged/not industrial -rated transceivers, the hardened platform temperature range is de-rated.

Catalyst 4500 Switches Support

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
WS-X4013	WS-G5483	--	--
	WS-G5484		
	WS-G5486		
	WS-G5487		
	CDWM GBIC		
WS-X4013+	WS-G5483	--	12.1(19)EW
	WS-G5484		
	WS-G5486		
	WS-G5487		
	CDWM GBIC		
	DWDM GBIC	12.1(19)EW	12.1(19)EW
WS-X4013+TS	GLC-SX-MM	--	12.2(20)EWA
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-BX-D	12.2(20)EWA	12.2(20)EWA
	GLC-BX-U		
DWDM SFP	CWDM SFP		
	DWDM SFP	12.2(37)SG	12.2(37)SG
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
WS-X4013+10GE	GLC-SX-MM	--	12.2(25)SG
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-BX-D	12.2(25)SG	12.2(25)SG
	GLC-BX-U		
DWDM SFP	CWDM SFP		
	DWDM SFP	12.2(37)SG	12.2(37)SG
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
WS-X4014	WS-G5483	--	12.1(13)EW
WS-X4232-GB-RJ			
WS-X4306-GB	WS-G5484	--	12.1(8a)EW
WS-X4412-2GB-T	WS-G5486		
	WS-G5487		
	CWDM GBIC	--	12.1(12c)EW
	DWDM GBIC	12.1(19)EW	12.1(19)EW
WS-X4418-GB	WS-G5484	--	12.1(8a)EW
	WS-G5486		
	WS-G5487		
	CWDM GBIC	--	12.1(12c)EW
	DWDM GBIC	12.2(19)EW	12.1(19)EW
WS-X4302-GB	WS-G5483	--	12.1(19)EW
	WS-G5484		
	WS-G5486		
	WS-G5487		
	CWDM GBIC		
	DWDM GBIC	12.2(19)EW	12.1(19)EW
WS-X4448-GB-SFP	GLC-T (1000BASE-T)	--	12.2(20)EW
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	CWDM SFP	12.2(20)EW	12.2(20)EW
	GLC-BX-D	12.2(20)EWA	12.2(20)EWA
	GLC-BX-U		
	GLC-EX-SMD ¹	15.1(1)SG	15.1(1)SG
	GLC-ZX-SMD	--	12.2(25)EWA 10

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
WS-X4506-GB-T	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	12.2(20)EWA
	GLC-BX-D GLC-BX-U CWDM SFP	12.2(20)EWA	12.2(20)EWA
	GLC-EX-SMD ¹	15.1(1)SG	15.1(1)SG
WS-X4515	WS-G5483	--	12.1(13)EW
	WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--	12.1(12c)EW
	DWDM GBIC	12.1(19)EW	12.1(19)EW
WS-X4516	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--	12.2(18)EW
	DWDM GBIC	12.2(18)EW	12.2(18)EW
WS-X4516-10GE	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(25)EWA
	GLC-BX-D GLC-BX-U CWDM SFP	12.2(25)EWA	12.2(25)EWA
	DWDM SFP	12.2(37)SG	12.2(37)SG
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
	GLC-ZX-SMD	--	12.2(25)EWA 10
WS-X45-SUP6-E	GLC-T	--	12.2(40)SG
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-BX-D	12.2(40)SG	12.2(40)SG
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
	GLC-EX-SMD ¹	15.1(1)SG	15.1(1)SG
	GLC-ZX-SMD	--	12.2(40)SG
WS-X4606-X2 with CVR-X2-SFP Twin Gig converter	GLC-T	--	12.2(40)SG
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD	3.7.2E	12.2(40)SG
	GLC-LH-SMD		
	GLC-BX-D	12.2(40)SG	12.2(40)SG
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
	GLC-EX-SMD ¹	15.1(1)SG	15.1(1)SG
	GLC-ZX-SMD	3.7.2E	12.2(40)SG
WS-X4624-SFP-E	GLC-T (1000BASE-T)	--	12.2(44)SG
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 4500 Switches Support

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
	GLC-ZX-SM		
	GLC-SX-MMD	3.7.2E	12.2(44)SG
	GLC-LH-SMD		
	GLC-BX-D	12.2(44)SG	12.2(44)SG
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
	GLC-EX-SMD ¹	15.1(1)SG	15.1(1)SG
	GLC-ZX-SMD	3.7.2E	12.2(44)SG1
WS-X45-SUP6L-E with CVR-X2-SFP Twin Gig converter	GLC-T (1000BASE-T)	--	12.2(52)SG
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-BX-D	12.2(52)SG	12.2(52)SG
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
	GLC-EX-SMD	15.1(1)SG	15.1(1)SG
WS-X4612-SFP-E	GLC-T (1000BASE-T)	--	12.2(54)SG
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD	3.7.2E	12.2(54)SG
	GLC-LH-SMD		

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
	GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(54)SG	12.2(54)SG
	GLC-EX-SMD ¹	15.1(1)SG	15.1(1)SG
	GLC-ZX-SMD	3.7.2E	12.2(44)SG1
WS-X4640-CSFP-E	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	15.0(2)SG
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	3.7.2E	15.0(2)SG
	GLC-BX-D GLC-2BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	15.0(2)SG	15.0(2)SG
	GLC-EX-SMD ¹	15.1(1)SG	15.1(1)SG
WS-X4712-SFP+E WS-X45-SUP7-E	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	3.1.0SG
	GLC-SX-MMD GLC-LH-SMD	3.7.2E	3.1.0SG
	GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.1.0SG	3.1.0SG

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
	GLC-BX40-D-I GLC-BX80-D-I GLC-BX40-U-I GLC-BX80-U-I GLC-BX40-DA-I	3.8.0E	3.8.0E
	GLC-EX-SMD ¹	3.4.1SG	3.4.1SG
	GLC-ZX-SMD	3.7.2E	3.4.1SG
WS-X45-SUP7L-E	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	3.2.0XO
	GLC-SX-MMD GLC-LH-SMD	3.7.2E	3.2.0XO
	GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.2.0XO	3.2.0XO
	GLC-BX40-D-I GLC-BX80-D-I GLC-BX40-U-I GLC-BX80-U-I GLC-BX40-DA-I	3.8.0E	3.8.0E
	GLC-EX-SMD ¹	3.4.1SG	3.4.1SG
	GLC-ZX-SMD	3.7.2E	3.4.1SG
WS-X45-SUP8-E	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	3.3.0XO
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	3.7.2E	3.3.0XO

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
	GLC-BX40-D-I GLC-BX80-D-I GLC-BX40-U-I GLC-BX80-U-I GLC-BX40-DA-I	3.0.8E	3.8.0E
	GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-EX-SMD ¹	3.3.0XO	3.3.0XO
WS-X45-SUP8L-E	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-EX-SMD ¹	3.8.1E	3.8.1E
	GLC-BX40-D-I GLC-BX80-D-I GLC-BX40-U-I GLC-BX80-U-I GLC-BX40-DA-I	3.8.1E	3.8.1E
WS-X4748-SFP-E WS-X4724-SFP-E WS-X4712-SFP-E	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-EX-SMD GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L	15.2(1)E	15.2(1)E

Catalyst 4500 series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
	SFP-GE-Z DWDM SFP		
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	3.7.2E	15.2(1)E

Catalyst 4500-E Series Support

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
WS-X45-SUP9-E	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX40-D-I GLC-BX80-D-I GLC-BX40-U-I GLC-BX80-U-I GLC-BX40-DA-I GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.10 XE	3.10 XE
	GLC-T GLC-TE	-	

Catalyst 4500X Series Support

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
WS-C4500X-32SFP+	GLC-SX-MM	--	3.3.0SG
WS-C4500X-F-32SFP+	GLC-LH-SM		
WS-C4500X-40X-ES	GLC-ZX-SM		
C4KX-NM-8SFP+			
	GLC-T	-	3.7.1E
	GLC-TE		3.8.4E
			3.10.0E
	GLC-SX-MMD	3.7.2E	3.3.0SG
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-BX-D	3.3.0SG	3.3.0SG
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)		
	GLC-BX40-D-I	3.8.0E	3.8.0E
	GLC-BX80-D-I		
	GLC-BX40-U-I		
	GLC-BX80-U-I		
	GLC-BX40-DA-I		
	GLC-EX-SMD ¹	3.4.1SG	3.4.1SG
	(CPN 10-2624-01		
	or later only)		
WS-C4500X-16SFP+	GLC-SX-MM	--	3.3.1SG
WS-C4500X-F-16SFP+	GLC-LH-SM		
WS-C4500X-24X-ES	GLC-ZX-SM		
	GLC-T	-	3.7.1E
	GLC-TE		3.8.4E
			3.10.0E
	GLC-SX-MMD	3.7.2E	3.3.1SG
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-BX-D	3.3.1SG	3.3.1SG
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 4900 Switches Support

Network Device	Minimum Software Release Required		
	Transceiver Module	DOM Support	Cisco IOS Support
DWDM SFP (add.)			
GLC-BX40-D-I	3.8.0E	3.8.0E	
GLC-BX80-D-I			
GLC-BX40-U-I			
GLC-BX80-U-I			
GLC-BX40-DA-I			
GLC-EX-SMD ¹	3.4.1SG	3.4.1SG	

Catalyst 4900 Switches Support

Network Device	Minimum Software Release Required		
	Transceiver Module	DOM Support	Cisco IOS Support
WS-C4912G	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--	--
WS-C4948	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	12.2(20)EWA
	GLC-BX-D GLC-BX-U CWDM SFP	12.2(20)EWA	12.2(20)EWA
	DWDM SFP	12.2(37)SG	12.2(37)SG
	DWDM (add.)	12.2(53)SG3	12.2(53)SG3

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 4900 Switches Support

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
WS-4928-10GE	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(46)SG
	GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(46)SG	12.2(46)SG
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
WS-C4948E(-F)	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	12.2(54)SG
	GLC-SX-MMD GLC-LH-SMD	15.2(3)E2	12.2(54)SG
	GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(54)SG	12.2(54)SG
	DWDM SFP (add.) GLC-EX-SMD ¹	12.2(53)SG3	12.2(53)SG3
	GLC-BX40-D-I GLC-BX80-D-I GLC-BX40-U-I GLC-BX80-U-I GLC-BX40-DA-I	15.2(4)E	15.2(4)E
	GLC-ZX-SMD	15.2(3)E2	12.2(53)SG3
WS-X4908 with CVR-X2-SFP Twin Gig converter in a WS-C4900M	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	12.2(40)XO or 12.2(44)SG

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 6500 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Support
	GLC-SX-MMD	15.2(3)E2	12.2(40)XO or 12.2(44)SG
	GLC-LH-SMD		
	GLC-BX-D	12.2(40)XO or	12.2(40)XO or
	GLC-BX-U	12.2(44)SG	12.2(44)SG
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
	GLC-BX40-D-I	15.2(4)E	15.2(4)E
	GLC-BX80-D-I		
	GLC-BX40-U-I		
	GLC-BX80-U-I		
	GLC-BX40-DA-I		
	GLC-EX-SMD ¹	15.1(1)SG	15.1(1)SG
	GLC-ZX-SMD	15.2(3)E2	12.2(40)XO

Catalyst 6500 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required		
		DOM Support	Cisco IOS Release	Catalyst OS
WS-X6K-SUP1-2GE	WS-G5483	--	12.1(13)E	7.2
WS-X6K-SUP1A-2GE				
WS-X6K-SUP1A-MSFC	WS-G5484	--	Please see release notes for details	Please see release notes for details
WS-X6K-SUP1A-MSFC2	WS-G5486			
WS-X6K-SUP1A-PFC	WS-G5487			
WS-X6K-SUP2U-MSFC2				
WS-X6K-S2-PFC2	CWDM GBIC	--	12.1(13)E	7.2
WS-X6K-SUP2-MSFC2	WS-G5483	--	12.1(13)E	7.2
WS-X6K-SUP2U-PFC2				
WS-X6408-GBIC	WS-G5484	--	Please see release notes for details	Please see release notes for details
WS-X6408A-GBIC	WS-G5486			
WS-X6416-GBIC	WS-G5487			
WS-X6516-GBIC				
WS-X6816-GBIC	CWDM GBIC	--	12.1(13)E	7.2
	DWDM GBIC	--	12.2(17a)SX	8.3.1
WS-X6516A-GBIC	WS-G5483	--	12.1(19)E1	7.5.1

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 6500 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required		
		DOM Support	Cisco IOS Release	Catalyst OS
WS-SUP720	WS-G5484	--	Please see release notes for details	Please see release notes for details
	WS-G5486	--		
	WS-G5487	--		
WS-SUP720	CWDM GBIC	--	12.1(19)E1	7.5.1
	DWDM GBIC	--	12.2(17a)SX	8.3.1
	GLC-T (1000BASE-T) GLC-TE (1000BASE-T)	--	12.2(17a)SX	8.3.1
WS-SUP720	GLC-SX-MM	--	12.2(14)SX	8.1(1)
	GLC-LH-SM	--	12.2(14)SX	8.1.1
	GLC-ZX-SM	--	12.2(17a)SX	8.1.1
	GLC-BX-D	--	12.2(17d)SXB1	8.2
	GLC-BX-U	12.2(18)SXE1	12.2(18)SXE1	8.4.1
	CWDM SFP	12.2(18)SXE1	12.2(18)SXE1	8.4.1
	DWDM SFP ²	12.2(18)SXE	12.2(17a)SX	8.3.1
	GLC-SX-MMD	12.2(33)SXH	15.1(3)S	--
	GLC-LH-SMD	--	15.1(3)S	--
	GLC-EX-SMD	--	15.2(1)S	--
WS-SUP720-3B WS-SUP720-3BXL	GLC-ZX-SMD	--	15.2(1)S	--
	GLC-TE	--	15.1(3)S	--
	GLC-T (1000BASE-T)	--	12.2(17d)SXB1	8.3.2
	GLC-TE (1000BASE-T)	--		
	GLC-SX-MM	--	12.2(14)SX	8.1(1)
WS-SUP720-3B WS-SUP720-3BXL	GLC-LH-SM	--	12.2(17d)SXB1	8.3.2
	GLC-ZX-SM	--	12.2(17d)SXB1	8.3.2

² Does not include support for the DWDM SFP transceivers (8 additional wavelengths). See Gigabit Ethernet Transceiver Models for specific model numbers.

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 6500 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required		
		DOM Support	Cisco IOS Release	Catalyst OS
	GLC-BX-D	--	12.2(17d)SXB1	8.3.2
	GLC-BX-U	12.2(18)SXE1	12.2(18)SXE1	8.4.1
	CWDM SFP	12.2(18)SXE1	12.2(18)SXE1	8.4.1
	DWDM SFP ²	12.2(18)SXE	12.2(17d)SXB1	8.3.2
	GLC-SX-MMD	12.2(33)SXH	15.1(3)S	--
	GLC-LH-SMD	--	15.1(3)S	--
	GLC-EX-SMD	--	15.2(1)S	--
	GLC-ZX-SMD	--	15.2(1)S	--
	GLC-TE	--	15.1(3)S	--
WS-SUP32-GE-3B WS-SUP32-10GE-3B	GLC-T (1000BASE-T)	--	12.2(18)SXF	8.4(1)
	GLC-TE (1000BASE-T)			
	GLC-SX-MM	--	12.2(14)SX	8.1(1)
	GLC-LH-SM	--	12.2(18)SXF	8.4(1)
	GLC-ZX-SM	--	12.2(18)SXF	8.4(1)
	GLC-BX-D	--	12.2(18)SXF	8.4(1)
	GLC-BX-U	12.2(18)SXF	12.2(18)SXF	8.4(1)
	CWDM SFP	12.2(18)SXF	12.2(18)SXF	8.4(1)
	DWDM SFP ²	12.2(18)SXF	12.2(18)SXF	8.4(1)
	GLC-SX-MMD	12.2(33)SXH	12.2(33)SXH	--
	GLC-LH-SMD	--	12.2(18)SXF	--
	GLC-ZX-SMD	--	12.2(18)SXF	--

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 6500 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required		
		DOM Support	Cisco IOS Release	Catalyst OS
WS-SUP32-GE-PISA	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP ² GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	12.2(18)ZY	--
VS-S720-10G-3C	GLC-T (1000BASE-T)	--	12.2(33)SXH	--
VS-S720-10G-3CXL	GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-LH-SMD GLC-ZX-SMD			
	GLC-BX-U CWDM SFP DWDM SFP ² GLC-SX-MMD		12.2(33)SXH	
WS-X6724-SFP	GLC-T (1000BASE-T)	--	12.2(17a)SX	8.3.1
WS-X6748-SFP	GLC-TE (1000BASE-T) DWDM SFP ²			
	GLC-SX-MM GLC-LH-SM		12.2(14)SX	8.1.1
	GLC-ZX-SM		12.2(17a)SX	8.1.1
	GLC-BX-D		12.2(17d)SXB1	8.2
	GLC-BX-U CWDM SFP		12.2(18)SXE1	8.4.1
	GLC-SX-MMD		15.1(2)S	--
	GLC-LH-SMD		15.1(2)S	--
	GLC-EX-SMD		15.1(2)S	--

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 6500 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required		
		DOM Support	Cisco IOS Release	Catalyst OS
	GLC-ZX-SMD		15.1(2)S	--
	GLC-TE		15.1(2)S	--
VS-S2T-10G	GLC-T (1000BASE-T)	--	12.2(50)SY	--
VS-S2T-10G-XL	GLC-TE (1000BASE-T)			
WS-X6824-SFP-2T	GLC-SX-MM			
WS-X6824-SFP-2TXL	GLC-LH-SM			
WS-X6848-SFP-2T	GLC-ZX-SM			
WS-X6848-SFP-2TXL	GLC-BX-D GLC-BX-U CWDM-SFP DWDM-SFP ² GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD			
WS-X6904-40G-2T	GLC-T (1000BASE-T)	--	15.1(1)SY	--
WS-X6904-40G-2TXL	GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM-SFP DWDM-SFP ² GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD			
C6800-SUP6T	GLC-T		15.3(1)SY	15.3(1)SY
C6800-SUP6T-XL	GLC-TE GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D CWDM-SFP DWDM-SFP			

Catalyst 6800 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
C6800IA-48FPD	GLC-BX-D	15.1(2)SY2	15.1(2)SY2
C6800IA-48TD	GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-T GLC-TE GLC-SX-MM		
	GLC-EX-SMD GLC-ZX-SMD GLC-ZX-SM GLC-LH-SM SLC-SX-MM DWDM-SFP CWDM-SFP	15.2(1)SY	15.2(1)SY
C6800IA-48FPDR	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-T GLC-TE GLC-SX-MM	15.1(2)SY3	15.1(2)SY3
	GLC-EX-SMD GLC-ZX-SMD GLC-ZX-SM GLC-LH-SM SLC-SX-MM DWDM-SFP CWDM-SFP	15.2(1)SY	15.2(1)SY
C6880-X	GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD GLC-ZX-SMD GLC-T GLC-TE GLC-ZX-SM GLC-LH-SM GLC-SX-MM GLC-BX-D GLC-BX-U CWDM-SFP DWDM SFP	15.1(2)SY1	15.1(2)SY1

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Catalyst 6800 Series Switches Support

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
C6800-32P10G(-XL)	GLC-LH-SMD	15.2(1)SY	15.2(1)SY
C6800-16P10G(-XL)	GLC-SX-MMD		
C6800-8P10G(-XL)	GLC-EX-SMD GLC-ZX-SMD GLC-T GLC-TE GLC-ZX-SM GLC-LH-SM GLC-SX-MM GLC-BX-D GLC-BX-U CWDM-SFP DWDM-SFP		
C6800-48P-SFP	GLC-T (1000BASE-T)	--	15.2(1)SY
C6800-48P-SFP-XL	GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM-SFP DWDM-SFP2 GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD		
C6816-X-LE	GLC-LH-SMD	15.2(2)SY	15.2(2)SY
C6824-X-LE-40G	GLC-SX-MMD		
C6832-X-LE	GLC-EX-SMD		
C6840-X-LE-40G	GLC-ZX-SMD GLC-T GLC-TE GLC-BX-D GLC-BX-U DWDM-SFP		
C6800-SUP6T	GLC-T	15.3(1)SY	15.3(1)SY
C6800-SUP6T-XL	GLC-TE GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D CWDM-SFP DWDM-SFP		

Data Center and Blade Switching Support

Cisco Catalyst 2350 Series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM support	Software Release
2350-48TD-S	GLC-T	--	Cisco IOS 12.2(46)EY
2350-48TD-SD (with CVR-X2-SFP TwinGig converter)	GLC-TE GLC-SX-MM GLC-SX-MMD		

Cisco Catalyst 2360 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
2360-48TD-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(53)EY

Cisco Catalyst 3000 and 3100 Blade Switches

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
WS-CBS3020-HPQ	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(35)SE
WS-CBS3030-DEL WS-CBS3040-FSC	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-SX-MMD	--	Cisco IOS 12.2(35)SE
WS-CBS-3120G-S WS-CBS-3130G-S (with CVR-X2-SFP TwinGig converter)	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD	--	Cisco IOS 12.2(40)EX1

Cisco Catalyst 3000 and 3100 Blade Switches

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-LH-SMD		
WS-CBS3032-DEL (with CVR-X2-SFP TwinGig converter)	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(40)EX1
WS-CBS3110X-S (with CVR-X2-SFP TwinGig converter)	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(52)SE

Cisco Nexus 2000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N2K-C2232PP-10GE	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	NX-OS 4.2(1)N2(1)
N2K-C2348UPQ	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD		NX-OS 7.0(3)N1(1)

Cisco Nexus 3000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C3064PQ-10GX (Native SFP+ ports)	GLC-T SFP-GE-T GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	When supported by transceiver module	NX-OS 5.0(3)U3(1)
	GLC-BX-U GLC-BX-D		NX-OS 5.0(3)U5(1)
	GLC-EX-SMD GLC-ZX-SMD		NX-OS 6.0(2)U1(a)
	GLC-TE		NX-OS 6.0(2)U3(1)
N3K-C3064PQ-10GE (Native SFP+ ports)	GLC-T SFP-GE-T GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	When supported by transceiver module	NX-OS 5.0(3)U1(2)
	GLC-BX-U GLC-BX-D		NX-OS 5.0(3)U5(1)
	GLC-EX-SMD GLC-ZX-SMD		NX-OS 6.0(2)U1(a)
	GLC-TE		NX-OS 6.0(2)U3(1)
N3K-C3064PQ-10GX	(QSFP ports with QSA: CVR-QSFP-SFP10G)	--	NX-OS 6.0(2)U3(1)
N3K-C3064PQ-10GE	w/ GLC-T w/ SFP-GE-T w/ GLC-TE		
N3K-C3048TP-1GE	GLC-T SFP-GE-T	--	NX-OS 5.0(3)U2(2b)
	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD		NX-OS 5.0(3)U2(2b)
	GLC-BX-U	--	NX-OS 5.0(3)U5(1)

Cisco Nexus 3000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-BX-D		
	GLC-EX-SMD	--	NX-OS 6.0(2)U1(a)
	GLC-ZX-SMD		
	GLC-TE	--	NX-OS 6.0(2)U3(1)

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C3132Q-40GE (Native SFP+ ports)	GLC-T GLC-TE SFP-GE-T	-	NX-OS 6.0(2)U4(1)
	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D		NX-OS 6.0(2)U4(1)
N3K-C3132Q-40GE	(QSFP ports with QSA: CVR-QSFP-SFP10G) w/ GLC-T w/ GLC-TE w/ SFP-GE-T	-	NX-OS 6.0(2)U3(1)
	w/ GLC-SX-MMD w/ GLC-LH-SMD		NX-OS 6.0(2)U3(1)
N3K-C3132Q-40GX (Native SFP+ ports)	GLC-T GLC-TE SFP-GE-T	-	NX-OS 6.0(2)U4(1)

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D		NX-OS 6.0(2)U4(1)
N3K-C3132Q-40GX	(QSFP ports with QSA: CVR-QSFP-SFP10G) w/ GLC-T w/ GLC-TE w/ SFP-GE-T	-	NX-OS 6.0(2)U4(1)
	w/ GLC-SX-MMD w/ GLC-LH-SMD		NX-OS 6.0(2)U4(1)
N3K-C3132Q-XL (Native SFP+ ports)	GLC-T GLC-TE SFP-GE-T	-	NXOS 7.0(3)I2(2)
	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D		NXOS 7.0(3)I2(2)
N3K-C3132Q-XL	(QSFP ports with QSA: CVR-QSFP-SFP10G) w/ GLC-T w/ GLC-TE w/ SFP-GE-T	-	NXOS 7.0(3)I2(2)
	w/ GLC-SX-MMD w/ GLC-LH-SMD		NXOS 7.0(3)I2(2)
N3K-C3132Q-V (Native SFP+ ports)	GLC-T GLC-TE SFP-GE-T	-	NX-OS 7.0(3)I4(1)

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D		NX-OS 7.0(3)I4(1)
N3K-C3132Q-V	(QSFP ports with QSA: CVR-QSFP-SFP10G) w/ GLC-T w/ GLC-TE w/ SFP-GE-T	-	NX-OS 7.0(3)I4(1)
	w/ GLC-SX-MMD w/ GLC-LH-SMD		NX-OS 7.0(3)I4(1)
N3K-C3172PQ-10GE (Native SFP+ ports)	GLC-T SFP-GE-T GLC-TE	-	NX-OS 6.0(2)U3(1)
	GLC-SX-MMD		NX-OS 6.0(2)U3(1)
	GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D		NX-OS 6.0(2)U4(1)
N3K-C3172PQ-10GE	(QSFP ports with QSA: CVR-QSFP-SFP10G) GLC-T SFP-GE-T	-	NX-OS 6.0(2)U3(1)
	GLC-TE	-	NX-OS 7.0(3)I2(1a)
	GLC-SX-MMD GLC-LH-SMD		NX-OS 7.0(3)I2(1a)
N3K-C3172TQ-10GT	(QSFP ports with QSA: CVR-QSFP-SFP10G) w/ GLC-T	-	NX-OS 6.0(2)U3(1)
	w/ GLC-TE w/ SFP-GE-T	-	NX-OS 7.0(3)I2(1a)

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	w/ GLC-SX-MMD w/ GLC-LH-SMD		NX-OS 7.0(3)I2(1a)
N3K-C3172PO-XL (Native SFP+ ports)	GLC-T GLC-TE SFP-GE-T	-	NXOS 7.0(3)I2(2)
	GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D		NXOS 7.0(3)I2(2)
N3K-C3172PQ-XL N3K-C3172TQ-XL	(QSFP ports with QSA: CVR-QSFP-SFP10G) w/ GLC-T w/ GLC-TE w/ SFP-GE-T	-	NXOS 7.0(3)I2(2)
	w/ GLC-SX-MMD w/ GLC-LH-SMD		NXOS 7.0(3)I2(2)
N3K-C31108PC-V (Native SFP+ ports)	GLC-T GLC-TE SFP-GE-T	-	NXOS 7.0(3)I4(1)
	GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D		NXOS 7.0(3)I4(1)
N3K-C31128PQ-10GE (Native SFP+ ports)	SFP-GE-T	-	NX-OS 7.0(3)I2(1a)
	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-EX-SMD GLC-ZX-SMD GLC-BX-U GLC-BX-D		NX-OS 7.0(3)I2(1a)
	GLC-T	-	NX-OS 7.0(3)I4(1)

Cisco Nexus 3100 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-TE		
	GLC-LH-SMD	NX-OS 7.0(3)I4(1)	

Cisco Nexus 3200 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N3K-C3264Q	GLC-SX-MM		
N3K-C3232C (Native SFP+ Ports)	GLC-SX-MMD	When supported by transceiver module	NX-OS 7.0(3)IX1(2)
	GLC-LH-SM		
	GLC-LH-SMD		
	GLC-T		
	SFP-GE-T		
	GLC-TE		NX-OS 7.0(3)I4(1)
	GLC-EX-SMD		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
N3K-C3232C	(QSFP ports with QSA: CVR-QSFP-SFP10G) w/ GLC-T w/ GLC-TE		NX-OS 7.0(3)I5(1)
	(QSFP ports with SLIC adapter) w/ GLC-T w/ GLC-TE w/ GLC-SX-MM*		NX-OS 7.0(3)I4(1)
	w/ GLC-SX-MMD*		
	w/ GLC-LH-SM*		
	w/ GLC-LH-SMD*		

* Up to 4 per SLIC adapter, up to 32 per switch through SLIC adapter

Cisco Nexus 3500 Series

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
N3K-C3548P-10G	GLC-SX-MM	NX-OS 5.0(3)A1(1)	NX-OS 5.0(3)A1(1)
N3K-C3524P-10G	GLC-SX-MMD		
	GLC-LH-SM		
	GLC-LH-SMD		
	GLC-T	-	NX-OS 6.0(2)A1(1)
	GLC-TE		NX-OS 6.0(2)A3(1)
	GLC-EX-SMD	NX-OS 6.0(2)A3(1)	
	GLC-ZX-SMD		
N3K-C3548P-10GX	GLC-SX-MM	NX-OS 6.0(2)A6(1)	NX-OS 6.0(2)A6(1)
N3K-C3524P-10GX	GLC-SX-MMD		
	GLC-LH-SM		
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
	GLC-T	-	
	GLC-TE		

Cisco Nexus 3600 Series

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
N3K-C36180YC-R	GLC-SX-MMD	NX-7.0(3)F3(1)	NX-7.0(3)F3(1)

Cisco Nexus 4000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N4K-4001I-XPX	GLC-T (1000BASE-T)	--	--
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		

Cisco Nexus 5000 Series

Network Device	Transceiver Model	Minimum Software Release Required		
		DOM Support	Software Release	
N5K-C5010P-BF	GLC-T (1000BASE-T)	--		NX-OS 4.1(2)E1(1)
N5K-C5020P-BF	GLC-TE (1000BASE-T)			
	GLC-SX-MM			
	GLC-LH-SM			
	SFP-GE-T (1000BASE-T)			
	SFP-GE-S		NX-OS 4.0(1a)N1(1)	NX-OS 4.0(1a)N1(1)
	SFP-GE-L			
	GLC-SX-MMD			
	GLC-LH-SMD			
N5K-C5548P-FA	GLC-T (1000BASE-T)	--		NX-OS 4.0(1a)N1(1)
N5K-C5548UP-FA	GLC-TE (1000BASE-T)			
N5KC5596UP-FA	GLC-SX-MM			
N55-M16P	GLC-LH-SM			
N55-M8P8FP	SFP-GE-T (1000BASE-T)			
N55-M16UP	DS-CWDM4G1470	--		NX-OS 5.0(3)N1(1B)
	DS-CWDM4G1490			
	DS-CWDM4G1510			
	DS-CWDM4G1530			
	SFP-GE-S		NX-OS 5.0(3)N1(1B)	NX-OS 5.1(3)N2
	SFP-GE-L			
	GLC-SX-MMD			
	GLC-LH-SMD			

Cisco Nexus 5000 Series

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
N5K-5672UP	GLC-TE	NX-OS 7.0(1) N1 (1)	NX-OS 7.0(1) N1 (1)
N5K-56128P			
N5K-5672UP-16G			

Cisco Unified Computing System

Minimum Software Release Required			
Network Device	Transceiver Model	DOM Support	Software Release
N10-S6100	SFP-GE-S	UCS Manager v1.3	NX-OS 5.0(3)N1(1B)
N10-S6200	SFP-GE-L		
N10-E0440	GLC-SX-MMD		
N10-E0600	GLC-LH-SMD		
N20-I6584	GLC-SX-MM GLC-LH-SM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T (1000BASE-T)	--	UCS Manager v1.3
UCS-FI-6248UP	SFP-GE-S	UCS Manager v2.0(1)	UCS Manager v1.3
UCS-FI-E16UP	SFP-GE-L		
UCS-IOM-2208XP	GLC-SX-MMD GLC-LH-SMD		
	GLC-SX-MM GLC-LH-SM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T (1000BASE-T)	--	UCS Manager v2.0(1)

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N7K-M148GS-11	SFP-GE-S	NX-OS 4.1(2)	UCS Manager v2.0(1)
	GLC-SX-MMD		NX-OS 4.1(2)
	SFP-GE-L		
	GLC-LH-SMD		
	SFP-GE-Z		
	GLC-SX-MM	--	
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-T (1000BASE-T)	--	NX-OS 4.2(1)
	GLC-TE (1000BASE-T)		NX-OS 4.2(1)
	SFP-GE-T (1000BASE-T)		
	CWDM SFP		
	DWDM SFP	NX-OS 4.2(1)	
	GLC-BX-D	NX-OS 5.2(1)	NX-OS 5.2(1)
	GLC-BX-U		
	GLC-EX-SMD	NX-OS 6.2(2)	NX-OS 5.2(1)
	GLC-ZX-SMD		
N7K-M148GS-11L	SFP-GE-S	NX-OS 5.0(2a)	NX-OS 6.2(2)
	GLC-SX-MMD		NX-OS 5.0(2a)
	SFP-GE-L		
	GLC-LH-SMD		
	SFP-GE-Z		
	CWDM SFP		
	DWDM SFP		
	GLC-SX-MM	--	
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-T (1000BASE-T)		
	GLC-TE(1000BASE-T)		
	SFP-GE-T (1000BASE-T)		
	GLC-BX-D	NX-OS 5.2(1)	NX-OS 5.2(1)
	GLC-BX-U		
	GLC-EX-SMD	NX-OS 6.2(2)	NX-OS 5.2(1)
	GLC-ZX-SMD		

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N7K-F132XP-15	SFP-GE-S GLC-SX-MMD SFP-GE-L GLC-LH-SMD SFP-GE-Z	NX-OS 5.1(1)	NX-OS 6.2(2) NX-OS 5.1(1)
	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T (1000BASE-T)	--	
	GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2(2)
N7K-F248XP-25	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	NX-OS 6.2(2)
	GLC-SX-MMD SFP-GE-S GLC-LH-SMD SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	NX-OS 6.0	NX-OS 6.0
	GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.0
N7K-F248XP-25E	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T(1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	NX-OS 6.2(2)

Cisco Nexus 7000 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-SX-MMD		NX-OS 6.1(2)
	SFP-GE-S		
	GLC-LH-SMD		
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.1(2)
N7K-F348XP-25	GLC-SX-MM	-	NX-OS 6.2(12)
	SFP-GE-S		
	GLC-SX-MMD		
	GLC-LH-SM		
	SFP-GE-L		
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SM		
	SFP-GE-Z		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-T	--	NX-OS 6.2(12)
	SFP-GE-T		
	GLC-TE	--	NX-OS 6.2(12)
N7K-M348XP-25L	GLC-TE	-	NX-OS 8.0
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-ZX-SMD	-	NX-OS 8.0(1)
	CWDM SFP-xxxx		
	DWDM SFP-xxxx		

Cisco Nexus 7700 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N77-F348XP-23	GLC-SX-MM	-	NX-OS 6.2(8)
	SFP-GE-S		
	GLC-SX-MMD		
	GLC-LH-SM		
	SFP-GE-L		
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SM		
	SFP-GE-Z		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-T		
	SFP-GE-T		
	GLC-TE	--	NX-OS 6.2(10)
N77-M348XP-23L	GLC-TE	-	NX-OS 7.3
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-ZX-SMD	-	NX-7.3(0)DX(1)

Cisco Nexus 9000 Series (Modular 9500) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-X97160YC-EX	GLC-SX-MMD	-	7.0(3)I5(2)
	GLC-LH-SMD		

Cisco Nexus 9000 Series (Modular 9500) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-SX-MM	--	7.0(3)I5(2)
	GLC-LH-SM		
	GLC-T (1000BASE-T)		
	GLC-TE (1000BASE-T)		
	SFP-GE-T		
	GLC-ZX-SMD		
	GLC-BX-U		
	GLC-BX-D		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	SFP-1000BX-10-U		
	SFP-1000BX-10-D		
	GLC-EX-SMD		
	GLC-BX40-D-I		
	GLC-BX40-U-I		
	GLC-BX40-DA-I		
N9K-X9564PX	GLC-SX-MM	--	NX-OS 6.1(2)I2(1)
	GLC-LH-SM		
	GLC-T (1000BASE-T)		
	GLC-TE (1000BASE-T)		
	GLC-SX-MMD	6.1(2)I2(1)	6.1(2)I2(1)
	GLC-LH-SMD		
	SFP-GE-T	--	6.1(2)I2(1)
	GLC-ZX-SMD	--	7.0(3)I3(1)
	GLC-BX-U		
	GLC-BX-D		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	SFP-1000BX-10-U		
	SFP-1000BX-10-D		
	GLC-EX-SMD		
	GLC-BX40-D-I	--	7.0(3)I1(2)
	GLC-BX40-U-I		
	GLC-BX40-DA-I		7.0(3)I5(2)
N9K-X9464PX	GLC-SX-MM	--	6.1(2)I2(2a)
	GLC-LH-SM		
	GLC-T (1000BASE-T)		
	GLC-TE (1000BASE-T)		

Cisco Nexus 9000 Series (Modular 9500) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-SX-MMD	6.1(2)I2(2a)	6.1(2)I2(2a)
	GLC-LH-SMD		
	SFP-GE-T	--	6.1(2)I3(1)
	GLC-ZX-SMD	--	7.0(3)I3(1)
	GLC-BX-U		
	GLC-BX-D		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	SFP-1000BX-10-U		
	SFP-1000BX-10-D		
	GLC-EX-SMD		
	GLC-BX40-D-I	--	7.0(3)I1(2)
	GLC-BX40-U-I		
	GLC-BX40-DA-I		7.0(3)I5(2)

Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C9396PX	GLC-SX-MM	--	6.1(2)I2(1)
	GLC-T (1000BASE-T)		
	GLC-TE (1000BASE-T)		
	GLC-SX-MMD	6.1(2)I2(1)	6.1(2)I2(1)
	GLC-LH-SMD		
	SFP-GE-T	--	6.1(2)I3(1)
	GLC-LH-SM	--	6.1(2)I3(3a)
	GLC-ZX-SMD	--	7.0(3)I3(1)
	GLC-BX-U		
	GLC-BX-D		
	GLC-BX80-D-I		

Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-BX80-U-I SFP-1000BX-10-U SFP-1000BX-10-D GLC-EX-SMD		
	GLC-BX40-D-I GLC-BX40-U-I	--	7.0(3)I3(2)
	GLC-BX40-DA-I		7.0(3)I5(2)
N9K-C9372PX	GLC-SX-MM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T	--	6.1(2)I3(1)
	GLC-SX-MMD GLC-LH-SMD	6.1(2)I3(1)	6.1(2)I3(1)
	GLC-LH-SM	--	6.1(2)I3(3a)
	GLC-ZX-SMD GLC-BX-U GLC-BX-D GLC-BX80-D-I GLC-BX80-U-I SFP-1000BX-10-U SFP-1000BX-10-D GLC-EX-SMD	--	7.0(3)I3(1)
	GLC-BX40-D-I GLC-BX40-U-I	--	7.0(3)I1(2)
	GLC-BX40-DA-I		7.0(3)I5(2)
N9K-C9372PX-E	GLC-SX-MM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T GLC-LH-SM GLC-BX40-D-I GLC-BX40-U-I	--	7.0(3)I2(1)
	GLC-ZX-SMD GLC-BX-U	--	7.0(3)I3(1)

Cisco Nexus 9000 Series (Fixed 9300) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-BX-D GLC-BX80-D-I GLC-BX80-U-I SFP-1000BX-10-U SFP-1000BX-10-D GLC-EX-SMD		
	GLC-SX-MMD GLC-LH-SMD	7.0(3)I2(1)	7.0(3)I2(1)
	GLC-BX40-DA-I		7.0(3)I5(2)
N9K-C93180YC-EX	GLC-SX-MM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T GLC-LH-SM GLC-ZX-SMD GLC-BX-U GLC-BX-D	--	NX-OS 703I4.2
	GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD	NX-OS 703I4.2	NX-OS 703I4.2
	GLC-T (100BASE-T) GLC-TE (100BASE-T)	-	7.0(3)I6(1)
N9K-C9348GC-FXP (NX-OS Mode)	(Supported on ports 49 through 52) GLC-T GLC-TE GLC-SX-MMD GLC-LH-MMD	-	NXOS-703I7.1
N9K-C93180YC-FX (NX-OS Mode)	GLC-SX-MM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T GLC-LH-SM GLC-ZX-SMD GLC-BX-U GLC-BX-D GLC-SX-MMD GLC-LH-SMD	-	NXOS-703I7.1

[Cisco Nexus 9000 Series \(Fixed 9300\) NX-OS Mode](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-EX-SMD		
N9K-C9364C (NX-OS Mode)	(Supported on ports 65 and 66 only) GLC-SX-MM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-EX-SMD	-	NXOS-703I7.2
N9K-C93108TC-EX	(QSFP ports with QSA: CVR-QSFP-SFP10G)		NXOS-703I7.1
N9K-C93180LC-EX	w/ GLC-LH-SMD w/ GLC-SX-MMD w/ GLC-TE		

[Cisco Nexus 9000 Series \(Fixed 9200\) NX-OS Mode](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C92160YC-X	GLC-SX-MM GLC-T (1000BASE-T) GLC-TE (1000BASE-T) SFP-GE-T GLC-LH-SM GLC-ZX-SMD	--	7.0(3)I2(1)
	GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-BX-D GLC-BX-U	7.0(3)I3(1)	7.0(3)I3(1)
N9K-C9236C	(QSFP ports with SLIC adapter) w/ GLC-T w/ GLC-TE w/ GLC-SX-MM* w/ GLC-SX-MMD* w/ GLC-LH-SM*	--	7.0(3)I4(1)

Cisco Nexus 9000 Series (Fixed 9200) NX-OS Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	w/ GLC-LH-SMD*		
	(QSFP ports with QSA: CVR-QSFP-SFP10G) --		NXOS-703I5.1
	w/ GLC-T (1000BASE-T)		
	w/ GLC-TE (1000BASE-T)		
	w/ GLC-SX-MM		
	w/ GLC-SX-MMD		
	(QSFP ports with QSA: CVR-QSFP-SFP10G)		NXOS-703I7.1
	w/ GLC-LH-SMD		
N9K-C92300YC	GLC-SX-MM	--	NXOS-703I6.1
	GLC-T (1000BASE-T)		
	GLC-TE (1000BASE-T)		
	SFP-GE-T		
	GLC-LH-SM		
	GLC-ZX-SMD		
	GLC-SX-MMD	NXOS-703I6.1	NXOS-703I6.1
	GLC-LH-SMD		
	GLC-EX-SMD		

* Up to 4 per SLIC adapter, up to 32 per switch through SLIC adapter

Cisco Nexus 9000 Series (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C9396PX	GLC-T (1000BASE-T)	--	ACI-N9KDK9-11.0
	GLC-TE (1000BASE-T)		
	GLC-SX-MMD		
	GLC-SX-MM	--	ACI-N9KDK9-11.0(2j)
	SFP-GE-T		
	GLC-LH-SMD		
	GLC-EX-SMD	--	ACI-N9KDK9-11.0(3f)
	GLC-LH-SM		

Cisco Nexus 9000 Series (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C9372PX	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MMD GLC-SX-MM SFP-GE-T GLC-LH-SMD GLC-LH-SM GLC-EX-SMD GLC-ZX-SMD	--	ACI-N9KDK9-11.0(3f)
N9K-C9372PX-E	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MMD GLC-SX-MM SFP-GE-T GLC-LH-SMD GLC-LH-SM GLC-EX-SMD GLC-ZX-SMD	--	ACI-N9KDK9-11.0(3f)
N9K-C93180YC-EX	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MMD GLC-SX-MM SFP-GE-T GLC-LH-SMD GLC-LH-SM GLC-EX-SMD GLC-ZX-SMD	--	ACI-N9KDK9-11.3
N9K-C93180YC-FX	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MMD GLC-SX-MM SFP-GE-T GLC-LH-SMD GLC-LH-SM GLC-EX-SMD GLC-ZX-SMD	--	ACI-N9KDK9-12.2A

Cisco Nexus 9000 Series (Fixed 9300) ACI Mode

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
N9K-C9364C (ACI Mode)	(Supported on ports 65 and 66 only) GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MMD GLC-SX-MM SFP-GE-T GLC-LH-SMD GLC-LH-SM GLC-EX-SMD GLC-ZX-SMD	-	ACI-N9KDK9-13.0

Cisco CSS 11500 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
CSS11506-2AC	GLC-T	--	ACI-N9KDK9-11.1(2h)
CSS11506-2DC	GLC-TE		
CSS11503-AC	GLC-SX-MM		
CSS11503-DC	GLC-LH-SM		
CSS11501			
CSS5-SCM-2GE			
CSS5-IOM-2GE			

Cisco MDS 9000 series: Please refer to the [data sheet](#).

Router Support

Cisco 892F series

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
CISCO892F-K9	GLC-SX-MM	--	15.1(2)T
CISCO892FW-K9	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-BX-D		
	GLC-BX-U		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		

Cisco 1921 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
HWIC-1GE-SFP	GLC-T	--	15.0(1)M2
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
EHWIC-1GE-SFP-CU	GLC-T	--	15.1(4)M
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		

Cisco1941 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
HWIC-1GE-SFP	GLC-T GLC-TE GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	15.0(1)M
EHWIC-1GE-SFP-CU	GLC-T GLC-TE GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	15.1(4)M

Cisco 2600 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC GLC-ZX-SMD	--	12.2(11)YT
NME-XD-24ES-1S-P	GLC-T	--	12.2(25)EZ
NME-XD-48ES-2S-P	GLC-TE GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD		

Cisco 2800 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NME-XD-24ES-1S-P	GLC-T	--	12.2(25)EZ
NME-XD-48ES-2S-P	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
HWIC-1GE-SFP	GLC-T	--	12.3(8)T4
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		

Cisco 2900 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
Cisco 2921	GLC-SX-MM	--	15.0(1)M
Cisco 2951	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-BX-U		
	GLC-BX-D		
	CWDM SFP		
	DWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
HWIC-1GE-SFP	GLC-T	--	15.0(1)M
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		

[Cisco 2900 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
SM-D-ES3G-48-P	GLC-T	--	15.0(1)M
SM-D-ES3-48-P	GLC-TE		
SM-D-ES2-48	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD		
EHWIC-1GE-SFP-CU	GLC-T GLC-TE GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	15.1(4)M

[Cisco 3200 Series Rugged Routers](#)[Cisco 3600 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
Cisco 3270	GLC-SX-MM-RGD GLC-LX-SM-RGD	--	12.4(6)XE
NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--	12.2(11)YT

Cisco 3700 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NM-1GE	WS-G5483	--	12.2(11)YT
	WS-G5484		
	WS-G5486		
	WS-G5487		
	CWDM GBIC		
NME-XD-24ES-1S-P	GLC-T	--	12.2(25)EZ
NME-XD-48ES-2S-P	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		

Cisco 3800 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NM-1GE	WS-G5483	--	12.2(11)YT
	WS-G5484		
	WS-G5486		
	WS-G5487		
	CWDM GBIC		
NME-XD-24ES-1S-P	GLC-T	--	12.2(25)EZ
NME-XD-48ES-2S-P	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
HWIC-1GE-SFP	GLC-ZX-SMD		
	GLC-T	--	12.3(8)T4
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		

Cisco 3800 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
Cisco 3825	GLC-SX-MM	--	12.3(11)T
	GLC-LH-SM		
	GLC-ZX-SM		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
Cisco 3845	GLC-SX-MM	--	12.3(11)T
	GLC-LH-SM		
	GLC-ZX-SM		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		

Cisco 3900 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
Cisco 3925	GLC-SX-MM	--	15.0(1)M
Cisco 3945	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-BX-U		
	GLC-BX-D		
	CWDM SFP		
	DWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
HWIC-1GE-SFP	GLC-T	--	15.0(1)M
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	CWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		

Cisco 3900 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
SM-D-ES3G-48-P	GLC-T	--	15.0(1)M
SM-D-ES3-48-P	GLC-TE		
SM-D-ES2-48	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-BX-U		
	GLC-BX-D		
	CWDM SFP		
	DWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
EHWIC-1GE-SFP-CU	GLC-T	--	15.1(4)M
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		

Cisco 4400 Series Router4451-X, 4431, 4351, 4331, 4321: [ISR 4000 Compatibility Matrix Link](#).Cisco 6400 Universal Access Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
C6400-NRP-2SV	WS-G5484	--	12.2(2)B6
	WS-G5486		
	WS-G5487		

Cisco 7200 Series Router

The Cisco 7200 series router supports multiple parallel release branches. Where several releases are grouped together, they provide support for all transceivers in the corresponding group.

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NPE-G1	WS-G5484	--	12.0(28)S
	WS-G5486	--	12.1(14)E
	WS-G5487	--	12.2(15)B
	CWDM GBIC	--	12.2(4)BW 12.2(14)S 12.2(14)SU 12.2(15)T9
	GLC-SX-MM	--	12.2(33)SRC2
	GLC-SX-MMD	--	12.4(15)T7 12.4(20)T1
	SFP-GE-T	--	12.2(33)SRC2 12.4(15)T7
Cisco 7201	SFP-GE-S	--	12.2(31)SB2
	SFP-GE-L	--	12.2(33)SRC2
	GLC-LH-SMD	--	12.4(15)T7
	SFP-GE-Z	--	
	CWDM SFP	--	
	GLC-SX-MM	--	12.2(33)SRC2
	GLC-SX-MMD	--	12.4(15)T7 12.4(20)T1
NPE-G2	SFP-GE-S	--	12.2(31)SB2
	SFP-GE-L	--	12.2(33)SRC2
	GLC-LH-SMD	--	12.4(15)T7
	SFP-GE-Z	--	
	CWDM SFP	--	
	GLC-SX-MM	--	12.2(33)SRC2
	GLC-SX-MMD	--	12.4(15)T7 12.4(20)T1
C7200-I/O-GE+E	WS-G5484	--	12.0(14)S2
	WS-G5486	--	12.1(3a)E5
	WS-G5487	--	12.1(5)T1
	WS-G5484	--	12.0(7)S
PA-GE	WS-G5486	--	12.0(6)T
	WS-G5487	--	12.1(1)E

[Cisco uBR7200 series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
uBR7200-NPE-G1	WS-G5484	--	12.2(11)CX
	WS-G5486		
	WS-G5487		
	CWDM GBIC		
uBR7200-NPE-G2	GLC-SX-MMD	12.2SB	12.2SB
	GLC-LH-SMD		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	CWDM SFP		

[Cisco 7300 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
CISCO7301	GLC-T (1000BASE-T)	--	12.2(18)S1
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
7300-NSE-100	WS-G5484	--	12.2(20)S
	WS-G5486		
	WS-G5487		
	WS-G5483	--	12.2(28)SB
	CWDM GBIC		
7304-NPE-G100	GLC-SX-MM	--	12.2(20)S
	GLC-LH-SM		
	GLC-ZX-SM		
	CWDM SFP		
7300-NSE-150	GLC-T	--	12.2(31)SB2
	GLC-TE		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		

[Cisco 7300 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-SX-MMD	12.2(31)SB2	12.2(31)SB2
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-BX-D		
	GLC-BX-U		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	CWDM SFP		

[Cisco 7500 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
GEIP	WS-G5484	--	Please see release notes
GEIP+	WS-G5486		
	WS-G5487		

Cisco 7600 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
OSM-1CHOC12/T1-SI	WS-G5484	--	Please see release notes
OSM-1CHOC12/T3-SI	WS-G5486		
OSM-2OC12-ATM-MM	WS-G5487		
OSM-2OC12-ATM-SI	CWDM GBIC		
OSM-2OC12-ATM-MM+			
OSM-2OC12-ATM-SI+			
OSM-4OC3-POS-SI			
OSM-4OC3-POS-SI+			
OSM-4OC12-POS-SI			
OSM-4OC12-POS-SI+			
OSM-8OC3-POS-MM			
OSM-8OC3-POS-SI			
OSM-8OC3-POS-SL			
OSM-8OC3-POS-SL+			
OSM-8OC3-POS-SI+			
OSM-16OC3-POS-MM			
OSM-16OC3-POS-SI			
OSM-16OC3-POS-SL			
OSM-16OC3-POS-SI+			
OSM-2OC12-POS-MM			
OSM-2OC12-POS-SI			
OSM-2OC12-POS-SL			
OSM-2OC12-POS-SI+			
OSM-2OC12-POS-MM+			
OSM4OC12-POS-MM			
OSM4OC12-POS-SI			
OSM4OC12-POS-SL			
OSM4OC12-POS-SI+			
OSM-1OC48-POS-SI			
OSM-1OC48-POS-SL			
OSM-1OC48-POS-SS			
OSM-1OC48-POS-SS+			
OSM-10C48-POS-SI+			
OSM-10C48-POS-SL+			
OSM-2OC48/1DPT-SS			
OSM-2OC48/1DPT-SI			
OSM-2OC48/1DPT-SL			
OSM-2+4GE-WAN+			
OSM-4GE-WAN-GBIC			
WS-SUP720	GLC-T (1000BASE-T)	--	15.1(3)S
WS-SUP720-3B	GLC-SX-MM		
WS-SUP720-3BXL	GLC-LH-SM GLC-ZX-SM		
	GLC-SX-MMD	--	15.1(3)S
	GLC-LH-SMD		
	GLC-TE (1000BASE-T)		

Cisco 7600 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-EX-SMD	--	15.2(1)S
	GLC-ZX-SMD		
	CWDM SFP	12.2(33)SRA	12.2(33)SRA
WS-SUP32-GE-3B	GLC-T (1000BASE-T)	--	12.2(33)SRA
	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-BX-D	12.2(33)SRA	12.2(33)SRA
	GLC-BX-U		
	CWDM SFP	12.2(33)SRB	12.2(33)SRB
	DWDM SFP	12.2(33)SRE	12.2(33)SRE
WS-X6724-SFP	GLC-T (1000BASE-T)	--	15.1(2)S
WS-X6748-SFP	GLC-TE (1000BASE-T)		
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	GLC-SX-MMD	--	15.1(2)S
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
	GLC-TE		
	SFP-GE-T (1000BASE-T)	--	12.2(33)SRB
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	DWDM SFP	--	12.2(33)SRE
RSP720-3C-GE	GLC-T (1000BASE-T)	--	15.1(3)S
RSP720-3CXL-GE	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	GLC-SX-MMD	12.2(33)SRE1	15.1(3)S
	GLC-LH-SMD		
	GLC-TE (1000BASE-T)		

Cisco 7600 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-EX-SMD	12.2(33)SRE1	15.2(1)S
	GLC-ZX-SMD		
	SFP-GE-T (1000BASE-T)	--	12.2(33)SRE1
	GLC-BX-D	12.2(33)SRE1	12.2(33)SRE1
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	SFP-GE-S		
	SFP-GE-L		
RSP720-10GE	GLC-T (1000BASE-T)	--	12.2(33)SRC
	GLC-SX-MM		
	GLC-LH-SM		
	GLC-ZX-SM		
	SFP-GE-T (1000BASE-T)		
	GLC-BX-D	12.2(33)SRC	12.2(33)SRC
	GLC-BX-U		
	SFP-GE-S		
	SFP-GE-L		
	GLC-SX-MMD	--	15.1(3)S
	GLC-LH-SMD		
	GLC-TE (1000BASE-T)		
	GLC-EX-SMD	--	15.2(1)S
	GLC-ZX-SMD		
	CWDM SFP	12.2(33)SRE1	12.2(33)SRE1
	DWDM SFP		
7600-ES+20G3C	SFP-GE-T	--	12.2(33)SRD
7600-ES+20G3CXL	SFP-GE-S	12.2(33)SRD	12.2(33)SRD
7600-ES+40G3C	SFP-GE-L		
7600-ES+40G3CXL	SFP-GE-Z		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-SX-MMD	--	15.1(2)S
	GLC-LH-SMD		
	GLC-TE		
	GLC-EX-SMD	--	15.2(1)S
	GLC-ZX-SMD		
	DWDM SFP (add.)	12.2(33)SRE	12.2(33)SRE

Cisco 7600 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
76-ES+T-20G	SFP-GE-S	12.2(33)SRD3	12.2(33)SRD3
76-ES+T-40G	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	SFP-GE-T	--	
	GLC-SX-MMD	--	15.1(2)S
	GLC-LH-SMD		
	GLC-TE		
	GLC-EX-SMD	--	15.2(1)S
	GLC-ZX-SMD		
	DWDM SFP (add.)	12.2(33)SRE	12.2(33)SRE
76-ES+XC-20G3C	SFP-GE-T	--	12.2(33)SRE
76-ES+XC-20G3CXL	SFP-GE-S	12.2(33)SRE	12.2(33)SRE
76-ES+XC-40G3C	SFP-GE-L		
76-ES+XC-40G3CXL	SFP-GE-Z		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	GLC-SX-MMD	--	15.1(2)S
	GLC-LH-SMD		
	GLC-TE		
	GLC-EX-SMD	--	15.2(1)S
	GLC-ZX-SMD		
	DWDM SFP (add.)		

Cisco 10000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ESR-1GE	WS-G5484	--	Please see release notes
	WS-G5486		
	WS-G5487		
ESR-HH-1GE	SFP-GE-T	--	12.0(23)S
	SFP-GE-S		
	SFP-GE-L	12.0(23)S	12.0(23)S

Cisco 10000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	SFP-GE-Z		

Cisco uBR10000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
UBR10-1GE	WS-G5484	--	Please see release notes
	WS-G5486		
	WS-G5487		
ESR-HH-1GE	SFP-GE-T	--	12.3(13)BC
	GLC-SX-MMD	12.3(13)BC	12.3(13)BC
	GLC-LH-SMD		
	GLC-ZX-SMD		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		

Cisco RF Gateway Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
RFGW-X4516-10GE	SFP-GE-S	12.2(44)SQ	12.2(44)SQ
	SFP-GE-L		
RFGW-DS48	SFP-GE-T	--	12.2(44)SQ
	SFP-GE-S	12.2(44)SQ	12.2(44)SQ
	SFP-GE-L		

Cisco 12000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
10x1GE-SFP-LC-B	GLC-SX-MM	--	12.0(21)S
	GLC-LH-SM		
4GE-SFP-LC	GLC-SX-MM	12.0(25)S	12.0(25)S
	GLC-LH-SM		
	GLC-ZX-SM		

[Cisco 12000 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-SX-MMD		12.0(32)S
	GLC-LH-SMD		
	GLC-ZX-SMD		
	CWDM SFP		
EPA-3GE-SX/LH-LC	GLC-SX-MM		12.0(23)S
	GLC-LH-SM		
	GLC-ZX-SM		

[Cisco NCS 5000 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NCS 5001	GLC-SX-MMD		XR 6.0.0
NCS 5002	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
	GLC-TE		
	CWDM-SFP-xxxx		
	DWDM-SFP-xxxx		

[Cisco NCS 5500 Series](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
NCS-5501	GLC-SX-MMD	--	XR 6.1.1
NCS-5501-SE	GLC-LH-SMD		
	GLC-TE (1000BASE-T)		
	GLC-ZX-SMD		XR 6.2.2
	GLC-EX-SMD		
	DWDM-SFP10G-xxxx		
	CWDM-SFP10G-xxxx		

Shared Port Adapters (SPAs)

Network Device	Transceiver Model	Minimum Software Release Required
SPA-5X1GE-V2	SFP-GE-T	SPA software support is determined by the platform on which the SPA is installed.
SPA-8X1GE-V2	SFP-GE-S	Refer to the SPA release notes for the correct software release.
SPA-10X1GE-V2	SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	
SPA-2X1GE-V2	SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	

CRS Router Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
CRS-16-RP	GLC-LH-SM GLC-LH-SMD	--	XR 2.0
CRS-16-RP-B	GLC-LH-SM GLC-LH-SMD	--	XR 3.3
CRS-FCC-SC-22GE	GLC-LH-SM GLC-LH-SMD	--	XR 3.4.1
42-1GE	SFP-GE-T (1000BASE-T)	--	XR 3.8.1
20-1GE-FLEX	SFP-GE-S GLC-SX-MMD SFP-GE-L GLC-LH-SMD SFP-GE-Z	XR 3.8.1	XR 3.8.1
CRS-8-PRP-6G	GLC-LH-SM	--	XR 4.0.2
CRS-8-PRP-12G	GLC-LH-SMD		

ASR 901 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
A901-12C-F-D	GLC-T	--	15.1(2)SNG
A901-12-C-FT-D	GLC-TE SFP-GE-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MM-RGD GLC-LX-SM-RGD		
	SFP-GE-S SFP-GE-L SFP-GE-Z	15.1(2)SNI	15.1(2)SNG
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U GLC-EX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	15.2(2)SNI	15.2(2)SNG
A901-4C-F-D	GLC-T	--	15.2(2)SNH1
A901-4-C-FT-D	GLC-TE		
A901-6CZ-F-D	SFP-GE-T		
A901-6-CZ-FT-D	GLC-SX-MM		
A901-6CZ-F-A	GLC-LH-SM		
A901-6-CZ-FT-A	GLC-ZX-SM GLC-SX-MM-RGD GLC-LX-SM-RGD		
	SFP-GE-S SFP-GE-L SFP-GE-Z GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U GLC-EX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	15.2(2)SNH1	15.2(2)SNH1

Cisco ASR 903 Series

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
A9K-40GE-TR	SFP-GE-T	--	XE 3.5.0S
	GLC-SX-MM-RGD		
	GLC-LX-SM-RGD		
	GLC-ZX-SM-RGD		
	GLC-BX-D	XE 3.5.0S	XE 3.5.0S
	GLC-BX-U		
	GLC-EX-SMD		
	GLC-SX-MMD	XE 3.6.0S	XE 3.6.0S
	GLC-LH-SMD		
	GLC-ZX-SMD		
ASR1000	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)		
	GLC-TE	-	3.18SP.1

ASR 1000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ASR1001	SFP-GE-T	--	XE 2.1
ASR1002	SFP-GE-S	XE 2.1	XE 2.1
ASR1002-F	SFP-GE-L		
ASR1002-X	SFP-GE-Z		
ASR1001-X*	CWDM SFP		
ASR1002-HX**	DWDM SFP		
ASR1001-HX***	GLC-GE-100FX		
	GLC-BX-D	XE 2.5	XE 2.5
	GLC-BX-U		
	GLC-SX-MMD	XE 3.4S	XE 3.4S
	GLC-LH-SMD		
	GLC-ZX-SMD		
	GLC-EX-SMD	XE 3.5S	XE 3.5S
	GLC-TE	XE 3.15.0S	XE 3.15.0S
	GLC-BX40-D-I	IOS XE Denali 16.3.1	IOS XE Denali 16.3.1
	GLC-BX40-DA-I		
	GLC-BX40-U-I		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	DWDM-SFP10G-C	IOS XE 16.7.1	IOS XE 16.7.1

[ASR 1000 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ASR 1000 platform with SPA cards	Software support on the ASR 1000 modular platforms is determined by the platform on which the SPA is installed. Refer to the SPA release notes for the correct software release.		
*ASR 1001-X supports the above mentioned SFPs from 3.12.0S or 'Minimum Software Release Required' whichever latest. ASR 1001-X supports GLC-GE-100FX from 16.2 or 'Minimum Software Release Required' whichever latest. ASR1001-X does not support GLC-LH-SM. Use GLC-LH-SMD instead.			
**ASR 1002-HX supports the above mentioned SFPs from 16.2 or 'Minimum Software Release Required' whichever latest.			
*** ASR 1001-HX supports GLC-GE-100FX on Bay 0 only.			

[ASR 9000 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
A9K-40GE-TR	GLC-SX-MMD	XR 5.2.2	XR 5.2.2
A9K-40GE-SE	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D		
	GLC-BX-U		
	GLC-GE-100FX		
	CWDM SFP		
	DWDM SFP		
	SFP-GE-T	-	
	GLC-TE	-	XR 5.3.4
A9K-40GE-B	SFP-GE-T (10/100/1000)	--	XR 3.9.0
A9K-40GE-E	SFP-GE-S	XR 3.7.3	XR 3.7.3
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)	XR 3.9.0	XR 3.9.0
	GLC-SX-MMD	XR 4.1.1	XR 4.1.1
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		

ASR 9000 Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
A9K-2T20GE-B	SFP-GE-T (10/100/1000)	--	XR 3.9.0
A9K-2T20GE-E	SFP-GE-S	XR 3.9.0	XR 3.9.0
A9K-2T20GE-L	SFP-GE-L		
A9K-40GE-L	SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)		
	GLC-SX-MMD	XR 4.1.1	XR 4.1.1
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
A9K-4T16GE-TR	GLC-SX-MMD	XR 5.3.0	XR 5.3.0
A9K-4T16GE-SE	GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U GLC-GE-100FX CWDM SFP DWDM SFP		
	SFP-GE-T	-	
	GLC-TE	-	XR 5.3.4
A9K-MPA-20X1GE	SFP-GE-T (10/100/1000)	--	XR 4.2.0
	SFP-GE-S	XR 4.2.0	XR 4.2.0
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		

[ASR 9000 Series Router](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
	GLC-BX40-D-I	XR 5.1.2	XR 5.1.2
	GLC-BX40-U-I		
	GLC-BX40-DA-I		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	GLC-TE	XR 5.2.2	XR 5.2.2
	GLC-GE-DR-LX		
A9K-RSP440-TR	SFP-GE-T (10/100/1000)	--	XR 4.2.1
A9K-RSP440-SE	SFP-GE-S	XR 4.2.1	XR 4.2.1
	SFP-GE-L		
	SFP-GE-Z		
	GLC-BX-D		
	GLC-BX-U		
	CWDM SFP		
	DWDM SFP		
	DWDM SFP (add.)		
	GLC-SX-MMD	XR 4.2.3	XR 4.2.3
	GLC-LH-SMD		
	GLC-EX-SMD	XR 5.2.0	XR 5.2.0
	GLC-ZX-SMD		
	GLC-TE	--	XR 5.2.2
	GLC-GE-DR-LX		

[ASR 9000 Series Router \(EOBC-supported optics\)](#)

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ASR-9001	SFP-GE-S	XR 4.3.0	XR 4.3.0
ASR-9001-S	GLC-SX-MMD	XR 4.3.0	XR 4.3.0
	GLC-LH-SMD		
	GLC-TE	--	XR 5.2.2
	GLC-GE-DR-LX		
	GLC-EX-SMD	XR 5.2.0	XR 5.2.0
	GLC-ZX-SMD		
ASR-9922-RP-SE	SFP-GE-S	XR 4.3.1	XR 4.3.1
ASR-9922-RP-TR	GLC-SX-MMD		
	GLC-LH-SMD		
A9K-RSP440-TR	SFP-GE-S	XR 4.2.1	XR 4.2.1
A9K-RSP440-SE	GLC-SX-MMD		

GLC-LH-SMD

ASR9000v Series Router

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
ASR-9000V-AC	SFP-GE-T	XR 4.3.0	XR 4.3.0
ASR-9000V-DC-A	SFP-GE-S		
ASR-9000V-DC-E	SFP-GE-L		
ASR-9000V-24-A	GLC-BX-D		
	GLC-LH-SM		
	GLC-BX-U	XR 4.3.0	XR 4.3.0
	SFP-GE-Z		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
	CWDM SFP		
	GLC-BX40-D-I	XR 5.1.1	XR 5.1.1
	GLC-BX40-U-I		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	GLC-BX40-DA-I	XR 5.2.0	XR 5.2.0
	GLC-TE	XR 5.2.2	XR 5.2.2
	GLC-GE-DR-LX		
	GLC-T	--	XR 4.2.3
A9KV-V2-AC	SFP-GE-T	XR 4.3.0	XR 4.3.0
A9KV-V2-DC-A	SFP-GE-S		
A9KV-V2-DC-E	SFP-GE-L		
	GLC-BX-D		
	GLC-LH-SM		
	GLC-BX-U	XR 4.3.0	XR 4.3.0
	SFP-GE-Z		
	GLC-SX-MMD		
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
	CWDM SFP		
	GLC-BX40-D-I	XR 5.1.1	XR 5.1.1
	GLC-BX40-U-I		
	GLC-BX80-D-I		
	GLC-BX80-U-I		
	GLC-BX40-DA-I	XR 5.2.0	XR 5.2.0
	GLC-TE	XR 5.2.2	XR 5.2.2
	GLC-GE-DR-LX		

Cisco MWR 2941 Mobile Wireless Routers

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
MWR-2941-DC	GLC-SX-MMD	12.4(19)MR1	12.4(19)MR1
	GLC-LH-SMD		
	SFP-GE-S		
	SFP-GE-L		
	SFP-GE-Z		
	GLC-SX-MM-RGD	--	12.4(19)MR1
	GLC-LX-SM-RGD		
	GLC-ZX-SM-RGD		
	SFP-GE-T	--	12.4(19)MR3 or 12.2(33)MRA
	CWDM SFP	12.4(19)MR3	12.4(19)MR3
	DWDM SFP	or 12.2(33)MRA	or 12.2(33)MRA
	GLC-BX-D	12.2(33)MRB	12.2(33)MRB
	GLC-BX-U	or 12.4(20)MRA	or 12.4(20)MRA
	GLC-EX-SMD	15.1(01)MR	15.1(01)MR

Appliance SupportASA5500 Series appliances

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
SSM-4GE	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	ASA 7.0

NAM 2200 Series appliances

Network Device	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
NAM2204-SFP	GLC-T (1000BASE-T) GLC-TE (1000BASE-T) GLC-SX-MM GLC-LH-SM	--	NAM 4.0

Wireless LAN Controllers Support

Cisco 5700 WLC Series

Controller or Module	Transceiver Module	Minimum Software Release Required	
		DOM Support	Cisco IOS Release
AIR-CT5760-25-K9	GLC-T (10/100/1000)	XE 3.2.0SE	XE 3.2.0SE
AIR-CT5760-50-K9	GLC-TE		
AIR-CT5760-100-K9	GLC-LH-SM		
AIR-CT5760-250-K9	GLC-LH-SMD		
AIR-CT5760-500-K9	GLC-SX-MM		
AIR-CT5760-1K-K9	GLC-SX-MMD		
AIR-CT5760-HA-K9	GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP DWDM SFP (add.)		

Cisco Security Appliance Minimum Software Release Requirements

Cisco Firepower

Network Device	Transceiver Model	Minimum Software Release Required	
		DOM Support	Software Release
FPR2K-NM-8X1G-F	GLC-SX-MMD	1.1.4	
	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
FPR4K-NM-8X1G-F	GLC-SX-MMD	1.1.4	
FPR9K-NM-8X1G-F	GLC-LH-SMD		
	GLC-EX-SMD		
	GLC-ZX-SMD		
	GLC-T		
	GLC-TE		

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, using the Cisco Bug Search Tool (BST), submitting a service request, and gathering additional information, see [What's New in Cisco Product Documentation](#).

To receive new and revised Cisco technical content directly to your desktop, you can subscribe to the [What's New in Cisco Product Documentation RSS feed](#). The RSS feeds are a free service.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Copyright © 2004-2017, Cisco Systems, Inc.

All rights reserved. Printed in USA.