



Cisco Wireless Solutions Software Compatibility Matrix

Last Updated: December 12, 2017

This document lists the software compatibility matrix information for the Cisco wireless devices used in a Cisco centralized and distributed wireless LAN solution and in converged access solutions.

Contents

This document contains the following sections:

- [Conventions, page 2](#)
- [Supported Access Points in Cisco Wireless Software Releases, page 2](#)
- [Supported Cisco WLC Platforms in Software Releases, page 14](#)
- [Cisco Prime Infrastructure Compatibility Matrix, page 15](#)
- [Cisco Connected Mobile Experiences \(CMX\) Compatibility Matrix, page 61](#)
- [Cisco Mobility Services Engine Compatibility Matrix, page 63](#)
- [Cisco Mobility Express Solution Compatibility Matrix, page 80](#)
- [Converged Access Solution Compatibility Matrix, page 82](#)
- [Supported Converged Access Solution Hardware, page 87](#)
- [Compatibility Matrix for Legacy Products, page 93](#)
- [Inter-Release Controller Mobility, page 111](#)
- [New Mobility Support Matrix, page 114](#)
- [Cisco Support Community, page 116](#)
- [Obtain Documentation and Submit a Service Request, page 116](#)



Conventions

See [Cisco Technical Tips Conventions](#) for information about document conventions.

Supported Access Points in Cisco Wireless Software Releases

[Table 1](#) lists the supported access points for various Cisco Wireless software releases.

For information about compatibility of Cisco Prime Infrastructure with Cisco WLC, see the “[Cisco Prime Infrastructure Compatibility Matrix](#)” section on page 15.

For information about compatibility of Cisco Mobility Services Engine with Cisco WLC, see the “[Cisco Mobility Services Engine Compatibility Matrix](#)” section on page 63.

For compatibility information about Cisco WLC and Cisco ISE, see the [Cisco ISE Compatibility Information page](#).

Table 1 Cisco WLC Software Releases, AP IOS Releases, and Supported Access Points

Cisco WLC Release	Access Point IOS Release	Supported Access Points
8.6.101.0	15.3(3)JG1	Lightweight APs: 1700, 1800i, 1810 OEAP, 1810W, 1815i, 1815m, 1815t, 1815w, 1830, 1850, 2700, 2800, 3702e, 3702i, 3702p, 3800, 700, 700W, AP803, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, 1570, and IW3700 Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.5.110.0	15.3(3)JF4	Lightweight APs: 1600, 1700, 1800i, 1810 OEAP, 1810W, 1815i, 1815m, 1815t, 1815w, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 700, 700W, AP802, AP803, ASA5506W-AP702
8.5.105.0	15.3(3)JF1	
8.5.103.0	15.3(3)JF	Outdoor and Industrial APs: 1532E, 1532I, 1540, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1560, 1570, and IW3700 Note The Cisco Aironet 1550 Series APs with 64-MB memory are not supported. Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.4.100.0	15.3(3)JE	Lightweight APs: 1600, 1700, 1810 OEAP, 1810W, 1815i, 1815w, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 700, 700W, AP802, AP803, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1560, 1570, and IW3700 Note The Cisco Aironet 1550 Series APs with 64-MB memory are not supported. Modules: AIR-RM3010L-x-K9 and AIR-RM3000M

Table 1 Cisco WLC Software Releases, AP IOS Releases, and Supported Access Points (continued)

Cisco WLC Release	Access Point IOS Release	Supported Access Points
8.3.133.0	15.3(3)JD11 15.3(3)JDA11	Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEAP, 1810W, 1815i, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702
8.3.132.0	15.3(3)JD9 15.3(3)JDA9	Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1560, 1570, and IW3700
8.3.130.0	15.3(3)JD7, 15.3(3)JDA7	Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.3.122.0 8.3.121.0	15.3(3)JD6 15.3(3)JD5	The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 or later are not supported on these access points.
8.3.112.0	15.3(3)JD4	Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEAP, 1810W, 1815i, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1560, 1570, and IW3700 Modules: AIR-RM3010L-x-K9 and AIR-RM3000M The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 or later are not supported on these access points.
8.3.102.0	15.3(3)JD	Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEAP, 1810W, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3700 Modules: AIR-RM3010L-x-K9 and AIR-RM3000M Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.
8.2.166.0	15.3(3)JC14 15.3(3)JCA14	Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEAP, 1810W, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702
8.2.164.0	15.3(3)JC9 15.3(3)JCA9	Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3700
8.2.161.0	15.3(3)JC8 15.3(3)JCA8	Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.2.160.0	15.3(3)JC7	Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.

Table 1 Cisco WLC Software Releases, AP IOS Releases, and Supported Access Points (continued)

Cisco WLC Release	Access Point IOS Release	Supported Access Points
8.2.151.0	15.3(3)JC6	Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEAP, 1810W, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702
8.2.141.0	15.3(3)JC5	
8.2.130.0	15.3(3)JC4	
8.2.121.0	15.3(3)JC3	Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3700 Modules: AIR-RM3010L-x-K9 and AIR-RM3000M Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.
8.2.111.0	15.3(3)JC2	Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEAP, 1810W, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3700 Modules: AIR-RM3010L-x-K9 and AIR-RM3000M Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.
8.2.110.0	15.3(3)JC1	Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEAP, 1810W, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3700 Modules: AIR-RM3010L-x-K9 and AIR-RM3000M Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.
8.2.100.0	15.3(3)JC	Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1830, 1850, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3700 Modules: AIR-RM3010L-x-K9 and AIR-RM3000M Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.

Table 1 Cisco WLC Software Releases, AP IOS Releases, and Supported Access Points (continued)

Cisco WLC Release	Access Point IOS Release	Supported Access Points
8.1.131.0	15.3(3)JBB6	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1830, 1850, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p>Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.</p>
8.1.122.0	15.3(3)JBB5	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1830, 1850, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.</p>
8.1.111.0	15.3(3)JBB1	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1850, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, and AP802</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, and 1570</p> <p>Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.</p>
8.1.102.0	15.3(3)JBB	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, and AP802</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, and 1570</p> <p>Note The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 and later are not supported on these access points.</p>

Table 1 Cisco WLC Software Releases, AP IOS Releases, and Supported Access Points (continued)

Cisco WLC Release	Access Point IOS Release	Supported Access Points
8.0.152.0	153-3.JA12 15.3(3)JAA12 12.4(25e)JAP12	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 1700, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP801, and AP802
8.0.150.0	15.3(3)JA11 15.3(3)JAA11 12.4(25e)JAP11	Note Cisco MSE Release 8.0.140.x and later includes wIPS support for the Cisco Aironet 1800, 2800, and 3800 series. However, CAS is not supported for these APs.
8.0.140.0	15.3(3)JA10/ 12.4(25e)JAP10	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3702
8.0.135.0	15.3(3)JA9/ 12.4(25e)JAP9	Note The Cisco Wireless Release 8.0.135.0 is a repost of the Cisco Wireless Release 8.0.132.0 and 8.0.133.0. This release impacts only the Cisco Aironet 1570 Series APs with -B regulatory domain and meet the following criteria: <ul style="list-style-type: none"> a. The Cisco 1570 APs that are made available on or after June 2, 2016, for the USA region b. The Cisco 1570 APs that are identified with version ID 02 (V02) This release ensures that Cisco 1570 APs that are made available to customers in the USA are in compliance with the new FCC rules that come into effect on June 2, 2016.
8.0.133.0	15.3(3)JA8/ 12.4(25e)JAP8	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 1700, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP801, and AP802
8.0.132.0	15.3(3)JA7/ 12.4(25e)JAP7	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3702
8.0.121.0	15.3(3)JA5/ 12.4(25e)JAP5	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 1700, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP801, and AP802
8.0.120.0	15.3(3)JA4/ 12.4(25e)JAP4	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, 1570, and IW3702
8.0.110.0 8.0.115.0	15.3(3)JA1/ 12.4(25e)JAP1	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 1700, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, 1552S, and 1570
8.0.100.0	15.3(3)JAB/ 12.4(25e)JAP	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 1700, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.6.130.0	15.2(4)JB6/ 12.4.25e-JAO6	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP801, and AP802
7.6.120.0	15.2(4)JB5/ 12.4(25e)JAO5	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.6.110.0	15.2(4)JB4/ 12.4(25e)JAO4	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 2600, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, AP801, and AP802
7.6.100.0	15.2(4)JB3/ 12.4(25e)JAO3	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1532E, 1532I, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552S

Table 1 Cisco WLC Software Releases, AP IOS Releases, and Supported Access Points (continued)

Cisco WLC Release	Access Point IOS Release	Supported Access Points
7.5.102.0	15.2(4)JA1/ 12.4(25e)JAN1	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 2600, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 600 OEAP, 700, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.4.150.0	15.2(2)JB6/ 12.4(25e)JAM6	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 2600, 3500e, 3500i, 3500p, 3600e, 3600i, 600 OEAP, AP801, AP802
7.4.140.0	15-2(2)JB5/ 12.4(25e)JAM5	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.4.130.0	15.2(2)JB3/ 12.4(25e)JAM4	
7.4.121.0	15.2(2)JB3/ 12.4(25e)JAM3	
7.4.110.0	15.2(2)JB2/ 12.4(25e)JAM2	
7.4.100.60	15.2(2)JB1/ 12.4(25e)JAM1	
7.4.100.0	15.2(2)JB/ 12.4(25e)JAM	
7.3.112.0	15.2(2)JA1/ 12.4(25e)JAL2	
7.3.101.0	15.2(2)JA/ 12.4(25e)JAL	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.2.115.2	12.4(25e)JA2	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 2600, 3500e, 3500i, 3500p, 3600e, 3600i, 600 OEAP, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552H, 1552I, 1552C, and 1552S
7.2.111.3	12.4(25e)JA2	
7.2.110.0	12.4(25e)JA1	
7.2.103.0	12.4(25e)JA	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 3500e, 3500i, 3600e, 3500p, 3600i, 600 OEAP, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552H, 1552I, 1552C, and 1552S
7.0.252.0	12.4(23c)JA10	Lightweight APs: 1040, 1120, 1130, 1140, 1220, 1230, 1240, 1250, 1260, 1300, 3500, OEAP 600 Series, 3500p, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524SB, 1552E, 1552H, 1552I, 1552C, and 1552S
7.0.251.2	12.4(23c)JA9	
7.0.250.0	12.4(23c)JA8	
7.0.240.0	12.4(23c)JA7	
7.0.235.3	12.4(23c)JA6	
7.0.235.0	12.4(23c)JA5	
7.0.230.0	12.4(23c)JA4	
7.0.220.0	12.4(23c)JA3	

Table 1 Cisco WLC Software Releases, AP IOS Releases, and Supported Access Points (continued)

Cisco WLC Release	Access Point IOS Release	Supported Access Points
7.0.116.0	12.4(23c)JA2	Lightweight APs: 1040, 1120, 1130, 1140, 1220, 1230, 1240, 1250, 1260, 3500e, 3500i, 3500p, 600 OEAP, AP801, AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552H, 1552I, and 1552C
7.0.98.218	12.4(23c)JZ	Lightweight APs: 1040, 1120, 1130, 1140, 1220, 1230, 1240, 1250, 1260, 1300, 3500, and AP801
7.0.98.0	12.4(23c)JA	Outdoor and Industrial APs: 1522, 1524PS, and 1524SB
6.0.202.0	12.4(21a)JHC	Lightweight APs: 1120, 1130, 1140, 1230AG, 1240, 1250, 1300, and AP801 Outdoor and Industrial APs: 1522, 1524PS, and 1524SB
5.2.193.0	12.4(18a)JA2	Lightweight APs: 1120, 1130, 1140, 1220, 1230AG, 1240, 1250, 1300, and AP801 Outdoor and Industrial APs: 1522 and 1524PS
4.1.192.35 M (Mesh Release 3)	—	1505, 1510, 1522, 1524PS, 1130, 1240
4.1.191.24 M (Mesh Release 2)	—	1505, 1510, 1522 (US, Canada, and RoW), 1130, 1240
4.1.190.5 (Mesh Release 1)	—	1505, 1510, 1522 (US and Canada)

Software Release Support for Specific Access Point Modules

Table 2 lists the Cisco WLC software releases that support specific Cisco access point modules. The First Support column lists the earliest Cisco WLC software release that supports the access point module. For access point modules that are not supported in ongoing releases, the Last Support column lists the last release that supports the access point module.

Table 2 Software Support for Access Point Modules

Access Points		First Cisco Wireless Release Support	Last Cisco Wireless Release Support	First IOS XE Release Support	Last IOS XE Release Support
700W Series	AIR-CAP702Wx-K9	7.6.120.0	—	3.6.0E	—
	AIR-CAP702W-xK910	7.6.120.0	—	3.6.0E	—
700 Series	AIR-CAP702I-x-K9	7.5.102.0	—	3.6.0E	—
	AIR-CAP702W-x-K9	7.6.120.0	—	3.6.0E	—

Table 2 Software Support for Access Point Modules (continued)

Access Points		First Cisco Wireless Release Support	Last Cisco Wireless Release Support	First IOS XE Release Support	Last IOS XE Release Support
1000 Series	AIR-AP1010	3.0.100.0	4.2.209.0	—	—
	AIR-AP1020	3.0.100.0	4.2.209.0	—	—
	AIR-AP1030	3.0.100.0	4.2.209.0	—	—
	Airespace AS1200	—	4.0	—	—
	AIR-LAP1041N	7.0.98.0	8.3.x	3.2.0SE	—
	AIR-LAP1042N	7.0.98.0	8.3.x	3.2.0SE	—
1100 Series	AIR-LAP1121	4.0.155.0	7.0.x	—	—
	AIR-LAP1131	3.1.59.24	8.0.x	—	—
	AIR-LAP1141N	5.2.157.0	8.3.x	3.2.0SE	—
	AIR-LAP1142N	5.2.157.0	8.3.x	3.2.0SE	—
1220 Series	AIR-AP1220A	3.1.59.24	7.0.x	—	—
	AIR-AP1220B	3.1.59.24	7.0.x	—	—
1230 Series	AIR-AP1230A	3.1.59.24	7.0.x	—	—
	AIR-AP1230B	3.1.59.24	7.0.x	—	—
	AIR-LAP1231G	3.1.59.24	7.0.x	—	—
	AIR-LAP1232AG	3.1.59.24	7.0.x	—	—
1240 Series	AIR-LAP1242G	3.1.59.24	8.0.x	—	—
	AIR-LAP1242AG	3.1.59.24	8.0.x	—	—
1250 Series	AIR-LAP1250	4.2.61.0	8.0.x	—	—
	AIR-LAP1252G	4.2.61.0	8.0.x	—	—
	AIR-LAP1252AG	4.2.61.0	8.0.x	—	—
1260 Series	AIR-LAP1261N	7.0.116.0	8.3.x	3.2.0SE	—
	AIR-LAP1262N	7.0.98.0	8.3.x	3.2.0SE	—
1300 Series	AIR-BR1310G	4.0.155.0	7.0.x	—	—
1400 Series	Standalone Only	N/A	—	—	—
1600 Series	AIR-CAP1602I-x-K9	7.4.100.0	8.5.x	3.2.0SE	—
	AIR-CAP1602I-xK910	7.4.100.0	8.5.x	3.2.0SE	—
	AIR-SAP1602I-x-K9	7.4.100.0	8.5.x	3.2.0SE	—
	AIR-SAP1602I-xK9-5	7.4.100.0	8.5.x	3.2.0SE	—
	AIR-CAP1602E-x-K9	7.4.100.0	8.5.x	3.2.0SE	—
	AIR-SAP1602E-xK9-5	7.4.100.0	8.5.x	3.2.0SE	—
1700 Series	AIR-CAP1702I-x-K9	8.0.100.0	—	3.7.0E	—
	AIR-CAP1702I-xK910	8.0.100.0	—	3.7.0E	—
1810 Series	AIR-OEAP1810-x-K9	8.2.110.0	—	—	—

Table 2 Software Support for Access Point Modules (continued)

Access Points		First Cisco Wireless Release Support	Last Cisco Wireless Release Support	First IOS XE Release Support	Last IOS XE Release Support
1810W Series	AIR-AP1810W-x-K9	8.2.110.0	—	—	—
1815 Series	AIR-AP1815I-x-K9	8.3.112.0	—	—	—
	AIR-AP1815W-x-K9	8.4.100.0	—	—	—
	AIR-AP1815M-x-K9	8.5.103.0	—	—	—
	AIR-AP1815T-x-K9	8.5.103.0	—	—	—
1830 Series	AIR-AP1832I-UXX9	8.1.122.0	—	3.7.3	—
	AIR-AP1832I-UXX910	8.1.122.0	—	3.7.3	—
	AIR-AP1832I-UXX9C	8.1.122.0	—	3.7.3	—
	AIRAP1832I-UXX910C	8.1.122.0	—	3.7.3	—
	AIR-AP1832I-x-K9	8.1.122.0	—	3.7.3	—
	AIR-AP1832I-x-K9C	8.1.122.0	—	3.7.3	—
1850 Series	AIR-AP1852I-UXX9	8.1.111.0		3.7.3	—
	AIR-AP1852I-UXX910	8.1.111.0		3.7.3	—
	AIR-AP1852I-UXX9C	8.1.111.0		3.7.3	—
	AIRAP1852I-UXX910C	8.1.111.0		3.7.3	—
	AIR-AP1852E-UXX9	8.1.111.0		3.7.3	—
	AIR-AP1852E-UXX910	8.1.111.0		3.7.3	—
	AIR-AP1852E-UXX9C	8.1.111.0		3.7.3	—
	AIRAP1852E-UXX910C	8.1.111.0		3.7.3	—
	AIR-AP1852E-x-K9	8.1.111.0		3.7.3	—
	AIR-AP1852E-x-K9C	8.1.111.0		3.7.3	—
	AIR-AP1852I-x-K9	8.1.111.0		3.7.3	—
	AIR-AP1852I-x-K9C	8.1.111.0		3.7.3	—
AP801	—	5.1.151.0	8.0.x	—	—
AP802	—	7.0.98.0	8.5.x	—	—
AP802H	—	7.3.101.0	8.5.x	—	—
AP803	—	8.1.122.0	—	—	—
ASA 5506W-AP702	—	8.1.122.0	—	—	—

Table 2 Software Support for Access Point Modules (continued)

Access Points		First Cisco Wireless Release Support	Last Cisco Wireless Release Support	First IOS XE Release Support	Last IOS XE Release Support
2600 Series	AIR-CAP2602I-x-K9	7.2.110.0	8.5.x	3.2.0SE	—
	AIR-CAP2602I-xK910	7.2.110.0	8.5.x	3.2.0SE	—
	AIR-SAP2602I-x-K9	7.2.110.0	8.5.x	3.2.0SE	—
	AIR-SAP2602I-x-K95	7.2.110.0	8.5.x	3.2.0SE	—
	AIR-CAP2602E-x-K9	7.2.110.0	8.5.x	3.2.0SE	—
	AIR-CAP2602E-xK910	7.2.110.0	8.5.x	3.2.0SE	—
2700 Series	AIR-CAP2702I-x-K9	7.6.120.0	—	3.6.0E	—
	AIR-CAP2702E-x-K9	7.6.120.0	—	3.6.0E	—
	AIR-AP2702I-UXK9	8.0.110.0	—	—	—
2800 Series	AIR-AP2802E-x-K9	8.2.110.0	—	—	—
	AIR-AP2802I-x-K9	8.2.110.0	—	—	—
3500 Series	AIR-CAP3501E	7.0.98.x	8.5.x	3.2.0SE	—
	AIR-CAP3501I	7.0.98.x	8.5.x	3.2.0SE	—
	AIR-CAP3502E	7.0.98.x	8.5.x	3.2.0SE	—
	AIR-CAP3502I	7.0.98.x	8.5.x	3.2.0SE	—
	AIR-CAP3502P	7.0.116.0	8.5.x	3.2.0SE	—
3600 Series	AIR-CAP3602I	7.1.91.0	8.5.x	3.2.0SE	—
	AIR-CAP3602E	7.1.91.0	8.5.x	3.2.0SE	—
3700 Series	AIR-CAP3702I	7.6.100.0	—	3.3.1SE	—
	AIR-CAP3702E	7.6.100.0	—	3.3.1SE	—
	AIR-CAP3702P	7.6.100.0	—	3.3.1SE	—
3800 Series	AIR-AP3802E-x-K9	8.2.110.0	—	—	—
	AIR-AP3802I-x-K9	8.2.110.0	—	—	—
	AIR-AP3802P-x-K9	8.2.110.0	—	—	—
600 Series	AIR-OEAP602I	7.0.116.0	8.3.x	—	—
1500 Mesh Series	AIR-LAP-1505	3.1.59.24	4.2.207.54M	—	—
	AIR-LAP-1510	3.1.59.24	4.2.207.54M	—	—

Table 2 Software Support for Access Point Modules (continued)

Access Points		First Cisco Wireless Release Support	Last Cisco Wireless Release Support	First IOS XE Release Support	Last IOS XE Release Support
1520 Mesh Series	AIR-LAP1522AG	-A and N: 4.1.190.1 or 5.2 or later ¹	8.0.x	—	—
		All other reg. domains: 4.1.191.24M or 5.2 or later ¹	8.0.x	—	—
	AIR-LAP1522HZ	-A and N: 4.1.190.1 or 5.2 or later ¹	8.0.x	—	—
		All other reg. domains: 4.1.191.24M or 5.2 or later ¹	8.0.x	—	—
	AIR-LAP1522PC	-A and N: 4.1.190.1 or 5.2 or later ¹	8.0.x	—	—
		All other reg. domains: 4.1.191.24M or 5.2 or later ¹	8.0.x	—	—
	AIR-LAP1523CM	7.0.116.0 or later.	8.0.x	—	—
	AIR-LAP1524SB	-A, C and N: 6.0 or later	8.0.x	—	—
		All other reg. domains: 7.0.116.0 or later.	8.0.x	—	—
	AIR-LAP1524PS	-A: 4.1.192.22M or 5.2 or later ¹	8.0.x	—	—
1530 Series	AIR-CAP1532I-x-K9	7.6.100.0	—	3.6.0E ²	—
	AIR-CAP1552E-x-K9	7.6.100.0	—	3.6.0E	—
1540 Series	AIR-AP1542I-x-K9	8.5.103.0	—	—	—
	AIR-AP1542D-x-K9	8.5.103.0	—	—	—
1550 Series ³	AIR-CAP1552I-x-K9	7.0.116.0	8.5.x	—	—
	AIR-CAP1552E-x-K9	7.0.116.0	8.5.x	—	—
	AIR-CAP1552C-x-K9	7.0.116.0	8.5.x	—	—
	AIR-CAP1552H-x-K9	7.0.116.0	8.5.x	—	—
	AIR-CAP1552SA-x-K9	7.0.220.0	8.5.x	—	—
	AIR-CAP1552SD-x-K9	7.0.220.0	8.5.x	—	—
	AIR-CAP1552CU-x-K9	7.3.101.0	8.5.x	—	—
	AIR-CAP1552EU-x-K9	7.3.101.0	8.5.x	—	—

Table 2 Software Support for Access Point Modules (continued)

Access Points		First Cisco Wireless Release Support	Last Cisco Wireless Release Support	First IOS XE Release Support	Last IOS XE Release Support
1552S	AIR-CAP1552SA-x-K9	7.0.220.0	8.5.x	—	—
	AIR-CAP1552SD-x-K9	7.0.220.0	8.5.x	—	—
1560 Series	AIR-AP1562I-x-K9	8.3.111.0	—	—	—
	AIR-AP1562E-x-K9	8.3.111.0	—	—	—
	AIR-AP1562D-x-K9	8.3.111.0	—	—	—
1570 version ID 01 (V01)	AIR-AP1572EAC-x-K9	8.0.110.0	—	3.7.0E	—
	AIR-AP1572ICy ⁴ -x-K9	8.0.110.0	—	3.7.0E	—
	AIR-AP1572ECy-x-K9	8.0.110.0	—	3.7.0E	—
1570 version ID 02 (V02)	AIR-AP1572EAC-B-K9	8.0.135.0	—	—	—
	AIR-AP1572EC1-B-K9	8.0.135.0	—	—	—
	AIR-AP1572EC2-B-K9	8.0.135.0	—	—	—
	AIR-AP1572IC1-B-K9	8.0.135.0	—	—	—
	AIR-AP1572IC2-B-K9	8.0.135.0	—	—	—
IW3700	IW3702-2E-UXXK9	8.0.120.0	—	—	—
	IW3702-4E-UXXK9	8.0.120.0	—	—	—
	IW3702-2E-B-K9	8.2.110.0	—	—	—
	IW3702-4E-B-K9	8.2.110.0	—	—	—
	IW3702-2E-M-K9	8.3.102.0	—	—	—
	IW3702-4E-M-K9	8.3.102.0	—	—	—
	IW3702-2E-R-K9	8.3.102.0	—	—	—
	IW3702-4E-R-K9	8.3.102.0	—	—	—
	IW3702-2E-Q-K9	8.3.102.0	—	—	—
	IW3702-4E-Q-K9	8.3.102.0	—	—	—
	IW3702-2E-S-K9	8.3.102.0	—	—	—
	IW3702-4E-S-K9	8.3.102.0	—	—	—

1. These access points are supported in the separate 4.1.19x.x mesh software release or with release 5.2 or later releases. These access points are not supported in the 4.2, 5.0, or 5.1 Releases.
2. The Cisco Aironet 1530 Series APs are supported operating only in Local mode; these APs in mesh mode are not supported.
3. The Cisco Aironet 1550 Series APs with 64-MB memory are not supported from Release 8.4.
4. y—Country DOCSIS Compliance, see ordering guide for details.

Related Information

- See the relevant release notes before you perform any software upgrade:
<https://www.cisco.com/c/en/us/support/wireless/wireless-lan-controller-software/products-release-notes-list.html>.
- Product Approval Status:
https://prdapp.cloudapps.cisco.com/cse/prdapp/jsp/externalsearch.do?action=externalsearch&page=EXTERNAL_SEARCH
- Wireless LAN Compliance Lookup:
<https://www.cisco.com/c/dam/assets/prod/wireless/wireless-compliance-tool/index.html>

Supported Cisco WLC Platforms in Software Releases

Table 3 lists the Cisco WLC software releases in which the support started and ended, as applicable, for various Cisco WLC hardware platforms.

Table 3 Cisco WLC Platform Support in Software Releases

Cisco WLC Platform	First Support	Last Support
2100	4.2.x	7.x
2504	7.0.x	8.5
3504	8.5	—
4400	4.2.x	7.x
5508	6.0.x	8.5
5520	8.1.x	—
7510	7.0.x	8.5
8510	7.3.x	8.5
8540	8.1.x	—
Virtual Controller (vWLC)	7.3.x	—
WiSM	4.2.x	7.x
WiSM2 (1 DP)	7.0.x	8.5
WiSM2 (2 DP)	7.2.x	8.5
SRE	7.0.x	—

For information about supported hardware for Cisco Converged Access Solution, see the “Supported Converged Access Solution Hardware” section on page 87

Cisco Prime Infrastructure Compatibility Matrix

This section contains the following topics:

- [Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix, page 15](#)
- [Cisco Prime Infrastructure and Cisco Converged Access Solution Compatibility Matrix, page 54](#)

Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix

[Table 4](#) lists the Cisco WLC releases, Cisco Mobility Service Engine (MSE) releases, and Identity Services Engine (ISE) versions that are compatible with the Cisco Prime Infrastructure releases.

For information about wireless device support in Cisco Prime Infrastructure, see the following URL: <https://www.cisco.com/c/en/us/support/cloud-systems-management/prime-infrastructure/products-device-support-tables-list.html>

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.3	8.6.101.0	10.4.x	10.4.x	10.4.x	2.3	
	8.5.110.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹	2.2	
	8.5.105.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹	2.2	
	8.5.103.0	8.0.130.0	8.0.130.0	8.0.130.0	2.1	
	8.4.100.0	8.0.120.7	8.0.120.7	8.0.120.7	2.0	
	8.3.133.0	8.0.120.0	8.0.120.0	8.0.120.0	2.0	
	8.3.132.0	8.0.110.0		8.0.110.0	1.4	
	8.3.130.0	8.0.100.0		8.0.100.0	1.3	
	8.3.12x.0	7.6.132.0		7.6.132.0		
	8.3.112.0	7.6.120.0		7.6.120.0		
	8.3.102.0	7.6.100.0		7.6.100.0		
	8.2.166.0	7.5.102.101		7.5.102.101		
	8.2.164.0	7.4.121.0		7.4.121.0		
	8.2.161.0	7.4.110.0		7.4.110.0		
	8.2.160.0	7.4.100.0		7.4.100.0		
	8.2.151.0	7.3.101.0		7.3.101.0		
	8.2.141.0	7.2.110.0		7.2.110.0		
	8.2.130.0	7.2.103.0		7.2.103.0		
	8.2.121.0	7.0.240.0				
	8.2.111.0	7.0.230.0				
	8.2.110.0	7.0.220.0				
	8.2.100.0	7.0.201.204				
	8.1.131.0	7.0.112.0				
	8.1.122.0	7.0.105.0				
	8.1.111.0					
	8.1.102.0					
	8.0.152.0					
	8.0.150.0					
	8.0.140.0					
	8.0.13x.0					
	8.0.121.0					
	8.0.120.0					
	8.0.115.0					
8.0.110.0						
8.0.100.0						

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.2.1	8.5.110.0	10.4.x	10.4.x	10.4.x	2.2	**The latest Cisco Identity Services Engine (ISE) Patch Version works.
	8.5.105.0	10.3.x ³	10.3.x	10.3.x	2.1 ²	
	8.5.103.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.4.100.0	10.2.2 ⁵	10.2.2 ⁵	10.2.2 ⁵	2.0 ²	
	8.3.133.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹	1.4 ^{**2}	
	8.3.132.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹	1.3 ^{**}	
	8.3.130.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.3.12x.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.3.112.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.3.102.0	8.0.110.0		8.0.110.0		
	8.2.166.0	8.0.100.0		8.0.100.0		
	8.2.164.0	7.6.132.0		7.6.132.0		
	8.2.161.0	7.6.120.0		7.6.120.0		
	8.2.160.0	7.6.100.0		7.6.100.0		
	8.2.151.0	7.5.102.101		7.5.102.101		
	8.2.141.0	7.4.121.0		7.4.121.0		
	8.2.130.0	7.4.110.0		7.4.110.0		
	8.2.121.0	7.4.100.0		7.4.100.0		
	8.2.111.0	7.3.101.0		7.3.101.0		
	8.2.110.0	7.2.110.0		7.2.110.0		
	8.2.100.0	7.2.103.0		7.2.103.0		
	8.1.131.0	7.0.240.0				
	8.1.122.0	7.0.230.0				
	8.1.111.0	7.0.220.0				
	8.1.102.0	7.0.201.204				
	8.0.152.0	7.0.112.0				
	8.0.150.0	7.0.105.0				
	8.0.140.0					
	8.0.13x.0					
	8.0.121.0					
	8.0.120.0					
	8.0.115.0					
	8.0.110.0					
	8.0.100.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.2	8.5.110.0	10.4.x	10.4.x	10.4.x	2.2	**The latest Cisco Identity Services Engine (ISE) Patch Version works.
	8.5.105.0	10.3.x ³	10.3.x	10.3.x	2.1 ²	
	8.5.103.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.4.100.0	10.2.2 ⁵	10.2.2 ⁵	10.2.2 ⁵	2.0 ²	
	8.3.133.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹	1.4 ^{**2}	
	8.3.132.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹	1.3 ^{**}	
	8.3.130.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.3.12x.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.3.112.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.3.102.0	8.0.110.0		8.0.110.0		
	8.2.166.0	8.0.100.0		8.0.100.0		
	8.2.164.0	7.6.132.0		7.6.132.0		
	8.2.161.0	7.6.120.0		7.6.120.0		
	8.2.160.0	7.6.100.0		7.6.100.0		
	8.2.151.0	7.5.102.101		7.5.102.101		
	8.2.141.0	7.4.121.0		7.4.121.0		
	8.2.130.0	7.4.110.0		7.4.110.0		
	8.2.121.0	7.4.100.0		7.4.100.0		
	8.2.111.0	7.3.101.0		7.3.101.0		
	8.2.110.0	7.2.110.0		7.2.110.0		
	8.2.100.0	7.2.103.0		7.2.103.0		
	8.1.131.0	7.0.240.0				
	8.1.122.0	7.0.230.0				
	8.1.111.0	7.0.220.0				
	8.1.102.0	7.0.201.204				
	8.0.152.0	7.0.112.0				
	8.0.150.0	7.0.105.0				
	8.0.140.0					
	8.0.13x.0					
	8.0.121.0					
	8.0.120.0					
	8.0.115.0					
	8.0.110.0					
8.0.100.0						

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.1.7	8.4.100.0	10.4.x	10.4.x	10.4.x	2.2	**The latest Cisco Identity Services Engine (ISE) Patch Version works.
	8.3.133.0	10.3.x ³	10.3.x	10.3.x	2.1 ²	
	8.3.132.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴	2.0 ²	
	8.3.130.0	10.2.2 ⁵	10.2.2 ⁵	10.2.2 ⁵	1.4 ^{**2}	
	8.3.12x.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹	1.3 ^{**}	
	8.3.111.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹		
	8.3.112.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.3.102.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.2.166.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.2.164.0	8.0.110.0		8.0.110.0		
	8.2.161.0	8.0.100.0		8.0.100.0		
	8.2.160.0	7.6.132.0		7.6.132.0		
	8.2.151.0	7.6.120.0		7.6.120.0		
	8.2.141.0	7.6.100.0		7.6.100.0		
	8.2.130.0	7.5.102.101		7.5.102.101		
	8.2.121.0	7.4.121.0		7.4.121.0		
	8.2.111.0	7.4.110.0		7.4.110.0		
	8.2.110.0	7.4.100.0		7.4.100.0		
	8.2.100.0	7.3.101.0		7.3.101.0		
	8.1.131.0	7.2.110.0		7.2.110.0		
	8.1.122.0	7.2.103.0		7.2.103.0		
	8.1.111.0	7.0.240.0				
	8.1.102.0	7.0.230.0				
	8.0.152.0	7.0.220.0				
	8.0.150.0	7.0.201.204				
	8.0.140.0	7.0.112.0				
	8.0.13x.0	7.0.105.0				
	8.0.121.0					
	8.0.120.0					
	8.0.115.0					
	8.0.110.0					
	8.0.100.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.1.6	8.4.100.0	10.4.x	10.4.x	10.4.x	2.2	**The latest Cisco Identity Services Engine (ISE) Patch Version works.
	8.3.133.0	10.3.x ³	10.3.x	10.3.x	2.1 ²	
	8.3.132.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴	2.0 ²	
	8.3.130.0	10.2.2 ⁵	10.2.2 ⁵	10.2.2 ⁵	1.4 ^{**2}	
	8.3.12x.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹	1.3 ^{**}	
	8.3.112.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹		
	8.3.111.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.3.102.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.2.166.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.2.164.0	8.0.110.0		8.0.110.0		
	8.2.161.0	8.0.100.0		8.0.100.0		
	8.2.160.0	7.6.132.0		7.6.132.0		
	8.2.151.0	7.6.120.0		7.6.120.0		
	8.2.141.0	7.6.100.0		7.6.100.0		
	8.2.130.0	7.5.102.101		7.5.102.101		
	8.2.121.0	7.4.121.0		7.4.121.0		
	8.2.111.0	7.4.110.0		7.4.110.0		
	8.2.110.0	7.4.100.0		7.4.100.0		
	8.2.100.0	7.3.101.0		7.3.101.0		
	8.1.131.0	7.2.110.0		7.2.110.0		
	8.1.122.0	7.2.103.0		7.2.103.0		
	8.1.111.0	7.0.240.0				
	8.1.102.0	7.0.230.0				
	8.0.152.0	7.0.220.0				
	8.0.150.0	7.0.201.204				
	8.0.140.0	7.0.112.0				
	8.0.13x.0	7.0.105.0				
	8.0.121.0					
	8.0.120.0					
	8.0.115.0					
	8.0.110.0					
	8.0.100.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.1.5	8.4.100.0	10.4.x	10.4.x	10.4.x	2.1 ²	**The latest Cisco Identity Services Engine (ISE) Patch Version works.
	8.3.133.0	10.3.x ³	10.3.x	10.3.x	2.0 ²	
	8.3.132.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.3.130.0	10.2.2 ⁵	10.2.2 ⁵	10.2.2 ⁵	1.4 ^{**2}	
	8.3.12x.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹	1.3 ^{**}	
	8.3.112.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹		
	8.3.102.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.2.166.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.2.164.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.2.161.0	8.0.110.0		8.0.110.0		
	8.2.160.0	8.0.100.0		8.0.100.0		
	8.2.151.0	7.6.132.0		7.6.132.0		
	8.2.141.0	7.6.120.0		7.6.120.0		
	8.2.130.0	7.6.100.0		7.6.100.0		
	8.2.121.0	7.5.102.101		7.5.102.101		
	8.2.111.0	7.4.121.0		7.4.121.0		
	8.2.110.0	7.4.110.0		7.4.110.0		
	8.2.100.0	7.4.100.0		7.4.100.0		
	8.1.131.0	7.3.101.0		7.3.101.0		
	8.1.122.0	7.2.110.0		7.2.110.0		
	8.1.111.0	7.2.103.0		7.2.103.0		
	8.1.102.0	7.0.240.0				
	8.0.152.0	7.0.230.0				
	8.0.150.0	7.0.220.0				
	8.0.140.0	7.0.201.204				
	8.0.13x.0	7.0.112.0				
	8.0.121.0	7.0.105.0				
	8.0.120.0					
	8.0.115.0					
	8.0.110.0					
	8.0.100.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.1.4	8.3.133.0	10.4.x	10.4.x	10.4.x	2.1 ²	**For Cisco Prime Infrastructure 3.1.4 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation.
	8.3.132.0	10.3.x ³	10.3.x	10.3.x	2.0 ²	
	8.3.130.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴	1.4 ^{**2}	
	8.3.12x.0	10.2.2 ⁵	10.2.2 ⁵	10.2.2 ⁵	1.3	
	8.3.112.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹		
	8.3.102.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹		
	8.2.166.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.2.164.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.2.161.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.2.160.0	8.0.110.0		8.0.110.0		
	8.2.151.0	8.0.100.0		8.0.100.0		
	8.2.141.0	7.6.132.0		7.6.132.0		
	8.2.130.0	7.6.120.0		7.6.120.0		
	8.2.121.0	7.6.100.0		7.6.100.0		
	8.2.111.0	7.5.102.101		7.5.102.101		
	8.2.110.0	7.4.121.0		7.4.121.0		
	8.2.100.0	7.4.110.0		7.4.110.0		
	8.1.131.0	7.4.100.0		7.4.100.0		
	8.1.122.0	7.3.101.0		7.3.101.0		
	8.1.111.0	7.2.110.0		7.2.110.0		
	8.1.102.0	7.2.103.0		7.2.103.0		
	8.0.152.0	7.0.240.0				
	8.0.150.0	7.0.230.0				
	8.0.140.0	7.0.220.0				
	8.0.13x.0	7.0.201.204				
	8.0.121.0	7.0.112.0				
	8.0.120.0	7.0.105.0				
	8.0.115.0					
	8.0.110.0					
	8.0.100.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.1.3	8.3.133.0	10.4.x	10.4.x	10.4.x	2.0 ²	*Cisco Aironet 1810 Series OEAPs are not supported. **For Cisco Prime Infrastructure 3.1.3 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation.
	8.3.132.0	10.3.x ³	10.3.x	10.3.x	1.4**2	
	8.3.130.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴	1.3	
	8.3.12x.0	10.2.2 ⁵	10.2.2 ⁵	10.2.2 ⁵		
	8.3.112.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹		
	8.3.102.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹		
	8.2.166.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.2.164.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.2.161.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.2.160.0	8.0.110.0		8.0.110.0		
	8.2.151.0	8.0.100.0		8.0.100.0		
	8.2.141.0	7.6.132.0		7.6.132.0		
	8.2.130.0	7.6.120.0		7.6.120.0		
	8.2.121.0	7.6.100.0		7.6.100.0		
	8.2.111.0	7.5.102.101		7.5.102.101		
	8.2.110.0	7.4.121.0		7.4.121.0		
	8.2.100.0	7.4.110.0		7.4.110.0		
	8.1.131.0	7.4.100.0		7.4.100.0		
	8.1.122.0	7.3.101.0		7.3.101.0		
	8.1.111.0	7.2.110.0		7.2.110.0		
	8.1.102.0	7.2.103.0		7.2.103.0		
	8.0.152.0	7.0.240.0				
	8.0.150.0	7.0.230.0				
	8.0.140.0	7.0.220.0				
	8.0.13x.0	7.0.201.204				
	8.0.121.0	7.0.112.0				
	8.0.120.0	7.0.105.0				
	8.0.115.0					
	8.0.110.0					
	8.0.100.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.1.1	8.3.13x.0 8.3.12x.0 8.3.112.0*** 8.3.102.0*** 8.2.16x.0 8.2.151.0 8.2.141.0 8.2.130.0 8.2.121.0 8.2.111.0 8.2.110.0 8.2.100.0 8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.115.0 8.0.110.0 8.0.100.0	10.4.x 10.3.x ³ 10.2.3 ⁴ 10.2.2 ⁵ 8.0.150.x ¹ 8.0.140.x ¹ 8.0.130.0 8.0.120.7 8.0.120.0 8.0.110.0 8.0.100.0 7.6.132.0 7.6.120.0 7.6.100.0 7.5.102.101 7.4.121.0 7.4.110.0 7.4.100.0 7.3.101.0 7.2.110.0 7.2.103.0 7.0.240.0 7.0.230.0 7.0.220.0 7.0.201.204 7.0.112.0 7.0.105.0	10.4.x 10.3.x 10.2.3 ⁴ 10.2.2 ⁵ 8.0.150.x ¹ 8.0.140.x ¹ 8.0.130.0 8.0.120.7 8.0.120.0	10.4.x 10.3.x 10.2.3 ⁴ 10.2.2 ⁵ 8.0.150.x ¹ 8.0.140.x ¹ 8.0.130.0 8.0.120.7 8.0.120.0 8.0.110.0 8.0.100.0 7.6.132.0 7.6.120.0 7.6.100.0 7.5.102.101 7.4.121.0 7.4.110.0 7.4.100.0 7.3.101.0 7.2.110.0 7.2.103.0	2.0 ² 1.4**2 1.3	**For Cisco Prime Infrastructure 3.1.1 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation. ***No new features of Cisco WLC 8.3.x are supported with Cisco Prime Infrastructure Release 3.1.1.

Table 4 *Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)*

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.1	8.2.16x.0	10.4.x	10.4.x	10.4.x	2.0 ²	**For Cisco Prime Infrastructure 3.1 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation.
	8.2.151.0	10.3.x ³	10.3.x	10.3.x	1.4 ^{**2}	
	8.2.141.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.2.130.0	10.2.2 ⁵	10.2.2 ⁵	10.2.2 ⁵	1.3	
	8.2.121.0	8.0.150.x ¹	8.0.150.x ¹	8.0.130.0		
	8.2.111.0	8.0.140.x ¹	8.0.140.x ¹	8.0.120.7		
	8.2.110.0	8.0.130.0	8.0.130.0	8.0.120.0		
	8.2.100.0	8.0.120.7	8.0.120.7	8.0.110.0		
	8.1.131.0	8.0.120.0	8.0.120.0	8.0.100.0		
	8.1.122.0	8.0.110.0		7.6.132.0		
	8.1.111.0	8.0.100.0		7.6.120.0		
	8.1.102.0	7.6.132.0		7.6.100.0		
	8.0.15x.0	7.6.120.0		7.5.102.101		
	8.0.140.0	7.6.100.0		7.4.121.0		
	8.0.13x.0	7.5.102.101		7.4.110.0		
	8.0.121.0	7.4.121.0		7.4.100.0		
	8.0.120.0	7.4.110.0		7.3.101.0		
	8.0.115.0	7.4.100.0		7.2.110.0		
	8.0.110.0	7.3.101.0		7.2.103.0		
	8.0.100.0	7.2.110.0				
		7.2.103.0				
		7.0.240.0				
		7.0.230.0				
		7.0.220.0				
		7.0.201.204				
		7.0.112.0				
		7.0.105.0				

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.0 Technology Package	8.2.16x.0	10.4.x	10.4.x	10.4.x	1.4**2	**For Cisco Prime Infrastructure 3.0 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation.
	8.2.151.0	10.3.x ³	10.3.x	10.3.x	1.3	
	8.2.141.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.2.130.0	10.2.2 ^{5,6}	10.2.2 ^{5,6}	10.2.2 ^{5,6}		
	8.2.121.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.2.111.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.2.110.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.2.100.0	8.0.110.0		8.0.110.0		
	8.1.131.0	8.0.100.0		8.0.100.0		
	8.1.122.0	7.6.132.0		7.6.132.0		
	8.1.111.0	7.6.120.0		7.6.120.0		
	8.1.102.0	7.6.100.0		7.6.100.0		
	8.0.15x.0	7.5.102.101		7.5.102.101		
	8.0.140.0	7.4.121.0		7.4.121.0		
	8.0.13x.0	7.4.110.0		7.4.110.0		
	8.0.121.0	7.4.100.0		7.4.100.0		
	8.0.120.0	7.3.101.0		7.3.101.0		
	8.0.115.0	7.2.110.0		7.2.110.0		
	8.0.110.0	7.2.103.0		7.2.103.0		
	8.0.100.0	7.0.240.0				
	7.0.230.0					
	7.0.220.0					
	7.0.201.204					
	7.0.112.0					
	7.0.105.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
	7.6.130.0					
	7.6.120.0					
	7.6.110.0					
	7.6.100.0					
	7.5.102.0					
	7.4.150.0					
	7.4.140.0					
	7.4.130.0					
	7.4.121.0					
	7.4.110.0					
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.0.3	8.1.131.0*	10.4.x	10.4.x	10.4.x	1.4**2	*No new features of Cisco WLC 8.1.131.0 are supported with Cisco Prime Infrastructure Release 3.0, but the Mobility Express features are supported. **For Cisco Prime Infrastructure 3.0 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation.
	8.1.122.0	10.3.x ³	10.3.x	10.3.x	1.3	
	8.1.111.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.1.102.0	10.2.2 ^{5,6}	10.2.2 ^{5,6}	10.2.2 ^{5,6}		
	8.0.15x.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹		
	8.0.140.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹		
	8.0.13x.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.0.121.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.0.120.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.0.115.0	8.0.110.0		8.0.110.0		
	8.0.110.0	8.0.100.0		8.0.100.0		
	8.0.100.0	7.6.132.0		7.6.132.0		
	7.6.130.0	7.6.120.0		7.6.120.0		
	7.6.120.0	7.6.100.0		7.6.100.0		
	7.6.110.0	7.5.102.101		7.5.102.101		
	7.6.100.0	7.4.121.0		7.4.121.0		
	7.5.102.0	7.4.110.0		7.4.110.0		
	7.4.150.0	7.4.100.0		7.4.100.0		
	7.4.140.0	7.3.101.0		7.3.101.0		
	7.4.130.0	7.2.110.0		7.2.110.0		
	7.4.121.0	7.2.103.0		7.2.103.0		
	7.4.110.0	7.0.240.0				
	7.4.100.60	7.0.230.0				
	7.4.100.0	7.0.220.0				
	7.3.112.0	7.0.201.204				
	7.3.101.0	7.0.112.0				
	7.2.115.2	7.0.105.0				
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.0.2	8.1.131.0*	10.4.x	10.4.x	10.4.x	1.4**2	<p>*No new features of Cisco WLC 8.1.131.0 are supported with Cisco Prime Infrastructure Release 3.0, but the Mobility Express features are supported.</p> <p>**For Cisco Prime Infrastructure 3.0 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation.</p>
	8.1.122.0	10.3.x ³	10.3.x	10.3.x	1.3	
	8.1.111.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.1.102.0	10.2.2 ^{5,6}	10.2.2 ^{5,6}	10.2.2 ^{5,6}		
	8.0.15x.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.0.140.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.0.13x.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.0.121.0	8.0.110.0		8.0.110.0		
	8.0.120.0	8.0.100.0		8.0.100.0		
	8.0.115.0	7.6.132.0		7.6.132.0		
	8.0.110.0	7.6.120.0		7.6.120.0		
	8.0.100.0	7.6.100.0		7.6.100.0		
	7.6.130.0	7.5.102.101		7.5.102.101		
	7.6.120.0	7.4.121.0		7.4.121.0		
	7.6.110.0	7.4.110.0		7.4.110.0		
	7.6.100.0	7.4.100.0		7.4.100.0		
	7.5.102.0	7.3.101.0		7.3.101.0		
	7.4.150.0	7.2.110.0		7.2.110.0		
	7.4.140.0	7.2.103.0		7.2.103.0		
	7.4.130.0	7.0.240.0				
	7.4.121.0	7.0.230.0				
	7.4.110.0	7.0.220.0				
	7.4.100.60	7.0.201.204				
	7.4.100.0	7.0.112.0				
	7.3.112.0	7.0.105.0				
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.0.1	8.1.131.0*	10.4.x	10.4.x	10.4.x	1.4**2	*No new features of Cisco WLC 8.1.131.0 are supported with Cisco Prime Infrastructure Release 3.0, but the Mobility Express features are supported. **For Cisco Prime Infrastructure 3.0 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation.
	8.1.122.0	10.3.x ³	10.3.x	10.3.x	1.3	
	8.1.111.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.1.102.0	10.2.2 ^{5,6}	10.2.2 ^{5,6}	10.2.2 ^{5,6}		
	8.0.15x.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.0.140.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.0.13x.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.0.121.0	8.0.110.0		8.0.110.0		
	8.0.120.0	8.0.100.0		8.0.100.0		
	8.0.115.0	7.6.132.0		7.6.132.0		
	8.0.110.0	7.6.120.0		7.6.120.0		
	8.0.100.0	7.6.100.0		7.6.100.0		
	7.6.130.0	7.5.102.101		7.5.102.101		
	7.6.120.0	7.4.121.0		7.4.121.0		
	7.6.110.0	7.4.110.0		7.4.110.0		
	7.6.100.0	7.4.100.0		7.4.100.0		
	7.5.102.0	7.3.101.0		7.3.101.0		
	7.4.150.0	7.2.110.0		7.2.110.0		
	7.4.140.0	7.2.103.0		7.2.103.0		
	7.4.130.0	7.0.240.0				
	7.4.121.0	7.0.230.0				
	7.4.110.0	7.0.220.0				
	7.4.100.60	7.0.201.204				
	7.4.100.0	7.0.112.0				
	7.3.112.0	7.0.105.0				
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
3.0	8.1.131.0 8.1.122.0* 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.115.0 8.0.110.0 8.0.100.0 7.6.130.0 7.6.120.0 7.6.110.0 7.6.100.0 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.115.2 7.2.111.3 7.2.110.0 7.2.103.0 7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0	10.4.x 10.3.x ³ 10.2.3 ⁴ 10.2.2 ^{5,6} 8.0.130.0 8.0.120.7 8.0.120.0 8.0.110.0 8.0.100.0 7.6.132.0 7.6.120.0 7.6.100.0 7.5.102.101 7.4.121.0 7.4.110.0 7.4.100.0 7.3.101.0 7.2.110.0 7.2.103.0 7.0.240.0 7.0.230.0 7.0.220.0 7.0.201.204 7.0.112.0 7.0.105.0	10.4.x 10.3.x 10.2.3 ⁴ 10.2.2 ^{5,6} 8.0.130.0 8.0.120.7 8.0.120.0	10.4.x 10.3.x 10.2.3 ⁴ 10.2.2 ^{5,6} 8.0.130.0 8.0.120.7 8.0.120.0 8.0.110.0 8.0.100.0 7.6.132.0 7.6.120.0 7.6.100.0 7.5.102.101 7.4.121.0 7.4.110.0 7.4.100.0 7.3.101.0 7.2.110.0 7.2.103.0	1.4**2 1.3	*No new features of Cisco WLC 8.1.122.0 or later including Mobility Express is supported with PI Release 3.0. **For PI 3.0 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation.

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
2.2.3	8.1.131.0	10.4.x	10.4.x	10.4.x	1.4**2	**For PI 2.2.3 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE 1.4.0 installation. Cisco Prime Infrastructure 2.2.2 allows you to manage Cisco WLC 8.1.x; however, features introduced in Cisco WLC 8.1.x are not supported.
	8.1.122.0	10.3.x ³	10.3.x	10.3.x	1.3	
	8.1.111.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.1.102.0	10.2.2 ^{5,6}	10.2.2 ^{5,6}	10.2.2 ^{5,6}		
	8.0.15x.0	8.0.150.x ¹	8.0.150.x ¹	8.0.150.x ¹		
	8.0.140.0	8.0.140.x ¹	8.0.140.x ¹	8.0.140.x ¹		
	8.0.13x.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.0.121.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.0.120.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.0.115.0	8.0.110.0		8.0.110.0		
	8.0.110.0	8.0.100.0		8.0.100.0		
	8.0.100.0	7.6.132.0		7.6.132.0		
	7.6.130.0	7.6.120.0		7.6.120.0		
	7.6.120.0	7.6.100.0		7.6.100.0		
	7.6.110.0	7.5.102.101		7.5.102.101		
	7.6.100.0	7.4.121.0		7.4.121.0		
	7.5.102.0	7.4.110.0		7.4.110.0		
	7.4.150.0	7.4.100.0		7.4.100.0		
	7.4.140.0	7.3.101.0		7.3.101.0		
	7.4.130.0	7.2.110.0		7.2.110.0		
	7.4.121.0	7.2.103.0		7.2.103.0		
	7.4.110.0	7.0.240.0				
	7.4.100.60	7.0.230.0				
	7.4.100.0	7.0.220.0				
	7.3.112.0	7.0.201.204				
	7.3.101.0	7.0.112.0				
	7.2.115.2	7.0.105.0				
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
2.2.2	8.1.131.0	10.4.x	10.4.x	10.4.x	1.3	Cisco Prime Infrastructure 2.2.2 allows you to manage Cisco WLC 8.1.x; however, features introduced in Cisco WLC 8.1.x are not supported.
	8.1.122.0	10.3.x ³	10.3.x	10.3.x		
	8.1.111.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴		
	8.1.102.0	10.2.2 ^{5,6}	10.2.2 ^{5,6}	10.2.2 ^{5,6}		
	8.0.15x.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.0.140.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.0.13x.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.0.121.0	8.0.110.0		8.0.110.0		
	8.0.120.0	8.0.100.0		8.0.100.0		
	8.0.115.0	7.6.132.0		7.6.132.0		
	8.0.110.0	7.6.120.0		7.6.120.0		
	8.0.100.0	7.6.100.0		7.6.100.0		
	7.6.130.0	7.5.102.101		7.5.102.101		
	7.6.120.0	7.4.121.0		7.4.121.0		
	7.6.110.0	7.4.110.0		7.4.110.0		
	7.6.100.0	7.4.100.0		7.4.100.0		
	7.5.102.0	7.3.101.0		7.3.101.0		
	7.4.150.0	7.2.110.0		7.2.110.0		
	7.4.140.0	7.2.103.0		7.2.103.0		
	7.4.130.0	7.0.240.0				
	7.4.121.0	7.0.230.0				
	7.4.110.0	7.0.220.0				
	7.4.100.60	7.0.201.204				
	7.4.100.0	7.0.112.0				
	7.3.112.0	7.0.105.0				
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
2.2.1	8.1.131.0	10.4.x	10.4.x	10.4.x	1.3	Cisco Prime Infrastructure 2.2.1 allows you to manage Cisco WLC 8.1.x; however, features introduced in Cisco WLC 8.1.x are not supported.
	8.1.122.0	10.3.x ³	10.3.x	10.3.x		
	8.1.111.0	10.2.3 ⁴	10.2.3 ⁵	10.2.3 ⁵		
	8.1.102.0	10.2.2 ^{5,6}	10.2.2 ^{5,6}	10.2.2 ^{5,6}		
	8.0.15x.0	8.0.130.0	8.0.130.0	8.0.130.0		
	8.0.140.0	8.0.120.7	8.0.120.7	8.0.120.7		
	8.0.13x.0	8.0.120.0	8.0.120.0	8.0.120.0		
	8.0.121.0	8.0.110.0		8.0.110.0		
	8.0.115.0	8.0.100.0		8.0.100.0		
	8.0.110.0	7.6.132.0		7.6.132.0		
	8.0.100.0	7.6.120.0		7.6.120.0		
	7.6.130.0	7.6.100.0		7.6.100.0		
	7.6.120.0	7.5.102.101		7.5.102.101		
	7.6.110.0	7.4.121.0		7.4.121.0		
	7.6.100.0	7.4.110.0		7.4.110.0		
	7.5.102.0	7.4.100.0		7.4.100.0		
	7.4.150.0	7.3.101.0		7.3.101.0		
	7.4.140.0	7.2.110.0		7.2.110.0		
	7.4.130.0	7.2.103.0		7.2.103.0		
	7.4.121.0	7.0.240.0				
	7.4.110.0	7.0.230.0				
	7.4.100.60	7.0.220.0				
	7.4.100.0	7.0.201.204				
	7.3.112.0	7.0.112.0				
	7.3.101.0	7.0.105.0				
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
2.2	8.0.15x.0	10.4.x	10.4.x	10.4.x	1.3	<p>* Prime Infrastructure 2.2 allows you to manage Cisco WLC Release 8.0.110.0. For the supported WLC features, see the “supported features” section of the Prime Infrastructure 2.2 Release Notes at the following URL. https://www.cisco.com/c/en/us/td/docs/net_mgmt/prime/infrastructure/2-2/release/notes/cpi_rn.html</p> <p>** Prime Infrastructure 2.2 allows you to manage Cisco MSE Release 8.0.110.0. For more information on MSE model and platform details, see Table 7.</p> <p>*** Prime Infrastructure supports ISE 1.2 in non-FIPS mode.</p> <p>Note For version compatibility for MSE 8.0 wIPS with PI 2.2, see Table 7.</p>
	8.0.140.0	10.3.x ³	10.3.x	10.3.x	1.2***	
	8.0.13x.0	10.2.3 ⁴	10.2.3 ⁴	10.2.3 ⁴	1.1	
	8.0.121.0	10.2.2 ^{5,6}	10.2.2 ^{5,6}	10.2.2 ^{5,6}	1.0	
	8.0.120.0	8.0.110.0**	8.0.130.0	8.0.110.0		
	8.0.115.0	8.0.100.0	8.0.120.7	8.0.100.0		
	8.0.110.0	7.6.132.0	8.0.120.0	7.6.132.0		
	8.0.100.0	7.6.120.0		7.6.120.0		
	7.6.130.0	7.6.100.0		7.6.100.0		
	7.6.120.0	7.5.102.101		7.5.102.101		
	7.6.110.0	7.4.121.0		7.4.121.0		
	7.6.100.0	7.4.110.0		7.4.110.0		
	7.5.102.0	7.4.100.0		7.4.100.0		
	7.4.150.0	7.3.101.0		7.3.101.0		
	7.4.140.0	7.2.110.0		7.2.110.0		
	7.4.130.0	7.2.103.0		7.2.103.0		
	7.4.121.0	7.0.240.0				
	7.4.110.0	7.0.230.0				
	7.4.100.60	7.0.220.0				
	7.4.100.0	7.0.201.204				
	7.3.112.0	7.0.112.0				
	7.3.101.0	7.0.105.0				
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
7.0.220.0						
7.0.116.0						
7.0.98.218						
7.0.98.0						

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
2.1.2***	8.0.15x.0	8.0.110.0**	8.0.130.0	8.0.110.0	1.0	<p>* Prime Infrastructure 2.1.2 allows you to manage Cisco WLC Releases 7.5.102.0, 7.6.x, and 8.0.x with the features of Cisco WLC 7.4.130.0 and earlier releases. Cisco Prime Infrastructure 2.1.2 does not support any features that are introduced in Cisco WLC Releases 7.5.102.0 and 7.6.x except the new access point platforms and the new mobility feature.</p> <p>** Prime Infrastructure 2.1.2 allows you to manage Cisco MSE Releases 7.5.102.101, 7.6.100.0, 7.6.120.0, 8.0.100.0, and 8.0.110.0 with feature compatibility of Cisco MSE Release 7.4.121.0. Prime Infrastructure 2.1.2 does not support any new features introduced in Cisco MSE Releases 7.5.102.101 and 7.6.120.0. For information on MSE model and platform details, see Table 7.</p> <p>*** Cisco AP701E is not supported by Prime Infrastructure 2.1.2.</p>
	8.0.140.0*	8.0.100.0**	8.0.120.7	8.0.100.0	1.1	
	8.0.13x.0*	7.6.132.0**	8.0.120.0	7.6.132.0	1.2	
	8.0.121.0*	7.6.120.0**		7.6.120.0		
	8.0.120.0*	7.6.100.0**		7.6.100.0		
	8.0.115.0*	7.5.102.101**		7.5.102.101		
	8.0.110.0*	7.4.121.0		7.4.121.0		
	8.0.100.0*	7.4.110.0		7.4.110.0		
	7.6.130.0*	7.4.100.0		7.4.100.0		
	7.6.120.0*	7.3.101.0		7.3.101.0		
	7.6.110.0*	7.2.110.0		7.2.110.0		
	7.6.100.0*	7.2.103.0		7.2.103.0		
	7.5.102.0*	7.0.240.0				
	7.4.150.0	7.0.230.0				
	7.4.140.0	7.0.220.0				
	7.4.130.0	7.0.201.204				
	7.4.121.0	7.0.112.0				
	7.4.110.0	7.0.105.0				
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
7.1.91.0						
7.0.220.0						
7.0.116.0						
7.0.98.218						
7.0.98.0						

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
2.1.1***	8.0.15x.0	8.0.110.0**	8.0.130.0	8.0.110.0	1.0	<p>* Prime Infrastructure 2.1.1 allows you to manage Cisco WLC Releases 7.5.102.0, 7.6.100.0, 7.6.110.0, 7.6.120.0, and 8.0.100.0 with the features of Cisco WLC 7.4.130.0 and earlier releases. Cisco Prime Infrastructure 2.1.1 does not support any features that are introduced in Cisco WLC Releases 7.5.102.0 and 7.6.x except the new access point platforms and the new mobility feature.</p> <p>** Prime Infrastructure 2.1.1 allows you to manage Cisco MSE Releases 7.5.102.101, 7.6.100.0, 7.6.120.0, 8.0.110.0 and 8.0.110.0 with feature compatibility of Cisco MSE Release 7.4.121.0. Prime Infrastructure 2.1.1 does not support any new features introduced in Cisco MSE Releases 7.5.102.101 and 7.6.120.0. For information on MSE model and platform details, see Table 7.</p> <p>*** Cisco AP701E is not supported by Prime Infrastructure 2.1.1. Also, Cisco Aironet 1700 Series Access Points are not supported by Prime Infrastructure until Prime Infrastructure Release 2.2.</p>
	8.0.140.0*	8.0.100.0**	8.0.120.7	8.0.100.0	1.1	
	8.0.13x.0*	7.6.132.0	8.0.120.0	7.6.132.0	1.2	
	8.0.121.0*	7.6.120.0**		7.6.120.0		
	8.0.120.0*	7.6.100.0**		7.6.100.0		
	8.0.115.0*	7.5.102.101**		7.5.102.101		
	8.0.110.0*	7.4.121.0		7.4.121.0		
	8.0.100.0*	7.4.110.0		7.4.110.0		
	7.6.130.0*	7.4.100.0		7.4.100.0		
	7.6.120.0*	7.3.101.0		7.3.101.0		
	7.6.110.0*	7.2.110.0		7.2.110.0		
	7.6.100.0*	7.2.103.0		7.2.103.0		
	7.5.102.0*	7.0.240.0				
	7.4.150.0	7.0.230.0				
	7.4.140.0	7.0.220.0				
	7.4.130.0	7.0.201.204				
	7.4.121.0	7.0.112.0				
	7.4.110.0	7.0.105.0				
	7.4.100.60					
	7.4.100.0					
	7.3.112.0					
	7.3.101.0					
	7.2.115.2					
	7.2.111.3					
	7.2.110.0					
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
2.1	7.6.120.0*	8.0.110.0**	—	8.0.110.0	1.0	<p>*Prime Infrastructure 2.1 allows you to manage Cisco WLC Releases 7.5.102.0 and 7.6.120.0 with the features of Cisco WLC 7.4.130.0 and earlier releases. Prime Infrastructure 2.1 does not support any features that are introduced in Cisco WLC Releases 7.5.102.0 and 7.6.x except the new access point platforms and the new mobility feature.</p> <p>** Prime Infrastructure 2.1 allows you to manage Cisco MSE Releases 7.5.102.101 and 7.6.120.0 with feature compatibility of Cisco MSE Release 7.4.121.0. Prime Infrastructure 2.1 does not support any new features introduced in Cisco MSE Releases 7.5.102.101 and 7.6.120.0. For information on MSE model and platform details, see Table 7.</p>
	7.5.102.0*	7.6.132.0		8.0.100.0	1.1	
	7.4.150.0	7.6.120.0**		7.6.132.0	1.2	
	7.4.140.0	7.5.102.101**		7.6.120.0		
	7.4.121.0	7.4.121.0		7.6.100.0		
	7.4.110.0	7.4.110.0		7.5.102.101		
	7.4.100.60	7.4.100.0		7.4.121.0		
	7.4.100.0	7.3.101.0		7.4.110.0		
	7.3.112.0	7.2.110.0		7.4.100.0		
	7.3.101.0	7.2.103.0		7.3.101.0		
	7.2.115.2	7.0.240.0		7.2.110.0		
	7.2.111.3	7.0.230.0		7.2.103.0		
	7.2.110.0	7.0.220.0				
	7.2.103.0	7.0.201.204				
	7.0.252.0	7.0.112.0				
	7.0.251.2	7.0.105.0				
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
2.0	7.5.102.0*	7.5.102.101**	—	7.5.102.101	1.0	<p>* Cisco Prime Infrastructure 2.0 enables you to manage Cisco WLC 7.5.102.0 with the features of Cisco WLC 7.4.130.0 and earlier releases. Prime Infrastructure 2.0 does not support any features that are introduced in Cisco WLC 7.5.102.0 or later releases including the new access point platforms.</p> <p>** Cisco Prime Infrastructure 2.0 enables you to manage 7.5.102.101 or later releases of Cisco MSE with features of Cisco MSE Release 7.4.121.0 and earlier releases. Prime Infrastructure 2.0 does not support any features that are introduced in Cisco MSE 7.5.102.101 or later releases. For information on MSE model and platform details, see Table 7.</p>
	7.4.150.0	7.4.121.0		7.4.121.0	1.1	
	7.4.140.0	7.4.110.0		7.4.110.0	1.2	
	7.4.130.0	7.4.100.0		7.4.100.0		
	7.4.121.0	7.3.101.0		7.3.101.0		
	7.4.110.0	7.2.110.0		7.2.110.0		
	7.4.100.60	7.2.103.0		7.2.103.0		
	7.4.100.0	7.0.240.0				
	7.3.112.0	7.0.230.0				
	7.3.101.0	7.0.220.0				
	7.2.115.2	7.0.201.204				
	7.2.111.3	7.0.112.0				
	7.2.110.0	7.0.105.0				
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
Update 2 for 1.4.0.45	7.5.102.0	7.6.100.0	—	7.6.100.0	1.0	The Update 2 for Cisco Prime Infrastructure 1.4.0.45 enables you to manage Cisco WLC 7.6.x with the features of Cisco WLC 7.5.102.0 and earlier releases. This release does not support any new features of Cisco WLC 7.6.x. However, this release supports two new AP platforms—Cisco 702w and Cisco 2700. Note For version compatibility for MSE 8.0 wIPS with Update 2 for 1.4.0.45, see Table 7 .
	7.4.150.0	7.5.102.101		7.5.102.101	1.1	
	7.4.140.0	7.4.121.0		7.4.121.0	1.2	
	7.4.130.0	7.4.110.0		7.4.110.0		
	7.4.121.0	7.4.100.0		7.4.100.0		
	7.4.110.0	7.3.101.0		7.3.101.0		
	7.4.100.60	7.2.110.0		7.2.110.0		
	7.4.100.0	7.2.103.0		7.2.103.0		
	7.3.112.0	7.0.240.0				
	7.3.101.0	7.0.230.0				
	7.2.115.2	7.0.220.0				
	7.2.111.3	7.0.201.204				
	7.2.110.0	7.0.112.0				
	7.2.103.0	7.0.105.0				
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
Update 1 for 1.4.0.45	7.5.102.0	7.6.100.0	—	7.6.100.0	1.0	The Update 1 for Cisco Prime Infrastructure 1.4.0.45 enables you to manage Cisco WLC 7.6.x with the features of Cisco WLC 7.5.102.0 and earlier releases. This release does not support any new features of Cisco WLC 7.6.x. However, the Aironet 3700 Series Access Points are supported. Note For version compatibility for MSE 8.0 wIPS with Update 1 for 1.4.0.45, see Table 7 .
	7.4.150.0	7.5.102.101		7.5.102.101	1.1	
	7.4.140.0	7.4.121.0		7.4.121.0	1.2	
	7.4.130.0	7.4.110.0		7.4.110.0		
	7.4.121.0	7.4.100.0		7.4.100.0		
	7.4.110.0	7.3.101.0		7.3.101.0		
	7.4.100.60	7.2.110.0		7.2.110.0		
	7.4.100.0	7.2.103.0		7.2.103.0		
	7.3.112.0	7.0.240.0				
	7.3.101.0	7.0.230.0				
	7.2.115.2	7.0.220.0				
	7.2.111.3	7.0.201.204				
	7.2.110.0	7.0.112.0				
	7.2.103.0	7.0.105.0				
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
1.4.0.45	7.5.102.0	8.0.110.0	—	8.0.110.0	1.0	—
	7.4.150.0	7.5.102.101		7.5.102.101	1.1	
	7.4.140.0	7.4.121.0		7.4.121.0	1.2	
	7.4.130.0	7.4.110.0		7.4.110.0		
	7.4.121.0	7.4.100.0		7.4.100.0		
	7.4.110.0	7.3.101.0		7.3.101.0		
	7.4.100.60	7.2.110.0		7.2.110.0		
	7.4.100.0	7.2.103.0		7.2.103.0		
	7.3.112.0	7.0.240.0				
	7.3.101.0	7.0.230.0				
	7.2.115.2	7.0.220.0				
	7.2.111.3	7.0.201.204				
	7.2.110.0	7.0.112.0				
	7.2.103.0	7.0.105.0				
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
	7.0.116.0					
	7.0.98.218					
	7.0.98.0					

Table 4 Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco WLC	Cisco MSE 3355	Cisco MSE 3365	MSE Virtual Appliance	ISE	Remarks
Update 4 for 1.3.0.20	7.4.150.0	7.4.121.0	—	7.4.121.0	1.0	—
	7.4.140.0	7.4.110.0		7.4.110.0	1.1	
	7.4.130.0	7.4.100.0		7.4.100.0	1.2	
Update 1 for 1.3.0.20	7.4.121.0	7.3.101.0		7.3.101.0		
	7.4.110.0	7.2.110.0		7.2.110.0		
1.3.0.20	7.4.100.60	7.2.103.0		7.2.103.0		
	7.4.100.0	7.0.240.0				
	7.3.112.0	7.0.230.0				
	7.3.101.0	7.0.220.0				
	7.2.115.2	7.0.201.204				
	7.2.111.3	7.0.112.0				
	7.2.110.0	7.0.105.0				
	7.2.103.0					
	7.0.252.0					
	7.0.251.2					
	7.0.250.0					
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
7.0.116.0						
7.0.98.218						
7.0.98.0						
1.2.1.12	7.3.112.0	7.3.101.0	—	7.3.101.0	1.0	—
	7.3.101.0	7.2.110.0		7.2.110.0	1.1	
	7.2.115.2	7.2.103.0		7.2.103.0		
	7.2.111.3	7.0.240.0				
	7.2.110.0	7.0.230.0				
	7.2.103.0	7.0.220.0				
	7.0.252.0	7.0.201.204				
	7.0.251.2	7.0.112.0				
	7.0.250.0	7.0.105.0				
	7.0.240.0					
	7.0.235.3					
	7.0.235.0					
	7.0.230.0					
	7.1.91.0					
	7.0.220.0					
7.0.116.0						
7.0.98.218						
7.0.98.0						

1. Cisco MSE Release 8.0.140.x and later is compatible with Cisco Prime Infrastructure Releases 3.1.7, 3.1.6, 3.1.5, 3.1.3, 3.1.1, 3.0.3.1, and 2.2.3.5. If you encounter reachability issues with the Cisco MSE, upgrade to Prime Infrastructure Release 3.1.3. (CSCuz19013)
2. ISE 2.x or ISE 1.4 only works with MSE 8.0 or earlier.
3. Cisco CMX Release 10.3.x supports Cisco MSE 3355. However, the HA feature in Cisco CMX Release 10.3.x is not supported on the Cisco MSE 3355.

4. Cisco CMX Release 10.2.3 (Cisco Hyperlocation and Cisco 2800 and 3800 series access points) is compatible with Cisco Prime Infrastructure Release 3.1.x with device pack and update patch.
PI 3.1.3 update patch:
<https://software.cisco.com/download/release.html?mdfid=286304360&flowid=&softwareid=284272933&release=3.1.3&relind=AVAILABLE&rellifecycle=&reltype=latest>.
PI 3.1.3 device pack:
<https://software.cisco.com/download/release.html?mdfid=286304360&softwareid=286208063&release=3.1.3&relind=AVAILABLE&rellifecycle=&reltype=latest>.
5. You manually download maps from Cisco Prime Infrastructure to Cisco CMX Release 10.2.2. Client display within Cisco Prime Infrastructure is not supported on Cisco CMX Release 10.2.2.
6. Cisco CMX Release 10.2.x (non-Cisco Hyperlocation apps) is compatible with Cisco Prime Infrastructure Release 2.2.x and 3.0.x.

Cisco Prime Infrastructure and Cisco Converged Access Solution Compatibility Matrix

Table 5 lists the Cisco IOS/IOS XE releases and the corresponding devices that are compatible with the Cisco Prime Infrastructure releases.

Table 5 Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.3	Cisco IOS XE Denali 16.3.1 Cisco IOS XE Denali 16.3.2 Cisco IOS XE Denali 16.3.3 Cisco IOS XE Denali 16.2.2 Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.

Table 5 Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.2	Cisco IOS XE Denali 16.3.1 Cisco IOS XE Denali 16.3.2 Cisco IOS XE Denali 16.3.3 Cisco IOS XE Denali 16.2.2 Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.
3.1.7	Cisco IOS XE Denali 16.3.5 Cisco IOS XE Denali 16.3.3 Cisco IOS XE Denali 16.3.2 Cisco IOS XE Denali 16.3.1 Cisco IOS XE Denali 16.2.2 Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.

Table 5 Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.1.6	Cisco IOS XE Denali 16.3.1 Cisco IOS XE Denali 16.3.2 Cisco IOS XE Denali 16.3.3 Cisco IOS XE Denali 16.2.2 Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.
3.1.5	Cisco IOS XE Denali 16.3.1 Cisco IOS XE Denali 16.3.2 Cisco IOS XE Denali 16.2.2 Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.

Table 5 Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.1.4	Cisco IOS XE Denali 16.3.1 Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.
3.1.3	Cisco IOS XE Denali 16.2.2 Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.
3.1.1	Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.

Table 5 Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.1	Cisco IOS XE Denali 16.1.2 Cisco IOS XE Denali 16.2.1 Cisco IOS XE Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.
3.0 Technology Pack	Cisco IOS XE Denali 16.1.1 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support MSE 8.0.x.
3.0.2	03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	
3.0.1	03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	

Table 5 Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.0	03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	
2.2.3	03.07.00E 03.06.03E 03.06.01E 03.06.00E 03.03.03S 03.03.04S 03.03.05SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	
	03.07.00E* 03.07.01E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E	*With Release 03.07.00.E, support is introduced for Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform.
2.2.2	03.07.00E 03.06.03E 03.06.01E 03.06.00E 03.03.03S 03.03.04S 03.03.05SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	
	03.07.00E* 03.07.01E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E	*With Release 03.07.00.E, support is introduced for Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform.

Table 5 Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
2.2	03.07.00E 03.06.03E 03.06.01E 03.06.00E 03.03.03S 03.03.04S 03.03.05SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	*With Release 03.07.00.E, support is introduced for Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform.
	03.07.00E* 03.07.01E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E	
2.1.2	03.06.03E 3.6.1E 3.6.0E 03.03.03S 03.03.04S 03.03.05SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch	We recommend that you use Cisco Prime Infrastructure 2.1.2 if MSE is also deployed.
		Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	We recommend that you use Cisco Prime Infrastructure 2.1 if MSE is not deployed.
2.1.1	3.6.0E 03.03.02SE 03.03.01SE 03.03.00SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch	We recommend that you use Cisco Prime Infrastructure 2.1.1 if MSE is also deployed.
		Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	We recommend that you use Cisco Prime Infrastructure 2.1 if MSE is not deployed.
2.1	3.6.0E 3.3.2SE 3.3.1SE 3.3.0SE 3.2.3SE 3.2.2SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	For Release 3.6.0E, we recommend that you use Cisco Prime Infrastructure 2.1 if MSE is not deployed. If MSE is deployed on your network, we recommend that you upgrade to Cisco Prime Infrastructure 2.1.1.
	3.6.0E 3.3.2SE 3.3.1SE 3.3.0SE	Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch	

Table 5 Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix (continued)

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
2.0	3.3.1SE 3.3.0SE 3.2.3SE	Cisco Catalyst 3850 Switch Cisco 5700 Series Wireless Controller	Cisco Catalyst 3650 Switch that is supported with 3.3.xSE release is not supported with Cisco Prime Infrastructure 2.0.
	IOS12.2(50)SE IOS12.2(50)SG IOS12.2(33)SXI	Cisco Catalyst 3750 Switch	Can be used only for monitoring purposes.
1.4.0.45	3.2.1SE 3.2.2SE	Cisco Catalyst 3850 Switch	Can be used only for monitoring purposes.
	IOS12.2(50)SE IOS12.2(50)SG IOS12.2(33)SXI	Cisco Catalyst 3750 Switch	Can be used only for monitoring purposes.
1.3.0.20	3.2.1SE	Cisco Catalyst 3850 Switch	Can be used only for monitoring purposes.
	IOS12.2(50)SE IOS12.2(50)SG IOS12.2(33)SXI	Cisco Catalyst 3750 Switch	Can be used only for monitoring purposes.
1.2.1.12	—	—	—
	IOS12.2(50)SE IOS12.2(50)SG IOS12.2(33)SXI	Cisco Catalyst 3750 Switch	Can be used only for monitoring purposes.

Cisco Connected Mobile Experiences (CMX) Compatibility Matrix

Table 6 lists the CMX solution compatibility matrix.

Important Notes:

- If you are running Cisco CMX Release 10.1.x, we strongly recommend that you upgrade to Cisco CMX Release 10.3.x or later.
- You must manually download maps from Cisco Prime Infrastructure to Cisco CMX Release 10.3.x or later. Auto-import is not supported.
- Cisco CMX Release 10.2.x and later are supported on the MSE 3355 but on a limited scale in terms of number of tracked clients and number of WLCs synchronized. Scale numbers for Location and Presence Analytics are documented in the <https://www.cisco.com/c/en/us/solutions/collateral/enterprise-networks/connected-mobile-experiences/datasheet-c78-734648.html>.
- Cisco MSE 3365 supports Cisco Prime Infrastructure 2.1.1 and later. Cisco MSE 3365 does not support Cisco Prime Infrastructure 2.1.0.
- Cisco Hyperlocation is not supported on the MSE 3355.

- Cisco WLC Release 8.1.131.0 or later is required to use with CMX Hyperlocation.
- Cisco WLC Release 7.x supports the complete set of Cisco CMX Connect services. However:
 - Cisco WLC Release 8.2 or later is required to use these features available on Cisco CMX Release 10.2.2: menu link, text link on login page, and DNS-ACL configuration.
 - Cisco WLC Release 8.3 or later is required to use the PMS policy uplink bandwidth enforcement feature available on Cisco CMX Release 10.2.2.
- The High Availability feature on Cisco CMX:
 - Is supported only in Cisco CMX Release 10.3.x and later.
 - Is supported on all platforms supported by Cisco CMX Release 10.3.x and later.



Note The HA feature in Cisco CMX Release 10.3.x or later is not supported on the Cisco MSE 3355.

- Requires that both primary and standby servers have the same virtual machine size and the same virtual Cisco MSE appliances.
- Hyperlocation with the High Availability feature on Cisco CMX requires Cisco WLC Release 8.4.1.210 or later.

Table 6 Cisco CMX Compatibility Matrix

Cisco CMX	Platform	Prime Infrastructure	WLC	Converged Access	Access Point Platforms
10.4.x	MSE Virtual Appliance CISCO_CMX-10.4 MSE 3365 MSE 3355 ⁵	3.0 to 3.3 2.2	8.0 to 8.6	n/a	Cisco Aironet 1540, 1552H, 1560, 1562, 1800, 1810, 1815, 1830, 1850, 2800, and 3800 series. ^{1,2,6} APs with integrated controller functionality: Cisco Aironet 1850 series, 1830 series ³
10.3.x	MSE Virtual Appliance CISCO_CMX-10.3 MSE 3365 MSE 3355 ⁵	3.0 to 3.2 2.2	8.0 to 8.5	n/a	APs without integrated controller functionality: Cisco Aironet 700i, 700w, 1600 series, 1700 series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series
10.2.3	MSE Virtual Appliance CISCO_CMX-10.2.3 MSE 3365 MSE 3355	3.x ⁶ 2.2.x ⁷	7.6 to 8.5	16.3.x 16.2.x	Cisco Aironet 1800i Access Point and the Cisco Aironet 1800s Wireless Network Sensor ⁴
10.2.2	MSE Virtual Appliance CISCO_CMX-10.2.2 MSE 3365 MSE 3355	3.x ^{7,8} 2.2.x ^{7,8}	7.6 to 8.5	16.3.x 16.2.x	

1. Cisco CMX Release 10.3.x supports Cisco access points supported by Cisco WLC Release 8.0 or later.
2. Cisco Aironet 1815I and 1560 (1560I, 1560E, 1560D) series are compatible with Cisco CMX Release 10.3.x.
3. Cisco CMX Release 10.2.3 or later supports Cisco Aironet 1850 and 1830 series.
4. Cisco CMX Release 10.4.x or later supports Cisco Aironet 1800i Access Point and the Cisco Aironet 1800s Wireless Network Sensor.

5. Cisco CMX Release 10.3.x or later supports Cisco MSE 3355. However, the HA feature in Cisco CMX Release 10.3.x or later is not supported on the Cisco MSE 3355.
6. Cisco CMX Release 10.2.3 (Cisco Hyperlocation and Cisco 2800 and 3800 series access points) is compatible with Cisco Prime Infrastructure Release 3.1.x with device pack and update patch.
PI 3.1.3 update patch:
<https://software.cisco.com/download/release.html?mdfid=286304360&flowid=&softwareid=284272933&release=3.1.3&relind=AVAILABLE&rellifecycle=&reltype=latest>.
PI 3.1.3 device pack:
<https://software.cisco.com/download/release.html?mdfid=286304360&softwareid=286208063&release=3.1.3&relind=AVAILABLE&rellifecycle=&reltype=latest>.
7. Cisco CMX Release 10.2.x (non-Cisco Hyperlocation apps) is compatible with Cisco Prime Infrastructure Release 2.2.x and 3.0.x.
8. You manually download maps from Cisco Prime Infrastructure to Cisco CMX Release 10.2.2. Client display within Cisco Prime Infrastructure is not supported on Cisco CMX Release 10.2.2.

Cisco Mobility Services Engine Compatibility Matrix

This section contains the following topics:

- [Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x, page 63](#)
- [Cisco MSE Compatibility Matrix for Legacy Software Versions, page 75](#)



Note

For information about the Cisco Connected Mobile Experiences (CMX) 10.x solution compatibility matrix, see [Table 5](#).

Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x



Note

For MSE Release 8.0.x HA and WLC Release 8.0 or later, Prime Infrastructure Release 2.2.x is compatible.



Note

AeroScout CLE is not bundled with Cisco MSE release 7.5 and later. However, AeroScout CLE is compatible with Cisco MSE Release 7.5 and later, which uses the API interface.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
8.0.150.x ^{1,2} 8.0.140.x ^{1,2}	8.0.150.x ^{1,2} 8.0.140.x ^{1,2}	8.0.150.x ^{1,2} 8.0.140.x ^{1,2}	3.1.7 3.1.6 3.1.5 3.1.3 3.1 3.0.3 2.2.3	8.3.13x.0 8.3.12x.0 8.3.112.0 8.3.111.0 8.3.102.0 8.2.16x.0 8.2.160.0 8.2.151.0 8.2.141.0 8.2.130.0 8.2.121.0 8.2.111.0 8.2.110.0 8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.110.0 8.0.100.0 7.6.130.0* 7.6.120.0* 7.6.110.0* 7.6.100.0* 7.5.102.0** 7.4.121.0** 7.4.110.0** 7.4.100.60** 7.4.100.0** 7.3.112.0** 7.3.101.0** 7.2.111.3** 7.2.110.0** 7.2.103.0** 7.0.240.0** 7.0.235.3** 7.0.235.0** 7.0.230.0** 7.1.91.0** 7.0.220.0** 7.0.116.0** 7.0.98.218** 7.0.98.0**	3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2	* For FIPS compliance, Cisco MSE 8.0 works with Cisco Prime Infrastructure 2.2, Cisco WLC 8.0.100.0, and Converged Access 3.6.0. ** The MSE 8.0 wIPS profile cannot be applied to Cisco WLC release 7.5 or prior using Cisco Prime Infrastructure 2.2 *** If you are you are running Analytics and Context Aware Service (Location Service) on different machines and using Cisco Prime Infrastructure 1.4, then additional setup is required. You can download the Setup script from this location.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
8.0.130.0	8.0.130.0	8.0.130.0	3.1 3.0.1 3.0 2.2 and later 1.4***	8.3.13x.0 8.3.111.0 8.3.102.0 8.2.16x.0 8.2.151.0 8.2.141.0 8.2.130.0 8.2.121.0 8.2.111.0 8.2.110.0 8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.110.0 8.0.100.0 7.6.130.0* 7.6.120.0* 7.6.110.0* 7.6.100.0* 7.5.102.0** 7.4.121.0** 7.4.110.0** 7.4.100.60** 7.4.100.0** 7.3.112.0** 7.3.101.0** 7.2.111.3** 7.2.110.0** 7.2.103.0** 7.0.240.0** 7.0.235.3** 7.0.235.0** 7.0.230.0** 7.1.91.0** 7.0.220.0** 7.0.116.0** 7.0.98.218** 7.0.98.0**	3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2	* For FIPS compliance, Cisco MSE 8.0 works with Cisco Prime Infrastructure 2.2, Cisco WLC 8.0.100.0, and Converged Access 3.6.0. ** The MSE 8.0 wIPS44 profile cannot be applied to Cisco WLC release 7.5 or prior using Cisco Prime Infrastructure 2.2 *** If you are you are running Analytics and Context Aware Service (Location Service) on different machines and using Cisco Prime Infrastructure 1.4, then additional setup is required. You can download the Setup script from this location.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
8.0.120.7	8.0.120.7	8.0.120.7	3.0.1 3.0 2.2.2*** 2.2.1 2.2 2.1.2*** 2.1.1*** 1.4*****	8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.110.0 8.0.100.0 7.6.130.0 7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0***** 7.4.150.0***** 7.4.140.0***** 7.4.130.0***** 7.4.121.0***** 7.4.110.0***** 7.4.100.60***** 7.4.100.0***** 7.3.112.0***** 7.3.101.0***** 7.2.111.3***** 7.2.110.0***** 7.2.103.0***** 7.0.240.0***** 7.0.235.3***** 7.0.235.0***** 7.0.230.0***** 7.1.91.0***** 7.0.220.0***** 7.0.116.0***** 7.0.98.218***** 7.0.98.0*****	3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2	* For FIPS compliance, Cisco MSE 8.0 works with Cisco PI 2.2, Cisco WLC 8.0.100.0, and Converged Access 3.6.0. ****With MSE 8.0 wIPS feature: If you are using Cisco Prime Infrastructure 2.2 or later releases with Cisco WLC 7.5 or earlier releases, use Cisco MSE 8.0.120 or later. ***** If you are you are running Analytics and Context Aware Service (Location Service) on different machines and using Cisco PI 1.4 release, then additional setup is required. You can download the Setup script from this location.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
8.0.120.0	8.0.120.0	8.0.120.0	3.0.1 3.0 2.2.2*** 2.2.1 2.2 2.1.2*** 2.1.1*** 1.4*****	8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.110.0 8.0.100.0 7.6.130.0 7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0**** 7.4.150.0**** 7.4.140.0**** 7.4.130.0**** 7.4.121.0**** 7.4.110.0**** 7.4.100.60**** 7.4.100.0**** 7.3.112.0**** 7.3.101.0**** 7.2.111.3**** 7.2.110.0**** 7.2.103.0**** 7.0.240.0**** 7.0.235.3**** 7.0.235.0**** 7.0.230.0**** 7.1.91.0**** 7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0****	3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2	* For FIPS compliance, Cisco MSE 8.0 works with Cisco PI 2.2, Cisco WLC 8.0.100.0, and Converged Access 3.6.0. ****With MSE 8.0 wIPS feature: If you are using Cisco Prime Infrastructure 2.2 or later releases with Cisco WLC 7.5 or earlier releases, use Cisco MSE 8.0.120 or later. ***** If you are you are running Analytics and Context Aware Service (Location Service) on different machines and using Cisco PI 1.4 release, then additional setup is required. You can download the Setup script from this location.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
8.0.110.0	—	8.0.110.0	2.2.1 2.2 2.1.2*** 2.1.1*** 2.1*** 2.0*** 1.4*****	8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.115.0 8.0.110.0 8.0.100.0 7.6.130.0 7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0***** 7.4.150.0***** 7.4.140.0***** 7.4.130.0***** 7.4.121.0***** 7.4.110.0***** 7.4.100.60***** 7.4.100.0***** 7.3.112.0***** 7.3.101.0***** 7.2.111.3***** 7.2.110.0***** 7.2.103.0***** 7.0.240.0***** 7.0.235.3***** 7.0.235.0***** 7.0.230.0***** 7.1.91.0***** 7.0.220.0***** 7.0.116.0***** 7.0.98.218***** 7.0.98.0***** 7.0.250.0 7.0.251.0 7.0.252.0	3.7.x 3.6.x 3.3.x 3.2.x	* For FIPS compliance, MSE 8.0 works with PI 2.2, Wireless LAN Controller (WLC) 8.0.100.0, and Converged access 3.6.0. ***While using PI 2.1.1 and 2.1.2, the MSE 8.0 wIPS will have MSE 7.4 feature parity. ****With MSE 8.0 wIPS feature: If you are using Cisco Prime Infrastructure 2.2 or later releases with Cisco WLC 7.5 or earlier releases, use Cisco MSE 8.0.120 or later. ***** If you are you are running Analytics and Location services on different machines and using Cisco Prime Infrastructure 1.4 Version, then additional setup is required. You can download the Setup script from this location.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
8.0.100.0*	—	8.0.100.0	2.2.1 2.2 2.1.2 2.1.1*** 2.1 2.0 1.4*****	8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.100.0 7.6.130.0 7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0**** 7.4.150.0**** 7.4.140.0**** 7.4.130.0**** 7.4.121.0**** 7.4.110.0**** 7.4.100.60**** 7.4.100.0**** 7.3.112.0**** 7.3.101.0**** 7.2.111.3**** 7.2.110.0**** 7.2.103.0**** 7.0.240.0**** 7.0.235.3**** 7.0.235.0**** 7.0.230.0**** 7.1.91.0**** 7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0****	3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2	* For FIPS compliance, MSE 8.0 works with PI 2.2, Wireless LAN Controller (WLC) 8.0.100.0, and Converged access 3.6.0. *** While using PI 2.1.1, the MSE 8.0 wIPS will have MSE 7.4 feature parity. ****With MSE 8.0 wIPS feature: If you are using Cisco Prime Infrastructure 2.2 or later releases with Cisco WLC 7.5 or earlier releases, use Cisco MSE 8.0.120 or later. ***** If you are you are running Analytics and Location services on different machines and using Cisco Prime Infrastructure 1.4 Version, then additional setup is required. You can download the Setup script from this location.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
7.6.120.0	—	7.6.120.0	2.2.1 2.2 2.1.2 2.1.1** 2.1 2.0 1.4.2	7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—	**Prime Infrastructure 2.1.1 allows you to manage Cisco MSE Releases 7.5.102.101 and 7.6.120.0 with feature compatibility of Cisco MSE Release 7.4.121.0. Prime Infrastructure 2.1.1 does not support any new features introduced in Cisco MSE Releases 7.5.102.101 and 7.6.120.0. Note For PI 2.1.1 to work with MSE 7.6, you need to install a patch for Cisco bug Id CSCup93101. Contact Cisco TAC for a patch.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
7.6.132.0	—	7.6.132.0	2.2.1 2.2 2.1.2 2.1.1** 2.1 2.0 1.4.2	7.6.130.0 7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—	**Prime Infrastructure 2.1.1 allows you to manage Cisco MSE Releases 7.5.102.101 and 7.6.120.0 with feature compatibility of Cisco MSE Release 7.4.121.0. Prime Infrastructure 2.1.1 does not support any new features introduced in Cisco MSE Releases 7.5.102.101 and 7.6.120.0. Note For PI 2.1.1 to work with MSE 7.6, you need to install a patch for Cisco bug Id CSCup93101. Contact Cisco TAC for a patch.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
7.6.100.0	—	7.6.100.0	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0 Update 1 for 1.4.0.45* Update 2 for 1.4.0.45**	7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—	*The Update 1 for Cisco Prime Infrastructure 1.4.0.45 enables you to manage Cisco WLC 7.6.x with the features of Cisco WLC 7.5.102.0 and earlier releases. This release does not support any new features of Cisco WLC 7.6.x including the new access point platforms. **The Update 2 for Cisco Prime Infrastructure 1.4.0.45 enables you to manage Cisco WLC 7.6.x with the features of Cisco WLC 7.5.102.0 and earlier releases. This release does not support any new features of Cisco WLC 7.6.x. However, this release supports two new AP platforms—Cisco 702w and Cisco 2700.

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
7.6.100.0	—	7.6.100.0	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0*	7.6.110.0** 7.6.100.0** 7.5.102.0** 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	3.2.2** 3.3.2**	*Cisco Prime Infrastructure 2.0 enables you to manage Cisco WLC 7.5.102.0 with the features of Cisco WLC 7.4.110.0 and earlier releases. Prime Infrastructure 2.0 does not support any features that are introduced in Cisco WLC 7.5.102.0 or later releases including the new access point platforms. **Supports 7.4 MSE feature parity—CAS, MSE 8.0 wIPS, and CMX Analytics service. Note MSE 8.0 wIPS profile cannot be pushed to Cisco Wireless LAN Controller (WLC) Version 7.5 or prior using the Prime Infrastructure 1.4.x or 2.x with MSE 7.6 Release.
7.5.102.101	—	7.5.102.101	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0 Update 1 for 1.4.0.45 1.4.0.45	7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—	—

Table 7 Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x (continued)

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	WLC	Converged Access	Remarks
7.5.102.101	—	7.5.102.101	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0*	7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	3.2.2** 3.3.2**	*Cisco Prime Infrastructure 2.0 enables you to manage Cisco WLC 7.5.102.0 with the features of Cisco WLC 7.4.110.0 and earlier releases. Prime Infrastructure 2.0 does not support any features that are introduced in Cisco WLC 7.5.102.0 or later releases including the new access point platforms. **Supports 7.4 MSE feature parity—CAS, MSE 8.0 wIPS, and CMX Analytics service.

1. Cisco MSE Release 8.0.140.x and later includes wIPS support for the Cisco Aironet 1800, 2800, and 3800 series. However, CAS is not supported for these APs.
2. Cisco MSE Release 8.0.140.x and later is compatible with Cisco Prime Infrastructure Releases 3.3, 3.2.x, 3.1.7, 3.1.6, 3.1.5, 3.1.3, 3.1.1, 3.0.3.1, and 2.2.3.5. If you encounter reachability issues with the Cisco MSE, upgrade to Prime Infrastructure Release 3.1.3. (CSCuz19013)

Cisco MSE Compatibility Matrix for Legacy Software Versions

Table 8 Cisco MSE Compatibility Matrix—Legacy Software Versions

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	WLC	Prime Infrastructure / NCS
7.4.121.0	—	7.4.121.0	4.5.2.16 4.4.2.11	—	7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	2.0 Update 1 for 1.4.0.45 1.4.0.45 Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20
7.4.110.0	—	7.4.110.0	4.4.2.11	—	7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	2.0 Update 1 for 1.4.0.45 1.4.0.45 Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20

Table 8 Cisco MSE Compatibility Matrix—Legacy Software Versions (continued)

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	WLC	Prime Infrastructure / NCS
7.4.100.0	—	7.4.100.0	4.4.2.11 4.4.2.7	—	7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	Update 1 for 1.4.0.45 1.4.0.45 Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20
7.3.101.0	7.3.101.0	7.3.101.0	4.4.2.4	—	7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12

Table 8 Cisco MSE Compatibility Matrix—Legacy Software Versions (continued)

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	WLC	Prime Infrastructure / NCS
7.2.110.0	7.2.110.0	7.2.110.0	4.4.2.4	—	7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12 1.1.1.24 1.1.0.58
7.2.103.0	7.2.103.0	7.2.103.0	4.4.1.4	—	7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12 1.1.1.24 1.1.0.58
7.0.240.0	7.0.240.0	—	4.3.1.10	7.0.240.0	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12 1.1.1.24 1.1.0.58 1.0.2.29
7.0.230.0	7.0.230.0	—	4.3.1.19	7.0.230.0	7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12 1.1.1.24 1.1.0.58 1.0.2.29

Table 8 Cisco MSE Compatibility Matrix—Legacy Software Versions (continued)

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	WLC	Prime Infrastructure / NCS
7.0.220.0	7.0.220.0	—	4.3.1.19	7.0.220.0	7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12 1.1.1.24 1.1.0.58 1.0.2.29 1.0.1.4
7.0.201.204	7.0.201.204	—	4.2.4.4	7.0.172.0	7.0.116.0 7.0.98.218 7.0.98.0	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12 1.1.1.24 1.1.0.58 1.0.2.29 1.0.1.4 1.0.0.96
7.0.112.0	7.0.112.0	—	4.2.4.4	7.0.164.3 7.0.164.0	7.0.98.218 7.0.98.0	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12 1.1.1.24 1.1.0.58 1.0.2.29 1.0.1.4 1.0.0.96
7.0.105.0	7.0.105.0	—	4.2.4.4	7.0.164.3	7.0.98.218	Update 4 for 1.3.0.20 Update 1 for 1.3.0.20 1.3.0.20 1.2.1.12 1.1.1.24 1.1.0.58 1.0.2.29 1.0.1.4 1.0.0.96

**Note**

AeroScout CLE is no longer bundled with MSE starting from Release 7.5 Release. However, AeroScout CLE is compatible with MSE Release 7.5 and later using the API interface.

**Note**

Cisco MSE 3310 and 3350 are not supported beyond Release 7.3.

**Note**

This compatibility matrix lists only the compatibility information of Cisco MSE with other Cisco wireless products. This matrix does not reflect compatibility information between Cisco WLC and Cisco Prime Infrastructure or Cisco NCS. For compatibility information about Cisco Prime Infrastructure with Cisco WLC and other wireless products, see the Cisco Prime Infrastructure Release Notes.

Cisco Mobility Express Solution Compatibility Matrix

This section contains compatibility information about the Cisco Mobility Express Solution.


Note

The Cisco Mobility Express solution is not compatible with other Cisco Wireless LAN Controller deployments and Cisco Network Assistant.

Table 9 *Mobility Express Software Compatibility Matrix*

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco Prime Infrastructure	Remarks
8.5.103.0	15.3(3)JF	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.2 3.1.6 3.1.5	*Cisco Aironet 1560 series, 1815i, and 1815w AP platforms are not supported on Cisco Prime Infrastructure.
8.4.100.0	15.3(3)JE	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1560 series, 1815i, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.2 3.1.6 3.1.5	*Cisco Aironet 1560 series, 1815i, and 1815w AP platforms are not supported on Cisco Prime Infrastructure.

Table 9 Mobility Express Software Compatibility Matrix (continued)

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco Prime Infrastructure	Remarks
8.3.130.0	15.3(3)JD7, 15.3(3)JDA7	APs with integrated controller functionality:			3.2	
8.3.122.0	15.3(3)JD6	<ul style="list-style-type: none"> Cisco Aironet 1560, 1830, 1850, 2800, and 3800 series 	-	-	3.1.6	
8.3.121.0	15.3(3)JD5				3.1.5	
8.3.112.0	15.3(3)JD4				APs without integrated controller functionality: <ul style="list-style-type: none"> Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series 	
8.3.102.0	15.3(3)JD	APs with integrated controller functionality: <ul style="list-style-type: none"> Cisco Aironet 1830, 1850, 2800, and 3800 series APs without integrated controller functionality: <ul style="list-style-type: none"> Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series 	-	-	3.2 3.1.6 3.1.5 3.1.4	
8.2.100.0	15.3(3)JC	APs with integrated controller functionality:	-	1.4	1.4 1.3	
8.1.122.0	15.3(3)JBB5	<ul style="list-style-type: none"> Cisco Aironet 1850 series, 1830 series APs without integrated controller functionality: <ul style="list-style-type: none"> Cisco Aironet 700i, 700w, 1600 series, 1700 series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series 			1.3	

Converged Access Solution Compatibility Matrix



Note Because of SHA-2 certificate implementation, MSE 7.6 is not compatible with Cisco IOS XE Release 3.6E. Therefore, we recommend that you upgrade to MSE 8.0.



Note IRCM Feature: Seamless roam between Cisco 5700 WLC/Catalyst 3850 and Cisco 5500 WLC / Cisco WiSM2 with Release 7.3.112.0 using New Mobility.



Note To see the list of supported Cisco AP models on the Cisco Catalyst [3650](#) and [3850](#) Series Switches, see the respective release notes.

Table 10 Converged Access Solution Compatibility Matrix

Catalyst 3850/3650	Cisco 5700 WLC	Cisco 5508 WLC or WiSM2	MSE	ISE	ACS	Cisco Prime Infrastructure
Cisco IOX XE Denali 16.3.3	03.07.05E	8.5	—	2.0 Patch 3	5.3	3.1.6
	03.07.04E	8.4		1.4 Patch 7	5.4	3.1.5
Cisco IOS XE Denali 16.3.2	03.07.03E	8.3		1.4 (Wireless)	5.5	3.1.4
	03.07.02E	8.2		1.3 Patch 6 (Wired and Wireless)		3.1.3
Cisco IOS XE Denali 16.3.1	03.06.07E	8.1		1.3 Patch 5 (Wired and Wireless)		3.1.1
	03.06.06E			1.3 Patch 3 (Wired)		3.1
Cisco IOS XE Denali 16.2.2	03.06.05E					3.0 Technology Pack
	03.06.04E					
Cisco IOS XE Denali 16.2.1	03.06.03E ¹					
Cisco IOS XE Denali 16.1.1						
03.07.05E	03.07.05E	8.1	8.0 ²	1.3	5.2	2.2
03.07.04E	03.07.04E	8.0			5.3	
03.07.03E	03.07.03E	7.6				
03.07.02E	03.07.02E					
03.07.01E	03.07.01E					
03.07.00E	03.07.00E					

Table 10 Converged Access Solution Compatibility Matrix

Catalyst 3850/3650	Cisco 5700 WLC	Cisco 5508 WLC or WiSM2	MSE	ISE	ACS	Cisco Prime Infrastructure
03.06.07E 03.06.06E 03.06.05bE 03.06.05E 03.06.04E 03.06.03E 03.06.02aE 03.06.01E 03.06.00E	03.06.07E 03.06.06E 03.06.05aE 03.06.05E 03.06.04E 03.06.03E 03.06.02aE 03.06.01E 03.06.00E	8.0 7.6	8.0	1.2	5.2 5.3	2.1.2 or 2.1.1 if MSE is also deployed ³ 2.1.0 if MSE is not deployed
03.03.05SE 03.03.04SE 03.03.03SE 03.03.02SE 03.03.01SE 03.03.00SE	03.03.05SE 03.03.04SE 03.03.03SE 03.03.02SE 03.03.01SE 03.03.00SE	7.6 ⁴ 7.5 ⁵	7.6 7.5	1.2	5.2 5.3	2.0

1. Cisco 5700 (Cisco IOS XE Release 03.06.03E/ 03.07.02E) inter-operates as a Peer MC with Catalyst 3850 running on Cisco IOS XE 03.06.03E/ 03.07.02E releases.
2. Because of SHA-2 certificate implementation, MSE 7.6 is not compatible with Cisco IOS XE Release 3.6E and later. Therefore, we recommend that you upgrade to MSE 8.0.
3. If MSE is deployed on your network, we recommend that you upgrade to Cisco Prime Infrastructure 2.1.2.
4. Cisco WLC Release 7.6 is not compatible with Cisco Prime Infrastructure 2.0.
5. Prime Infrastructure 2.0 enables you to manage Cisco WLC 7.5.102.0 with the features of Cisco WLC 7.4.110.0 and earlier releases. Prime Infrastructure 2.0 does not support any features of Cisco WLC 7.5.102.0 including the new AP platforms.

Table II Converged Access Software Compatibility Matrix

Cisco 5700 WLC	Catalyst 3850	Catalyst 3650	Catalyst 4500E with Sup 8-E	Cisco WLC Release for Cisco 5508 WLC, WiSM2, or 2504 ¹ WLC Platforms	Cisco MSE	ISE	ACS	Cisco Prime Infrastructure
03.07.05E	03.07.05E	03.07.05E	03.09.01E	8.3.x	8.0	1.3	5.2	3.0
03.07.04E	03.07.04E	03.07.04E	03.09.00E	8.2.x			5.3	
03.07.03E	03.07.03E	03.07.03E	03.08.03E	8.1.x				
03.07.02E	03.07.02E	03.07.02E	03.08.02E	8.0				
03.07.01E	03.07.01E	03.07.01E	03.08.01E	7.6				
03.07.00E	03.07.00E	03.07.00E	03.08.00E					
03.06.07E	03.06.07E	03.06.07E	03.07.03E					
03.06.06E	03.06.06E	03.06.06E	03.07.02E					
03.06.05aE	03.06.05b	03.06.05b	03.07.01E					
03.06.04E	E	E	03.07.00E					
03.06.02aE	03.06.04E	03.06.04E						
03.06.01E	03.06.03E	03.06.03E						
03.06.00E	03.06.02a	03.06.02a						
	E	E						
	03.06.01E	03.06.01E						
	03.06.00E	03.06.00E						
03.07.05E	03.07.05E	03.07.05E	03.07.03E	8.1.x	8.0	1.3	5.2	2.2
03.07.04E	03.07.04E	03.07.04E	03.07.02E	8.0			5.3	
03.07.03E	03.07.02E	03.07.03E	03.07.01E	7.6				
03.07.02E	03.07.01E	03.07.02E	03.07.00E					
03.07.01E	03.07.00E	03.07.01E						
03.07.00E	03.06.06E	03.07.00E						
03.06.06E	03.06.05a	03.06.06E						
03.06.05aE	E	03.06.05a						
03.06.05E	03.06.05E	E						
03.06.04E	03.06.04E	03.06.05E						
03.06.02aE	03.06.02a	03.06.04E						
03.06.01E	E	03.06.02a						
03.06.00E	03.06.01E	E						
	03.06.00E	03.06.01E						
		03.06.00E						

Table 11 Converged Access Software Compatibility Matrix (continued)

Cisco 5700 WLC	Catalyst 3850	Catalyst 3650	Catalyst 4500E with Sup 8-E	Cisco WLC Release for Cisco 5508 WLC, WiSM2, or 2504 ¹ WLC Plat-forms	Cisco MSE	ISE	ACS	Cisco Prime Infrastruc-ture
03.06.05aE 03.06.05E 03.06.04E 03.06.02aE 03.06.01E 03.06.00E	03.06.05b E 03.06.05E 03.06.04E 03.06.03E 03.06.02a E 03.06.01E 03.06.00E	03.06.05b E 03.06.05E 03.06.04E 03.06.03E 03.06.02a E 03.06.01E 03.06.00E	—	8.0 8.0.x 7.6.x	8.0 ²	1.2	5.2 5.3	2.2 2.1.2 or 2.1.1 if MSE is also deployed 2.1.0 if MSE is not deployed ³
03.03.03SE 03.03.02SE 03.03.01SE 03.03.00SE	03.03.03S E 03.03.02S E 03.03.01S E 03.03.00S E	03.03.03S E 03.03.02S E 03.03.01S E 03.03.00S E	—	7.6 ⁴ 7.5 ⁵	7.6 7.5	1.2	5.2 5.3	2.0
03.02.03SE	03.02.03S E	—	—	7.6.x 7.5 7.3.112.0	7.6 7.5	1.1.3 1.1.2	5.2 5.3	2.0
03.02.02SE	03.02.02S E	—	—	7.6.x 7.5 7.3.112.0	7.6 7.5	1.1.3 1.1.2	5.2 5.3	—
03.02.01SE	03.02.01S E	—	—	7.3.112.0	—	1.1.3 1.1.2	5.2 5.3	—
03.02.00SE	03.02.00S E	—	—	7.3.112.0	—	1.1.1 MR	5.2	—

1. New Mobility is supported on Cisco 2504 WLC in 8.0.x and later releases.
2. Because of SHA-2 certificate implementation, MSE 7.6 is not compatible with Cisco IOS XE Release 3.6E and later. Therefore, we recommend that you upgrade to MSE 8.0.
3. If MSE is deployed on your network, we recommend that you upgrade to Cisco Prime Infrastructure 2.1.2.
4. Cisco WLC Release 7.6 is not compatible with Cisco Prime Infrastructure 2.0.
5. Prime Infrastructure 2.0 enables you to manage Cisco WLC 7.5.102.0 with the features of Cisco WLC 7.4.110.0 and earlier releases. Prime Infrastructure 2.0 does not support any features of Cisco WLC 7.5.102.0 including the new AP platforms.

Table 12 Cisco IOS XE to Cisco IOS Version Number Mapping

Cisco IOS XE Version	Cisco IOSd Version	Cisco Wireless Control Module Version	Access Point IOS Version
16.4.0	Not applicable	16.4.1.0	15.3(3)JPD
16.3.3	Not applicable	16.3.3.0	15.3(3)JPC3
16.3.2	Not applicable	16.3.2.0	15.3(3)JPC2
16.3.1	Not applicable	16.3.1.1	15.3(3)JPC1
16.3.0	Not applicable	16.3.1.0	15.3(3)JPC
16.2.1	Not applicable	16.2.2.0	15.3(3)JPB1
16.2.0	Not applicable	16.2.1.0	15.3(3)JPB
16.1.2	Not applicable	16.1.3.0	15.3(3)JNP2
16.1.1	Not applicable	16.1.2.0	15.3(3)JNP1
16.1.0	Not applicable	16.1.1.0	15.3(3)JNP
03.09.01E	15.2(5)E1	10.5.110.0	15.3(3)JND1
03.09.00E	15.2(5)E	10.5.100.0	15.3(3)JND
03.08.03E	15.2(4)E3	10.4.130.0	15.3(3)JNC3
03.08.02E	15.2(4)E2	10.4.120.0	15.3(3)JNC2
03.08.01E	15.2(4)E1	10.4.111.0	15.3(3)JNC1
03.08.00E	15.2(3)E	10.3.100.0	15.3(3)JNB
03.07.05E	15.2(3)E5	10.3.150.0	15.3(3)JNB6
03.07.04E	15.2(3)E4	10.3.141.0	15.3(3)JNB5
03.07.03E	15.2(3)E3	10.3.130.0	15.3(3)JNB3
03.07.02E	15.2(3)E2	10.3.120.0	15.3(3)JNB2
03.07.01E	15.2(3)E1	10.3.100.0	15.3(3)JNB1
03.06.07E	15.2(2)E7	10.2.170.0	15.3(3)JN12
03.06.06E	15.2(2)E6	10.2.160.0	15.3(3)JN11
03.06.05aE	15.2(2)E5	10.2.155.0	15.3(3)JN10
03.06.05E	15.2(2)E5	10.2.150.0	15.3(3)JN9
03.06.04E	15.2(2)E4	10.2.140.0	15.3(3)JN8
03.06.03E	15.2(2)E3	10.2.131.0	15.3(3)JN7
03.06.02E	15.2(2)E2	10.2.120.0	15.3(3)JN4
03.06.01E	15.2(2)E1	10.2.111.0	15.3(3)JN3
03.06.00E	15.2(2)E	10.2.102.0	15.3(3)JN
03.03.05SE	15.0(1)EZ5	10.1.150.0	15.2(4)JB7
03.03.04SE	15.0(1)EZ4	10.1.140.0	15.2(4)JB6
03.03.03SE	15.0(1)EZ3	10.1.130.0	15.2(4)JB5h
03.03.02SE	15.0(1)EZ2	10.1.121.0	15.2(4)JB3h

Table 12 Cisco IOS XE to Cisco IOS Version Number Mapping

Cisco IOS XE Version	Cisco IOSd Version	Cisco Wireless Control Module Version	Access Point IOS Version
03.03.01SE	15.0(1)EZ1	10.1.110.0	15.2(4)JB2
03.03.00SE	15.0(1)EZ	10.1.100.0	15.2(4)JN
03.02.03SE	15.0(1)EX3	10.0.120.0	15.2(2)JN
03.02.02SE	15.0(1)EX2	10.0.111.0	15.2(2)JN
03.02.01SE	15.0(1)EX1	10.0.101.0	15.2(2)JN
03.02.00SE	15.0(1)EX	10.0.100.0	15.2(2)JN

Supported Converged Access Solution Hardware

Supported Cisco 5760 Wireless Controller Models

Table 13 Cisco WLC 5700 Models

Part Number	Description
AIR-CT5760-25-K9	Cisco 5760 Wireless Controller for up to 25 Cisco access points
AIR-CT5760-50-K9	Cisco 5760 Wireless Controller for up to 50 Cisco access points
AIR-CT5760-100-K9	Cisco 5760 Wireless Controller for up to 100 Cisco access points
AIR-CT5760-250-K9	Cisco 5760 Wireless Controller for up to 250 Cisco access points
AIR-CT5760-500-K9	Cisco 5760 Wireless Controller for up to 500 Cisco access points
AIR-CT5760-1K-K9	Cisco 5760 Wireless Controller for up to 1000 Cisco access points
AIR-CT5760-HA-K9	Cisco 5760 Series Wireless Controller for High Availability

Supported Catalyst 3850 Switch Models

Table 14 Catalyst 3850 Switch Models

Switch Model	Cisco IOS Image	Description
WS-C3850-24T-L	LAN Base	Cisco Catalyst 3850 Stackable 24 10/100/1000 Ethernet ports, with 350-WAC power supply 1 RU, LAN Base feature set (StackPower cables must be purchased separately)
WS-C3850-48T-L	LAN Base	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet ports, with 350-WAC power supply 1 RU, LAN Base feature set (StackPower cables must be purchased separately)
WS-C3850-24P-L	LAN Base	Cisco Catalyst 3850 Stackable 24 10/100/1000 Ethernet PoE+ ports, with 715-WAC power supply 1 RU, LAN Base feature set (StackPower cables must be purchased separately)
WS-C3850-48P-L	LAN Base	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet PoE+ ports, with 715-WAC power supply 1 RU, LAN Base feature set (StackPower cables must be purchased separately)
WS-C3850-48F-L	LAN Base	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet PoE+ ports, with 1100-WAC power supply 1 RU, LAN Base feature set (StackPower cables must be purchased separately)
WS-C3850-12X48U-L	LAN Base	Stackable 12 100M/1G/2.5G/5G/10G and 36 1G UPoE ports, 1 network module slot, 1100 W power supply
WS-C3850-24T-S	IP Base	Cisco Catalyst 3850 Stackable 24 10/100/1000 Ethernet ports, with 350-WAC power supply 1 RU, IP Base feature set
WS-C3850-48T-S	IP Base	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet ports, with 350-WAC power supply 1 RU, IP Base feature set
WS-C3850-24P-S	IP Base	Cisco Catalyst 3850 Stackable 24 10/100/1000 Ethernet PoE+ ports, with 715-WAC power supply 1 RU, IP Base feature set
WS-C3850-48P-S	IP Base	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet PoE+ ports, with 715-WAC power supply 1 RU, IP Base feature set
WS-C3850-48F-S	IP Base	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet PoE+ ports, with 1100-WAC power supply 1 RU, IP Base feature set
WS-C3850-24PW-S	IP Base	Cisco Catalyst 3850 24-port PoE IP Base with 5-access point license
WS-C3850-48PW-S	IP Base	Cisco Catalyst 3850 48-port PoE IP Base with 5-access point license

Table 14 Catalyst 3850 Switch Models (continued)

Switch Model	Cisco IOS Image	Description
Catalyst 3850-12S-S	IP Base	12 SFP module slots, 1 network module slot, 350-W power supply
Catalyst 3850-24S-S	IP Base	24 SFP module slots, 1 network module slot, 350-W power supply
WS-C3850-12XS-S	IP Base	Catalyst 3850 12-port SFP+ transceiver, 1 network module slot, support for up to 10 G SFP+, 350 W power supply
WS-C3850-16XS-S	IP Base	Catalyst 3850 16-port SFP+ transceiver, 1 network module slot, support for up to 10 G SFP+, 350 W power supply. 16 ports are available when the C3850-NM-4-10G network module is plugged into the WS-C3850-12XS-S switch.
WS-C3850-24XS-S	IP Base	Catalyst 3850 24-port SFP+ transceiver, 1 network module slot, support for up to 10 G SFP+, 715 W power supply.
WS-C3850-32XS-S	IP Base	Catalyst 3850 32-port SFP+ transceiver, 1 network module slot, support for up to 10 G SFP+, 715 W power supply. 32 ports are available when the C3850-NM-8-10G network module is plugged into the WS-C3850-24XS-S switch.
WS-C3850-12X48U-S	IP Base	Stackable 12 100M/1G/2.5G/5G/10G and 36 1 G UPoE ports, 1 network module slot, 1100 W power supply
WS-C3850-24T-E	IP Services	Cisco Catalyst 3850 Stackable 24 10/100/1000 Ethernet ports, with 350-WAC power supply 1 RU, IP Services feature set
WS-C3850-48T-E	IP Services	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet ports, with 350-WAC power supply 1 RU, IP Services feature set
WS-C3850-24P-E	IP Services	Cisco Catalyst 3850 Stackable 24 10/100/1000 Ethernet PoE+ ports, with 715-WAC power supply 1 RU, IP Services feature set
WS-C3850-48P-E	IP Services	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet PoE+ ports, with 715-WAC power supply 1 RU, IP Services feature set
WS-C3850-48F-E	IP Services	Cisco Catalyst 3850 Stackable 48 10/100/1000 Ethernet PoE+ ports, with 1100-WAC power supply 1 RU, IP Services feature set
WS-3850-24U-E	IP Services	Cisco Catalyst 3850 Stackable 24 10/100/1000 Cisco UPOE ports, 1 network module slot, 1100-W power supply

Table 14 Catalyst 3850 Switch Models (continued)

Switch Model	Cisco IOS Image	Description
WS-3850-48U-E	IP Services	Cisco Catalyst 3850 Stackable 48 10/100/1000 Cisco UPOE ports, 1 network module slot, 1100-W power supply
Catalyst 3850-12S-E	IP Services	12 SFP module slots, 1 network module slot, 350-W power supply
Catalyst 3850-24S-E	IP Services	24 SFP module slots, 1 network module slot, 350-W power supply
WS-C3850-12XS-E	IP Services	Catalyst 3850 12-port SFP+ transceiver, 1 network module slot, support for up to 10 G SFP+, 350 -W power supply.
WS-C3850-16XS-E	IP Services	Catalyst 3850 16-port SFP+ transceiver, 1 network module slot, support for up to 10 G SFP+, 350 W power supply. 16 ports are available when the C3850-NM-4-10G network module is plugged into the WS-C3850-12XS-E switch.
WS-C3850-24XS-E	IP Services	Catalyst 3850 24-port SFP+ transceiver, 1 network module slot, support for up to 10 G SFP+, 715 W power supply.
WS-C3850-32XS-E	IP Services	Catalyst 3850 32-port SFP+ transceiver, 1 network module slot, support for up to 10 G SFP+, 715 W power supply. 32 ports are available when the C3850-NM-8-10G network module is plugged into the WS-C3850-24XS-E switch.
WS-C3850-12X48U-E	IP Services	Stackable 12 100M/1G/2.5G/5G/10G and 36 1 G UPoE ports, 1 network module slot, 1100 W power supply

Supported Catalyst 3650 Switch Models

Table 15 Catalyst 3650 Switch Models

Switch Model	Cisco IOS Image	Description
Catalyst 3650-24TS-L	LAN Base	Stackable 24 10/100/1000 Ethernet downlink ports, four 1-Gigabit SFP (small form-factor pluggable) uplink ports, 250-W power supply
Catalyst 3650-48TS-L	LAN Base	Stackable 48 10/100/1000 Ethernet downlink ports, four 1-Gigabit SFP uplink ports, 250-W power supply
Catalyst 3650-24PS-L	LAN Base	Stackable 24 10/100/1000 PoE+ ¹ downlink ports, four 1-Gigabit SFP uplink ports, 640-W power supply

Table 15 Catalyst 3650 Switch Models (continued)

Switch Model	Cisco IOS Image	Description
Catalyst 3650-48PS-L	LAN Base	Stackable 48 10/100/1000 PoE+ downlink ports, four 1-Gigabit SFP uplink ports, 640-W power supply
Catalyst 3650-48FS-L	LAN Base	Stackable 48 10/100/1000 Full PoE downlink ports, four 1-Gigabit SFP uplink ports, 1025-W power supply
Catalyst 3650-24TD-L	LAN Base	Stackable 24 10/100/1000 Ethernet downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 250-W power supply
Catalyst 3650-48TD-L	LAN Base	Stackable 48 10/100/1000 Ethernet downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 250-W power supply
Catalyst 3650-24PD-L	LAN Base	Stackable 24 10/100/1000 PoE+ downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48PD-L	LAN Base	Stackable 48 10/100/1000 PoE+ downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48FD-L	LAN Base	Stackable 48 10/100/1000 Full PoE downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 1025-W power supply
Catalyst 3650-48FQ-L	LAN Base	Stackable 48 10/100/1000 Full PoE downlink ports, four 10-Gigabit SFP+ uplink ports, 1025-W power supply
Catalyst 3650-48PQ-L	LAN Base	Stackable 48 10/100/1000 PoE+ downlink ports, four 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48TQ-L	LAN Base	Stackable 48 10/100/1000 Ethernet downlink ports, four 10-Gigabit SFP+ uplink ports, 250-W power supply
Catalyst 3650-24TS-S	IP Base	Stackable 24 10/100/1000 Ethernet downlink ports, four 1-Gigabit SFP uplink ports, 250-W power supply
Catalyst 3650-48TS-S	IP Base	Stackable 48 10/100/1000 Ethernet downlink ports, four 1-Gigabit SFP uplink ports, 250-W power supply
Catalyst 3650-24PS-S	IP Base	Stackable 24 10/100/1000 PoE+ downlink ports, four 1-Gigabit SFP uplink ports, 640-W power supply
Catalyst 3650-48PS-S	IP Base	Stackable 48 10/100/1000 PoE+ downlink ports, four 1-Gigabit SFP uplink ports, 640-W power supply

Table 15 Catalyst 3650 Switch Models (continued)

Switch Model	Cisco IOS Image	Description
Catalyst 3650-48FS-S	IP Base	Stackable 48 10/100/1000 Full PoE downlink ports, four 1-Gigabit SFP uplink ports, 1025-W power supply
Catalyst 3650-24TD-S	IP Base	Stackable 24 10/100/1000 Ethernet downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 250-W power supply
Catalyst 3650-48TD-S	IP Base	Stackable 48 10/100/1000 Ethernet downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 250-W power supply
Catalyst 3650-24PD-S	IP Base	Stackable 24 10/100/1000 PoE+ downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48PD-S	IP Base	Stackable 48 10/100/1000 PoE+ downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48FD-S	IP Base	Stackable 48 10/100/1000 Full PoE downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 1025-W power supply
Catalyst 3650-48FQ-S	IP Base	Stackable 48 10/100/1000 Full PoE downlink ports, four 10-Gigabit SFP+ uplink ports, 1025-W power supply
Catalyst 3650-48PQ-S	IP Base	Stackable 48 10/100/1000 PoE+ downlink ports, four 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48TQ-S	IP Base	Stackable 48 10/100/1000 Ethernet downlink ports, four 10-Gigabit SFP+ uplink ports, 250-W power supply
Catalyst 3650-24TS-E	IP Services	Stackable 24 10/100/1000 Ethernet downlink ports, four 1-Gigabit SFP uplink ports, 250-W power supply
Catalyst 3650-48TS-E	IP Services	Stackable 48 10/100/1000 Ethernet downlink ports, four 1-Gigabit SFP uplink ports, 250-W power supply
Catalyst 3650-24PS-E	IP Services	Stackable 24 10/100/1000 PoE+ downlink ports, four 1-Gigabit SFP uplink ports, 640-W power supply
Catalyst 3650-48PS-E	IP Services	Stackable 48 10/100/1000 PoE+ downlink ports, four 1-Gigabit SFP uplink ports, 640-W power supply
Catalyst 3650-48FS-E	IP Services	Stackable 48 10/100/1000 Full PoE downlink ports, four 1-Gigabit SFP uplink ports, 1025-W power supply

Table 15 Catalyst 3650 Switch Models (continued)

Switch Model	Cisco IOS Image	Description
Catalyst 3650-24TD-E	IP Services	Stackable 24 10/100/1000 Ethernet downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 250-W power supply
Catalyst 3650-48TD-E	IP Services	Stackable 48 10/100/1000 Ethernet downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 250-W power supply
Catalyst 3650-24PD-E	IP Services	Stackable 24 10/100/1000 PoE+ downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48PD-E	IP Services	Stackable 48 10/100/1000 PoE+ downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48FD-E	IP Services	Stackable 48 10/100/1000 Full PoE downlink ports, two 1-Gigabit SFP and two 10-Gigabit SFP+ uplink ports, 1025-W power supply
Catalyst 3650-48FQ-E	IP Services	Stackable 48 10/100/1000 Full PoE downlink ports, four 10-Gigabit SFP+ uplink ports, 1025-W power supply
Catalyst 3650-48PQ-E	IP Services	Stackable 48 10/100/1000 PoE+ downlink ports, four 10-Gigabit SFP+ uplink ports, 640-W power supply
Catalyst 3650-48TQ-E	IP Services	Stackable 48 10/100/1000 Ethernet downlink ports, four 10-Gigabit SFP+ uplink ports, 250-W power supply

1. PoE+ = Power over Ethernet plus (provides up to 30 W per port).

Compatibility Matrix for Legacy Products

This section contains the following subsections:

- [Cisco Prime Network Control System Compatibility Matrix, page 93](#)
- [Cisco Wireless Control System Compatibility Matrix, page 97](#)
- [Cisco WCS Navigator Compatibility Matrix, page 105](#)

Cisco Prime Network Control System Compatibility Matrix

Table 16 lists the compatibility matrix of Cisco Prime NCS, controller, access point images, Identity Services Engines (ISE), and mobility services engines (MSE).

Table 16 Cisco Prime Network Control System Compatibility Matrix

Cisco NCS	Cisco WLC	Cisco MSE	ISE
1.1.1.24	7.2.115.2	7.2.110.0	ISE 1.0
	7.2.111.3	7.2.103.0	ISE 1.1
	7.2.110.0	7.0.240.0	
	7.2.103.0	7.0.230.0	
	7.0.252.0	7.0.220.0	
	7.0.251.2	7.0.201.204	
	7.0.250.0	7.0.112.0	
	7.0.240.0	7.0.105.0	
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0 ¹		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		
1.1.0.58	7.2.103.0	7.2.103.0	ISE 1.0
	7.0.252.0	7.0.240.0	ISE 1.1
	7.0.251.2	7.0.230.0	
	7.0.250.0	7.0.220.0	
	7.0.240.0	7.0.201.204	
	7.0.235.3	7.0.112.0	
	7.0.235.0	7.0.105.0	
	7.0.230.0		
	7.1.91.0 ²		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		

Table 16 Cisco Prime Network Control System Compatibility Matrix (continued)

Cisco NCS	Cisco WLC	Cisco MSE	ISE
1.0.2.29	7.0.252.0	7.0.240.0	ISE 1.0
	7.0.251.2	7.0.230.0	
	7.0.250.0	7.0.220.0	
	7.0.240.0	7.0.201.204	
	7.0.235.3	7.0.112.0	
	7.0.235.0	7.0.105.0	
	7.0.230.0	6.0.202.0	
	7.1.91.0 ³	6.0.103.0	
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		
	6.0.202.0		
	6.0.199.4		
	6.0.196.0		
	6.0.188.0		
	6.0.182.0		
	6.0.108.0		
	4.2.209.0		
	4.2.207.0		
	4.2.205.0		
	4.2.176.0		
	4.2.173.0		
	4.2.130.0		
	4.2.112.0		
	4.2.99.0		
	4.2.61.0		

Table 16 Cisco Prime Network Control System Compatibility Matrix (continued)

Cisco NCS	Cisco WLC	Cisco MSE	ISE
1.0.1.4	7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0 6.0.202.0 6.0.199.4 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	7.0.220.0 7.0.201.204 7.0.112.0 7.0.105.0 6.0.202.0 6.0.103.0	ISE 1.0
1.0.0.96	7.0.116.0 7.0.98.218 7.0.98.0 6.0.202.0 6.0.199.4 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	7.0.201.204 7.0.112.0 7.0.105.0 6.0.202.0 6.0.103.0	ISE 1.0

1. If you upgrade to the 7.1.91.0 software release of Cisco Wireless LAN Controller from an earlier release, we suggest that you also upgrade Cisco Wireless Control System to 7.0.220.0 and MSE to 7.0.220.0. This upgrade ensures that you get support for the latest 3600i and 3600e lightweight access points.
2. If you upgrade to the 7.1.91.0 software release of Cisco Wireless LAN Controller from an earlier release, we suggest that you also upgrade Cisco Wireless Control System to 7.0.220.0 and MSE to 7.0.220.0. This upgrade ensures that you get support for the latest 3600i and 3600e lightweight access points.
3. If you upgrade to the 7.1.91.0 software release of Cisco Wireless LAN Controller from an earlier release, we suggest that you also upgrade Cisco Wireless Control System to 7.0.220.0 and MSE to 7.0.220.0. This upgrade ensures that you get support for the latest 3600i and 3600e lightweight access points.

Cisco Wireless Control System Compatibility Matrix

Table 17 lists the Cisco Wireless Control System (WCS) compatibility matrix.

Table 17 Cisco WCS Compatibility Matrix

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
7.0.240.0	7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0 6.0.202.0 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	—	7.0.240.0	7.0.230.0 7.0.220.0 7.0.172.0 7.0.164.3 7.0.164.0 6.0.202.0 6.0.196.0 6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0

Table 17 Cisco WCS Compatibility Matrix (continued)

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
7.0.230.0	7.0.235.3 7.0.235.0 7.0.230.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0 6.0.202.0 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	—	7.0.230.0	7.0.220.0 7.0.172.0 7.0.164.3 7.0.164.0 6.0.202.0 6.0.196.0 6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0
7.0.220.0	7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0 6.0.202.0 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	—	7.0.220.0	7.0.172.0 7.0.164.3 7.0.164.0 6.0.202.0 6.0.196.0 6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0

Table 17 Cisco WCS Compatibility Matrix (continued)

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
7.0.172.0	7.0.116.0 7.0.98.218 7.0.98.0 6.0.202.0 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	—	7.0.201.204	7.0.164.3 7.0.164.0 6.0.202.0 6.0.196.0 6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0
7.0.164.3	7.0.98.218 7.0.98.0 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	—	7.0.112.0 7.0.105.0	6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0

Table 17 Cisco WCS Compatibility Matrix (continued)

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
7.0.164.0	7.0.98.218 7.0.98.0 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	—	7.0.112.0 7.0.105.0	6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0
6.0.196.0	6.0.199.4 6.0.199.0 (pulled from CCO) 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 5.1.163.0 5.1.151.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	6.0.102.0	6.0.105.0	6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0

Table 17 Cisco WCS Compatibility Matrix (continued)

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
6.0.181.0	6.0.199.4 6.0.199.0 6.0.196.159 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 5.1.163.0 5.1.151.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	6.0.101.0	6.0.103.0	6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
6.0.170.0	6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 5.1.163.0 5.1.151.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	6.0.97.0	6.0.97.0	6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0

Table 17 Cisco WCS Compatibility Matrix (continued)

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
6.0.132.0	6.0.182.0 6.0.108.0 5.2.178.0 5.2.157.0 5.1.163.0 5.1.151.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	6.0.85.0	6.0.85.0	5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.2.148.0	5.2.193.0 5.2.178.0 5.2.157.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.2.100.0	5.2.100.0	5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.2.130.0	5.2.178.0 5.2.157.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.2.91.0	5.2.91.0	5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0

Table 17 Cisco WCS Compatibility Matrix (continued)

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
5.2.125.0 (pulled from CCO)	5.2.178.0 5.2.157.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.2.91.0	5.2.91.0	5.2.110.0 5.1.65.4 5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.2.110.0	5.2.157.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.2.91.0	5.2.91.0	5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.1.65.4	5.1.163.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.1.35.0	5.1.35.0	5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.1.64.0	5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.1.30.0	5.1.30.0	5.0.56.2 5.0.56.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0

Table 17 Cisco WCS Compatibility Matrix (continued)

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
5.0.72.0	5.0.148.2 5.0.148.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0	4.0.38.0	—	5.0.56.2 5.0.56.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0
5.0.56.2	5.0.148.0 4.2.61.0 4.1.x.x	4.0.33.0	—	5.0.56.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0
5.0.56.0	5.0.148.0 4.2.61.0 4.1.x.x	4.0.32.0	—	4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0
4.2.128.0	4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.43.0	—	4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0
4.2.110.0	4.2.176.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.42.0	—	4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0

Table 17 Cisco WCS Compatibility Matrix (continued)

WCS Version	Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
4.2.97.0	4.2.176.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.38.0	—	4.2.81.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0
4.2.81.0	4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.36.0	—	4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0
4.2.62.11	4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.35.0	—	4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0
4.2.62.0	4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.35.0	—	4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0

Cisco WCS Navigator Compatibility Matrix

Cisco WCS and Cisco WCS Navigator must be from the same release in order to be compatible (see [Table 18](#)). Although the release numbers will not be the same, you must verify whether they were part of the same release.

For example, Cisco WCS Navigator 1.0 is compatible with Cisco WCS 4.1, and Cisco WCS Navigator 1.1.x is compatible with any Cisco WCS 4.2.x.



Note

When Cisco WCS Navigator is upgraded to a new version, the corresponding Cisco WCS must also be upgraded to the corresponding new version. For example, if Cisco WCS Navigator is upgraded to version 1.6, Cisco WCS must also be upgraded to the corresponding version 7.0.

Table 18 *WCS and Navigator Compatibility Matrix*

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.6.230.0	7.0.240.0 7.0.230.0	1.6.220.0
		1.6.172.0
		1.6.164.3
		1.6.164.0
		1.5.202.0
		1.5.196.0
		1.5.181.0
		1.5.170.0
		1.5.132.0
		1.4.148.0
		1.4.130.0
		1.4.125.0
		1.4.110.0
1.6.220.0	7.0.220.0	1.6.172.0
		1.6.164.3
		1.6.164.0
		1.5.202.0
		1.5.196.0
		1.5.181.0
		1.5.170.0
		1.5.132.0
		1.4.148.0
		1.4.130.0
		1.4.125.0
		1.4.110.0
		1.6.172.0
1.6.164.0		
1.5.202.0		
1.5.196.0		
1.5.181.0		
1.5.170.0		
1.5.132.0		
1.4.148.0		
1.4.130.0		
1.4.125.0		
1.4.110.0		

Table 18 WCS and Navigator Compatibility Matrix (continued)

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.6.164.3	7.0.164.3	1.6.164.0 1.5.202.0 1.5.196.0 1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0
1.6.164.0	7.0.164.0 7.0.164.3	6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0
1.5.202.0	6.0.132.0 6.0.181.0 6.0.202.0	1.5.196.0 1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0

Table 18 WCS and Navigator Compatibility Matrix (continued)

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.5.196.0	6.0.196.0	1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.5.181.0	6.0.181.0	1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.5.170.0	6.0.132.0	1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0

Table 18 WCS and Navigator Compatibility Matrix (continued)

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.5.132.0	6.0.132.0	1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.4.148.0	5.2.148.0	1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.2.72.0 1.2.56.2 1.2.56.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.4.130.0	5.2.130.0 5.2.110.0	1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.2.72.0 1.2.56.2 1.2.56.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0

Table 18 WCS and Navigator Compatibility Matrix (continued)

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.4.110.0	5.2.110.0	1.3.64.0 1.2.72.0 1.2.56.2 1.2.56.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.3.64.0	5.1.64.0	1.2.56.2 1.2.56.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.1.128.0	4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0 4.2.110.0 4.2.128.0	1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0 1.0.91.0 1.0.83.0
1.1.110.0	4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0 4.2.110.0	1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0 1.0.91.0 1.0.83.0
1.1.97.0	4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0	1.1.81.0 1.1.62.11 1.1.62.0 1.0.91.0 1.0.83.0
1.1.62.11	4.2.62.11 4.2.62.0	1.1.62.0 1.0.91.0 1.0.83.0
1.1.62.0	4.2.62.0	1.0.91.0 1.0.83.0
1.0.91.0	4.1.91.0 4.1.83.0	1.0.83.0
1.0.83.0	4.1.83.0	—

Inter-Release Controller Mobility

This section contains the following Inter-Release Controller Mobility (IRCM) topics:

- [IRCM Compatibility Matrix, page 112](#)
- [CUWN Converged Access Solution Components and New \(Hierarchical\) Mobility IRCM Compatibility Matrix, page 113](#)

IRCM Compatibility Matrix

Table 19 *IRCM Compatibility Matrix: 4.2.x to 7.6.x Releases*

CUWN Service	4.2.x	5.0.x	5.1.x	6.0.x	7.0.x	7.2.x	7.3.x	7.4.x	7.6.x
Layer 2 and Layer 3 Roaming	Y	—	—	Y	Y	Y	Y	Y	Y
Wireless Guest Access/Termination	Y	Y	Y	Y	Y	Y	Y	Y	Y
MSE 8.0 wIPS and AwIPS Rogue Detection	Y	—	—	Y	Y	Y	Y	Y	Y
Fast Roaming (CCKM) in a mobility group	Y	—	—	Y	Y	Y	Y	Y	Y
Location Services	Y	—	—	Y	Y	Y	Y	Y	Y
Radio Resource Management (RRM)	Y	—	—	Y	Y	Y ¹	Y ²	Y	Y
Management Frame Protection (MFP)	Y	—	—	Y	Y	Y	Y	Y	Y
AP Failover	Y	—	—	Y	Y	Y	Y	Y	Y

1. In the 7.2.x.x release, RF Groups and Profiles were introduced. RRM for 7.2.x.x and later releases is not compatible with RRM for any previous release.
2. In the 7.3.101.0 release, changes were made to RF profiles that are not backwardly compatible with 7.2.

Table 20 *IRCM Compatibility Matrix: 7.0.x to 8.0.x Releases*

CUWN Service	7.0.x	7.2.x	7.3.x	7.4.x	7.6.x	8.0.x
Layer 2 and Layer 3 Roaming	Y	Y	Y	Y	Y	Y
Wireless Guest Access/Termination	Y	Y	Y	Y	Y	Y
MSE 8.0 wIPS and AwIPS Rogue Detection	Y	Y	Y	Y	Y	Y
Fast Roaming (CCKM) in a mobility group	Y	Y	Y	Y	Y	Y
Location Services	Y	Y	Y	Y	Y	Y
Radio Resource Management (RRM)	Y	Y ¹	Y ²	Y	Y	Y
Management Frame Protection (MFP)	Y	Y	Y	Y	Y	Y
AP Failover	Y	Y	Y	Y	Y	Y

1. In the 7.2.x.x release, RF Groups and Profiles were introduced. RRM for 7.2.x.x and later releases is not compatible with RRM for any previous release.
2. In the 7.3.101.0 release, changes were made to RF profiles that are not backwardly compatible with 7.2.

Table 21 *IRCM Compatibility Matrix: 7.4.x to 8.1.x and Later Releases*

CUWN Service	7.4.x	7.6.x	8.0.x	8.1.x	8.2.x	8.3.x	8.4.x	8.5.x
Layer 2 and Layer 3 Roaming	Y	Y	Y	Y	Y	Y	Y	Y
Wireless Guest Access/Termination	Y	Y	Y	Y	Y	Y	Y	Y
MSE 8.0 wIPS and AwIPS Rogue Detection	Y	Y	Y	Y	Y	Y	Y	Y
Fast Roaming (CCKM) in a mobility group	Y	Y	Y	Y	Y	Y	Y	Y
Location Services	Y	Y	Y	Y	Y	Y	Y	Y
Radio Resource Management (RRM)	Y	Y	Y	Y	Y	Y	Y	Y
Management Frame Protection (MFP)	Y	Y	Y	Y	Y	Y	Y	Y
AP Failover	Y	Y	Y	Y	Y	Y	Y	Y

CUWN Converged Access Solution Components and New (Hierarchical) Mobility IRCM Compatibility Matrix

Table 22 *CUWN Converged Access Solution Components and New (Hierarchical) Mobility IRCM Compatibility Matrix*

Service	7.3.112.0 7.5 and later releases	IOS XE 3.2.0SE and later releases
Layer 2 and Layer 3 Roaming	Y	Y
Wireless Guest Anchor/Termination ¹	Y	Y
MSE 8.0 wIPS and AwIPS Rogue Detection ²	Y	Y
Fast Roaming (CCKM) in a mobility group	Y	Y
Location Services	Y	Y
Radio Resource Management (RRM) ³	Y	Y
Management Frame Protection (MFP)	Y	Y
AP Failover and SSO ⁴	Y	Y

1. Guest Anchor Termination is only supported on Cisco 2500 Series, 5700 Series, 5500 Series, 8500 Series, and Cisco WiSM2 platforms. The Cisco 2500 Series, 5700 Series, 5500 Series, 8500 Series, Cisco WiSM2, and Catalyst 3650 and 3850 are all supported as foreign controllers.
2. Rogue Detector Mode is not supported on Catalyst 3650 and 3850.
3. In Release 7.2, RF profiles and groups feature was introduced. RRM for Release 7.2 and later is not backward compatible with the earlier releases. RRM Converged Access is compatible with the controller software 7.6 and later releases but does not support RF Profiles and Groups feature that was introduced in Release 7.2.
4. AP SSO support for Cisco 5700 series controllers is supported in IOS XE 3.3.0SE release. AP Intra-OS Platform Fast Failover Supported. AP Inter-OS Platform Image Download and Reboot performed.

New Mobility Support Matrix

This section lists the New Mobility support matrix for Cisco WLC platforms per various Cisco Wireless releases:

- [Cisco 2504 and 5508 Wireless Controller and WiSM2, page 114](#)
- [Cisco 8510 Wireless Controllers, page 115](#)
- [Cisco 3504, 5520, and 8540 Wireless Controllers, page 115](#)



Note

New Mobility is not supported on Cisco Flex 7510 WLC and Cisco Virtual Wireless Controller (vWLC).

Cisco 2504 and 5508 Wireless Controller and WiSM2

Table 23 New Mobility Support Matrix for Cisco 2504 and 5508 WLCs and WiSM2

Feature	7.3.112.0	7.4	7.5	7.6	8.0	8.1	8.2	8.3	8.4	8.5
New Mobility—Guest Anchor Controller	Y	N	Y	Y	Y	Y	Y	Y	Y	Y
New Mobility—Mobility Controller	Y	N	Y	Y	Y	N	N	N	N	N
New Mobility—Mobility Controller SPG	Y	N	Y	Y	Y	N	N	N	N	N
Native IPv6	N	N	N	N	N	N	N	N	N	N
HA AP SSO	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
HA Client SSO	N	N	N	N	N	N	N	N	N	N
Sleeping Clients	N	N	N	Y	Y	Y	Y	Y	Y	Y
Mobility Statistics	Y	N	Y	Y	Y	Y	Y	Y	Y	Y
Mobility Oracle configuration	N	N	Y	Y	Y	Y	Y	Y	Y	Y
EoGRE Tunnel Support	N	N	N	N	N	N	N	N	N	N
Mobility Support for Microsoft Lync calls	N	N	N	N	N	N	N	N	N	N
Mesh RAP channel synchronization across mobility groups	N	N	N	N	N	N	N	N	N	N
AVC Profile	N	N	Y	Y	Y	Y	Y	Y	Y	Y
Internal DHCP	N	N	N	N	N	N	N	N	N	N
PMIPv6	N	N	N	N	N	N	N	N	N	N
Fast SSID Switching	N	N	N	Y	Y	Y	Y	Y	Y	Y
802.11r	N	N	N	N	Y	Y	Y	Y	Y	Y

Table 23 New Mobility Support Matrix for Cisco 2504 and 5508 WLCs and WiSM2

Feature	7.3.112.0	7.4	7.5	7.6	8.0	8.1	8.2	8.3	8.4	8.5
802.11k	N	N	N	N	Y	Y	Y	Y	Y	Y
802.11v	N	N	N	N	Y	Y	Y	Y	Y	Y

Cisco 8510 Wireless Controllers

Table 24 New Mobility Support Matrix for Cisco 8510 WLCs

Feature	8.0	8.1	8.2	8.3	8.4	8.5
New Mobility—Guest Anchor Controller	Y	Y	Y	Y	Y	Y
New Mobility—Mobility Controller	Y	Y	Y	Y	N	N
New Mobility—Mobility Controller SPG	N	N	N	N	N	N
Native IPv6	N	N	N	N	N	N
HA AP SSO	Y	Y	Y	Y	Y	Y
HA Client SSO	N	N	N	N	N	N
Sleeping Clients	Y ¹	Y	Y	Y	Y	Y
Mobility Statistics	Y	Y	Y	Y	Y	Y
Mobility Oracle configuration	N	N	N	N	N	N
EoGRE Tunnel Support	N	N	N	N	N	N
Fast SSID Switching	Y	Y	Y	Y	Y	Y
802.11r	Y	Y	Y	Y	Y	Y
802.11k	Y	Y	Y	Y	Y	Y
802.11v	Y	Y	Y	Y	Y	Y

1. Supported from Release 8.0.140.0 onwards.

Cisco 3504, 5520, and 8540 Wireless Controllers

Table 25 New Mobility Support Matrix for Cisco 3504, 5520, and 8540 WLCs

Feature	8.1	8.2	8.3	8.4	8.5
New Mobility—Guest Anchor Controller	Y	Y	Y	Y	Y
New Mobility—Mobility Controller	Y	Y	Y	N	N
New Mobility—Mobility Controller SPG	N	N	N	N	N
Native IPv6	N	N	N	N	N
HA AP SSO	Y	Y	Y	Y	Y
HA Client SSO	N	N	N	N	N
Sleeping Clients	Y	Y	Y	Y	Y

Table 25 New Mobility Support Matrix for Cisco 3504, 5520, and 8540 WLCs

Feature	8.1	8.2	8.3	8.4	8.5
Mobility Statistics	Y	Y	Y	Y	Y
Mobility Oracle configuration	N	N	N	N	N
EoGRE Tunnel Support	N	N	N	N	N
Mobility Support for Microsoft Lync calls	N	N	N	N	N
Mesh RAP channel synchronization across mobility groups	N	N	N	N	N
AVC Profile	Y	Y	Y	Y	Y
Internal DHCP	N	N	N	N	N
PMIPv6	N	N	N	N	N
Fast SSID Switching	Y	Y	Y	Y	Y
802.11r	Y	Y	Y	Y	Y
802.11k	Y	Y	Y	Y	Y
802.11v	Y	Y	Y	Y	Y

Cisco Support Community

Cisco Support Community is a forum for you to ask and answer questions, share suggestions, and collaborate with your peers. Join the forum at <https://supportforums.cisco.com/index.jspa>.

Obtain Documentation and Submit a Service Request

For information on obtaining documentation, using the Cisco Bug Search Tool (BST), submitting a service request, and gathering additional information, see [What's New in Cisco Product Documentation](#).

To receive new and revised Cisco technical content directly to your desktop, you can subscribe to the [What's New in Cisco Product Documentation RSS feed](#). The RSS feeds are a free service.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2017 Cisco Systems, Inc. All rights reserved.